Popular
Scien
MONTH
Amazing New Avia
Resulting from Oversea Flights . Des

You wouldn't stuff yourself tonight —then go hungry all next week!

DON'T expect your radio storage battery to bring in programs loud and clear when you work it day after day without replenishing the power. Keep the battery strong and active by feeding it regularly—with a Rectigon Home Charger.

Charge at trickle or high rate—Rectigon does both.

With the Rectigon you can get a steady "trickle" to replace "A" power as you use it. In case of heavy drains due to prolonged use of the set, by a mere rearrangement of the leads you charge "A" or "B" batteries quickly, at a heavy rate. Either way, when you turn on your radio, you have power to spare. There are no acids or chemicals with Rectigon — no moving parts. You just attach the leads and plug into the light socket. It will charge your automobile battery the same quiet, "no trouble" way.

Rectigon, the many purpose charger, at good radio stores.

WESTINGHOUSE ELECTRIC & MANUFACTURING COMPANY, EAST PITTSBURGH, PENNSYLVANIA
OFFICES IN ALL PRINCIPAL CITIES ' REPRESENTATIVES EVERYWHERE ' TUNE IN WITH KDKA—KYW—WBZ

BESIDES Rectigon for better battery charging, Westinghouse also makes Micarta Panels and tubing for better insulation, and power testing instruments for better reception.



Rectigon Home Charger for radio and automobile storage batteries.

Westinghouse

Scientists Perfect Light Socket Power

OUT of the wizardry of retorts and test tubes, born of molten temperatures far beyond the conception of the average mind, scientists have wrought a new miracle that makes possible light socket power as dependable as your own house current, that demands no more attention than your electric iron, sweeper, or toaster.

Scientists, led by Professor S. J. M. Allen, Ph. D., of the Post Graduate College of Engineering, University of Cincinnati, working with metals and minerals in temperatures and electric furnaces of unheard-of proportions after years of experimenting, succeeded in re-arranging the entire atomic structure of copper, thus converting an ordinary conductor material into this new metal, now known to the scientific world as Kuprox.

The Replacement Unit, a series of simple Kuprox metal discs, riveted together.

A tiny disc of Kuprox, scarcely as large as a half-dollar now does the work that formerly required charging bulbs, noisy vibrators, and ruinous jars of acid and electrolyte.

Kuprox is now offered in stores of radio dealers the country over in many forms. Units, delivering radio "A" power, radio "B" power, and compact single units from which all radio power necessary for the operation of a set, is obtained are among the new items in which this new rectifying metal is used.



How the Kuprox Replacement Unit replaces the acid jar on trickle chargers.

One of its most interesting forms is the Kuprox Replacement Unit, consisting of a series of several Kuprox Discs, with which to replace the acid jar and charging unit on all existing electrolytic trickle chargers and power units. With this unique replacement unit, retailing for only $4.50, it is but the work of a few minutes to do away with all the bothersome watering and other attention that has been necessary to keep a trickle charger functioning. Two simple binding post connections are all that are necessary. Merely disconnect the present acid jar from the transformer of the trickle charger, throw it away and connect the same two leads to two binding posts on the Kuprox Replacement Unit. Thus any electrolytic charger becomes absolutely dry. In addition to eliminating all the attention necessary with the ordinary wet charger, this replacement unit of course does away with the acid fumes and the possibility of ruined clothing and furniture. The Replacement Unit also gives a great deal higher charging rate, resulting in greater operating efficiency of the battery.

Revolutionizing Radio Socket Power!

No acid, liquids, or charging bulbs - - Dry, permanent power No watering or bother!

At last, radio power as dependable and permanent as your house current, that requires no more attention than the snap of a switch. KUPROX, the new, dry metallic rectifier supplies all radio power, A, B, and C, constantly, dependably - - probably the greatest of all developments in light socket radio power.

With KUPROX Devices your set is truly electric. KUPROX is all-metal - - dry - - it needs no watching or watering - - it cannot wear out. Various models, from Trickle Chargers to the Combinations which supply all radio power from a single compact unit.

IS KUPROX

RADIO POWER DEVICES



KUPROX "A" TRANSIFIERS—Batteryless, noiseless, electric "A" power. Dry, dependable, needs no attention. Operates any receiver. 4-volt or 6-volt, $28.50 and up.

KUPROX A & B TRANSIFIERS—All radio power from a single unit. Controlled from set switch. Absolutely dry, requires no attention. $57.50 and up.

KUPROX "B" TRANSIFIERS—Dry, permanent, free of hum. Models for all sets and circuits, $14.50 and up.

KUPROX Replacement Unit—For replacing acid jar on all standard trickle chargers and power units. $4.50

KUPROX Trickle Chargers — 1-amp. rate. Large model gives 2½-amp. booster charge. $10.50 and $18.50.



[*Free Booklet*—"The Secret of Battery Elimination." Contains performance curves on most standard eliminators.]

THE KODEL RADIO CORPORATION, 500 E. Pearl St., CINCINNATI, O.

© 1927 K. R. Corp.

IS This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

WHAT IS NEW THIS MONTH

Table of Contents for September

LEADING ARTICLES

AMERICA TAKES TO THE AIR . . . *By Frank Parker Stockbridge* 9
Strides we are making toward "sky traffic"

OUR SUN IS SHRINKING! . . . . . *By Arthur A. Stuart* 17
Latest discoveries of our solar neighbor's secrets

COULD AIR INVADERS DESTROY US? . . . *By Caleb Johnson* 18
A startling picture of a future war terror

HOW ANIMALS MAKE LOVE . . . . . *By Elwell Crissey* 20
Strange mating ways of odd creatures

BLASTS THAT SAVED A CITY . . . . . *By Orville H. Kneen* 21
Wonderful new uses of dynamite

NEXT WE'LL SEE TO PARIS . . . . *By George Lee Dowd, Jr.* 23
Plans of a "television" pioneer to span the Atlantic

WHY WE MOB HEROES . . . . . *By A. A. Brill* 24
A psychologist's remarkable disclosure of the reason we hail "supermen"

PLOWS A THOUSAND ACRES A DAY . . . *By Wheeler McMillen* 27
Mechanical wonders of an up-to-date farm

HE TRAPPED THREE BANDITS WITH A MICROSCOPE! 29
By Edwin Ketchum
How chemistry aided a thrilling man hunt

WHAT'S AT THE TOP OF THE SKY? . . . *By Alden P. Armagnac* 30
Sensational air dashes into the greatest unexplored region of all

WHEN NEPTUNE SCOWLS . . . . . *By Jack O'Donnell* 35
Queer misadventures of ships at sea

$10,000,000 WAR ON WORMS 40
A glimpse of a nation-wide struggle with the devastating corn borer

AIRPLANES 2,000 YEARS OLD! . . . . . *By H. C. North* 41
Remarkable "modern" devices used by ancient priests

TO EUROPE BY ROCKET 43
An amazing airship that could cross the ocean in ninety minutes

WHAT EVERYONE ASKS ABOUT FLYING 62
Answers to familiar but little-understood aviation queries

SAM LOYD'S PUZZLE PAGE 65

A HOUSE WITH 30 SERVANTS . . . . *By John R. McMahon* 66
Modernizing your home with electricity

SOME FINE POINTS OF VALVE GRINDING . . *By Martin Bunn* 69
Gus and Joe discuss an "easy" job

DID YOU EVER *See* TONE QUALITY? 6

WHY PUBLIC UTILITIES ARE A GOOD INVESTMENT 4
By Wallace Ames

FICTION

SCHEDULE OR— . . . . . *By Leo F. Creagan* 14
A thrilling story of an express train's race against time

WHIRLING WHEELS—PART 2 . . . . *By Edmund M. Littell* 32
An unusual novel of the automobile's invention

RADIO

TRICKS OF THE RADIO QUACKS . . . *By Alexander E. Senauke* 63

THE HOME WORKSHOP

NEW WAYS TO PAINT FURNITURE . . . . . *By Berton Elliot* 73

HOW TO BUILD A B-ELIMINATOR . . . . *By Alfred P. Lane* 74

SYSTEM IN SURFACE GRINDING . . *By Hector J. Chamberland* 78

Automobiles

Illuminating Gas for Your Car? . 39
Wheel Operates Car Lights . . . 44
A Motorist's Rocking Chair . . . 45
Sight-Seeing Bus Has Balcony . . 45
Baggage Car for Your Auto . . . 45
Your Car's Brakes 47
Motors Race to Garage Roof . . 52
Electric Brakes for Autos . . . 53
"Sidecarette" Carries Three . . 58
Headlight Utility 68
Old Tube Holds Luggage 68
A Wheel Puller 68
Protection against Thieves . . . 68
Wire Loop Holds Screw 68

Aviation

Flying Safety Increases 38
Super-Beacon for Chicago . . . 45
Radio Beacons Guide Airmen . . 48
"Balloon Bicycle" Invented . . 52
A "Flying Doughnut" 52
Plans Plane to Fly Forward, Backward, Up or Down 59
Flyer Takes His Car Along . . . 59

Exceptional People

Takes Notes beneath the Sea . . 12
Steel Magnate Plows Own Farm . 12
Smallest Grandfather in the World? 13
Making Gigantic Statue of Christ . 13
Prepares Cheap "Platinum" . . 39
Mimics Wood with Concrete . . 48
Gets Medal for Purest Insulin . . 50
Man Races Horse 53
"Hops Off" from Surf Board . . 53
Makes Clock Case of 5000 Pieces . 55
Build Their Own Speed Boat . . 55
He Made Himself an Automobile . 55

Health and Hygiene

New War on Heart Disease . . . 39
Perspiration Causes Weight Loss . 44
Lights Show Inside of Eye . . . 45
Heart Murmurs "Tuned-In" . . . 52
Refutes Attack on Oatmeal . . . 57
Wakes Up Sleeping Muscles . . 57
Manikin Teaches Posture . . . 59

Laboratory Discoveries

Frauds Bared by Strange Detective Rays 37
Test Plants with Ultra-Violet Light . 38
Engineers Check Earth's Slip . . 39
Every Atom a Flashlight . . . 39
Approaching Synthetic Life . . . 39
Fingerprint Records on Skin . . . 44
Poison Ivy Antidote Found . . . 44
"Armor" of Germ Analyzed . . . 45
What the Moon Is Made Of . . . 46
Squirrel's Memory Tested . . . 50
Charts Predict Track Record . . . 51
Bricks Are Now Tested by Their Ring 53

September, 1927, Vol. 111, No. 3. **Popular Science Monthly** is published monthly at 250 Fourth Avenue, New York, N. Y., by the Popular Science Publishing Co., Inc. Entered as second-class matter Dec. 28, 1918, at the Post Office at New York under the act of March 3, 1879; additional entry as second-class matter at Chicago, Illinois. Entered as second-class matter at the Post Office Department, Canada. Printed in U. S. A. Copyright, 1927, by the Popular Science Publishing Co., Inc. Single copy, 25 cents. Yearly subscriptions to United States, its possessions, and Canada, $2.50; foreign countries, $3. The contents of this magazine must not be reprinted without permission. In presenting in its editorial columns numerous stories of new products of applied science, **Popular Science Monthly** does not underwrite the business methods of the individuals or concerns producing them. The use of **Popular Science Monthly** articles for stock-selling schemes is never authorized. O. B. Capen, President and Treasurer; R. C. Wilson, Vice-President; A. L. Cole, Secretary.

A New X-Ray Discovery . . . 56
Germs Give Light 57
Uranium Aids Growing Crops . . 57
Only Four Basic Odors 59

Models

Models Show Earth's Buckling . . 38
A Skyscraper of Glass 50
Builds *Old Ironsides* 54
Lawyer's Hobby Repairing Old Ship Models 54
A School for Ship Modeling . . . 54
Ship Replicas Their Business . . 54
Makes "Spanish Galleon" . . . 54
Model Yacht Tests Odd Design . 54
Electric Motor Drives Baby Plane . 55
Making Blocks for Ship Models . 105
Ship Models Built from Our Blueprints 108

New Devices for the Home

Gravity Operates This Salt-Shaker . . 60
Unusual Coffee Pot Has Strainer in Lid 60
Automatic Heat Control for Iron . . 60
Combination Salt and Pepper Shaker 60
Makes Your Candlesticks Electric . 60
New Tongs Save Your Hands . . 60
Double Fork Picks Up Hot Things 60
Odd Ladle Drains Vegetables . . 61
A Percolator You Can Take Apart . 61
Peels Oranges with Two Motions . 61
Space-Saving Refrigerator Dishes . 61
Sanitary Waste Receptacle . . . 61
A Picnic Container for Seasoning . 61
One-Hand Serving Utensils . . . 61
Prongs Keep Your Pictures Straight 61
Toasts Four Slices at Once . . . 61

New Processes and Inventions

Latest Armored Car Charged with Electricity 13
Matching Colors by Machine . . 38
Boards from Lumber Chips . . . 39
Machine Fights Forest Fires . . 44
Builds Diving Motor Boat . . . 46
Vibrating Bed Woos Sleep . . . 47
Mask Saves Pugilist's Face . . . 47
Clock Like Speedometer 48
Device Indicates North Star . . . 48
A Razor-Blade Lawnmower . . . 48
Folds 5000 Letters an Hour . . . 48
Fertilizer Applied by Hose . . . 49
Canoe Built of Paper 49
Saves Gold for Dentists 49
Scarlet Ray Is New Traffic Signal . 49
"Seasick Chair" Tests Sailors . . 49
Magnifier in Pencil Style . . . 51
Turbine Locomotive Tested . . . 52
Telephone Meter Sells by Word . 56
Lifeboat Inflated Like Tire . . . 56
Self-Service Hat Checker . . . 57
Amazing Engine Tested 57
Tent Train Saves Pavement . . 58

Radio

Electric Device Makes Synthetic Music 12
Engineer and Brakeman Talk by Radio 12
Wave of Hand Starts Steel Mill . 12
Lights Controlled by Radio . . . 39
Turns Your Phone into a Radio Set 49
Big Gain in Radio Precision . . 51
Neat Wiring Made Easier . . . 64
Binding Posts That Hold . . . 64
Locating the B-Eliminator . . . 64
Shield the Detector Tube . . . 64
A B C's of Radio 64

Unusual Facts and Ideas

Baseball at Night under Floodlights 13
Giant Locomotive and Its "Pup" . 13
Huge Switchboard for Summer White House 13
World's Highest Dam 37
Your Capacity to Learn 38
Tiny Plants Tunnel in Stone . . 38
Can Animals Run Machines? . . 38
A Welding Shop on Wheels . . . 44
Thousands of Tons of Color . . 44
Personalities Made Over . . . 45
Bees Sip Poison 45
Largest Dock in the World . . . 46
Earthquake "Made to Order" . . 46
Expedition to "Lost World" . . 46
Hop Growers Work on Stilts . . 46
How Much Do You Know of the World You Live In? 46
Dike to Enlarge Holland . . . 47
Bulkiest Freight Parcel 47
Aviator Chases Rainbow . . . 47
Horse's Mummy in Coffin . . . 47
Biggest Family, 44 Children? . . 50
Seeds Forecast Tree Sizes . . . 50
Dropper Feeds Tiny Birds . . . 50
Garden Is Floral U. S. Map . . 50
Unpacking a 23-Foot Python . . 51
Huge Book Taller Than a Man . 51
Rat-Proof Ships End Plague . . 51
Start of Balloon Race 52
Fearless Men Vanishing from the Earth? 52
Almost Beats the Camera . . . 53
Prehistoric Monster Lives . . . 53
2,000,000-Year-Old Pine Cone . . 53
Schoolboys Build a House . . . 55
Live on a Vast Ice Cake 56
Pipe Sweetened by Steam . . . 56
Fights Skyscraper Fires 57
What Turns Animals White? . . 58
Mighty Natural Springs Could Supply Cities 58
Birds' Nest in Mop 58
Organ Nearly Wrecks Itself . . 58
Insane Sleep in Sawdust Bed . . 137
Zoo Sells Elephant Hides . . . 137
Roman "Cannon Ball" Found . . 143
Grasshopper in a Glacier . . . 143

For the Home Builder

Are You Planning to Buy an Oil Burner? 59
Sash Weights Force Stubborn Window 82
Shelves for a Child's Room . . . 86
Invisible Springs Keep Windows from Rattling 86
Adding a Room to Your House . . . 94
How to Insert Flashing under Old Shingles 104
Combination Awning and Shutter for Bungalow 110
Puttying Sash Lights 112

Hints for the Mechanic

Draft Regulator Protects Boiler . . 116
Milling Cutter Locates Index Plate Holes 116
Simple Shop-Made Chuck for Hole Grinding 117
Old Auto Motor Used for Hoist . . 117
Illuminated Table for Tracing Blueprints 118
Pencil Holder for Dividers 118
Angle Iron Rack Holds Many Tools 119
Indexing Welded Gear Teeth . . . 119
How to Obtain a Light Driving Fit Quickly 120
Clamp for Holding Small Round Finished Plates 120
Triple Center Punch Lays Out Dies . 121
Welding Torch Bushes Holes in Foundry Flasks 121
Piston Ring Keeps Line Shafting Clean 121

Ideas for the Handy Man

Improvises Rudder Post from Car Parts 55
My Motorized Shop Cost $20 . . . 76
Unique Noah's Ark Toy Floats or Runs on Land 80
A Handmade Canoe Paddle 80
Simply Built Reading Tables . . . 81
What You Can Make of Stone . . . 82
How to Take Up Rod Bearings . . 84
Hints on Using Hand Screws for Woodwork 84
A Cube for You to Whittle 88
Toy Auto Built for Speed 90
A Cabinet for Your Curios 92
An Aquarium at Low Cost 96
How to Make Tables, Chairs and Accessories for the Camp 98
Simple Straw Instrument Measures Humidity 100
Net Handle Aids in Shooting a Bow . 101
How to Make a Sewing Cabinet with Lyre-Shaped Legs 102
A Dressing Table for Baby 104
"Framing" Pictures with Fiber Wallboard 106
What Do You Want to Make? . . . 107
Making Garden Hose Washers . . . 110
Replacing a Broken Glass Knob . . 110
Iron Holder and Stand 111
Tightening Loose Casters 111
Linoleum Drainboards 112
New Ways to Paint 113
Combed Stencil Effects for the Ameteur Decorator 113
Ammonia in the Home Workshop . 114
How to Prolong the Life of a Wooden Mitre Box 115
An Easy-to-Fit Cork 115

More Than 250 Striking Articles in This Single Issue
Cover from Every Angle the Latest Developments
in the World of Invention and Discovery

Increasing
THE
Security
underlying your investment
IN
SMITH BONDS
through
Sinking Fund Provisions

Every First Mortgage securing bonds offered by this House carries a provision by which the owner of the property is obliged to pay into a sinking fund a specified amount at regular intervals for the retirement of a portion of the bonded indebtedness, thereby proportionately increasing the security of the investor in Smith Bonds.

Our long experience enables us to surround a First Mortgage Bond issue with safeguards for the investor that have created

World-Wide
Confidence
IN
SMITH BONDS

Present offerings
Yield 6½%
Denominations of $1000, $500, $100.
Maturities from 2 to 10 years.

Booklet explaining issues and the safeguards that protect every investor in our First Mortgage Bonds may be had by filling out the attached coupon.

Our Mail Service Department

No matter where you may be you can avail yourself of the Mail Order Service of our Home Office in Washington, D. C. Your investments and inquiries will be given the same personal, efficient and courteous attention you would receive if you called at one of our offices.

The **F. H. SMITH CO.**
Founded **1873**
Smith Building, Washington, D.C.
285 Madison Ave., New York, N.Y.
Continental & Commercial Bank Bldg., Chicago, Ill.
BOSTON ALBANY BUFFALO
MINNEAPOLIS ST. LOUIS

Kindly send Booklet and information regarding SMITH BONDS.
NAME_____ "75-31"
ADDRESS_____

Why PUBLIC UTILITIES Are a *Good* Investment

By WALLACE AMES, *Financial Editor*

THE following letter to POPULAR SCIENCE MONTHLY brings up an interesting subject.

"WALLACE AMES, *Financial Editor*,
Dear Sir:

"I have been interested in reading your recent articles on public utilities and their investment value. Undoubtedly the utilities have established some wonderful records in the past few years, but how is this going to affect their continued future growth? For instance, I read somewhere that the number of new homes wired for electricity is on the decrease. Can I expect that the business and the earnings of electric light and power companies will continue to increase?"

IT IS TRUE that 1924 was the peak year in number of newly wired homes. 1,783,000 homes were wired that year as compared with 1,222,550 in 1926, according to *Electrical Merchandising*. But there are many other factors that will affect the future of public utilities as a form for investment.

The 58% or 60% of America's homes which have already been wired for electricity include mostly homes in the larger towns and cities, places having 1,000 population or over. There are still a big proportion of the homes in villages, hamlets and farms to be wired for light and power.

The "super-power" development, which in layman's English means the interconnecting of generating stations is steadily making it possible to reach more and more of these homes in thinly settled districts. It will not be long before electricity will be available to almost every home in the United States. This means there will be a satisfactory continuance in the number of newly wired homes.

But let us assume that the 1924 record will never be duplicated. It does not follow that there will be a let-up in the business done by the utilities.

As we said in our article in the August issue of POPULAR SCIENCE MONTHLY, the average home consumption of electric current is now only $27.89 per year. The goal of the utilities in this branch is $85 a year.

To begin with, home owners are being educated to have their houses more completely wired. The number of outlets per home is on the increase. In addition to the more extensive use of table and floor lamps, in addition to wall and ceiling lights, plugs are being installed in kitchens, laundries, bath rooms, etc., so that electrical appliances may be more extensively used.

This table of figures from *Electrical Merchandising* will indicate how great is the future market for electric current in the 16,000,000 homes which are now wired.

74.9% of homes are as yet without an electric toaster;
62.9% have no vacuum cleaner;
97% have no electric range;
73.3% have no electric clothes washer;
98.3% have no electric ironer;
73.9% have no electric fan;
97.6% have no electric refrigerator;
86.5% have no electric heater;
95.3% have no electric cooker.

BOTH manufacturers of electric appliances and electric light and power companies are rapidly educating the public to the wider use of labor-saving and comfort-producing electrical devices. And a comparison of wages and cost of living, shows that the public is able to afford more electrical conveniences.

In 1913 wages and cost of living were both represented by 100. In 1926 the cost of living figure had risen to about 175, but the wage figure had mounted to about 290, showing a wide purchasing margin which did not exist in 1913.

The laborious work of the farmer is still a subject of popular discussion and still one of his grievances. In the early days of electric light and power development it was not possible for central stations to transmit current far enough from their generating plants to make it available to the farmer and the resident of the small village. But that situation is being overcome and the future will witness electric farms which will compare favorably in modern conveniences with the electric home so common today.

We will soon see much of the hand labor of the farm done by electricity. Irrigation is already a big source of electric revenue. The day is coming when electric power will be commonly used for incubators, illumination for the increase of egg production, shelling and cleaning numerous crops, threshing, cream separating, running grindstones, silage cutting, milking, churning, operating lathes, drills, pumps and other machinery, horse and sheep clipping, and sawing, refrigeration, sterilization and all the household uses now common to the cities.

(Continued on page 5)

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Retire in 15 years on your Present living Budget

by investing in safe 6½% First Mortgage Bonds

Follow the definite plan given in this book, and your financial independence is won.

The plan works just as surely, whether you are now earning $1,000 or $100,000 a year.

The way is certain—each step plainly indicated and absolutely safe—independent of luck, business genius or speculation.

Every fact has been harvested out of the 46 years' experience of Cochran & McCluer in the first mortgage investment banking business.

The plan is so simple, anyone can understand it—so definite anyone can follow it—and so certain, no one can fail.

In addition to the Financial Independence Plan and the unique budget schedule, the book gives suggestions that enable you to enjoy more of the good things of life, both while building your independent fortune and after you have attained it.

We invite the most skeptical to read this plain, straightforward, interesting book.

Send coupon. We employ no salesmen, therefore none will call.

Mail this

P-9

Cochran & McCluer Co.
46 N. Dearborn St., Chicago, Ill.
Please send me, without obligation, your book, "Behind The Scenes Where Bonds Are Made."

Name.....

Street.....

City.....State.....

Cochran & McCluer Co.
Established 1881—Never a loss to any investor.
46 North Dearborn Street,
CHICAGO

Construction of Small Alternating Current Motors

By PROF. A. E. WATSON
Brown University

This book contains complete instructions for building small alternating current motors in several sizes. The designs will be found in harmony with those of the very best manufacturers and they can be worked out by the amateur for making useful instruments.

Fully Illustrated. **Price, $1.50**

POPULAR SCIENCE MONTHLY
250 Fourth Ave. New York City

A Good Investment

THE figures show that through the introduction of more efficient methods the utilities are being able, year by year, to make better use of the capital they raise by selling their bonds and preferred stock to the investing public. Total capitalization, according to the *Wall Street Journal*, was $4,100,000,000 in 1920 and $7,500,000,000 in 1926. Between 1915 and 1926 the k. w. h. production of all utilities increased from 16,175,000,000 to 68,732,000,000.

These facts may be translated into a very interesting investment story. One of the first rules of investment is to buy the bonds and the stock of companies whose future market is assured. Styles, trends and customs change and with the change some industries decline and others advance. It is plain to see that the future market for electric current will constantly increase, thus assuring increased revenue to the light and power companies.

OF COURSE, the references we have made in this article apply only to the electric branch of the entire public utility world. Utilities sell other services than electric light and power. Other major services include gas, transportation, water, heat, steam power, ice, etc. In general, our remarks about the progressiveness of electric companies apply also to companies rendering other services.

Your investment banker (or your local utility, if you buy its stock direct) is prepared and will gladly furnish you with full information regarding any investment he recommends to you.

To Help You Get Ahead

THE Booklets listed below will help every family in laying out a financial plan. They will be sent on request.

How to Build an Independent Income (1927 Edition)—Describes a plan for buying 6½% First Mortgage Bonds by payments of $10 or more a month, and shows the results that may be accomplished by systematic investment. Address: The F. H. Smith Company, Smith Building, Washington, D. C. Ask for Booklet 75.

The House Behind the Bonds reminds the investor of the importance, not only of studying the investment, but of checking up the banker who offers it. Address: Fidelity Bond & Mortgage Co., 1188 New York Life Building, Chicago, Ill.

Behind the Scenes where Bonds Are Made tells how you can retire in fifteen years and have an income equal to your present living budget. This booklet can be secured by writing to Cochran and McCluer Company, 46 North Dearborn Street, Chicago, Ill.

Thirty-two page illustrated booklet, describing one of the largest public utility companies, of interest to investors. Utility Securities Company, 230 S. LaSalle St., Chicago, Ill.

You can WATCH YOUR MONEY WORK

INVESTORS who demand safety *first* favor public utility securities because they know that most of the money invested in this way goes into great *permanent properties* where it can be seen at work day and night, every day in the year.

The recently published 1927 year book of the Commonwealth Edison Company of Chicago (send the coupon below if you want a copy) illustrates this fact with an interesting chart showing that 38 cents of every Edison dollar is invested in the Company's five inter-connected generating stations—the greatest steam-operated central station system, in fact, in the world.

A little more than 39 cents of every Edison dollar is similarly invested in the maze of underground cables which, with the Company's 99 sub-stations, comprises the distribution system.

Dividends on the capital stock of the Commonwealth Edison Company, one of many public utility companies which we represent, have been paid without interruption for 38 years.

Our Monthly Savings Plan of $10 per share per month is available for investors who wish to acquire dividend-paying utility shares out of income rather than capital. Interest is allowed at 6%. Send the coupon below for details.

UTILITY SECURITIES COMPANY

230 S. La Salle St., Chicago

St. Louis Indianapolis Milwaukee Louisville

WRITE

name and address in the margin below—then tear it off and mail to us and we will send you a free copy of the Edison Year Book with list of our current investment offerings and details of the Monthly Savings Plan.

He's Looking at Music!

Not a sound can be heard, yet this engineer is testing a set for tone quality. Whenever possible, the Institute substitutes electromechanical devices for the inaccurate human senses in judging the merit of a product

DID YOU EVER *SEE* TONE QUALITY?

YOU may not want distance, you may not even be particularly interested in getting a very selective receiving set, but you certainly *do* want true tone quality.

The Popular Science Institute has been able to substitute the eye for the ear in judging this quality.

The tone quality of a radio set is really a measure of the faithfulness with which it reproduces in the form of sound the electrical impulses that it receives from the broadcasting station by way of the receiving antenna or loop. In carrying out this function in a perfect manner, the following characteristics are of importance:

1. Its ability to amplify with equal effectiveness all the audible frequencies that compose music and speech.

2. Its freedom from self-generated stray oscillations which combine with and distort the form of the received electrical impulses.

3. Its ability to maintain the relative strength of the electrical impulses while they are being detected and amplified.

The ideal set, from the standpoint of absolute perfection, should show no departure from perfect in any of these characteristics throughout the range of broadcast wave lengths in the radio-frequency end and within the audible range in the audio end.

No radio set is absolutely perfect. Its relative quality depends on how much it deviates from perfection. As no two ears are the same, ear tests cannot be reliable. By the Institute's method, the performance of the set is translated into forms that will affect a visual meter so that a pointer moving across a dial is substituted for the erratic and uncertain human ear.

Of the imperfection to which the radio set may be subject, the presence of any stray audio- or radio-frequency oscillations is most harmful because they are sure to result in distortion. Consequently, absolute freedom from such distortion is necessary.

The test arrangement for obtaining the over-all audio-frequency characteristics is of particular interest because in one single rapid test it reveals the accumulated effect of the small distortions that may be caused by the various parts of the set or circuit.

This arrangement consists of a perfect miniature broadcasting statio capable of transmitting for test pu poses an unvarying test signal on an desired wave length and modulated a any desired frequency in such a wa that the modulation can be change through the entire audible scale with out altering the degree of modulation or the intensity of the signal.

The set is exactly tuned to thi transmitter and the output of the se is connected to a measuring syste that is the exact equivalent of what a perfect loudspeaker would be if such a perfect mechanism were obtainable.

The modulation of the transmitting wave is then varied through the audible range and the response of the receiving set is recorded. Throughou the test, the transmitter is kept under constant observation by means of a cathode ray oscillograph to make certain that the transmitted wave used in the test is of uniform strength and that the modulation is constant.

Using the figures obtained in thi way, the engineers of the Institute are able to plot a graphic curve which represents a perfect picture of the over-all efficiency of the radio set. It is no a case of forming an *opinion* regarding a set's tone quality, but of determining *facts* by actual measurements.

A 20-page booklet on buying, in stalling and operating a radio outfit that also contains a list of reliable tested equipment, can be secured from Popular Science Institute, 250 Fourth Ave., New York City, for 25 cents.

Popular Science Monthly
GUARANTEE

The above seal on an advertisement indicates that the products referred to have been approved after test by the Popular Science Institute of Standards.

POPULAR SCIENCE MONTHLY guarantees every article of merchandise advertised in its columns. Readers who buy products advertised in POPULAR SCIENCE MONTHLY may expect them to give absolute satisfaction under normal and proper use. Our readers in buying these products are guaranteed this satisfaction by POPULAR SCIENCE MONTHLY. THE PUBLISHERS

When You Switch on Anything Marked

Day-Fan

You Get What You Want!

THAT means just what it says, when you're talking about the Day-Fan Radio, because this year *for the first time in radio history,* these fine receivers get their power through a silent little *motor and a generator* supplied with the receiver! How's that for a great advance? No Batteries! No Eliminators!

Never any worry about "will I get what I want?" Never any worry about run-down equipment. Go away and leave your radio for six months—when you come back switch it on full flood o'power, as easy as your electric fan. Tremendous volume when you want to dance—beautiful quality always.

Day-Fan, the radio receiver used by great broadcasting stations to listen to their own programs (list on request), still stands alone. If you want fine battery powered sets, we make them from $65.00 up. If you want the new light socket AC tube set, we make that too. Whatever you want in radio this year, ask a Day-Fan dealer for it.

The New Day-Fan receivers illustrated are (at top) the Day-Fan Junior, battery operated 6-tube, $65.00; the Motor-Generator powered De Luxe (lower left); and the 6-tube Day-Cee Six (AC Tube set operated from light socket).

RADIOS

FANS

MOTORS



In addition to Radio Receivers as illustrated above, Day-Fan makes the other products shown on this page. These include the popular types of electric fans driven by the powerful Day-Fan motor for long life and efficient service and the small motors themselves, such as are used by prominent manufacturers of electric refrigerators and household appliances.

PREMULGORS Ⓢ

CLEANERS

The Day-Fan line includes also Premulgors, which are motor-driven blenders and emulsifiers for use in drug stores, kitchens, hotels and restaurants, and the famous hand size vacuum cleaner. This handiest of household helpers weighs only three pounds, is the size of a whisk broom, and costs little. It owes its efficiency to the famous Day-Fan motor. Send for circular about it.

The coupon is for your convenience. Fill it out and send it in, or drop a post card

DAY-FAN ELECTRIC COMPANY
DAYTON, OHIO

Send me information regarding the items checked:

☐ Radios ☐ Motors ☐ Vacuum Cleaners ☐ Fans ☐ Premulgors

Name _____

Address _____ P. S. 1

Ⓢ This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Grebe Now Offers

four products of superlative merit—

In the Synchrophase Seven will be found new developments that greatly increase tone, selectivity and distance reception:

A three-point tuning drive, mechanically positive in action, operates the five condensers in unison and maintains the perfection of the factory adjustments; seven tubes—each actually contribute to the production of tone, volume and distance; tube-isolating circuits give greater selectivity, better reception of low waves and nullify oscillation; concealed rigid wiring completely shielded; Binocular Coils are Litz-wound so that high waves are as strong as low ones; one controlling dial.

Cabinet of butt grain walnut with panel in French marquetry of exquisite design and workmanship.

The Synchrophase Five with special features that provide exceptional tone, selectivity and distance; one, two or three dial control at will; power tube operation; Colortone; complete station coverage; Litz-wound Binocular coils.

Grebe 20-20 Cone
$35

The Grebe 20-20 Cone
reproduces with full tone color, the complete range from highest to lowest notes; made 20″ in diameter and 20° angle to prevent internal resonances or paper rattles and to radiate the lower frequencies that give quality reproduction.

The Grebe Socket Power
Type 671
gives dependable "B" and "C" power supply. It is quiet—self-adjusting—durable, shielded and sealed—has ample voltage for 180-volt power tube—for 5 and 6-tube receivers and the Grebe Synchrophase Seven.



Grebe B & C Socket Power
Type 671 *less tube* $50

For full information send for Booklet P

A. H. Grebe & Co., Inc., 109 West 57th St., N. Y. C.
Factory: Richmond Hill, N. Y.
Western Branch: 443 So. San Pedro St., Los Angeles, Calif.

The oldest exclusive radio manufacturer

The GREBE SYNCHROPHASE RADIO
TRADE MARK REG. U.S. PAT. OFF.

Grebe Synchrophase Seven $135

Grebe Synchrophase Five $95

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Popular Science Monthly

FOUNDED 1872 — FIFTY-SIXTH YEAR

SEPTEMBER, 1927 — SUMNER N. BLOSSOM *Editor* — VOL. III, NO. 3

America Takes to the Air

With 600 Aviation Companies Carrying Passengers, 4000 Landing Fields in Operation and 1200 Miles of Lighted Airways under Construction, a New Flying Era Is Beginning

By FRANK PARKER STOCKBRIDGE

I PARKED my car on the edge of the prairie, a dozen miles back from Lake Michigan, and looked at the dashboard clock. It was five-fifteen in the morning and the sun was just struggling through Chicago's dawn. This particular stretch of prairie looked like any of the million square miles lying around in that region, except for the row of sheds that lined its edge, but to me it was the most interesting spot in America. For this was Maywood Field, the heart and center of the United States Air Mail Service. And around this nucleus of the Air Mail, America is just beginning the development of a system of aerial passenger traffic which is already challenging Europe's supremacy in commercial aviation.

Two important things have happened, since the first of last May, to make it a safe prediction that in another year, perhaps sooner, traveling by air will be as popular in the United States as it is today in Europe.

First, the United States Government has gone out of the airmail carrying business.

Secondly the people of America have become at last "air conscious."

If you doubt that last statement, look at your morning paper and count the headlines over aviation news. And the significance of the other fact just cited I shall try to make clear.

There weren't many signs, I'll admit, of any such nation-wide interest in aviation, that morning at Maywood Field. Two or three spectators, like myself, passing the time of day with the mechanics working on planes in the hangars or out in the field. A few postal clerks sorting and sacking mail. A group of keen-eyed, bird-nosed youngsters inspecting the machines in which they were presently to fly to the four winds, or gossiping among themselves and looking forward to the first day of August, the date scheduled for the Post Office Department to turn over the last of its air routes to private contractors.

A big monoplane rolls out of a hangar. The pilot who is to fly it to Detroit at eight o'clock steps in, roars across the prairie and rises for a test spin. The plane which will start for New York at the same hour is still sleeping in its shed. The Detroit flyer lands, and the sound of his engine has hardly ceased before out of the rising sun emerges the black speck of the night mail from New York. Literally, it has come only from Cleveland, this plane which circles now to a perfect landing. It left Cleveland at 2:15 this morning, after taking the mail from another plane which left the East at 9:35 last night.

The pilot from Cleveland is hardly out of the cockpit before another plane is heard, this time from the West. "Here comes Omaha!" cries a mechanic. Husky porters are carrying mail sacks from the New York plane to a waiting Post Office truck and to other planes waiting for their starting signals. The Omaha plane, finishing the last leg of the San-Francisco-Chicago transcontinental route, glides down.

Leaders in America's advance in aviation. Left to right: Charles L. Lawrence, designer of Wright Whirlwind engine which drove three American planes to Europe; Anthony Fokker designer of Fokker monoplane used in flights to North Pole, France and Hawaii; Charles H. Colvin, designer of earth inductor compass which guided sea flyers

THREE planes stand waiting, pilots in their seats, mechanics standing by. Porters dump mail sacks from the new arrivals into each of them. Then, sharp on the dot of five-fifty, all three taxi down the field, rise and wheel away toward their destination—one to St. Louis, another to Kansas City, where another plane will take on the mail it carries for Dallas and intermediate points, and the third for Minneapolis and St. Paul.

That is the daily morning drama of the Air Mail, enacted at Maywood Field with variations and additions ever since May, 1919, when the Government, after a brief experiment with a New York-Washington air mail service in 1918, established the first link of the Transcontinental Airway, from Cleveland to Chicago. Five of the eighteen commercial airways established by the Government center here at Chicago now. And over these eighteen air-

ways, totaling more than 10,000 miles and crossing the country in both directions from coast to coast and from Canada to Mexico and the Gulf, 194 airplanes in the year 1926 flew 4,474,772 miles. In that year these planes carried 433,649 pounds of mail and there was but one mortal accident to all of these planes.

That sort of thing has been going on for eight years, but the public has displayed no great interest in flying until now. The air mail service as such meant nothing to most of the people.

When the Government decided to go no farther in the operation of its own mail planes and contracted with private companies for carrying air mail, as it does with the railroad companies for carrying ordinary mail, passenger transportation by air in America began to look up a little; for the contracting companies carrying mail were permitted to carry passengers and express matter on the same trips. People began to ride with the air mail.

FEW realize that in the year 1926 676,567 passengers paid their fare and were carried in airplanes for longer or shorter rides, in the United States. Besides these 94,353 passengers traveled "dead-head," according to figures compiled by William P. McCracken, Jr., Chief of the Division of Civil Aeronautics of the Department of Commerce, to whom every airplane operator in the United States is now required to report.

The biggest passenger business of the year was done by the line operating between Philadelphia, Washington and Norfolk during the Sesquicentennial Exposition, from July to December. It carried 3,695 passengers in five months. As many others were carried to their destinations all over the United States, along with mail and baggage. The rest of the air passengers in 1926 flew in one or another of the 1,536 commercial planes, operated by approximately 600 individuals or companies, as "taxi" planes, on sightseeing tours, or in exhibition flying, advertising stunts, aerial photography, plant-spraying and so on.

These non-scheduled flights aggregated 18,746,640 miles. Add to that the scheduled flights already mentioned, of 4,474,772 miles, and another 88,940 miles flown on specially-arranged tours, cross-country contests and exploring expeditions, and we have the respectable total of 23,310,352 miles of airplane flights by strictly non-military planes in 1926. And when you add again the 25,133,640 miles flown during the same year by Army, Navy and Marine Corps pilots, making some 48,443,992 miles of flying in the United States in the latest complete calendar twelvemonth, it looks as if America were then pretty well up in the air.

BUT we weren't—as compared with Europe. Aviation is America's own game, but Europe has been beating us at it ever since the war. Only a few months ago, in fact, the outlook for commercial aviation in the United States seemed almost hopeless. The Government had refused to consider a subsidy for flying. Commercial aircraft operators were having difficulty in getting capital and in inducing young men to go into training as airplane pilots. Even the Army and Navy were not getting nearly enough recruits for flying service.

Then Russell Maughan made his coast-to-coast non-stop flight. *That* got newspaper headlines and caused a ripple of subconscious popular interest in flying. Later when Commander Byrd flew across the North Pole the ripple came a little nearer the surface of the public's consciousness.

Then, one day last May, an air mail pilot named Charles Lindbergh casually flew from San Diego to Paris, making short stops en route at St. Louis and New York. *That* made a big splash. People everywhere began to wake up to the possibilities of flying. And when Chamberlin and Levine, and then Byrd and his crew, followed Lindbergh, the whole popular view of aviation in America was changed.

THAT was what I meant when I said that America had at last become air conscious, in the sense that Europe has been air conscious for several years. Instead of nobody wanting to fly, now everybody, broadly speaking, wants to fly.

From all over the country in recent weeks have come announcements indicating the expansion of aviation activities. New air mail routes and airways. Capital coming forward to invest in airplane manufacture and operation. More important than these, the firing of America's youth with the desire to fly like Lindbergh.

That boy did for aviation in America what Mussolini is trying to do for aviation in Italy by offering everybody a free ride in a Government airplane. Mussolini is trying to make the Italian people air conscious; Lindbergh has done that for America. Aviation schools are overwhelmed with applications for instruction. Instead of paragraphs about flying accidents, newspapers print pages of constructive information about the present and future of aviation.

No wonder Secretary Hoover has predicted that before the end of 1927 the commercial aviation mileage flown in the United States may be expected to reach a total within 25,000 miles a month of that being flown in all Europe.

Those figures of passengers carried in American airplanes last year may have seemed impressive, but consider them again for a moment. Out of nearly 750,000 passengers, only about one percent, or around 7,000, went by airplane because they wanted to get somewhere. The other 99 percent flew as a stunt. That has been the American way of looking at aviation; as a rather hazardous stunt, to be indulged in for fifteen minutes or so just to see what the sensation of flying is like. In Europe virtually all passengers fly because they want to get somewhere in a hurry.

Precisely what the Government has done, is doing and has pledged itself to do for the furtherance of commercial aviation has been clearly expressed by Secretary Hoover, in whose Department of Commerce is now vested control of all non-military flying, including the air mail.

"The thing immediately necessary in the development of commercial aviation," said Mr. Hoover, "is airports or terminals which should be provided by the principal



Map drawn by W. Parke Johnson from data supplied by the U. S. Government agencies

This map shows the network of airlines already existing in the United States with those proposed, which within a short time will provide America with an air service that will rival that of Europe—due in a large measure to the advance of interest following the successful transoceanic flights

municipalities in the same way coast cities provide docking facilities. Such suitably equipped landing fields as are necessary will make a city an airport in the same way that docks and shipping facilities make them seaports. Air routes can scarcely be expected unless there is a chain of airports, where supplies, shelter conveniences and storage for mail and express are available. While cities are providing the airports, the Government will be providing the emergency landing fields where needed, mapping the air routes, licensing pilots, supplying air charts, and providing lighthouses for the air, as it does for mariners. These things the Government is now doing, as well as developing forms of direction finding, enabling the maintenance of the service in all sorts of weather.

"We will not develop a passenger service, or even a safe postal and express service, unless we apply such safeguards as are now in force under the law. There must be rigorous inspection of planes and the licensing of pilots must be vested in the Federal Government, as it now is. If you study accidents in the United States you will find that an extraordinarily high percentage of them are the result of planes having been flown that never should have been allowed to leave the ground, or of planes being piloted by incompetent persons. There must be an assurance of rigid inspection and of competent operating personnel if we are to establish confidence in aerial navigation. Every ship that departs from our shores is inspected as to safety of construction and equipment; every officer has been tested as to his efficiency."

Enough progress has already been made toward completion of the program Mr. Hoover outlined to justify the declaration of the Department of Commerce that within a short time the Federal Government will have provided 9300 miles of airways with emergency fields, 7300 miles of these airways lighted and, with Chicago as the hub, connecting twenty cities with a population of 25,000,000.

There are now in existence more than 4000 landing fields in the United States, listed at the Department of Commerce. One thousand of these are included in the "officially approved" classification. Two hundred and seven cities have already provided municipal airports, ninety-three more cities have begun arrangements to provide them.

The difference between an airport and a landing field is largely a matter of equipment and location. (*Continued on page 129*)

Our Amazing World

A Wave of the Hand Starts Steel Mills or Produces Music—Baseball Games at Night—Other Strange Sights

By waving his hands over a remarkable sound producing instrument, M. Termene, French inventor, claims he can reproduce any voice or musical instrument. Sensitive electrical circuits, governing pitch and volume, are affected by the nearness or farness of his hands

Flags and hand signals in the operation of long freight trains will be supplanted by radio if the method illustrated above proves dependable. The engineman is seen communicating with the brakeman in the caboose, more than a mile away. A short-wave transmitter is used. First tests of the apparatus were successful

Seated at his desk in New York City, Judge Elbert H. Gary, U. S. Steel Corporation chief (left), recently set in motion new steel mills near Pittsburgh, Pa., simply by moving his hand above a silver-lined glass sphere. This released a minute electrical charge from a sensitive "grid-glow" tube. By radio relay this charge controlled the distant machinery

Wearing special diving helmet and bathing suit, William Beebe, noted naturalist-explorer, recently jotted down on a zinc plate his observations while thirty feet under the sea near Port-au-Prince, Haiti

"Get close to the soil and never grow old," says Charles M. Schwab, Bethlehem Steel Corporation head, shown here practicing as he preaches, on his 1200-acre Pennsylvania farm. The magnate is tilling the land with a tractor, as he plans to do much of the time while he makes the country place his chief residence. "Immergrun," as it is called, has blooded livestock, gardens and golf links and much of the land is under cultivation

Night-time baseball games are an innovation among employes of an electrical company at Lynn., Mass. Seventy-two flood lights on fifty-foot poles make the diamond as light as day



All the armor in this new car for banks is charged with electricity, hence the danger sign. The guard's swivel turret, with machine gun, has bulletproof windows. The tires have sponge tubes and cannot be punctured by bullets



This is a hand, raised as in benediction, of the gigantic cement statue of Christ being made by Paul Landowski, Parisian sculptor, to be erected on Mount Corcavado, overlooking Rio de Janeiro

The giant locomotive and its "pup," shown with it, are the "Flying Scotsman," famous on the London and North Eastern Railway, and a miniature of it, built for a narrow-gage line in Kent. The big fellow weighs 150 tons; the other weighs only eight. The "pup" is about a third of the "daddy's" size

The gentleman on the right, photographed with a white visitor in Papua, has been acclaimed the smallest grandfather in the world. He is a pygmy, although his race are not dwarfs and some are unusually tall

Enough telephone apparatus for an office building was put in the Summer White House in South Dakota to keep President Coolidge in touch with Washington and the nation. Girls in the Chicago plant of the Western Electric Company are seen at right, checking out some of the great bulk of equipment needed

Schedule Or—

Skill and Pride on Trial as the Limited Thunders in the Race against Time

By

LEO F. CREAGAN

Illustrated by H. M. D. Rundle

Marley, slumping on the fireman's seatbox, wrestled with the tremendous problem

NEWS of the appointment of Barnard Sylvester as executive director of transportation of the Atlantic and Pacific Railroad reached Daniel Marley in his office at Kingston Junction a moment after the superintendent's arrival for the day. A Montreal newspaper, heavily blue-penciled where the item appeared, caught his eye before he had time to indulge in his morning ritual of toying with the row of push buttons on his desk. As he read and reread the announcement he was conscious of a feeling of distinct apprehension.

Now, in ordinary circumstances the addition of one more name to a railroad's official roster would have had little effect upon the personnel, particularly to a man like Marley who, by the sheer force of his dynamic personality, had forged his way in five years from a lowly place as "King Snipe" of a track gang to a superintendent's fine chair. But Marley had not forgotten the bitter humiliation attending a forced resignation two years before. No matter if subsequent events had returned him to his former place of grandeur; he could not forget that a temporary change in the management high up had brought about his official downfall and had woefully wounded his pride. And the man who had literally wrung his resignation as superintendent from him had been a stranger like this Barnard Sylvester person, one who could not know of the part he had played in building and maintaining what he fondly believed to be the finest link in Canada's transcontinental railroad chain. Thus it might happen again, for Sylvester's coming had been as sudden and as secret as that of his predecessor two years before.

Marley stared at the paper with glazed eyes, but the words came to him clearly. Mr. Sylvester was no stranger to the people of Montreal, it read. He had come from the P. & C., a road reputed to be the Atlantic and Pacific's strongest competitor for western business, and the newspaper hinted at important developments in the near future. To Marley, alone in his office, the promised developments could have but one meaning—his resignation. So certain of it was he, that he felt the future would be too long to wait for the dreaded news. "An' what is an execootive director of transportation?" he asked, when General Manager Lemuel C. McCutcheon answered his long distance telephone call.

"OH, HELLO, that you, Daniel?" McCutcheon's voice sounded friendly and almost reassuring. "An executive director of transportation, if you refer to Sylvester's appointment, is a high sounding title meant to fit the fancy salary we are paying him."

"An' is he to be me boss?" the superintendent inquired suspiciously.

"Not directly, Daniel," the Montreal official replied. "Of course, he will have certain authority over all departments, but Mr. Sylvester is a traffic man. How's everything on the road this morning?"

"An' how should I be knowin', whin the first thing I see whin I open me door is an announcement of an execootive somethin' er other?"

McCutcheon's hearty laugh served only to increase the hurt of Marley's wounded feelings.

"No need for you to bother your head about Sylvester," said McCutcheon. "I'll have some conversation with you about him the first time I see you. So long, Daniel."

Keen disappointment shone in Marley's deep-set blue eyes as he pushed the telephone from him. McCutcheon had withheld the information he sought. It would have been kinder had he spoken at once. Better to know the worst than to undergo the agony of suspense.

Gloomily he turned to the business of superintending the affairs of the Ontario division. With a deliberation new to him, he performed each act as if it were his last one. Something told him that when the blow came it would descend with a suddenness that would afford little time for changing decisions.

IT WAS while he was in this dismal frame of mind that the telegram from Barnard Sylvester came, a message courteously worded but clearly mandatory in intent, inviting the superintendent to meet the executive director of transportation in Montreal two days later to accompany him over the Ontario division.

Marley's eyes flashed and his hands became fists.

"Be gar, 'tis a personal job o' liftin' the pin on me official office the mutt be doin'!" he remarked as grimly he set about clearing the accumulation of two years from the pigeonholes of his desk.

When General Manager McCutcheon had confirmed the report of the coming of Sylvester to the A. & P., he had no idea of the storm he was stirring in Superintendent Marley's soul. It would have been all the same in any event. Not that McCutcheon would deliberately hurt Marley. On the contrary, he had the warmest admiration for his superintendent. But, truth to tell, Barnard Sylvester had been forced upon the general manager by Sir Samuel Van Cleve, a new and highly influential member of the board of directors.

Van Cleve was partly right in his belief that the A. & P. needed a man of Sylvester's reputed traffic ability. The inauguration of extra-fare passenger train service a month hence was an epoch-making event in railway circles, and it was no secret that McCutcheon did not favor the addition of a new train in each direction between Montreal and Chicago. Overruled

"Well, Marley," said Sylvester, "it's up to you. If there's a failure tonight it'll be a man failure—one you'll have to answer for"

by the U. & C., his western connection at the International border, McCutcheon had been forced to accede to their demand that new service become effective November first. And in much the same manner was McCutcheon forced to announce the appointment of the man to supply the enthusiasm for the new project, enthusiasm which Van Cleve believed the general manager lacked.

Thus it happened that Daniel Marley, without sufficient cause, had worked himself up to the point of assault and battery, and as he waited for the object of his spleen, that fine October morning, his weather-tanned face was set in grim lines. Prepared to despise the man at sight, Marley found a hard beginning in Sylvester's gripping handshake and the seeming gladness reflected in his dark eyes.

"I've been hearing about you, Marley," Sylvester smiled, and motioned the superintendent to a chair in his private car.

"'Tis nothin' else ye could be doin' if ye ever worked annyplace in the Dominion," Marley naïvely remarked.

Sylvester laughed and held an open cigar case before his guest.

"WONDERFUL railroad we have," he remarked as the train drew away from Bonaventure Station. "Understand you helped build it."

"That I did, sir." Marley expelled cigar smoke like a volcano. "Wit' me own hands I drive the first spike whin some o' the links in the west is started, an' whin it was finished I drive the last one."

"Well, that was quite an honor, being selected to drive the first and last spikes. Who gave it to you?"

"'Twas me own self which had the givin'," he declared, "so I select the man that's handiest with a spike maul, fer the job, which is meself. They call me 'Mile-a-day Marley' in thim days, because I lay me mile o' rails ivver' day."

"Then you selected the right man," Sylvester smiled approvingly, "and I suppose the track will be good for our new extra-fare train, the Frontier Special?"

"It will that."

"Fine. We have the track, that's the important thing. Then the new equipment and engines should be here in a—"

"Ingines?" questioned Marley. "Is it some ingines we be gettin'?"

"Yes, we are advertising new equipment from engine pilot to observation platform; everything to be lettered "Frontier Special"—even the engine tanks."

"But, Mr. Sylvester, sir, ingines is not built in a couple o' weeks."

"I know." Sylvester smiled knowingly. "I had to do a little second-story work to get them. Incidentally, I had to spend considerable A. & P. Railroad money to induce a railroad and a locomotive builder in the States to part with six engines that had been built for another line. Here's the design," he handed Marley a blueprint, "and here's a picture of the finished product. Aren't they beauties?"

For several minutes the superintendent studied design and photograph. A shadow of annoyance passed over his face as he returned them to the other official.

"An' have ye already boughten thim, an' paid—"

"Contracted for them, yes," Sylvester admitted. "Why? Don't you like the looks of them?"

"The looks is fine," Marley declared, "but 'tis white elephants we'll be a havin' on our hands."

"White elephants!" Sylvester elevated his eyebrows. "Just what do you mean, Mr. Marley?"

"The dimensions of the wheels—too low for high speed. Isn't it a seven-hour schedule ye wish to make wit' the new—"

"Yes, but don't worry about those engines not being able to run," Sylvester smiled. "I rode one of them at fifty-five miles an hour for a short distance not—"

Marley grinned reproachfully.

"Maybe fer a short distance they can, but like a fat man—"

"Pardon me, Mr. Marley," Sylvester interrupted icily, "the engines will be here in a couple of weeks. We'll use them on the new trains."

It was a thoughtful Marley that bade good-bye to Mr. Sylvester late that afternoon. The cloud in his sky had already begun taking form. The smiling Mr. Sylvester would personally deliver into his hands the tool with which he must work his own undoing: a tool in the form of a giant locomotive unsuited to pull the extra-fare trains.

Ten days later the engines were reported in the yards at Montreal. Calling together his mechanical staff, Marley boarded the first train for the East. Arriving at the outer yards he learned there had been a delay in bringing the engines across the St. Lawrence River. This was due, he was told, to the breadth of the super-locomotives, which necessitated taking measurements in order to determine whether their great pouter-pigeon steam chests would clear certain structures. At noon the engines arrived, and the afternoon was spent in firing them up, inspecting and lubricating them for the trial runs.

For a week the tests went on. With a short train of freight cars loaded to the approximate weight of the new passenger trains, Marley and his mechanical assistants thundered up and down the Ontario division. It was a discouraging business, for it forced upon the superintendent a disagreeable duty, one that he felt would only hasten the inevitable call for his resignation. But truth would have no other. Gladly would he have admitted that the design and photograph had deceived him. He knew they had not. Reluctantly he admitted that the engines were impressively designed and capable of hauling heavy tonnage on a mountain grade, but he was prepared to prove by actual tests that they were not built for high speed.

WHEN Marley told McCutcheon the engines could not make the time with the extra-fare trains, the general manager uttered a half-suppressed chuckle and sent for Sylvester. The executive director of transportation came, cordiality in his eyes and warmth in the enthusiastic handclasp he gave Marley.

"Well, how are the new engines testing out?" he asked.

"Sure, Mr. Sylvester, sir," Marley hesitated, "'tis me that hates to tell ye, but thim engines reminds me more an' more o' some sacred oxes which I onct see in the zoo."

Sylvester threw back his head and laughed heartily.

"So you've changed them from white elephants to sacred oxen, have you, Marley?"

"I have, an' sorry I be to say the wurrds. We must use our

old ingines on the new trains," he announced firmly.

"No, we can't do that, Marley," Sylvester frowned. "We've advertised the new engines and we'll use them. If your men are afraid to run them, I'll have the factory send—"

"Divil a bit is me min afraid!" Marley cried. "But, Mr. Sylvester, sir, the ingines, they can't make the time."

"Yes, they can make the time, and they must."

SYLVESTER turned to the general manager.

"If that's all you wish to see me about, I'll be going. I'm due at the Algonquin Golf Course right now."

Sylvester smiled his way out. Marley sat staring at McCutcheon. The general manager saw the mute appeal in Marley's gaze and he drummed on the table with his fingers.

"You've heard the saying, Daniel—'power behind the throne'— haven't you?" He forced a smile.

"But I be tellin' ye, Mr. McCutcheon, thim ingines—"

"I know, I know," McCutcheon interrupted testily, "but Sylvester is handling that. I've agreed to let him do it. I've agreed to a number of things recently that I don't particularly favor but—"

"Be gar, if I was gineral manager," Marley started to protest, but the look in the other man's face stopped him.

"Take my advice, Daniel," McCutcheon said in a tired voice, "don't antagonize Sylvester. Go the limit for him—as you have always done for me."

It was a perplexed Marley that started toward the elevator. Just what had McCutcheon meant by "power behind the throne"? And "go the limit" for a man that . . . Could it be that McCutcheon . . . ?

November first dawned cold and rainy. In his private car in the outer yards in Montreal, Marley woke to a day which promised only dire disaster. If Sylvester were only out of the way, he reflected, what a day it could be! Then he could use his splendid high-wheeled engines on the new trains; engines that already had more than a year's flawless service behind them, instead of Sylvester's expensive misfits.

The temptation to defy Sylvester had been in his mind for a week. He had only played with the idea. Marley knew he could not afford to run counter to the will of his superior officer—without the general manager's approval. And McCutcheon's significant warning that he go the limit for the other man had crossed his mind countless times since that last interview. Well, he knew that the path of wisdom led away from anything designed to confound the new official. And what was infinitely worse, he knew that that path led to certain failure, for tonight the new train service was to be inaugurated.

NOW, failure of any kind was a thing apart from the stuff that generated Marley's life. To fail with the eyes of the railroad world upon him, to go limping into Toronto hours late with a fine new train, a train whose only excuse for existence was the guarantee of "on time" service in return for the extra fare charged, this was a bitter thought. And what rendered the situation almost unbearable was the knowledge that the failure which hung like a terrible specter before his eyes need not occur. For the A. & P. Railroad had capable engines idling in its roundhouses, engines specially built for high speed, any one of which could easily make a whip-cracker out of the "Frontier Special."

"If Mr. McCutcheon only l'ave me tell him that Sylvester's greener than a goose about railroadin'," he muttered, a hard light in his eyes.

In spite of his worries, Marley breakfasted well, and donning a long raincoat, set out across the network of rain-swept yard tracks for the roundhouse. Inside the great barrackslike building the first object to meet his eyes was one of the new engines undergoing final touches for the night run. In the next stall stood its mate, handsome in appearance but wholly deficient in the speed-producing qualities needed to maintain a fifty-mile-an-hour schedule across the Ontario division.



As the "Frontier Special" rumbled through Kingston Junction, Marley leaned out and hooked his arm through the train order hoop held aloft by the operator

With a grunt of disgust Marley passed on to another part of the shop where painters were at work on the tender of an engine that was the pride of his heart—the great 951. His eyes lighted as they fondly rested upon drivewheels as high as his own head and upon the towering symmetrical boiler to which was coupled a long cylindrical tender.

"Be gar, if I could use the 951 on the "Frontier Special" this night," he muttered, "'twould be—"

He stopped short and stood staring at the engine. Then, in a moment, his jaws snapped and, swinging about, he hurried to the master mechanic's office.

An hour later Marley's private car, drawn by engine 951, slipped out of the yards, headed for the west. And at about the same hour, a full sister of the 951 was speeding eastward from Toronto, each in obedience to Marley's command, bound whither only the train dispatcher at Kingston Junction knew.

THE waiting rooms and ramps at the Bonaventure Station in Montreal were jammed with an eager crowd long before nine o'clock, the hour set for the westward departure of the A. & P.'s extra-fare train. On track Number 11 the train stood, colorful and splendid in brilliantly lighted equipment and newly uniformed crews, the finest product of car-building art.

Railway officials jostled newspaper and picture men and happy passengers followed grinning porters struggling with new luggage through the crowds.

McCutcheon and a group of passenger department men stood near the observation car, to which car was hung a large round marker bearing in rose-colored lights: "Frontier Special."

At the front of the train Marley paced and, with a look of disgust on his face, watched Sylvester posing for the picture men. One hand resting on the shoulder of the engineer and the other touching the great steam chest of the locomotive, the executive director of transportation smiled into the camera while a flashlight was made. Then, observing Marley, he beckoned the superintendent to his side.

"Well, Marley," said Sylvester, losing his smile for a moment, "it's up to you. As I've told you, we have the track, the engine—everything. If there's a failure tonight, it'll be a man failure, one that you'll have to answer for."

Marley's face flushed and his lips moved to reply, but no words came. A blind rage possessed him, a fury that sent his blood surging through him. He wanted to throttle the man, to choke and throw him aside as he had subdued drunken mule skinners back in his track-building days. Something within held him, and wordlessly he turned to seek out McCutcheon.

The train was about ready to start when the general manager felt a hand tugging his sleeve.

"Oh, hello, Daniel," he smiled dryly. "Everything lined up for on-time performance tonight?"

(Continued on page 18)

Our Sun Is Shrinking!

Reduces 800 Miles in Three Years; Strange Flickerings Upset the Weather and Radio

By ARTHUR A. STUART



Reading instruments at the solar observatory on Mt. Brukkaros, Southwest Africa. One is a thermometer that records a millionth of a degree. Left: Observer reading a thermometer housed to protect it from storms at the Table Mountain station, California

YOUR radio set picks up a distant station you never heard before. The barometer outside your window jumps to "Fair"; another 300 miles away suddenly indicates "Rain." A swarm of mosquitoes buzzes about your screens. These would seem to be a set of unrelated coincidences. Yet all have sprung from the same cause—the sun has slacked up momentarily on its job of supplying the earth with heat and light.

Startling new discoveries that link up the sun's brilliance, sunspots, the weather, and radio have just been announced by Dr. C. G. Abbot, of the Smithsonian Institution at Washington, D. C. They are the achievement of the men who have watched the sun daily from the observation stations that the Smithsonian Institution maintains at scattered points on the globe—at Table Mountain, California, in the desert at Calama, Chile, and on desolate Mt. Brukkaros in Southwest Africa.



W. H. Hoover, director of the Smithsonian Institution's Mt. Brukkaros station, making measurements of the sun's radiation. Notice the observers' hut at left

WHEN the sun "flickers" from day to day, they have just discovered, so does weather change and radio misbehave. Sunspots, too—the mysterious magnetic whirlpools on the sun's face—appear and disappear with these flickerings. And the biggest solar commotions occur every twenty-two months—well within the eleven-year "sunspot cycle" already known. This means that in a little less than two years today's weather is likely to repeat itself.

Long-distance weather forecasting soon may follow. Already Dr. Dayton C. Miller, noted astronomer and physicist who invented the machine that compared weather and sun records to help make these discoveries, has used the machine to make startlingly accurate solar predictions. The Chile observatory reports his predictions fulfilled. H. H. Clayton, weather forecaster for the Argentine Government, has been using the Smithsonian reports of the sun's flickering to prepare weather predictions a week in advance. Sold to Argentine farmers and business men, they have proved strikingly accurate.

Fast as we are learning how the sun behaves, the "why" of it is still a mystery. Where does the sun's unending heat come from? What caused the sunspots blamed for the torrential rains that recently flooded Berlin and started a mosquito plague? Or the others that deranged this country's telegraph lines last April?

Down where the sun's heat comes from, in its incandescent interior, is some dense substance twelve times as heavy as the radioactive metal, uranium—that has the heaviest atoms known on earth. Either it is a new substance of monster atoms, as Dr. J. H. Jeans, English astronomer, now suggests, or it is a mixture of familiar gases under such terrific heat and pressure that their molecules are "squashed" into an amazing "gas" thicker than water. The latter is the belief of Dr. Abbot.

Huge atoms, says Dr. Jeans, are continually breaking down like radium and loosing the energy that the sun hurls toward us. Could these be "coronium," a new element found on the sun by eclipse observers? Dr. Abbot says the opposite may be true. Perhaps, he suggests, small atoms are combining and sacrificing some of their mass as electric energy. This might explain the discovery by Prof. Giuseppe Armellini, Italian astronomer, that the sun has shrunk more than eight hundred miles in diameter since 1924. It waxes and wanes in size, and every time it gets smaller sunspots increase.

At present the sun is having an unusually severe epidemic of sunspots, presaging strange weather and freak electric storms. The sun's corona, always more striking at a time of many sunspots, was unusually intense during the eclipse last June. At Giggleswick, England, a wind blew away heavy clouds three minutes before the total eclipse, and permitted the party of Sir Frank Dyson, astronomer royal, to make observations of inestimable value, using a forty-five-foot camera to photograph the vivid corona.

Could Air Invaders Destroy Us?

Ruin of Great Cities by 4000-Plane Armada Made Possible by Progress of Ocean Flight

By CALEB JOHNSON

THREE airplanes have just flown across the Atlantic. Another has crossed the Pacific, from San Francisco to Honolulu. By the time this appears in print another half dozen transoceanic flights may have been made. Which raises the question: If four, why not four thousand?

The flight to Hawaii was a military demonstration. It proved that military airplanes can cross 2400 miles of water and find their destination by the unaided use of their own instruments, even when their mark is so small a speck on the earth's surface as the Hawaiian Islands.

It is apparent from these latest flying feats that something has happened since the President's aircraft board was asked eighteen months ago to solve this puzzle: "Is the United States in danger by air attack from any potential enemy of menacing strength?"

"Our answer to this question is no," said the board, after examining ninety-nine experts; but it qualified the "no."

"This conclusion is based on the facts *as they now are*," said the board. "No airplane capable of making a transoceanic flight to our country with a useful military load, and of returning to safety, is now in existence."

THAT last statement is still true. Why worry? What has happened?

Just this. These recent feats have proved that aviation is not standing still. They have brought forcibly home the fact that in the nine years since the war ended flying has progressed farther than in the dozen years before, when men were just learning to fly. At the same rate, the "facts as they now are" will be as obsolete nine years from now as the facts when the war ended are obsolete today.

The highly developed monoplane and the radial engine are the outstanding advances since the war—those and the earth inductor compass. But these are by no means the last word in aviation. It is a practical certainty that the next nine years will see the development of planes and engines "capable of making a transoceanic flight to our country with a useful military load."

It is easy to say that nobody will want to invade us. It is also foolish.

What would happen if such an attack were made?

POSSIBLY the first news of such an invasion would come from ships at sea, reporting by radio a huge flock of planes flying toward America. The enemy would rely upon engine power and luck, and allow for losing a quarter or more of his forces by storm or accident.

Four thousand planes might well constitute this aerial armada. Two thousand would be multimotored bombers, battleships of the air. Monoplanes—or, possibly, sesquiplanes—with a wing spread approaching 200 feet, engines delivering 2000 horsepower, capable of flight at an altitude of 10,000 feet and a speed of 120 miles an hour. They would weigh, perhaps, 30,000 pounds when loaded.

Half the weight would be the plane itself. Another third would be fuel, 1750 gallons of gasoline, weighing five and three fourths pounds to the gallon, sufficient at a gas consumption of five miles to the gallon to give a cruising range of 8450 miles. If that seems absurd, consider Lindbergh's mileage of more than nine miles to the gallon, carrying eight pounds more weight per horse-power!

FIVE thousand pounds of bombs and crew account for the rest of the weight. Allowing six men to the crew, there would be room for two tons or more of "eggs." Two thousand tons of



The drawing on these pages is our artist's conception of the annihilation of a great city such as New York or Chicago by an armada of airplanes, blackening the sky with their numbers, toppling buildings with a rain of thousands of explosive bombs and killing the populace in hundreds of thousands with a deluge of deadly gas

high explosive bombs would be more than enough to destroy the essential nerve-centers of our nation. The enemy could lose three fourths of his battle fleet on the way and still have munitions left to paralyze the heart of America.

Flying in triangular formation, like a huge flock of geese, this bombing fleet would cover more than a hundred square miles of sky. Ahead of the bombers would be the scout cruisers of the air, a thousand two-seater observation planes. Each would carry 500 bombs, charged with poison gas far deadlier than anything yet used in war. And above the observation planes would be the third unit, the high-speed pursuit planes, swift single-seaters ready to go into action the instant our aerial defenders should appear on the scene.

An attack by airplanes would be all the enemy would really fear. While artillery and naval experts believe anti-aircraft guns have been or soon will be made effective weapons, experienced air fighters ridicule the idea that "archies" can ever be a serious menace. Not more than a dozen hits were made against such huge targets as Zeppelins, by the British anti-aircraft guns, in all of the 107 Zeppelin raids over Great Britain during the last war. And many of these hits did not bring down the airships.

Draw a triangle on the map of the United States, with its angles at Boston, Minneapolis and Atlanta, and you have included in its area most of the nation's wealth, industries, important railroad centers, seaports, electric power sources and population. At this heart of America the enemy would strike with high explosive bombs and poison gas to destroy railroad terminals, industrial plants, water supplies, electric power systems, shipping and docks, telegraph and telephone centers and financial institutions.

The enemy would divide his fleet into squadrons, to make practically simultaneous attacks upon widely separated points. Destruction of Chicago's rail terminals would practically cut off transportation between east and northwest. The great steel works of South Chicago and Gary might be wrecked. One plane could cut off Chicago's water supply by blowing up two pumping stations.

Similar tactics would be employed at the other Great Lakes cities, Detroit, Cleveland and Buffalo. At Detroit the automobile plants would be destroyed.

NEW YORK would be the focus of the enemy's most intensive efforts, and chaos would prevail should the enemy succeed. To cut off New York completely by rail it would be necessary only to wreck the ferry terminals, destroy the Pennsylvania tunnel and demolish the three bridges which give rail communication northward. The wreck of Hell Gate Bridge would form an effectual blockade to Long Island Sound navigation. Less than a ton of gas dropped at each end of the Pennsylvania tunnel would prevent its use for weeks.

Explosive bombs could destroy the largest ships in New York harbor and shatter power houses, throwing the city into darkness and tying up transit lines. Tall buildings in the downtown section might be shattered to paralyze the financial machinery of the nation.

Sixteen tons of gas, according to experts, can destroy all life in an area of a square mile. Doubtless there will be improvements in gas as well as in airplanes before such a series of events as we are discussing here could take place.

Tens of thousands might perish in the panic of the first gas alarm should the attack come during business hours. It takes nearly two hours to empty the skyscrapers of lower New York of their workers. Statisticians have estimated that if all of the persons employed south of Fulton Street should leave the buildings at once they would fill the streets of downtown Manhattan three deep! The struggle to leave all at once would crush thousands to death in stairways and elevators.

New York is never provisioned for more than ten days; the outlying districts are seldom more than that ahead of starvation. With the main food supplies destroyed or inaccessible, famine would quickly prevail.

A horrible picture? Yes; but a possible one. Not probable, but possible.

It goes without saying that no nation today is able to attack the United States by air. On the whole, the military and naval air power of the United States equals that of most other great powers and is superior to that of many. But there are differences of opinion. The President's aircraft board reported that the figures of our Army's airplane strength ranged all the way from 34 planes to 1396! Somewhere in between is the truth about our effective fighting air force.

And if some nation should resolve to bring America to its knees, some time in the future, with airplanes developed as far beyond those of today as those of today are ahead of 1918, what has been pictured could happen, and possibly would happen unless our country were prepared for war in the air.

How Animals Make Love

Zoölogists Watch Insects Woo by Gifts, Perfumes and Mad Dances—Queer Courtships of Birds and Crocodiles

By ELWELL CRISSEY

WHEN a young man gives his best girl a bouquet or a box of candy to show his affection, is he making love as only mankind knows how, or is a similar courtship practiced by the animals, birds and insects?

Professor Julian Sorell Huxley, of Oxford University, started a vigorous debate among naturalists recently when he told the British Association for the Advancement of Science that he had seen lowly forms of animal life dance, sing, pose, and give presents, as part of complicated love affairs.

In many ways these courtships are astonishingly like human conduct. Some insects Professor Huxley told about use delicate flower and fruit perfumes to make themselves appealing. It has been known for some time that many birds and animals, and even some reptiles, sing love songs to their mates. And dancing is a favorite way among the insects of showing deep affection.

A typical courtship in wild bird life. The male peacock pheasant spreads his gorgeous plumage to attract his modestly attired lady-love; apparently she pays little attention. Among nearly all species of bird and animal life the males display decorative coloring, while the females are drab and inconspicuous

FOR example, observe the two kinds of spiders, the hunters that prowl around and capture their prey, and the web-spinners that wait in ambush for their victims. These two varieties, Professor Huxley says, do their love-making very differently, because the latter kind are almost blind. He described how he had watched the male hunters go through a series of complicated dances in front of their sweethearts. On approaching his mate, one lover was seen to hump himself up on one side and crouch down on the other by doubling up his legs. In this ridiculous posture he sidled rapidly around in front of Miss Spider, and then suddenly reversed and went the other way. He circled nearer and nearer. At last, apparently won by the demonstration, she rushed toward him. The swain held her off by his forelegs, slowly retreated, and started circling all over again. More than 100 circles were counted before the two joined for a last mad whirl, round and round in one spot. Some of these waltzing spiders are decorated with bright spots of color.

BECAUSE the web-spinners are practically blind, they have to express their love by other ways than dancing. Professor Huxley contrasted their subtle methods with the wild display of the hunters. The web-spinner comes up to the web of his ladylove, much as any modern Romeo might come to the balcony of his Juliet. Instead of strumming a ukulele, though, he strokes a thread of the net, setting up peculiar vibrations which the lady spider recognizes as different from the agitation a fly causes when entangled in the net. This cautious announcement is quite necessary, too, otherwise the vicious lady might mistake her lover for a stranger and eat him! Among some varieties she does this anyway, after mating.

One kind of hunting spider entices his mate by offering her a choice fly neatly wrapped in silk. This same instinct of giving presents, which figures so largely in human courtship, appears also in the carnivorous flies, *empidae*. The male of this species makes a flower bouquet for his love. First he blows up a ball of bubbles from a viscous fluid which he secretes, then he attaches it to his legs, and sticks a flower petal or a little leaf in it. Describing this peculiarity, Professor Huxley stated, "Here, in quite a different evolutionary line from our own, we find quite definitely the employment of a nonutilitarian present, as gift from male to female." Some other varieties of this fly make their gifts useful, though, by tucking a morsel of food instead of a flower into the balloon.

BUTTERFLIES and moths shame all other creatures in the gorgeousness of their colors, and yet, strange to say, they do not use color to make themselves attractive to their own kind, but employ perfumery. The white powder on the wings of the male garden white butterfly smells delicately of balsam or lemon. Some butterflies have even rose perfume, and the magnificent Brazilian varieties carry still heavier odors. This appeal to smell is used by other lovers, too, as we shall see presently.

Man is by no means the only creature that woos by serenades. The insects have no lungs, of course, so cannot sing. But jarflies, crickets, and grasshoppers send their love calls far and wide by loudly fiddling their wings over their legs. Anyone who has lived in the country during a hot summer has heard the monotonous, pulsating song of the frogs and toads. Usually these noises are merely vocal advertisements, which broadcast the presence of the males, but Dr. C. M. Breder, Jr., of the New York City Aquarium, tells of one frog courtship, which was won entirely by the bullfrog's fine bass voice.

A BIG frog was bellowing on the edge of a pond, he says, when a female approached and paused in interest. The bullfrog stopped singing and almost immediately saw Miss Frog start hopping off towards other serenaders near by. The jilted one appeared disappointed, and started after her, but seeing that she paid him no more attention, returned to his bower and started singing louder than ever. The fickle one stopped, listened, and seemingly made mental comparisons, then hopped back to her first choice.

"Crocodile tears" long has been a synonym for make-believe sympathy—laughed at because it seemed impossible to conceive of crocodiles showing any delicate emotions. And yet we are now told by naturalists that the homely crocodile shows a greater ecstasy in his love-making than possibly any other creature. When showing off before the idol of his heart, young Mr. Crocodile puffs himself up almost to the bursting point, then raises his head and tail high in the air and twirls himself around in the shallow water, churning *(Continued on page 140)*

Digging a drainage ditch with dynamite. Tons of earth are flung high, instantly completing a job that otherwise would require several weeks

A ditch dug by dynamite at Tyler, Tex., to drain low marshland in a campaign to destroy mosquitoes and fight malaria and other diseases

Blasts *That* Saved *a* City

Wonderful New Uses for Dynamite, the Giant That Tames Floods, Digs Tunnels, Topples Cliffs and Catches Whales

By
ORVILLE H. KNEEN

WEEKS of heavy and widespread rains over forty-one per cent of the country's area had swelled the Mississippi to a deluge. Half a million people had lost their homes, crops and businesses. As the crest approached the great port of New Orleans, La., all records were topped, until the waves lapped over the levees. Behind 106 miles of dikes another half million citizens trembled at the thought of a crevasse which might inundate 30,000 square miles of basin, lying ten to twenty feet below the levees. To John Klorer, levee engineer, they gave "plenary powers to do all things necessary and requisite" for the city's safety. He decided to relieve the pressure of flood waters by opening the main levee at Poydras, a few miles below the city.

WITH seaplanes circling and patrol boats and guardsmen clearing a three-mile zone, a diver placed three quarters of a ton of dynamite in forty-eight holes in the levee, and fired. A trickle of muddy water seeped through. Other shots were placed. Swiftly the current eroded the crevasse, until it roared through a 3,000-foot opening, sweeping across fertile lands to Breton Sound. Above the break the river stayed level, then lowered two and a half feet. At a cost of $15,000, thirty-five tons of dynamite saved the city. The millions to be paid the owners of inundated lands will be only a fraction of the loss that would have been suffered had the torrents made their own opening. Hundreds of lives and millions of dollars were saved by the only force which could break the mighty dams.

To learn more about the uses of this wonderful agent of force, I went recently to the men who produce it.

"Modern high explosives," said Col. George G. King, President of the Institute of Makers of Explosives, "can force a way through any obstacle Nature has erected. American industry is using explosives in ways undreamed of a few years ago. Blasting powder and dynamite are used to mine coal. The metals in your telephone, iron, copper, lead, and others, all are blown from the ground. The buildings, tools and machines of our daily lives depend upon explosives to get iron ore for steel, rock from which cement is made, lead for paints. Even ice cream is cheaper because dynamite blasts out rock salt used in its freezing. Without explosives, industries as we know them would come instantly to an end."



A perfectly planned dynamite blast at an electric power plant in Baltimore, Md., brings down a towering smokestack without doing the least damage to costly buildings near by

So powerful are these modern genii compressed in the little orange-colored cartridges, I learned, that they have even brought oceans together. Fifty million pounds of dynamite, laid in holes which together, end to end, would have reached three times through the earth, opened a passage through Culebra Cut in the Panama Canal.

THE explosive nitroglycerin was discovered in 1846. In 1863 Alfred Nobel made liquid nitroglycerin into safe dynamite, by adding an inert substance, keiselguhr. For sixty-four years dynamite has moved the earth and the waters thereof, that man might build skyscrapers and dams, canals and channels, ports, highways, railroads, subways —even kill mosquitoes and whales! The story of dynamite has no counterpart in the realm of chemistry, engineering, or romance.

In the last twenty years Samuel R. Russell, senior technical expert for the du Pont company, has shot more than 6,000,000 pounds of dynamite—probably more than any other man in the world. He has never failed on a job. He told me how dynamite recently tamed the Arkansas River at Pueblo, Colorado.

"Cloudbursts and rapid melting of mountain snows caused the river to leap its banks. It flooded the city fourteen feet deep in places, and enormous jams of rocks, logs, mud and debris began to pile up the water over miles of lowlands. Scores were drowned and more than $10,000,000 damage had been done when men hurled sticks of dynamite, with wires attached, into the midst of the jams and so saved further loss.

"Pueblo wanted no more such floods. With the aid of dynamite again, a new



Sculptors dynamiting rough outlines of the heads of Jefferson Davis and Stonewall Jackson for the Confederate memorial on the face of Stone Mountain, Ga.

channel for the river was cut straight through the city, 250 feet wide and deep enough to carry off twice the maximum flood waters. More than a million cubic yards of rock and earth were blasted out, much of it within a few feet of dwellings, without injury or damage. A barrier dam was erected six miles above the city. The irresistible force of water was curbed by the even greater force of dynamite!"

Every spring northern rivers hurl enormous blocks of ice against piers, bridges, boats and power houses. But wherever the jam is thickest has become the place for a gelatin-dynamite party. This shattering explosive is waterproof, and will sink. Once when an ice jam in the great Niagara Falls gorge was blasted, about 2700 pounds of dynamite was fired in two charges. That was an extreme case, the ice being seventy feet high. One bad winter, I was told, the fishing village of Stonington, Maine, located on an island, was saved from starvation when dynamiters mounted a huge ice jam and cut a channel for relief boats.

EXPLOSIVES will tear apart iron, steel or masonry as readily as will cold chisel and hammer, pick, sledge or crowbar—and more effectively. A cast-iron pulley wheel, weighing more than a ton, once was blasted into pieces and the hub removed without harming the shaft to which it had rusted fast.

One manufacturing concern not long ago found itself with a surplus brick chimney 150 feet high, almost encircled with valuable buildings ten to fifty feet away, and a new $9,000 stack only nine feet distant. They gave C. V. Weaver, an expert, the job of reducing the stack to brick and mortar within a narrow lane, leaving intact several thousand windows, and many delicate silk machines. He arrived with a box of dynamite, a blasting box, a brick-drill and a tamping stick.

The expert sighted a center line along the narrow "landing field," and marked where it intersected the stack. Then he drilled a series of holes halfway around the stack, fifteen inches above the ground, partly through. In the rear he drilled another row of "weakening holes" clear through, three feet from the ground.

Above: Machine used to fire 1,000 explosions in six minutes during filming of war scenes for a recent motion picture. Each mine and shell was exploded by a wire leading from a contact on the semicircular control board



Right: One of the levee blasts that saved New Orleans. Workmen are seen in the picture laying new charges within a stone's throw of the blast

When sticks of dynamite, placed in the holes, were fired, the result was like chopping down a giant tree. The stack tottered, then swayed and fell with a roar. The job required an hour and five minutes, and the only thing broken was the silence.

The same expert once dropped a tall stack so accurately that it drove a lining-up stake into the ground. Again he lifted a cornerstone from a building without injuring the records contained within, and reduced a huge safe to bits without the bank's patrons knowing what was going on. When asked for his "secret" he remarked: "It's all a matter of being careful. Handle dynamite correctly, and it will do almost anything you want it to do."

Russell explained to me how dynamite does its work.

"An explosive exerts an expansive force, which works along the lines of least resistance. The charge must be proportioned to the depth of the hole and the mass around it. The charge can be so placed that all its force will be absorbed by the material, either shattering it into fragments or merely cracking it.

"IT MAY surprise you to know that the tearing force of TNT is only equal to that of medium strength dynamite. Its advantage, however, is that it can be handled, dropped, even melted or fired into without detonating. An entire car was burned last year without exploding. TNT is used for shells, bombs and mines, but is too costly for ordinary use. Black powder, made of saltpeter, sulphur and charcoal, is used for blasting coal, slate and marble; also for fireworks and fuse. Smokeless powder, the most difficult of all explosives to make, is now the best explosive for ammunition."

Tons of dynamite have been employed to tear down miles of vertical rock cliff, as was done recently for an approach to the Bear Mountain bridge over the Hudson River. In large cities, when blasting is to be done, mats of woven cable are placed over the charge. Recently I heard a New York dynamiter reprimanded because a few pebbles cracked a window across the street! Yet he had lifted from a hillside dozens of 100- and 150-ton masses of solid rock, as large as a garage, and had laid them on the ground within fifty feet of apartments.

Dynamite has opened the earth for the passage of railway trains, automobiles, water and power supplies. It made possible the new vehicular tube, under the Hudson River, through which 17,000,000 motor cars will drive every year. In northern California the Pacific Electric has blasted a tunnel twenty-three feet high by twenty-two wide to lead an underground river four miles to its turbines. In Colorado the Moffat Tunnel through the Continental Divide, now virtually completed, will save twenty-three miles of railway travel and 2,406 feet of climb. In the Argentine the tunnel between Amadores and Alijilan cuts the running time from twenty-seven to eight hours. When the (*Continued on page 129*)

Next We'll *See* to Paris

So Says John Baird, Who Brings His New Television System to America to Prove He Can Do It

By GEORGE LEE DOWD, JR.

LESS than five years ago John L. Baird, a young Scotch inventor, labored in an attic room in the Soho district of London, with few possessions save the dream of achieving electrical vision at a distance. His experimental apparatus he had made with his own hands from derelict odds and ends — old bicycle sprockets, lenses from bicycle lamps, tin cans—mounted on a framework of old sugar boxes, and tied together with string and sealing wax.

Now, this same young inventor is coming to the United States to demonstrate the first transmission of human faces and other moving images by radio across the Atlantic!



Right: The Baird radio vision receiving apparatus. Light from a neon tube, controlled by incoming signals, passes through lenses in a rotating disk, reproducing the transmitted image on a ground glass screen. Below: The inventor of the apparatus, J. L. Baird, in his workshop in London



In the transmitter rotating disks divide the face into patches of light of varying intensity. These the photo-electric cell translates into correspondingly fluctuating electric current

While engineers of the Bell Telephone Laboratories have been astonishing America with the first practical demonstrations of distant vision by wire and radio, as described recently in POPULAR SCIENCE MONTHLY, Baird, in England, has been achieving similar wonders. He has established what has been called the world's first television transmitting station—Station 2TV, licensed by the British Post Office. A few weeks ago he surpassed the American 200-mile record of television from Washington to New York, by transmitting distinguishable moving faces by wire from London to Glasgow, Scotland, a distance of 438 miles. And he is reported to be perfecting a television receiving apparatus which, at moderate cost, may be installed in a home like an ordinary radio receiver.

Already he has succeeded in sending the "sound of a face" some three thousand miles across the Atlantic. Recently, as he sat before his "televisor" in London, scratchy sounds produced by signals carrying the image of his face were recorded in New York.

A year ago so poor that an attic bedroom-laboratory was his only available stage for a demonstration before members of the Royal Institution in London, he comes to this country with the backing of a $625,000 company—which, it is reported, plans to establish a number of television stations here and in Europe.

Baird is one of the remarkable figures in invention today. For, working virtually single handed, he has solved an enormous problem which elsewhere has required the elaborate apparatus of great research laboratories and the coöperation of hundreds of expert minds. And in basic principle, the television system which he has worked out is strikingly like that which required the services of nearly a thousand men in the recent Washington-New York demonstration.

In fact, he has made use of the same general theory which has been followed, with varying success, by virtually every recent experimenter in television, including such men as C. Francis Jenkins, of Washington, D. C.; Dr. E. F. W. Alexanderson of the General Electric Company research laboratories, and Edouard Belin of France. Like them, he has developed his own method of using the light-sensitive photo-electric cell to scan the face or scene to be transmitted. The face is divided into tiny patches of varying light and shade. The light of each of these, in turn, is translated by the photo-electric cell into corresponding electric impulses, and these impulses in succession are sent by wire or through the ether. At the receiving end they are translated back into light and patched together into a mosaic likeness of the original.

The problem of television always has been to speed up this process to the point where, to human eyes, it will give a truthful effect of motion. This requires the scanning and transmission of an entire face or scene at least sixteen times a second—the speed of motion pictures.

In this, Baird has gained success first, by the invention of an extremely sensitive photo-electric cell, the exact nature of which he has kept a guarded secret; second, by an (*Continued on page 135*)

Why We Mob Heroes

A Noted Psychologist Explains Our Frenzied Idolatry of Aviators, Athletes, Movie Stars—Even Murderers!

By A. A. BRILL, M. D.

Doctor Brill is one of the world's foremost students of human thoughts and emotions. A physician and psychologist, he brings his knowledge here to explain recent popular waves of hero worship. He has been head of the psychiatric clinic at Columbia University, and lecturer on abnormal psychology at New York University, and is the author of widely read works

WHY has Charles Lindbergh stirred two continents to the wildest frenzy of hero worship ever accorded a single human being?

Why do we mob motion picture stars, go mad over the first woman Channel swimmer and idolize baseball celebrities and boxing champions? Why, for that matter, did thousands cluster on the street corners of New York just to watch the passing of a condemned murderess on her way to Sing Sing?

The international outburst over Lindbergh differed from many recent explosions of hero worship only in its intensity. "Red" Grange, Helen Wills, Gertrude Ederle, Bobby Jones, Byrd and Chamberlin—they and others have in turn swept us off our feet in a storm of crowd hysteria.

What is back of this odd phenomenon?

Why does hero worship erupt tumultuously at the death of Valentino, while the simultaneous passing of a great educator like Charles W. Eliot attracts only meager notice?

Among the mere onlookers at Lindbergh's triumphant parades were veterans of the war and pioneers in aviation who had risked their lives as daringly as he, and for greater causes. Orville Wright, who made the airplane possible, was a secondary figure in the news photographs of Lindbergh, who used the airplane in a thrilling but practically useless feat.



The wildest display of hero worship ever accorded a single human being—New York City's hysterical welcome to Charles Lindbergh. The photograph shows lower Broadway as Lindbergh passed in a downpour of "ticker tape" and confetti. In idolizing Lindbergh, says Dr. Brill, millions found an outlet for repressed instincts

I have asked some who joined in the Lindbergh frenzy to explain their own emotions. The best answer they have to offer is:

"Oh, I don't know. I just seemed to have the Lindbergh bug."

Those who rioted at Valentino's funeral, and those who fought their way into the courtrooms to catch a glimpse of Ruth Snyder or "Peaches" Browning on the witness stand, are equally unable to describe their true motives.

Yet the fundamental explanation is really the same in each case. Whether we are cheering Lindbergh or gossiping about "Peaches" Browning, it is the cave man speaking out within us.

In these popular obsessions with some personality of the hour, man's primitive self is bursting through the restraints of modern civilization. The violent energies of sex and of belligerency—the great appetites for pleasure, power and immortality—thus find outlet.

I have a friend who has had to stop going to boxing matches because he always gets into trouble. As the fight waxes furious in the ring, he begins lashing out blindly with his own fists—and some of his neighbors acquire bloody noses.

The stimulus of the roaring crowd around him and the sight of the boxers' blows release pent-up primitive impulses. But most of us are able to transform such emotions into cheering and catcalls. We are all, for the moment, such unbalanced hero worshipers that we call upon our favorite to kill his opponent; and the group hysteria around us gives social approval to our demands for gore.

In other words, "the bug" that bites a frenzied hero worshiper is the germ of crowd contagion. But the man bitten is not his civilized self. It is the savage ancestor within him. Remember that in tens of thousands of years, man's physical structure has not perceptibly altered, but in a few thousand years his mode of living has changed materially. Instead of a jungle cave he now has a cozy fireside, police to protect him, a corner grocery store to furnish food. But he has the same nerves, the same glands, the same muscles and internal organs as the cave man; and he still has the same reserves of energy seeking outlet through them.

TODAY we can't go around fighting our neighbors, stealing their women and slaughtering animals. But the unchanged savage within us wants to. We find an outlet for these primitive instincts by going to the movies, the football games, the murder trials and prize fights.

By identifying ourselves with the actors in these public spectacles we secure an emotional outlet for our own repressed energies. This release, obtained in shouting or pounding a neighbor on the back, is called an emotional catharsis. I go to boxing matches not only to get it myself, but to study its effect on others. I paid $55 to see a four-minute fight between Dempsey and Firpo, and I got my money's worth because every second of it was violent action. But I saw Wills

and Firpo go twelve rounds and everybody shouted, "Fake!" Because there was no action or blood; the cave man within them had not been released emotionally.

WHEN the football player or varsity oarsman puts forth "superhuman" efforts in the last gruelling moment we see evidence of these latent powers. The intense emotion aroused in a close contest sets free the athlete's primitive reserve of energy. That is why "Red" Grange can run faster in a game than he could if nobody were chasing him; it is why Helen Wills played "superhuman" tennis against Lili d'Alvarez.

They say in Washington that President Coolidge made the most telling speech of his career in his welcome to Lindbergh. The emotions stirred by a nation's hero worship called forth in him untapped powers of oratory.

But how does all this explain hero worship itself?

Let's take various types of cases. Jack Dempsey for one. Why does the small boy worship Dempsey and ignore Gene Tunney who licked him?

Dempsey in build, in physiognomy and in methods of fighting typifies brute force. Tunney is thought of as the gentleman, the highbrow. He frankly fought to make money. Jack Dempsey fought, so the small boy thinks, because he loves to fight. One of the small boy's chief desires is to shine in physical combat.

Because Dempsey typifies the born fighter, his followers seize upon him as the supreme embodiment of the unsatisfied fighting instinct within themselves. Furthermore, Dempsey in defeat has been trying to come back. We are all of us defeated by life at every turn. We are beaten in business. We are beaten in golf. We, too, want to come back.

There you have the answer. Every object of hero worship represents some simple or complex wish unsatisfied in our own lives. The popular idol can do things which we cannot, but which we want to. By projecting ourselves into his rôle, and by celebrating his exploits, we enjoy a release of emotions more intense than the ordinary routine of our lives permits.

As a youngster I used to go down to a saloon on Essex Street, New York, just to look at a picture there of John L. Sullivan, the greatest pugilist of them all. John L. fought all the time. Crowds would gather just to stare at his gloves exhibited in a window. Anything closely associated with a hero helps the onlooker to make more vivid his self-identification with the hero's deeds.



Millions went mad over Gertrude Ederle, the first woman to swim the English Channel. She personified their balked desires for physical conquest over the elements, and they enjoyed emotional release in celebrating her exploit. This view on Amsterdam Avenue, New York, shows the elaborate welcome prepared by her neighbors

Remember that our emotions are feelings which accompany the completion of a current through our nervous system. Some object stimulates the outer nerves of touch or sight; the stimulus, perhaps comparable to an electric current, passes to the infinitely elaborate telephone exchange of spinal cord and brain, and from there it is sent out again to selected muscles and glands through whose operation we feel the emotion.

THAT'S why the crowd stared at John L. Sullivan's gloves, and why the Parisian mob tore pieces from Lindbergh's plane. If a small boy can make off with a ball knocked over the fence by Babe Ruth, he shares among the rest of the gang some of Babe Ruth's glory. Thus things associated with a popular hero seem to have supernatural powers, and the hero himself becomes a sort of demi-god.

Children still get satisfaction in fairy story heroes. But adults, experienced with the reality of life, have to find their release in another kind of fairy story. They find it on the stage, on the screen and in modern fiction. On the screen you see people just like yourself, in surroundings like your own, gratifying desires which you cannot gratify. You project yourself into them, live through the adventures they are having, and so escape from the realities of your own existence.

Now the popular film stars, whether Mary Pickford, Charlie Chaplin, Douglas Fairbanks, or who you will, are always the same in whatever part they play. Thus it is not the character played by a star, but the star himself who becomes a sort of demi-god, able to realize freedom from the hard facts of the average man's life.

For instance, a girl once showed me a letter she had received from a famous motion picture star. She was fluttering with emotion as she held it in her hand. A divinity had raised her to his level by deigning to write to her. When I said that I had heard her hero started as waiter in New York, she was utterly crushed.

Hero worship requires that its object be something above and apart from us ordinary mortals. If the hero is not superior, how can he achieve the desires denied to us?

Sooner or later every hero is discovered to be only a human being. Then he falls from grace.

Valentino would have fallen, but he died in time. There is no mystery about the demonstrations surrounding Valentino's death and funeral. The death of no other star would have aroused similar intensity of emotion, because no other star typified so perfectly the Great Lover for this age. The women who sat in Valentino's audiences were, in imagination, replacing the actress who received his kisses.

Crowds welcoming the Prince of Wales on his arrival at Aberyswyth, Wales. Students are seen dragging his car by a rope to the University College. The young prince symbolizes the fulfillment of man's inner craving for social distinction

CONTRAST this with the case of Douglas Fairbanks. Fairbanks is the fairy story type of hero. He does impossible things, performs athletic feats which we envy, and he carries off the girl only incidentally. But Valentino was the love-maker in concentrated form. Through him millions obtained a by-path outlet for the strongest and most re-

It required a force of strong-armed London "bobbies" to save Mary Pickford from the crowds which almost mobbed her. Like other great movie stars, she has commanded the worship of multitudes, who realize in her a sense of freedom from hard, unromantic facts of daily existence

pressed of their primitive instincts.

Hence, while he lived, he was mobbed wherever he went. Women sought to get near him, to touch him, to pass notes to him, just as the youngster tags Jack Dempsey around or tries to make off with one of Babe Ruth's home-run baseballs. And when Valentino died, women jammed the funeral church. Those who attend a funeral are intimately associated with the deceased. Women striving for emotional intimacy with their hero, through participation in his funeral, created a jam that called for police control.

THE simultaneous passing of a great educator produced no similar mobs of mourners simply because the desire to be a great educator is not deeply rooted in us. Our cave-man desires are to excel in love, war and the chase—not in learning. It is action we crave.

Your small son wants to be a policeman, a fireman, a sailor or iceman or soldier. He wants to be the husky grown-up who *does* things.

Modern civilization encourages us in mental accomplishment. But it thwarts our physical reserves of energy. So it is the frustrated physical instincts that attach themselves to popular heroes.

Now, to take another type of hero worship before we come to the extreme case of Lindbergh, let's consider Ruth Snyder. In cases like her sensational trial our elemental wishes again account for the mobs that squeeze into the courtroom. Most of us are able to repress the desire to transgress the law and moral conventions. But the law and conventions are recent compared to the primitive instincts we have inherited from remote past.

SINCE the desires are still shut up somewhere inside of us, we are eager to see them enacted in real life by others. The woman who murders her husband so she may share the insurance money with her sweetheart interests us because she has broken laws which, in some way or another, we all chafe against. The interest in Ruth Snyder was only another form of hero worship. That part of our primitive selves which chafes against social restraint was actually glorifying her, although with our spoken thoughts we united in condemning her actions.

In every case of hero worship, then, the fundamental explanation is the identification of ourselves with another who succeeds in doing something we want to do, either consciously or unconsciously. Sometimes our want is one of the elemental instincts, backed up by an untapped reserve of physical energy. Sometimes it is a higher ambition, which I call the wish of human beings to annihilate space, time and mortality.

We don't all want to swim the English Channel, any more than we want to murder members of our family. But we do want to be superior to our fellows. That is one of the ambitions that makes for human progress. The girl who swims the English Channel, and the man who flies alone to Paris, personify superiority and freedom from the hard, earth-bound realities of our own lives.

So they are objects of widespread interest. Publicity concentrates upon them. The social stimulus of publicity intensifies still more our own interest. We break out into various forms of applause. The applause gives us a pleasurable outlet, in action, for the pent-up energies which modern civilization ordinarily compels us to restrain.

At an inter-collegiate football game, for example, insane yelling becomes a social convention. Others do it, and so you can. You may be a phlegmatic person; at various points in your nervous system there are centers of resistance that stand in the way between stimulus and muscular response. But at some point the stimulus from the crowd's action is strong enough to break through these resistance points, and you, too, begin to yell.

The resistance once broken is not as strong next time. The emotional outlet through a certain channel becomes a habit. That is why some of us are baseball fans, some fight fans, or golf or tennis fans.

MASS outbursts of welcome to homecoming heroes may become a habit in similar fashion. Lindbergh's reception would have been likely to exceed previous demonstrations because we had learned the trick and enjoyed it. But the Lindbergh craze was an extreme case in the annals of hero worship for several interesting and human reasons.

To begin with, he received more publicity than any other individual in history. In the first two weeks following his start from the Pacific coast to New York he filled 27,000 columns of newspaper space. His mother was deluged with 220,000 more clippings concerning him than the press bureaus made concerning Peary after the discovery of the North Pole. Through newspapers, magazines, radio, movies, wirelessed pictures, the eyes of two continents were focussed upon him.

But why was all this publicity given?

His flight was part of a contest. We are always interested in contests. We stop to watch when we see two dogs fighting. Life being a struggle, only those who are interested in contests can survive. Every form of adult play is a contest, whether bridge or golf, shooting or fishing.

And these contests are comparatively useless, just as Lindbergh's flight, Ederle's swim and Byrd's polar hop were practically useless to the rest of the world. The player who (*Continued on page 130*)

Premier Mussolini of Italy reviewing an army of wildly cheering Fascisti. The hysterical worship of his followers, says Dr. Brill, is the outburst of primitive instincts for leadership and power

Plows 1000 Acres a Day

World's biggest wheat man demonstrates how machinery helps solve farm problems

By WHEELER McMILLEN

Above: A mechanical loader, operated by tractor, dishing up half a ton of sugar beets. A windlass at the back hoists the bucket, after it has been driven into the beet pile. Then it backs on its own track and drops the load into a truck. Below: A tractor hauling a trainload of crops

IF A farmer of the time of the Pharaohs had come to life in America in 1827 he could have gone to farming with about the same tools he left behind him in ancient Egypt, it was remarked recently by the world's biggest wheat farmer, Thomas D. Campbell. But he would be submerged in wonder were he to show up today on Campbell's huge farm where more than half a million bushels of wheat are grown each year entirely by machinery!

With the equipment on his great wheat farm, Tom Campbell can plow 1000 acres a day and harvest 2000 acres a day. In a single day he has plowed, disked, seeded, and packed a full section—640 acres. One of his huge engines will at one time perform all those operations on a strip twelve feet wide, sowing thirty acres a day.

For eight years Campbell has grown an average of 40,000 acres of wheat annually, and since 1921 has done it profitably. Each year, as his industrial methods are improved, his costs go down. Fifty tractors, ranging from forty to seventy-five horsepower, drive his machinery. Mechanics' wages are paid to the workmen. The big power units reduce the costs until Campbell's wheat is probably the most cheaply produced in the world.

In its size, and to an extent in its equipment, Campbell's immense farm is unique; yet it is typical of the transformation which mechanical science has worked in the American farm.

After the Civil War, the blue-clad veteran laid aside his musket to grasp a plow handle, a hoe, a sickle, a pitchfork, a cradle, a corn knife, and a husking peg. From his easy chair today, the old veteran listens to throbbing tractors, pulling wide bottomed gang plows, swift two-row cultivators, combines, and corn pickers.

The pioneer broke his wheat ground with a two-horse plow, cutting a ten or twelve-inch furrow, and smoothed it with a two-horse harrow. Swinging a heavy bag under his arm, he broadcast the seed a handful at a time. He cut the wheat with sickle or cradle, tied the sheaves with straw, and threshed the crop by hand with a flail, later with a horse-power threshing machine.

Contrast those rude methods with the system of harvesting employed on Campbell's great farm. There four binders are hitched behind one tractor. The sheaf-tying device is removed, and extension carriers provided, so that the four binders deliver the cut grain loose in one continuous windrow. One man suffices for the four machines. The grain cures quickly. The combine then goes down the windrows, threshing as it goes, dumping the grain in wagons and leaving the straw on the ground. Three men operate this machine; a dozen and a half are required for the ordinary threshing machine. The expense for twine and for hand-shocking has been eliminated, and Campbell's cost of harvesting reduced fifty percent. Threshing is finished two days after the cutting ends.

CAMPBELL is a pioneer in industrialized farming. He uses no horses. His methods, he declares, are applicable to any farm with 160 acres of grain. Indeed, power and machinery are rapidly revolutionizing grain harvesting on thousands of farms. New types of combined har-



A stationary tractor-operated threshing outfit on the 40,000-acre wheat farm of Thomas D. Campbell, operated in a section where use of the binder and combined harvester and thresher was not practicable. This Montana farm set a world's record by threshing 4,321 bushels of wheat in a day



This sixty-foot-wide seeder travels three miles an hour and plants 150 acres a day on the huge Campbell wheat farm in Montana. At right: A combine harvesting soy beans

vesters and threshers cut and thresh as they go. With a combine three men do the work that formerly required twelve to twenty. The harvest that once spread over weeks is finished in a few days and one to three bushels more wheat are gleaned to the acre. The farmer is saved fifteen to twenty cents a bushel in harvesting costs—possibly the difference between profit and loss.

THE combine is being used not only for wheat, but to gather oats, rye, barley, sweet clover, soy beans and grain sorghums. It represents the greatest mechanical contribution to the reduction of farm costs since the tractor came into use.

Invention likewise has made vast reduction in the labor of raising corn. The tractor plows and fits the fields; two-row cultivators stir the soil and destroy weeds, supplanting the old walking cultivators and the hoe. At the Iowa Experiment Station even six-row cultivators have been used successfully.

"The corn harvest on my farm," said E. L. Ketzenbarger, whose land is in northwestern Ohio, "used to be a hot and heavy job. We had to cut each stalk or hill by hand and carry an armful at a time to the shock. Later the ears were husked by hand. Now my picking machine does the work of five men. This machine glides across the field behind a tractor. The fallen stalks are lifted, the ears snapped off and carried over rollers that clean off all the husks, after which a carrier delivers the ears to a wagon hitched to the same tractor. At the crib an automatic dump unloads the wagon and a carrier lifts the ears into the crib. No hand operations or heavy muscular labor are employed, from plowing to storing the harvest."

For haying, tractors are made now with mower attachments that swiftly cut wide sweeps. A side delivery rake stirs the hay to hasten its curing, then heaps it into continuous swaths. Over these the tractor pulls a wagon upon which the loader delivers the hay. At the barn a power hoist, in conjunction with slings or double harpoon forks, swiftly lifts the load and, suspended on a steel track, it slides back into the mows. A wagon may

Tractor drawing and operating corn picker and wagon which latter is filling. At right: T. D. Campbell, agricultural captain of industry

be unloaded in five or ten minutes. F. W. Chase, a Pawnee County, Nebraska, farmer, requires only two hours to cut, cure, rake, load and store an acre of hay.

The dairy farmer no longer must milk each cow by hand a spoonful at a time. To two or six cows at a time he attaches the pliant "cups" of a milking machine that does the work by suction.

"The milking machine," says L. D. Orr, of Indiana, "enables me to milk my twenty-two cows in two hours. By hand it would take two of us four hours a day each."

Much hand labor remains necessary in the production of vegetables, yet the large truck grower plows and fits his ground with tractor power. The small grower uses the garden tractor, a small motor-driven machine. Large unit sprayers and dusters fight insect pests. Overhead irrigation by perforated pipes overcomes irregular rainfall and makes certain a plentiful crop.

Potatoes are cut for seed by machine and planted by machine. A digging machine and a mechanical sorter prepare the crop for market. Tractor cultivation and power spraying aid also in the orange groves and apple orchards.

OF THE great American crops, cotton alone has held out against the inventor. Over most of the South the patches are still plowed by mule power, thinned by a hand hoe, and picked boll by boll with human fingers. The first successful agricultural use of the airplane, however, has been for applying calcium arsenate to cotton to destroy the boll weevil. The airplanes dust 300 to 1,000 acres an hour.

A better conception of a modern midwest farm's equipment may be obtained by examining an actual farm. A. S. McDonald and his son operate near Peoria a typical up-to-date Illinois farm of 470 acres. Their major equipment includes a heavy plow tractor, a smaller tractor that can make short turns and is adaptable to almost any task where horses could be used, mower and cultivator attachments, a power hay hoist, a tractor-pulled binder, wide disks and harrows, cultipacker, limestone crusher, endgate lime spreader, grader and ditcher, concrete mixer, grain separator, grain dump and elevator, clover huller, ensilage cutter, electric light and water system, straw spreader, feed grinder and various motors necessary for pumping, grinding, concrete mixing and other purposes. Of course his automobile and radio should be included. Practically all farmers have motor cars, and about a fourth—1,252,126, according to Department of Agriculture figures—have radio sets. About one farmer in ten has a tractor.

"IN DECIDING whether to install a new machine," says McDonald, "I balance the investment against the labor the machine will save and the timeliness it will gain. The profit on a crop often depends upon getting

(Continued on page 133)

He Trapped *Three* Bandits *with a* Microscope!

A Chemist's Great Man Hunt with Three Grains of Salt

By EDWIN KETCHUM

ON A night in October 1923, Southern Pacific Express Train No. 13, speeding southward across the Klamath range in Southern Oregon, had just entered the Siskiyou tunnel near the California border, when bandits crawled forward on the locomotive tender and covered the engineer and fireman with revolvers. Forcing the engineer to halt the train, they shot both men down in cold blood! Then they blew up one end of the mail car with dynamite, killing the mail clerk. A brakeman they killed with another bullet.

When police arrived, the bandits had escaped into the mountains without their booty. Four innocent men had been murdered; and the only clue to the slayers was exactly three grains of salt!

These were in a burlap bag which had been wrapped around a shoe of one of the bandits. The burlap had been painted with pitch from a fir tree, apparently to destroy scent in case of pursuit by bloodhounds.

Several days later a chemist bent over a microscope in a laboratory at Berkeley, Calif. He was Edward Oscar Heinrich, an expert in criminal investigation, a former police chief of Alameda, and an instructor in the University of California. The object of his scrutiny was the three bits of salt. And, building step by step from what they revealed under the microscope, he was able shortly to emerge from his laboratory with the startling announcement:

"ONE of three men who committed this crime was a left-handed, brown-haired lumberjack, not more than twenty-five years old, about five feet eight inches tall, thick-set, fastidious in his personal habits, clean shaven. He had recently been working in Northwestern Oregon or Western Washington in the camps where fir trees are felled!"

Experienced detectives, incredulous at first, lived to be convinced. For today, as the result of that remarkable description, and after a four-year man hunt extending to many corners of the world, the three bandit-slayers—Hugh, Ray and Roy d'Autremont — are in the Salem, Ore., penitentiary, beginning life sentences for murder. Hugh, almost perfectly fitting the chemist's first description, was captured early this year in Manila where he was serving in the Army. In June his brothers, twins, were caught at Steubenville, Ohio. They confessed their part in the train holdup, though blaming Hugh for the killings.



Sherlock Holmes up to date. Edward Oscar Heinrich, chemist-detective, trailing the Siskiyou train bandits in his laboratory

And all from three grains of salt! How was it possible?

To begin with, chemical analysis revealed to Heinrich that the salt was of a peculiar variety used in artificial salt licks for cattle. Following this lead, he visited several cattle ranches. Near one of these, and close to a salt lick, he came upon a cabin hidden in a deep canyon. Within were scattered fragments of burlap of the same texture as that picked up at the scene of the crime. These, likewise, were stained with pitch from Douglas fir trees, which grew about the place.

In the cabin, too, Heinrich found a towel on which were comparatively fresh wipings of hair and lather from shaving. Studying the hair under a microscope, he determined that the towel had been used by three different men. Then, comparing the shavings with standard tables showing the condition of human hair at various ages, he learned that all of the men were under twenty-five years old. Moreover, bits of skin from the towel showed that the men were of light complexion and of probable Latin ancestry.

Another search of the scene of the crime brought to light a pair of overalls. More grains of salt in the pockets and more pitch stains gave evidence that they had been worn by one of the bandits. They indicated to Heinrich also that the fugitives were woodsmen; for the owner of the overalls had worn them over the tops of his three-quarter boots, instead of tucked in, as cattlemen and farmers wear them.

FROM their size and cut, Heinrich likewise estimated the stature of the wearer. And, from the location of pitch stains on the overalls, he reasoned that the wearer was left-handed. Finding of many finger nail parings led to the conclusion that the man was scrupulous about his appearance.

It remained now to find the man answering the description. A bulge in a pocket of the overalls showed that a revolver had been carried there. Eventually a revolver was found in a clump of brush near the cabin.

The revolver was traced to a dealer in Oregon, whose records showed he had sold it to one "William Elliott" a short time before the holdup. Comparison of marks in the gun barrel with those on the murder bullets established that this was the weapon that had killed the trainmen.

Detectives traced "William Elliott" to a little house in Eugene, Ore., where lived the father of the d'Autremont boys. Additional evidence—hair, bits of cloth, finger prints—gathered in the d'Autremont cottage and examined by the chemist, established the identification.

Photographs and descriptions of the brothers were broadcast throughout the United States and in other lands. Rewards were offered. Months passed. And then, one afternoon at Manila, an infantry sergeant stepped before a private, stripped him of his arms, and sent him to the guardhouse. The private was Hugh d'Autremont. A few months later Ray and Roy were arrested in Ohio.

What's *at the* Top *of the* Sky?

Aerial Explorers Pierce Mysteries of Vast Upper Regions—How It Feels to Look Down Eight Miles!

By ALDEN P. ARMAGNAC

AT A flying field in Illinois the other day a pilot climbed into the basket of his balloon and swung aloft, into the clouds. Shortly after he gazed at the far-off earth through the one remaining clear spot on the left side of his frost-coated goggles. He was more than eight miles above it—higher than man had ever flown before!

Thus Capt. Hawthorne C. Gray, with a new world's altitude record of 42,470 feet, blazed a trail into the greatest unexplored region of all. Above your head as you look upward is a mysterious area that would swallow up many times the ice-caps and jungles of the earth. Explorers have traveled thousands of miles to reach the poles, and succeeded; they have tried to penetrate only eight miles straight up, and until now they have been turned back. Five or six miles—as far as a morning's walk, perhaps—this is the distance that most have ventured into the baffling void.



Official Photographs, U. S. Army Air Corps

Among the clouds. A remarkable aerial photograph of a plane climbing to the upper reaches of the atmosphere, taken from a companion plane

WHAT is there, out beyond the earth—where the electric aurora flashes, and meteors whiz to incandescence? Is it a dead world, frigid and empty, or teeming with perhaps some strange kind of life we do not know? What unknown terrors, besides the very real ones we have learned, await the venturesome aeronaut who would pioneer into the thinnest of thin air?

Foremost among aerial explorers has been Lieut. John A. Macready—like Capt. Gray, of the Army Air Service. It was he who recently told us how the earth looks to one soaring above three fourths of its air. Repeatedly the special Government-built altitude plane XCO5-A has carried him seven miles high, and on one occasion he reached what remained until Gray's feat the American altitude record of 38,704 feet.

What altitude flyers carry to bring back upper air records. Lieut. J. A. Macready, above took these instruments up seven miles. His oxygen tank is seen with them

Last year a French aviator, Jean Callizo, took off from Le Bourget flying field at Paris and bettered his own altitude record, rising in his biplane 40,820 feet.

Balloons, too, have gone before on epochal voyages above the clouds. As long ago as 1901, two German aeronauts, Suring and Berson, attained a height of 35,424 feet, a record for man-carrying balloons that stood until Capt. Gray's flight.

Though unmanned "sounding" balloons have risen higher, Gray's is the greatest altitude that has ever been reached by a human being.

"At the top of my balloon flight," Capt. Gray told me, "I experienced a feeling of detachment, as though I were in a world of my own. I saw the earth at a great distance, swimming in its sea of clouds. How much of it might have been visible I cannot tell; thin cirro-cumulous clouds made a distant view impossible. Above, the sun shone brightly in a sky of the deep blue color well known to pilots who fly above ten thousand feet. The air at the top was extremely cold. My thermograph registered sixty-seven degrees F. below zero."

ON A clear, wintry day, says Lieut. Macready, the view of the earth through the cloud-free air is a magnificent panorama. Cities and towns become infinitesimal pin points upon the vast "skyscape," and one could imagine himself a superior being looking down upon the work of Lilliputians. At great heights above McCook field, at Dayton, O., Macready could plainly see the distant cities of Indianapolis, Cincinnati, Columbus and Toledo, and their dark smoke trails, against a snow-white earth.

It was thought that the clear upper air might render the sun a blazing beacon, the sky inky black and stars brilliantly apparent. "There were no stars," Macready reported, "but the atmosphere was very bright, the sky having a tinge of blue"—a fact confirmed by Gray.

THESE are observations snatched from the upper void under every conceivable difficulty and hazard. Men who go into these frigid regions find their minds wandering, their lungs not working. Half of the world's air lies below the three-and-a-half-mile level; half of what remains, in the next such distance. Up where Capt. Gray saw through clouded eyes the first eight-mile-high view, his barograph proved the air more than five times thinner than that on earth! Like all altitude flyers, he carried oxygen to sustain his life in the void. But even then a pilot's lungs do not function normally. His brain becomes foggy, and the least exertion causes acute distress. If his oxygen should give out—

The insidious thing about running out of oxygen is that there is no gasping for breath, no danger signal to warn the pilot. The figures on his instrument dials gradually grow blurred, but he thinks nothing of it; for his mind is wandering. The clock seems to stop, the altimeter to run backward. Over the nose of the machine the horizon of clouds wobbles, swings to and fro. The earth, infinitely far away, does not enter into the matter at all. A terrible weariness overcomes the pilot. He is angry, too—dully angry that he should be up here—alone, flying, it seems, for countless hours, with everything getting darker. . . . Then oblivion; the plane tilts on end, drops like a plummet out of the sky. With luck, the pilot may revive in time to right it.

That happened to Major R. W. Schroeder, another altitude flyer of the U. S. Air Corps. Holder before Macready of the "icicle crown," as airmen term the altitude record, he had reached a height of 33,000 feet when his oxygen gave out. Six miles down—the longest fall on record—and he came to in the nick of time, to right his plane and make a perfect landing.



Captain Hawthorne C. Gray, wearing oxygen mask, at the start of his record-breaking balloon ascension of 42,470 feet from Scott Field, Ill.

Right: Jean Callizo, French flyer who is among the few men to reach the air's second layer. He made a new world's airplane altitude record of 40,820 feet

MEN like these, unafraid of risks, will go higher—if they can. But their planes won't, at present. Only more powerful engines than we have now, more efficient "superchargers" to feed them compressed air as a pilot is fed oxygen, can force machines farther into the void. At its "ceiling," the top limit of its flight, a plane wallows with its wings and propeller slipping through the thin air—unable to "take hold."

Little better off is a balloon—even one as large as Captain Gray's, that was buoyed up by 80,000 cubic feet of hydrogen gas. Even before it reaches a "ceiling" where the outside air is as light as the hydrogen, it refuses to carry the pilot's weight any higher.

When new altitude machines are built, another danger awaits the next record breaker. Perhaps human beings have a "ceiling," too. They were made to live in an atmosphere that presses with a weight of fifteen pounds on every square inch of their bodies. Take them up where there is almost no pressure, and anything may happen.

"Macready to Explode for the Benefit of Science," was the headline that startled the airman shortly before his record flight. He hastened to disclaim any such intention. The height he reached produced only slight discomfort, but greater altitudes may prove more serious.

"Unless some artificial aid is devised," says Macready, "this will probably form the barrier which will eventually limit man's upward flight." The Army Air Corps tested a "pressure cabin"—a barrel-shaped affair built into the plane. Compressed air filled the cabin from a wind-driven pump; and the relief valve that lowered and regulated the pressure failed to work. Just in time to avert a tragedy, the pilot landed and mechanics pried open the door the air pressure had clamped shut. The device was discarded; but other inventions may still solve the problem.

Chart showing successive layers of earth's atmosphere and records made by various altitude flyers



Launching pilot balloon to explore upper air currents. Some reach twenty-mile altitudes. They are watched through a "theodolite"

IF THERE are living things, birds or insects, that can dwell in the icy void far above the earth, no trace of them has yet been found. The present altitude record for any living thing except man is thought to be that of the "choughs," or Asiatic crows, that explorers saw flying near the summit of Mount Everest at a height of 27,000 feet. And the highest-dwelling creatures in the world are probably the "minute and incongruous black spiders" seen on the same peak at 24,000 feet.

"No indication of bird or insect life was noted," said Capt. Gray, after his record balloon flight. But he pointed out that his observations were limited to a clear spot the size of a nickel on one of his goggles. On his next trip he expects to make elaborate observations and to take photographs. Another airman, Lieut. G. W. Goddard, also intends to take a special camera eight miles high and to take pictures that will surpass the 36,000-foot record photo made by Macready and a companion over Dayton, Ohio.

The upper air, lit by the aurora's flashes, is a queer place. Its dust is the dust of meteors; into it rise smoke clouds from volcanoes, sometimes forty miles high. No matter what storms may be raging on earth, the region between 15,000 and 30,000 feet is calm; beyond this terrific winds sometimes sweep through it.

Though one "sounding" balloon recorded a temperature of 133 below, eleven miles above the equator, the altitude pilot is burned by the sun's ultra-violet rays unless he coats his hands and face with grease.

Greater heights than man has ever reached yield their secrets to the "sounding" and "pilot" balloons, sent up here and abroad. In this country the U. S. Weather Bureau now has established forty-three balloon stations where regular observations of the upper air are made. Eight-layer weather maps are prepared as an aid to aviators. "Sounding

(*Continued on page 138*)

Whirling Wheels

The Story of the Automobile Age—A Vivid Novel of Youthful Genius in the Race for Invention

By EDMUND M. LITTELL

Author of "Midge" and "Fire Shy"

Illustrated by B. J. Rosenmeyer

WHEN Gil Herrick, a young mechanic fresh from apprenticeship in Massachusetts, drifted into the village of Wendenville, Mich., he also drifted unwittingly into a feud with big Jim Wenden, the town bully. There were reasons for rivalry. First, Gil refused to be bullied; second, there was a blue-eyed girl, Abigail Caswell; and finally, there was a matter of speed supremacy.

Gil met the bullying in a quiet way that was disconcerting. Moreover, he found an unexpected champion in Jim's father, old Zach Wenden, the influential village blacksmith. As for Abby, Jim regarded her with a sense of proprietorship, and it did not lessen his animosity toward the newcomer to know that Gil was quartered as a lodger in the Caswell house, where lived the girl and her proud Boston-bred mother, even though Mrs. Caswell saw to it that the strange "mechanic" and her daughter were never left alone together.

The speed rivalry grew from the time that Gil began tinkering secretly in a small workshop he had set up in the Caswell barn, and established a bicycle and repair shop in the village. Word leaked out that Gil was building a motor wagon. Jim publicly scoffed at the "inventor"; then, by his insistence, drew Gil into a bicycle race. Gil won; and when Abby handed a bunch of flowers to the victor, Jim's bitterness increased.

With a motor wagon race scheduled for Chicago, Gil rushed his machine to completion. The first public demonstration, with Zach Wenden as a passenger, failed dismally, ending his hope of entering the race. But he went to Chicago, nevertheless. Jim went also. The outcome was that Gil returned with new ideas for improving his machine, while Jim brought back word that he had purchased a new Benz motor wagon.

Months later, a forty-five-mile motor-wagon race between the rivals was a great event in Wendenville. This time Jim, with his foreign machine, won. But this time Abby ignored the victor. "Where's them flowers?" demanded Jim. And when she offered none, he attempted to steal a kiss, instead. The girl struggled in vain. Gil flung himself upon the strong-armed bully, only to be caught in the grip of a hammer lock. Gil jerked desperately; his arm snapped and he fainted—but not before he had struck one last futile blow. In the eyes of the crowd and of the girl, Jim, in his victory, became the loser. Now read on:

GIL came up out of unconsciousness that evening long enough to discover himself in his own bed. The white moustached Dr. Simms was above him, the black beard of Zach Wenden at one side of him, the teary eyes of Abigail on the other. Then pain shrieked through him and he went out again. After that came blurred awareness of confused events until hours later when he woke up, relaxed as from a long sleep. His left arm was bound to his side, but otherwise he felt strong. Then he heard voices downstairs, arguing about . . . him.

Mrs. Caswell's sharp voice, and—hers. "Gail," that's what he would call her. Didn't like "Abby" at all. Her voice was clear and strong with a deadly earnestness, her mother's harsh. The talk was confused at first, but he listened shamelessly to the interlocking sounds because his name was being used, and gathered some little sense out of the jumble.

"I won't go!" That was Gail. "I'm going to stay here with Gil."

"But he's only a grease-covered mechanic with nothing his name!" That was Mrs. Caswell.

"He loves me, doesn't he? Didn't he fight for me?"

"Only made a fool of himself, as you too."

"I don't care; I love him, and I'm going to stay!"

"If you do I'll cut you off without a penny."

It was heated, furious, terrible. Gil scrambled out of bed as best he could and struggled into some clothes. Furious how weak he felt, when a moment before he had surged with strength. Dizzy, too. He crawled downstairs.

"Gil, you mustn't!" It was Gail, running to him as he staggered in the doorway. "Go back upstairs!"

"I want to hear." His voice wavered strangely. "You're talking about me."

"Indeed we were. And



Gil found it hard to leave Wendenville. Old Zach Wenden tried to express the feelings of the town: "Any time you want to come back, Gil, you can have about anything you want here. An' if you see Jim, tell him he'll have to hustle"

"What company you working for?" Jim asked. "Myself." Gil pointed to a booth displaying a sign, "Herrick Runabout"

this is as good a time as any to—"

"Mother, you be quiet! Shame on you! Sick and weak like this—and you—"

"After all I've done for you!"

"And all you've made me do for you the last two years—"

"Gail, I—I'm tired."

IT WAS anything but pleasant, the talk that followed her leading him to a chair, nor was it finished then. But by the time he was strong enough to go back to the shop, where the townfolk greeted him with a new resonance of liking and respect in their voices, he knew the whole story. Mr. Caswell, it seemed, had not left a complete wreck behind him; there had been a very comfortable residue after everything was figured out. With that, Mrs. Caswell was—of course—returning to Boston. The bitter words that Gil had heard were a struggle between a mother who loved in her own peculiar way and a daughter who refused, now that the issue was there, to abandon her new-found lover.

With Gil present as a third party to the conferences, some sanity was achieved in the discussions, though Gail remained as stubborn as before, until Mrs. Caswell wept—not a pleasant sight when one of her cold restraint broke into harsh and wracking sobs; then Gail wept, too. She hadn't really known that her mother loved her, and said so, with a questioning, fearful glance, when she had returned from nursing her mother into bed.

"What shall I do?" she whispered. They were sitting on the front porch, Gil's arm tight about her. "She—I—can I leave her now, Gil? I didn't know—"

"She'll have Boston," Gil said. "And if you go I'll be alone again."

That recalled her first comment about him. "An orphan," she had said. She twisted about to assure him with warm, fierce caresses, that he should never be that way again—"even if I do leave you, just for a little while . . . 'Gail,' I love it. How did you come to think of that?"

"It's like you—Gail."

"I hate 'Abby.' I'm not a cat, am I? When did you know you loved me? And will you always—"

Then, after a long time, back to her mother again. "Gil, dear, don't you—can't you—it's so selfish to leave her now, when she's going home after so long. We're so young and she—why, she's old! Wouldn't it be selfish to let her go alone?"

After many such talks it was so agreed. "You can work, oh so hard!" and "I'll have to; I've got to."

Mrs. Caswell, restored to her normal state of mind, hastened preparations for departure with a triumphant light in her cold eyes. She may have failed to restrain her emotions once, but that momentary weakness had given her a victory. Gil and Gail were planning to be married "just as soon as mother is settled," but—so much can happen when lovers are separated. They parted, Gail in tears at the station, her mother almost vivacious at the prospect of Boston, Gil quiet but with eyes that spoke volumes. Can steel-gray eyes be warm? Gail knew, and summoned their message in later days when letters were overdue. For Gil drove himself through four years of work before he saw her again.

Four years, with Jim not there to jeer, but with his taunts still ringing in his ears. For Jim had left Wendenville very soon after the race. He had blustered and laughed at the coolness of Wendenville for a while, called and apologized to a quite indifferent Gail, then had climbed into his wagon and driven away.

"You don't know so much about motor wagons, do you?" was the way he apologized to Gil before he left, and Gil looked up from his work bench with eyes as hard as marbles.

"Well, I made one, didn't I?" said he. "I didn't buy it. And I finished a race without pushing."

Jim laughed. "Well, pleasant dreams with your pencil and paper," he drawled. "I'll come back and wake you up one of these days."

He did, in the fall, looking the prosperous city man and making much talk about what he was going to do.

"Some folks think they got something with this here hydrocarbon engine," he said in the post office. "Ain't been to the city, where electrics are so thick on the streets you can't walk without gettin' run over. I'll be makin' electrics when some fellers 're—"

"WHO put that idea in your head?" asked Gil, and some of his friends laughed.

"Come down to New York some day," drawled Jim. "I'll show you a factory that's turnin' 'em out like sausages."

Soon his father permitted it to be known that Jim had sold his farm and bought into a company that was manufacturing electrically driven buggies—and Gil went to work.

Four years, with Gil quietly calling attention at various times to the events that were going on in the world outside. Electrics? When Barnum and Bailey's circus that very year put one of Duryea's wagons at the head of its parade and plastered the country with signs showing it? Electrics, when the following year



"Gil, you mustn't! Go back upstairs!" It was Gail, running to him as he staggered in the doorway. "I want to hear," he said, his voice wavering strangely. "You're talking about me"

Alexander Winton drove his gas engine runabout from Cleveland to New York in less than ten days? When, in '99, Haynes-Apperson made a trip from Kokomo to New York in twenty-one days, only ten of which were driving days? Suppose electrics were in the ascendancy in cities, suppose they were dominating the bicycle shows where they were being exhibited; they were at the mercy of charging stations and never could get far away. Gil proposed to perfect a vehicle that could go anywhere, that could refuel itself at any wayside drug store. And big Zach, combing his beard, said "-m-m!" and watched Gil go.

Four years. Not too long in which to devise a better means of making rear wheels turn, not too long to arrive at a more reliable method of introducing a spark into a cylinder, to rebuild the entire running gear. Remarkably short, in fact, when the slowness of previous advancement was considered; short, too, considering that a living had to be made at the same time, for Gil was conserving his capital for a very definite purpose.

The jumping off of the drive belt had been caused by the different speeds of the rear wheels in making a turn. That meant that a compensating device of some kind had to be arranged; so, after many experiments, Gil drove the rear axle instead of the wheels, splitting it in the center and installing a clutch arrangement there, on the outside of which he placed a sprocket. This he drove, with a chain similar to that of a bicycle, carried back from the crank shaft of the engine. The axles being live ones now, a housing for them was necessary, with ball bearings to support them. Because of excessive vibration in his engine, he reduced it to a one-cylinder of the same Otto type, setting it horizontally pointing forward in a frame made of bicycle tubing. The sparking plug having come over from France, he used it with dry cells and an induction coil to displace the cumbersome system of make-and-break that had supplanted the original hot tube method of Daimler's devising.

Daimler? Who was he? Some of the boys wanted to know, and Gil recited a history. Did they know that men had been trying for centuries to make vehicles go under self-contained power? Well, they had. 'Way back in 1600 a man named Stevin put a sailboat on wheels and carried twenty-eight people along the shore of Belgium. Then Sir Isaac Newton made an engine out of himself in 1655, putting a chair on wheels and driving it with a hand crank. After that Watt found out what steam would do, and a man named Cugnot put a boiler on wheels in 1710, in France. Then great steam-driven things began to crush the roads of Europe and drive at terrific speeds—ten, fifteen miles an hour over the roads—until England passed a Red Flag Law which compelled every operator to keep a man in front of his vehicle with a red flag as warning. It was not until 1884 that one Gottlieb Daimler of the Otto gas engine works secured the compression of hydrocarbon gas in a small cylinder; 1889 before he had given it the two cylinders and four horsepower that Gil had used six years later.

Daimler had used a hot tube method of ignition, a metal tube heated by a Bunsen burner that gave a hit-and-miss explosion. That had been supplanted by the make-and-break, and now—the sparking plug. No danger of fire there; no call upon the driver to get out and bend a sparking lever with a fire beside the road. And with a movable brush on the crank shaft commutator, he could increase or retard the speed of his engine. For safety's sake Gil installed a governor to keep the engine at steady speed, and a cut-out arrangement whereby, on level roads, the engine could be released for racing.

Then he changed the wheels, going from buggy size to thirty-four-inch wire ones, with two-inch single tube pneumatics glued to the rims, as with bicycles. The only thing that remained unchanged after the four years' work was the original body. That was something he could arrange for when he had achieved mechanical perfection.

"I've got a real runabout," he wrote to Gail at last. "And I'm going to move to Detroit. Most of my machine work has been done there lately, and there's an excellent foundry there, too, so it would be foolish to try to manufacture here. There's talk of a real automobile show in New York this coming November. The Automobile Club of America is arranging for it and it will be one where they show automobiles only; no bicycles. If I can get my model finished in time, I'll exhibit. Then I'll come up to you!"

Wendenville was hard to leave for the last time, and Wendenville hated to see him go. Even the horses of the countryside no longer shied at him and his fearful chariot. And old Zach Wenden—he was shrewd, old Zach—saw, behind Gil's plugging, more than just an effort to make something new. He saw a spirit of "show Jim up or bust"—and he tried to express the feelings of the town, his great voice buzzing warmly.

"Any time you want to come back, Gil, you can have about anything you want here. An' if you see Jim, tell him he'll have to hustle."

His great hand was crushing Gil's almost as much as Jim's had done, but above the black beard a pair of eyes glowed warmly, not maliciously. Gil said nothing, only swallowed, and nodded, and tried to return the squeeze. Then he kicked free the ratcheted clutch pedal, pulled back on the short hand lever that rose out of the right-hand side of the seat, and was gone. A fine bunch of folks, those who stood there, wishing him Godspeed. He shoved the lever forward, and the higher speed of the planetary transmission took hold. A fine town, Wendenville.

"Reckon you won't ever need any help, lad," Zach had said, "but if you ever do—"

DETROIT, the city founded by a Frenchman, where Canada lies south of the United States. Extending along the river between-the lakes like an opened fan, with some of its tree-shaded streets the ribs. City of great stove factories, settled folk of family who lived sedately and were quite averse to the few noisy things that ran through their streets and frightened their sleek horses. Gil had thought of Cleveland first, for Winton's spectacular achievements with his racer were causing many eyes to turn that way. Winton had established records for speed that began, only sixty days after the organization of his company in '97, with a mile on a circular track in 1:48. He had made a second run to New York in five days, was entering foreign racing events—and selling runabouts as a result. Then there was the White Sewing Machine Company with its steam car, and Stearns with his gas runabout. But Gil's connections were already made, so he went to Detroit.

Out on one of those ribs of streets was (*Continued on page 1*

When Neptune Scowls

How Tempests, Fogs, and Stealthy Icebergs Challenge a Mariner's Skill—Queer Mishaps of the Sea

By JACK O'DONNELL



How a Mediterranean rock wrecked the bow of the new Orient liner *Otranta*, on her maiden voyage from England to Australia

SHARPLY to starboard careened the S. S. *Malolo*, largest and swiftest commercial craft ever built in America. A convulsive shiver traversed her hull. Below her water line, six thousand tons of sea water were roaring into her gashed hold. More than three hundred passengers stood, terrified, awaiting the inevitable call to lifeboats.

A moment before, the *Malolo's* geared turbines had been driving her through thick fog in a trial run off Nantucket, Mass. Just built in a Delaware shipyard, she was about to be placed in service in the Pacific. Then, without warning, up out of the mist loomed the Norwegian freighter *Jacob Christensen*, and the next instant the Norwegian buried her prow in the new steamship, twenty-four feet below the water line.

But the call to lifeboats never came. While the freighter, leaking badly, made for port, the *Malolo's* crew leaped into feverish activity. Pumps were manned, auxiliary engines started. Already the automatic bulkheads had swung shut. The ship's designers had averted the tragedy of the *Titanic*, sunk by an iceberg. Self-closing doors walled off the torrent that was inundating the engine room and stoke hole.

A tanker and a trawler, followed closely by Coast Guard cutters and wrecking tugs, answered the *Malolo's* first S O S calls. Aided by radio direction finders, they raced to the rescue, only to find that no rescue was necessary. The disabled ship's passengers lined the rail and watched the salvage preparations with calm unconcern; the most serious part of the mishap, in their opinion, was that the stoppage of the engine put the ship's galley out of commission so that no hot food could be served. The boiler room crew made their first hot drink with the aid of blowtorches; later the trawler *Fisher*, standing by, loaded with fish for the New York market, sent over huge pans of steaming fish to the hungry passengers.

When the *Malolo* arrived at New York, in tow of powerful tugs, divers reported that the hull was rent by a gash twenty feet wide and ten feet long. The impact of the collision had even cracked a plate on the opposite side of the hull, as the freighter's keel had buried itself ten feet deep in the *Malolo*. That the liner should have floated safely for days after its terrific crash was the most amazing feature of the incident, and a tribute to the recent progress of marine construction. "It is unprecedented," said Admiral David W. Taylor, U. S. N., retired, a passenger on the vessel, "to see a ship rammed square amidships and still afloat. We owe our escape to the lessons learned in the *Titanic* disaster."

The doomed crew of the Japanese ship *Raifuku Maru*, clinging to her bridge as she rolled over to sink off Halifax; photographed from the *Homeric* which stood by, powerless in the tempest

THE remarkable escape of the *Malolo* was the result of one of those strange accidents which ever menace men who go down to the sea in ships. A vast majority of the casualties at sea follow the familiar rule of collision, explosion or fire, but there are enough unusual happenings such as the *Malolo's* close call to vary the monotony of shipwrecks and bring gray hairs to the heads of shipowners and marine underwriters.

Three days out of St. John's the schooner *Ponhook*, Gibraltar bound, ran into some uneommonly dirty weather. By nightfall a furious gale was blowing across her slippery decks. The crew went about their duties with no concern, however, for the *Ponhook* had ridden out many a gale in her day and was considered a competent little ship.



Lifeboat leaving the foundering *Ignacio Florio*, from which the *President Harding* saved all souls in an Atlantic storm

The hold of the *Ponhook* was jammed with dried codfish, just weighty enough to give the schooner reassuring steadiness.

The rain came down in slanting sheets. The wind blew relentlessly. The seas ran high, pounding the little craft with unbridled cruelty. Her decks were awash. Then, shortly before midnight, one crashed down on her and smashed a hatch. Sharp commands followed that blow. Despite the devastating fury of the storm, men, held together by ropes, succeeded in closing the opening to the hold. But not before several tons of water had poured in to keep the codfish company.

That water lost no time seeping into the cracks of the boxed codfish. Immediately the codfish began to swell. The wooden boxes burst open, giving the water a better chance to work. As the fish swelled, the boxes on the outside were jammed against the ship's steel plates and burst, providing more fish for the water to expand.

THE captain knew there was only one way to relieve the pressure—jettison part of his cargo. But how? The air was full of flying water, the wind screeched. Wave upon wave looted the decks with unchained fury. Even if men could live on those decks long enough to open a hatch they would invite quicker disaster by letting more water into the hold.

There was nothing to do but wait and hope—hope that the codfish would absorb the water already in the hold before the expanding fish pressed against the ship's sides hard enough to loosen her plates.

Toward dawn the inevitable happened. The seams of the ship loosened and more water seeped into the hold. Gradually the water rose despite furiously working pumps. By nightfall the *Ponhook* was riding sluggishly through the heavy seas. Her head was bowed as if she were weary. Throughout the night she settled and preparations were made to abandon the ship in the one remaining lifeboat.

The storm abated about noon the following day just as the *Ponhook* was ready to go down by the head. She was sighted by a Norwegian steamer, the *Kronstad*, her crew taken off and landed a few days later at Galveston, Texas.

ONE shudders at what might have happened to the crew and 730 passengers aboard the Allan liner, *Grampian*, a few years ago, had not the captain of that ship thought and acted with superb rapidity.

The *Grampian*, enroute from Montreal to Liverpool, was plowing through a moonlit July sea. Men, women and children were slumbering. Into their rooms through open portholes poured cool Atlantic breezes. What if they were off Cape Race—the Graveyard of the Sea? Was it not July, the midsummer season when Neptune lapses into untroubled sleep?

But navigators who know the north Atlantic never sleep. They live in a sort of terror of sea sneaks. Icebergs. They never forget the *Titanic*. They never forget the ships before the *Titanic* which dis-

(*Continued on page 134*)

Wreck of a Coast Guard vessel on icy rocks of Narragansett Bay. A mate plodded barefoot over the snow to summon aid

All that remains above water of the *Ruth E. Merrill*, world's largest six-master, which sank in Vineyard Sound, Mass., with 4,000 tons of coal aboard, while bound from Newport News, Va., to Portland, Me. She was one of the only three remaining American six-masted schooners, once numbering more than a hundred



It took forty hours to bring the crew of the steamer *Wiltshire* to shore in the breeches buoy after she was wrecked off New Zealand

Frauds Bared *by Strange* Detective Rays

Under the detective rays finger nails glow vividly. Note, in contrast, the dull appearance of the ring

INVISIBLE rays that read secret writing, test food, and detect forgeries issue from a remarkable new type of lamp developed by a manufacturer in Hanau, Germany. Made of quartz, instead of glass, to permit the passage of ultra-violet light, the lamp is equipped with a filter, which absorbs all the visible rays of the spectrum. When its powerful "black light" falls on any one of a huge class of substances, the substance "tells its story" by giving off a deep purple, green, or brilliant orange light.

Paper, for instance, glows with different colors under ultra-violet light, depending on how, and of what, it is made. The genuineness of bank notes or rare postage stamps is detected by comparing under the rays the ones in doubt with others known to be authentic. If one turns yellow, say, and the other blue, forgery is proved. Secret writing and erasures, too, glare out strikingly.

Bank notes being tested under filtered ultra-violet rays of the quartz lamp. Counterfeit money is instantly detected because it gives a glow of different shade from that of genuine bills

Forged Bank Notes, Adulterated Foods, Fake Silk, Exposed under Lamp Glare

Testing a tannin solution under the quartz lamp to see if it is genuine or artificial

Artificial tannin, sometimes used to adulterate the vegetable tannin of the leather and dyeing industries, is revealed in tests devised by Professor O. Grengross of the Charlottenburg Engineering College, by its brilliant glowing light under the rays. The natural tannin does not glow.

Examination of food by the new lamp has been conducted by Dr. Popp, legal chemist at Frankfort-on-Main. A bluish glow shows the amount of tendons in a sample of sausage, and decay is revealed by a violet shine. Natural fruit juices identify themselves. Wool shows a different fluorescence than cotton or silk.

World's Highest Dam Turns Valley into Lake



Looking down on the Pacoima Canyon Dam in course of construction. Concrete, mixed on the mountainside, is poured down in chutes

THE highest dam in the world is nearing completion at Pacoima Canyon, near Los Angeles, Calif. When it is finished, at a cost of $2,500,000, a sheer 385-foot wall of masonry will hold back the waters of a lake that will fill a valley. Floods will be averted; for the structure will impound the waters during thaws and rains, and release them when all danger is past.

Already its lower half blocks completely a narrow mountain gorge, the outlet to the natural basin between two ridges of peaks. Its upper half, when completed, will close the 600-foot gap across the valley and transform it into a huge lake —a storage reservoir of surplus water.

Rugged mountains surrounding the Pacoima Dam presented unusual problems to the builders. Engineers conveyed materials straight up the side of one mountain by a novel tramway. At the top they mixed the concrete, then slid it down chutes to the dam in the ravine below. Enough concrete to pave ten miles of road—more than two hundred thousand cubic yards—will go into its construction. Its base will be more than a hundred feet thick; its top, only eight.

Tramway built up mountainside carries concrete materials to top to be mixed and then "shot" to dam below

Unusual strength must go into a dam of this extraordinary height, whose bursting would in itself precipitate a terrible flood. Contrary to popular belief, the force that is constantly seeking to overthrow a dam has nothing to do with the size of the lake behind it; this force depends on the dam's height alone. A dam twice as high as another must be eight times as strong. Imagine, then, the pressure the Pacoima dam must resist!

Other achievements in dam building are the 351-foot Arrowrock Dam in Idaho, the Hetch Hetchy Dam for San Francisco's water and power, others such as the 284-foot Roosevelt Dam in Arizona, the 328-foot Shoshone Dam in Wyoming, and the recent 330-foot Exchequer Dam in California.

Unusual Ideas *Put to* Work

New Synthetic Lumber; Strange Fireworks of the Atoms; Surprising Discoveries about Men, Animals and Plants

Significant accomplishments in research and invention in many scientific fields that bear upon the daily interests of life, as well as upon its many problems, are recorded in these pages each month.

Your Capacity to Learn

"NEVER too old to learn" contains more scientific fact than fiction. In a recent series of experiments with persons of various ages, Dr. E. L. Thorndike, professor of educational psychology at Columbia University, found that men and women approaching the half-century mark learn more rapidly than children, and almost as rapidly as youths of twenty to twenty-four years. Even persons over fifty years can learn new things.

In the learning of elementary school subjects, adults of forty-two progressed about five sixths as fast as adults of twenty-two. Both these groups learned more per hour of study than children comparable to them in natural intelligence.

Further experiments with adults learning algebra, science, foreign languages, shorthand and typewriting, led to the conclusion that the ability to learn increases in youth until about the age of twenty. Then, after remaining unchanged for several years, it declines very slowly.

"The chief reason why adults seldom learn a new language or trade," concludes Dr. Thorndike, "is not lack of ability, but the lack of opportunity or desire."

Flying Safety Increases

ALMOST everyone, these days, would like to fly. But first, just how hazardous is it?

An answer to the question that is on the lips of millions recently was supplied by Dr. Frederick L. Hoffman, consulting statistician of one of America's largest life insurance companies, and it reveals surprising progress in flying safety.

On the basis of air mail records, the present risk is only one death to more than a million miles of flight. In the Army and Navy services the risk is one fatality to half a million miles. Hazards in commercial flying, according to Dr. Hoffman, are diminishing rapidly as the area of operations expands. Recent legislation providing for inspection of aircraft and periodical examination of pilots, he says, will further increase safety.

In a tent in London's Botanical Gardens these girl students are experimenting to determine the effect of ultra-violet rays on tropical plants when transplanted to a temperate climate

Tiny Plants Tunnel in Stone

HOW a mole can burrow its way through hard-packed earth under the sod is always a source of wonder; yet there live creatures that actually can make their way through solid stone. These creatures are not sturdy animals, but living plants; so small you cannot see them without a powerful microscope.

That such amazing tunnel makers exist was revealed recently before the French Academy of Sciences. They belong to the tribe of algæ, like those that form the green scum on stagnant water. And they possess the unusual power of dissolving the rock on which they grow, provided the rock contains lime. Billions of them, growing along the seashore, are known to have eaten away huge limestone cliffs.

Tiny life such as this swarms all about us, unseen and virtually unknown, yet profoundly influencing the world we live in. Many lowly algæ capture carbon dioxide from the air, build it into their bodies and enrich the soil when they die. Certain soil bacteria serve as wreckers that tear down dead plant and animal bodies and return their substance to the dust for the use of growing things.

Can Animals Run Machines?

WILL animals eventually run our machines, relieving men of monotonous drudgery?

That startling possibility has just been suggested by R. J. Rousseau, a French student of animal habits, as the result of

The "colorimeter," invented by Arthur C. Hardy (left) and Frederick W. Cunningham, of the Massachusetts Institute of Technology, makes it possible to match colors exactly. Here they are measuring the color of an apple, seen in front of the motor at the right of the illustration



As the earth cooled it shrank; its crust, "buckling," formed mountains. Dr. T. A. Link, of the University of Chicago, reproduces this action in model mountains of concrete and plaster layers by the means of pressure applied with a jack and saws them for cross section study

fascinating experiments conducted by Claude Bussard, a young inventor associated with the Pasteur Institute in Paris. While studying the intelligence of lower animals, Bussard invented a machine which automatically performs the operations of animal training, as moving doors and making electrical contacts. The animal actually operates the mechanism which teaches it to perform a certain act.

If animals can thus train themselves mechanically, asks Rousseau, why may not trained animals be able to operate the machines of men? Their skill might be increased, he further suggests, by breeding races of animals for each task.

New War on Heart Disease

PHYSICIANS of the American Medical Association recently joined in a concerted effort to cut down the increasing toll of heart disease, which claims more victims in the United States than any other malady, being now responsible for one fifth of all the adult deaths. Doctors have advanced various theories. Dr. Henry Albert, health commissioner of Iowa, believes heart trouble is one of the prices we pay for the increased span of life in the last thirty years. While maladies such as scarlet fever and rheumatic fever have been brought more or less under control, their survivors have been left with weakened constitutions. Scarlet fever brings heart weakness in later years, says Dr. Albert, while rheumatism is responsible for twenty-five percent of deaths from heart disease.

Fat persons are especially subject to heart ailments, according to Dr. Stewart R. Roberts, of Atlanta, Ga. High blood pressure, goiter and disturbances of the thyroid gland have been cited as causes by other physicians.

Of first importance in treatment, physicians generally agree, are regular habits of living, rest and relaxation from strain.

Boards from Lumber Chips

MUCH the same method of explosion that produces puffed cereals for breakfast recently has been used in the manufacture of a lumber which, says the Smithsonian Institution, is stronger than natural wood. Waste wood chips are first exploded, then compressed into boards. The chips are made to absorb steam under pressure. When the pressure is suddenly released the steam expands, blowing the chips into fluffy fibers, which can be pressed into boardlike sheets.



Digging a hundred feet to solid rock, Massachusetts Institute of Technology engineers will place a bench mark to determine in time whether the ground above is slipping seaward

Every Atom a Flashlight

MORE wonderful happenings in the tiny world of atoms have been discovered by Drs. W. H. Crew and E. O. Hulburt, of the U. S. Naval Research Laboratory, Washington, D. C., through their careful and extended study of light given off by hydrogen atoms.

The seemingly continuous glow that is observed in electrified hydrogen in a glass tube, they found, actually consists of myriad sparks of light so numerous that they all blend together. These little light flashes represent the disruption and recombination of atoms. In an amount of hydrogen the size of a pea, more than four billion billions of atoms go through this process and flash every second!

If everybody on earth were to light matches one after another as rapidly as possible, each person would have to light nearly five hundred million matches a second to equal the record of the atoms!

Approaching Synthetic Life

BELIEF that life eventually may be produced artificially has been strengthened recently by Sir Oliver Lodge, famous British physicist, and Dr. Daniel T. MacDougal, of the Carnegie Institution of Washington.

In a lecture at Oxford University, Sir Oliver said that many organic compounds found in living matter, such as sugar, already have been manufactured in the chemical laboratory. If such manufacture can be continued, he added, until a mass of artificial protoplasm is produced, that protoplasm may show vitality in some form of life.

Substantiating this view is an important advance reported by Dr. MacDougal, inventor of an "artificial cell" which behaves in many ways like the cells of living plants. He has produced a new cell which resembles living cells even more closely. This he has done by adding chemicals called lipoids, which are present in plants. The new cell will absorb chemicals in the solution around it, just as cells of plant roots absorb chemical materials from water in the soil.

Lights Controlled by Radio

A FORETASTE of the part radio may play in industry was given recently when Westinghouse engineers, with a working model, demonstrated control of street lights by radio waves, turning lights and groups of lights on and off at will.



T. D. Kelley, London chemist, is mixing his inexpensive new alloy of earth metal oxides, called "solium," previously described in POPULAR SCIENCE MONTHLY. It is called a perfect substitute for costly platinum



The U. S. Bureau of Standards is testing the efficiency of illuminating gas as a possible alternative of gasoline as a fuel in motor cars. Here an electric pump is measuring gas passing to the motor mounted at right



Borers at work on three typical ears of field corn from an infested area, where seventeen percent of the grain was destroyed



A few of the three hundred and eleven borers found in a single hill of corn. Destruction of the husks and stubble helps curb the advance of the pests

An ear showing punctures by borers. First young tassels are attacked, then the stalk and the grain when it develops

$10,000,000 War on Worms

Fire and Plows Used in National Campaign against Corn Borers That Devastate Fields

This field was devastated by borers, which worked up and down in the stalks, making them break before the young sweet corn could mature. The area infested by these worms increased fifty percent last year

FIRES have blazed on 400,000 farms from New York to and through the Middle West, in the last few months, in the campaign to check the alarming advance of European corn borers, the worms that live on corn and that multiplied fifty percent last year.

Congress appropriated $10,000,000 for the campaign in which states coöperated with the U. S. Department of Agriculture. Railroads provided special trains to traverse devastated regions and those not yet reached by the pests, carrying experts who explained methods of destroying and warding off the borers. Quarantines against corn from infested areas were enforced by guards who halted autos suspected of carrying contraband.

Stubble and all else that remains of corn in which borers are found must be burned or plowed under.

The millions spent to eradicate the borers are trifling compared with the millions saved; for the pests, if unchecked, would have destroyed in a few years the whole corn-growing industry.

A hill of sweet corn with the stalks cut to show the work of the borers inside. In this field the borers averaged thirty-seven to the plant. The stalks were so eaten away that they were mere shells, and no ears grew

A ruined field being plowed to destroy borers. The worms cannot live underground and when all the corn is turned under they abandon it and go to the surface. There they starve, or are devoured by birds or insects

Burning stubble and corn remnants of a field ruined by the destructive corn borers. The apparatus includes fuel-pressure tank, pump and "burning carriage" with nozzles that develop heat of 1400 degrees F.

Airships 2,000 Years Old!

Steam engines, motion pictures, and many other "modern" inventions were used by ancient priests to mystify

By H. C. NORTH

STEAM, electricity, motion pictures, airplanes, gunpowder—those are inventions and discoveries which characterize modern civilization. They come to mind whenever present-day progress is mentioned; they make our age. But do you know that the ancients stumbled on many of our recent mechanical and engineering discoveries—the steam engine, for example—centuries before Christ?

You probably do not, for very few of the inventions of antiquity survived their day or saw useful application. But the recent appropriation of $100,000 yearly by the Italian Government, to cover the expense of excavations in the ancient Roman city of Herculaneum, has focused attention on the scientific discoveries of two thousand years ago. Concealed in the lava from Vesuvius since the first century of our era, Herculaneum—one acre of which is now uncovered—is every day revealing more than archæologists ever before have known of ancient life and knowledge.

The inventions which today run our factories, light our offices, carry our mail, and add to our comfort were employed first to perform feats of magic to make people believe the priests in heathen temples had mysterious and supernatural powers. They were painfully worked out to deceive and trick the ignorant, and being the trade secrets of the temples, were not common property. In their search for tricks, these ancient priests blundered upon the principles of practically every branch of modern science. Those principles were carefully guarded secrets, concealed in mystery and presented as miracles.

THAT medieval prophet of science, Roger Bacon, in the early part of the thirteenth century, predicted many of our modern inventions, such as steamboats, automobiles, airplanes, diving suits, and so on. All of these, he asserted, were known to the ancients. "These devices," he said, "were made in antiquity, and they are certain. I am acquainted with them explicitly."

Steam was used in the temples of Babylonia, that strip of country north of what is now Arabia, as early as the eighteenth century before Christ. Here, amid mystic rites, images of gods were caused to nod their heads, lift their arms, or open their eyes. Invariably, beneath the altar before the idols, a metal box or tank was concealed. Pipes ran from the tank to a mechanism within the image. Before the supposed miracle was to be staged, hot water was poured into the tank and live coals placed on the altar. A slight pressure of steam was thus generated. It took but the added heat of incense and scented wood to force steam through the pipes and set in motion the crude machinery which animated the idol.



Illustrated by G. M. Richards

How the doors of ancient Greek temples were opened, as if by the gods, when the priest kindled a fire on the altar

Busterich, who received the homage of the Teutons in barbaric Germany, was a famous idol whose mighty spirit was none other than steam. He was constructed of metal, with a hollow head, and his eyes and mouth were made of wooden plugs. Hot coals placed on his head heated the water within, and the steam thus generated pushed out the plugs and spurted from the apertures.

Hero of Alexandria, Greek writer and geometer of the first century, A.D., described one of the earliest steam engines. He also told of the employment of steam to cause statues to pour libations and serpents to hiss.

The Greek "flying chariot" of more than twenty centuries ago. Suspended from a gas bag, which was said to contain a "minor god," it was propelled by huge wings flapped by a hand crank

HERO further described the use of hydraulics and pneumatics in the Greek temples. Mechanical birds sang when air was driven through pipes by the pressure of flowing water. Temple doors were opened, as if by the gods, whenever a fire was kindled in the altar. This was done by means of an air chamber within the altar, from which a pipe led through the floor to a spherical vessel containing water. The altar fire expanded the air, forcing some of the water from the vessel into a bucket which was hung from pulley ropes in such a way that its descent rotated a pair of posts on which the temple doors were fixed. When the fire was extinguished the process was reversed and a counterweight closed the doors. The syphon, which today conducts water over mountains, caused bronze birds and animals to drink wine. Magic drinking horns and inexhaustible jars, fed by a syphon from a tank concealed in another room, impressed the laity by always remain-

ing filled regardless of the quantity of wine drawn off.

One invention of the priests which did not die with its inventors but has passed directly down to us, and is still used by magicians on the modern stage, is the concave mirror. From it sprang the magic lantern and lately its lineal descendant, the motion picture.

DAMASCIUS, the philosopher of Damascus who taught in Athens during the sixth century, A. D., describes an apparition in a temple of Alexandria, Egypt. It first appeared on the wall above the altar as a small light. Then the light grew larger and brighter until it "resolved itself into a face, divine and supernatural, severe but gentle and beautiful." This illusion was effected by placing before a concave mirror, concealed in a darkened room, a brightly illuminated painting or sculpture of a face. The image of the face was thus projected upon the wall of the temple. You have probably noticed this same illusion in your own home, when sitting in a dimly lighted room with the shades drawn. The sun is shining brightly outside, and figures passing on the street are projected upon the ceiling through a small crack beneath one of the shades.

Still more startling was the illusion when pictures of the gods were projected upon smoke from the altar fires, the smoke acting as the screen does for the motion picture. To the superstitious, the apparitions were spirits conjured out of thin air. Huge silver mirrors, perfect in detail, were used by the magicians. And as they grew more adept in the art, living images were cast upon the smoke. Assistants dressed as gods and demons were substituted for the paintings originally used; here, however, two mirrors were found necessary to counteract inversion. When the trick is performed by experts, the aerial figures are uncanny even to those familiar with the operation.

The secret of air navigation was known to several ancient sorcerers. But it was too great a feat of conjury to be divulged even to confederates; so the mystic formula was lost and several times rediscovered before modern times.

THE Greek experimenter, Archytas, who also constructed many hydraulic mysteries, invented in 400 B.C. a dove that could fly. But once it had alighted it could not take flight again until set in motion by its master. Of that wonderful bird, a Latin commentator of the second century, A.D., Aulus Gellius, wrote that it was "suspended by balancing and animated by a spirit." Gellius, however, explained that its motion was due to machinery concealed in the body. We now know that the bird was "suspended" after the manner of the airplane, and that the "spirit" which set it in motion was compressed air escaping from a valve.

One of the earliest flying machines was the eagle, formed by Johann Muller, fifteenth century German astronomer, which greeted Emperor Maximilian by flying three times around him. An iron fly, built by the same inventor, could soar in a wide arc and return to his hand.

Lighter-than-air machines contributed to the miracles of the Greek priests as far back as 500 B.C. A statue of Apollo, carried in religious festivals, raised itself into the air, then descended into the arms of the magicians. The statue was hollow and filled with natural gas volatile enough to raise and float the image for a moment.

But far more wonderful was the flying chariot which could be guided through the air by a magician who rode in it. As described by an early historian, the chariot was "carried through space by one of the minor gods imprisoned in a bag above." The minor god, of course, was a gas with which the bag was filled. The chariot suspended from this bag was driven forward by huge artificial wings which were operated by machinery. The passenger furnished the power by turning a crank inside the chariot.

The ancestor of magic lanterns and motion pictures—Egyptian priests used a concave mirror to produce apparitions on walls. In a darkened room an illuminated face was held inverted before the mirror, which projected the image

The lashing of a sword to the mast of a vessel as a protection against lightning can be traced in the superstitions of all countries. Though it was regarded purely as a superstition, and was forbidden as such in medieval times, it was really the forerunner of the lightning rod of Ben Franklin.

Numa, generally considered a magician by the Romans of 400 B.C., carried on electrical experiments under the guise of summoning Jupiter from the clouds. A pupil, Tullus Hostilius, was killed by lightning while repeating his experiments, or "sacrifices," as they were called. By placing swords upright on the temples of Juno, Numa was able to attract the lightning and cause it to crackle within the temples. The lightning rod for ships came as a result of his studies, but like all ancient miracle workers, Numa pretended that it was an offering to appease Jupiter.

That the early priests employed magnets in their wizardry we know by the statues of the Greek goddess, Diana, and the Egyptian Serapis, which were elevated to the tops of temples and suspended there by magnetic force. The stone images had metal rings in their hair so that the magnets in the temple roofs would attract them.

IT IS well known that the Chinese had invented gunpowder centuries before the foundation of their empire in 300 B.C. It was used by their magicians for rockets and bombs in religious festivals prior to its use in combat. Even among the Christians it was looked upon with superstition, for Constantine, the first Christian Roman emperor, was supposed to have received its secret, in the third century, A.D., from an angel. The formula was disguised in mystic writing until it was finally lost. As late as the thirteenth century, Roger Bacon concealed a formula for black powder in his directions for making the "philosophers' egg."

The wheels, cogs, shafts, and pistons which run our factories, first invented to deceive, were anticipated in the machinery which animated the automata or mechanical images of the ancients. Among the earliest were the prehistoric statues created by the Greek sculptor, Dædalus, which walked and moved. The Greek philosopher, Aristotle (384–322 B.C.), said that they were animated by putting mercury in them, but we know that they were controlled by wheels and weights similar to our modern clockwork.

BECAUSE of a craze for these toys, which persisted until the eighteenth century, when it reached its height, the ingenuity of the ancient mechanic-magician was preserved. Albertus Magnus, Robert Grosseteste, and Roger Bacon, in the thirteenth century, made images that walked and spoke, as well as moving, speaking heads. Then followed the bleating sheep and barking dog of Le Droz; the singing bird of Maillardet; the walking duck of Vaucanson, which ate and digested its food; and the talking machine of Kratzenstein, which could pronounce simple words when air was forced through its various shaped pipes. These and hundreds of others contributed to the science of mechanics and of sound.

Other devices (*Continued on page 138*)



Max Valier, astronomer-aviator, and the trans-Atlantic passenger rocket he proposes

To Europe *by* Rocket

Airship Shot through Sky Could Reach Paris in Ninety Minutes, Says Designer

NEW YORK to Paris in an hour and a half! With rockets instead of propellers to drive it, an amazing airplane proposed by Max Valier, German aviator and astronomer, could, he says, whiz across the Atlantic Ocean loaded with passengers and cargo in this incredibly swift time. A rocket ship, which, he asserts, is capable of climbing to the thin air fifty miles above the sea and roaring through it at more than a mile a second, has been designed by Valier.

To cross the ocean, according to the inventor, you would climb into the cigar-shaped central cabin that houses passengers, cargo, and the machinery that steers and controls the strange craft. All is ready; the pilot jerks a lever. With a tremendous roar the rocket airplane races up an almost vertical runway, flings itself free, and heads straight into the upper air. At an altitude of fifty miles the pilot flattens his course; now he can put on full speed without any danger of burning up the craft like a meteor, for there is little air resistance here. Hardly more than an hour after leaving New York you are over Paris; the craft slows, and descends, and auxiliary rocket motors bring it gently to the earth. Perhaps one stop was made en route for fuel, say at Vigo, on the coast of Spain.

This is possible, Valier says, with a finned ship that carries on its sides huge rocket tubes for propulsion. Besides passengers, it would hold three times its own weight of fuel. Gunpowder, ordinarily used in skyrockets, would be much too heavy. But recent progress has been made in laboratory experiments with rockets using fluid propellant and a new ignition system. Liquefied hydrogen and oxygen under great pressure would furnish sufficient speed by their explosive combustion, according to the inventor. New fuels may prove better still.

Controls would enable the pilot to shut off or to turn on the rockets at will, in order to maneuver his craft. A gyroscopic indicator like those now used in airplanes would guide his flight above the clouds. There would be a "gas lever" to control the speed of the super-airship.

In carrying out his design, Valier says he will avoid risking anyone's life in a full-sized machine. Careful tests must be made before we can tell how to control such a craft. The first experiments will be made with a seven- to ten-foot model. Then several of the "rocket tubes" developed in this way will be placed on the wings of an ordinary airplane to see how the rocket works in flight. If this proves successful, the rocket ship will then be built.

It might prove capable of leaving the earth altogether, says Valier, like other exploring rockets proposed by various inventors. If a speed of eight miles a second were attained, the craft could escape from the earth's gravity and journey to the moon or through interstellar space. But here arises new danger—could human beings live away from gravity?

Even in an earth flight the ship would have to be maneuvered with great care in starting and turning, lest its terrific speed prove fatal to the occupants. During recent airplane races, in which new speed records were made, pilots became momentarily unconscious at the turns of the course. But gradual control of a rocket ship within the limits of human endurance is technically possible, Valier believes.

Fingerprint Records on Skin

WHILE treating a patient with a certain solution and ultra-violet rays, Dr. Maurice A. Aaronson, of Long Branch, N. J., was startled recently to see brown fingerprints appear all over the patient's back. They were his own. Investigation showed he had accidentally found a new process for discovering and making as permanent as desired, fingerprints on a human body—a "find" which is said to be of importance in criminology.

The method consists of brushing the suspected flesh with a solution whose composition is kept secret, and exposing the body to the ultra-violet rays from a small portable machine. The resulting brown prints are not removed by rubbing, and can only be scrubbed off.

Machine Fights Forest Fires

ONCE a battle against overwhelming odds, the fighting of forest fires has now become a science. Forestry officials from Washington and San Francisco recently saw demonstrated at Barley Flats, near Mt. Wilson, Calif., the latest aid to fire-fighters—an amazing tractor-plow that cuts away a swath of brush straight across the path of the fire to serve as a barrier. When the pillar of smoke and flame that presages a forest fire appears in the distance, this marvelous engine on its "caterpillar" tread is rushed through the woods and fields, shearing off and uprooting everything in its way. If the oncoming fire is small, this path alone will stop it; while if it is of giant proportions, the forest rangers use the clearing as a boundary to start a "backfire" that burns away the brush in the path of the threatening blaze.

Tractor drags sharp-edged triangular plow, clearing path to bar flames where primitive methods failed



Shop is seen at right prepared for rush to factory to save delay and expense by welding machine part without dismantling

Welder, having reached scene at twenty-five miles an hour, generates power and repairs casting "while you wait"

Poison Ivy Antidote Found

AT LAST a cure for the irritation caused by poison ivy, familiar toxic weed of the East, has been found. Dr. James B. McNair, of the University of Chicago, reports that after years of work he has distilled and isolated the ivy's poison, a gummy brown substance in the leaves, and discovered an antidote for it.

Ferric chloride solution, a well-known salt of iron, effects the cure, Dr. McNair says. A five percent solution in half-and-half alcohol and water, or glycerine and water, is the mixture used; the materials are obtainable from any drug store, and are cheap. When the skin is rubbed with this solution either before going into a place where poison ivy grows or after exposure to it, poisoning never develops, tests have shown. Instead of ferric chloride, ferrous sulphate, another iron salt, can be used with equal success, in a strong solution whose exact strength does not matter.

Another effective remedy, suggested by J. F. Clough, chemist of the U. S. Department of Agriculture, is a permanganate of potash solution to treat the poisoned skin. It brings immediate relief, he says.

DO YOU LOSE weight when you perspire? Yes, say Dr. Francis G. Benedict and Cornelia G. Benedict of the Carnegie Institution of Washington. With the moisture exhaled in breathing, the weight lost hourly is one ounce for the average woman; a third more for a man. They used balances able to hold a man's weight, one 100 times more sensitive than the other.

A Welding Shop on Wheels

TWO mechanics of Dayton, O., have devised a machine that travels to the job and generates its own current for electrical welding.

A welder is mounted on a rebuilt tractor, the wheelbase lengthened by building the device on an ordinary automobile frame. The tractor has a side crank and operates the generator by a belt hook-up. Under the generator, which produces an ample current of 300 amperes, is a resistance coil which tends to stabilize the arc.

The possibilities are almost unlimited. The shop may be rushed to a factory to repair a heavy machine part, saving delay and expense of dismantling.



Wheel Operates Car Lights

WITH both hands on the steering wheel, a driver may now dim his lights or sound his horn. In a new French invention, a second wheel that operates the warning signal and makes all headlight changes, is set just inside the usual one. It may be reached easily with the thumbs while control of the steering apparatus is retained. The new arrangement, it is said, makes driving safer.

Thousands of Tons of Color

THIRTY thousand tons of color is the present yearly production of dyestuffs in this country, according to a recent estimate. But this is only about half the capacity of our plants. France and Switzerland produce about seventy percent of their plant's capacity.

"Armor" of Germ Analyzed and Found Made of Wax

NOW the germ that causes tuberculosis has been chemically analyzed, and a new phosphorus-containing fat has been discovered that has remarkable physical properties. Recently Prof. R. J. Anderson of Yale University took eight pounds of the deadly bacilli into his chemical laboratory and performed a careful analysis to find what they were made of. These germs possess a waxy shell which gives them unique powers of resistance against the germ-destroying corpuscles of the blood. Prof. Anderson removed it with alcohol and ether, obtaining a pound of wax, a half pound of fat, and a half pound of a unique fatlike substance containing phosphorus, to which he gave the name "phosphosucride."

"This compound differs from all other known phosphorized fats," Prof. Anderson stated. While he is endeavoring to find its formula, investigators at the Rockefeller Institute for Medical Research, in New York City, are testing the remarkable substance to find a possible clue to a new treatment for tuberculosis.

Another great step against the disease may be taken if a way can be devised to destroy the waxy armor of the tuberculosis organisms, which has enabled them to defy the phagocytes that "police" the body. Instead of being destroyed by these "biological patrolmen" the bacilli have survived and multiplied among them to continue their deadly work.

A Motorist's Rocking-Chair



ALMOST a rocking-chair, with all its comfort, is said to be an automobile seat equipped with a new set of springs to fit beneath it. According to the maker, the oil-tempered springs absorb jolts and jars incidental to motoring and make long drives a pleasure instead of an endurance test. Any tilting seat of the type used generally in closed cars may have the shock absorbers attached; two suffice for most persons, and three for heavyweights.

POPULAR SCIENCE MONTHLY is glad to supply, when possible, the names and addresses of the makers of apparatus and devices described in these pages. Inquiries should be addressed to Information Dept., POPULAR SCIENCE MONTHLY, 250 Fourth Ave., New York City.

Through the front windows these elevated rear deck passengers see as well as the riders in the front row

Interior of novel two-floor sight-seeing bus, showing first level, steps and balcony to which they lead

Sight-Seeing Bus Has Balcony

PASSENGERS in back, as well as those in front, have an unobstructed view ahead in a novel sight-seeing bus recently introduced in Germany. The rear half is raised like a theater balcony, reached by steps inside the bus, and occupants peer over their fellow passengers' heads through the windows of a "second story" that pierces the roof. For the first time, all occupants of a bus may have a clear view of the picturesque country in the suburbs of Berlin, where the innovation has been placed in operation.

Personalities Made Over

YOUR personality did not develop until late childhood, and even now it is subject to change, according to Dr. Charles Judd, of the University of Chicago. Differing with other modern psychologists, who believe that a man's character becomes definitely established in the first five or ten years of his life, Dr. Judd declares that human nature is never wholly fixed. The school years are most important in shaping character, he says. Social "instincts" and "taste" are acquired only after a long train of highly complicated experiences, but at any time, he states, it is possible for a grown person, under proper discipline and training, entirely to make over his character.

Lights Show Inside of Eye

NOW it is possible to look into a living eye through a microscope. This striking feat has been performed by Dr. Basil Graves, of London, England, inventor of a method of lighting that sends powerful beams into the side of the eye. Until the present time it has been impossible to illuminate the eye sufficiently to use a microscope without injury to the organ. A direct beam would play havoc with the sensitive retina which corresponds to the film in a camera; but by sending intense light rays sidewise into the eye, Dr. Graves is able to examine it from the front through the powerful lenses of an ordinary microscope.

Super-Beacon for Chicago

MORE powerful even than the airplane beacons of London and Paris is to be a searchlight at Chicago to guide night pilots New York and Chicago bound. This is the most spectacular feature of a landing place recently planned for Grant Park, a few minutes' ride from Chicago's business center, which will facilitate a night air service between the cities. The super-beacon, 500 feet above street level, will be visible at Milwaukee, Wis., eighty miles away. Like the new fog-piercing scarlet light for the guidance of airplanes, recently described in POPULAR SCIENCE MONTHLY, it may employ electric tubes filled with neon gas.

Baggage Car for Every Motor

A NEW extension for attachment to any motor car, as shown in the picture below, looks like and serves as a trunk when trunk service alone is required; but can be opened and made to carry small trunks, bags, camping equipment or whatnot when occasion requires. The device is of steel and easily carries more than 360 pounds. Salesmen's samples and dairy farmers' milk cans are among the innumerable bulky things whose transportation problems this equipment has solved.

Bees Sip Poison

HONEY that poisons has been discovered in Asia Minor by Dr. K. Krause, German explorer. Eating it causes giddiness and sometimes temporary unconsciousness, he says. Poisonous species of rhododendrons are believed to furnish the nectar the bees turn into toxic honey. This same poisonous honey was described by the Greeks, Xenophon and Aristotle.



Just a trunk ordinarily, this motor car accessory can be opened out to carry small trunks, bags, furniture and so on

World's Largest Dock Can Load an Entire Fleet at Once



WITH completion of the $35,000,000 Gladstone Dock at Liverpool, England claims the largest, and most completely equipped, shipping dock in the world. This monster structure occupies fifty-five acres over the water. It has sixty-six electric cranes to load and unload the numerous vessels which can be moored simultaneously to the huge pier.

Regardless of tides, a unique lock system permits access to vessels of all sizes. The Graving Dock, largest dry dock in Europe, is part of the system. Some idea of the immensity of the docks is given by the men discernible at the waterfront end of the nearer pier in the illustration.

How Much Do You Know of the World You Live In?

TEST yourself with the twelve questions below, selected from hundreds sent in by our readers. For the correct answers turn to page 151.

1. Which is the best harbor in the United States?
2. Where are there blind fish that live in caves?
3. Where are foxes raised for market?
4. What are tortillas?
5. What island is called the "Gate of Treasure?"
6. What is the largest river in the world?
7. What is the Maelstrom?
8. What bird cleans the crocodile's teeth?
9. For what town is muslin named?
10. What is a lama?
11. Where are houses built in trees?
12. Where are small idols put in oyster shells to be covered with pearl?

Builds Diving Motor Boat

MOTOR boat or submarine at will is a remarkable craft designed by Ettore Bugatti, French automobile manufacturer, and now under construction at Moulsheim, Alsace. It can be closed to make a dive, coming up now and then for air; in calm weather it travels on the surface. With this novel craft Bugatti believes that he can cross the Atlantic Ocean from Brest, France, to New York in about fifty hours.

Lateral fins govern the depth at which the craft travels. Six motors, with a total of 2400 horsepower, will give an estimated speed of seventy-five miles an hour. More than a hundred feet long and eight feet wide, it will have a crew of eight.

Earthquake "Made to Order"

WHEN a geologist addresses an audience on earthquakes, he cannot readily arrange a lecture table demonstration as do the chemist and physicist. But Nature came to the aid of James P. Fox, who recently lectured in Los Angeles before the Geological Society of America, on the active rifts or rock faults responsible for local quakes. In the midst of his talk a minor rock-slip occurred, and the meeting was treated to a plainly perceptible temblor.

Expedition to "Lost World"

SOON the "lost world" of Mt. Roraima, Brazil, will yield its secrets to the American Museum of Natural History's expedition, now under way. The high plateau with the sharp-cliffed peak of Mt. Roraima, the scene of Sir Conan Doyle's famous story and movie, "The Lost World,"—is older geologically than most of South America, a promising place to look for prehistoric traces.

The expedition has no hope of finding the dinosaurs and winged pterodactyls of Conan Doyle's romance; but its biologists, T. D. Carter and G. H. H. Tate, believe that they may come upon other animals, possibly descendants of these, unlike any known at the present time.

What the Moon Is Made Of

ONE common earth rock is totally absent on the moon, says Dr. F. E. Wright of the Carnegie Institution at Washington, D. C., after a remarkable series of studies of our nearest heavenly neighbor made with polarized light, which differs from ordinary light waves in that its vibrations are on a flat plane.

Basalt is the missing rock, says Dr. Wright. Originally formed by volcanic action, it is abundant on earth. Other rocks detected on the moon are familiar; they include pumice and granite. Both of the latter reflect light in an ordinary way, as does any other rock containing much of the element silicon found in sand and glass. But when a ray falls on basalt, it behaves quite differently. All its vibrations except those in one flat sheaf are "rubbed off" and the light is "polarized." With delicate optical apparatus that could measure this polarization, incomplete at best, Dr. Wright studied the materials that compose the moon's surface.

Hop Growers Work on Stilts

YOU have to be good at walking on stilts to raise hops in Kent, England. In preparing the eighteen-foot poles to carry the trailing hop vines, gardeners make the rounds on lofty stilts, carrying with them a supply of twine. The scheme has worked out splendidly, for it takes a worker only a few minutes to restring the poles with cord to carry the vines, as he goes walking along with giant strides many feet above the ground.

Walking on high stilts, the English gardener above restrings the poles for his hop vines



Airplane view of completed sea wall to island of Wieringen

Dike to Enlarge Holland

WITH the recent completion of a sea wall from the Dutch mainland to the island of Wieringen, engineers have accomplished the first step of a gigantic undertaking that will totally change the map of Holland. They plan to remove the Zuyder Zee—that great arm of the North Sea that swept into the interior of the Netherlands six hundred years ago and has remained there ever since.

A wide expanse of water only ten to twenty feet deep, yet fifteen hundred square miles in area, is now to be blocked off by a huge dike, fifteen miles long. Then the gulf will be drained, increasing the country's total land area by more than a tenth. Begun in 1925, the project is now well under way and will probably be completed in ten years.

Vibrating Bed Woos Sleep

SLEEP is easy in a new bed that rocks like a cradle, the invention of Sir Alfred Yarrow, British physicist. Long troubled with insomnia, he found that the rocking motion of a railway train put him to sleep. Under his direction, the National Physical Laboratory in England constructed a bed that reproduced the same motions. They occur at the rate of eighty a minute, and the vibrations are short—only three eighths to three quarters of an inch in range. Lest the movements produce nausea, they are made to occur irregularly.

Aviator Chases Rainbow

ALTHOUGH many a child has raced after a rainbow to find the legendary pot of gold at its end, it remained for an Army aviator to pursue one in an airplane. Flying east to Washington to participate in the recent air maneuvers, Lieut. P. E. Skanse saw appear below him a magnificent rainbow which formed a complete circle—a rare spectacle reserved for aviators, sailors and mountain climbers. The colorful ring glowed above an Illinois plain, near Chicago.



Mask Saves Pugilist's Face

IN ORDER to protect a champion boxer's face from possible damage at the hands of his sparring partners, a curious new type of mask has been invented in Germany. First reported from Berlin, it has already been adopted by several German boxers for their training bouts. The grotesque headgear is attached by straps about the head. Its padded ridges protect the eyes, nose and jaw of the boxer without hindering his breathing, sight, or movements.

World's Biggest Freight "Parcel," 80 Tons

A TOWER used in the manufacture of gasoline recently made the largest piece of freight ever shipped over a railroad. Just delivered at Los Angeles from Boston, the eighty-five-foot tower, weighing nearly eighty tons, was carried on three flat cars. Due to its length and weight, a route was chosen that avoided extreme curves and grades. The consignment was unloaded step by step; as each car was slid from under, blocks were inserted to support the tower. Erection at the refinery required use of two gigantic poles as legs of a derrick. Eight minutes of breath-taking effort swung it into place after days of preparations.





Above: Hoisting one-piece tower with reinforced derrick. At right: Unloading the eighty-five-foot tube from three long flat cars was an engineering feat

Horse's Mummy in Coffin

HORSES as well as human beings were preserved as mummies by the early Egyptians, according to a recent discovery by British officials at Sakkara, near Cairo, Egypt. They found an eighteen-year-old Egyptian horse that had been mummified and ceremoniously buried about 3000 years ago. It had been wrapped in cloth, and the doubled-up legs were tied together with papyrus ropes.

KNOW YOUR CAR

THE brakes on your motor car depend for their effect on the amount of friction that is developed between the brake lining and the brake drums. And the amount of friction is determined by the condition of the friction surfaces.

Under ideal conditions, the effect produced by the brakes should always be the same for any particular amount of pressure that is applied to the brake pedal. However, those conditions never can be completely obtained, because of varying weather, increasing effects of wear and imperfect adjustment.

Dry and dusty brake lining grips strongly. Wet and slimy lining is not nearly so effective. Rough or badly scored brake drums cause wear on the linings and this throws out the adjustment so that the brake pedal leverage changes.

For best results from your brakes, follow these rules:

1. **Make sure that the brake drums are smooth and that they run true.**
2. **Have the brakes lined with the best lining you can buy.**
3. **See that they are kept properly adjusted.**
4. **Don't expect them to hold as well in rainy weather.**
5. **Adjust the brake bands so that they do not touch the drums when your foot is off the pedal.**

A Dozen Products

An unusual clock with a face like a speedometer is the invention of B. M. Campbell, of Utica, O. In the upper window bold figures indicate the hour, while minutes are shown on a revolving drum below. The clock can be inserted behind the instrument board of any motor car



Radio beacons will be set up across the nation by the United States Government to guide aviators in darkness or fog. Their distinctive signal, "Bzz, bzz," tells the airman he is within two miles of a landing field. C. B. Hempel, U. S. Bureau of Standards, is shown at left with one of the beacons



This rustic fence and stile gate in San Antonio, Tex., was made of concrete by Dionecio Rodriguez, a Mexican artist, to fool woodpeckers and people and outlast real wood. When the concrete had set, he painted it and fixed the colors with acid so as to reproduce ax scars, wormholes and broken bark

The concrete tree seat pictured above is grooved to represent wood planks. Fissures and paint "worn off" by the artist suggest great age

This lawn mower has thirty-six blades, and, like a safety razor, interchangeable. New ones cost a dime each. It "shaves" the ground short if required, and an attachment throws out stones before the blades can reach them

Amateur astronomers can find the North Star with the aid of this ingenious device invented by Clement Engel, of New York City. Two magnetized steel bars, balanced to swing horizontally as they hang on a thread, point north and guide an inclined wooden rod to show the position of the polestar. Within a wooden ring is a small model of the earth shown at correct inclination

As accountant at the Alabama Polytechnic Institute, S. J. T. Price saw time and energy wasted folding and inclosing letters. He set out to construct a machine to do the job, and the result was the model at the right, completed after four years. He claims it will fold and feed into envelopes 5000 letters an hour—the task of ten men working at top speed!

# of Inventive Skill

Now you can turn your phone into a radio set. George F. Mitchell, of the U. S. Department of Agriculture, invented this simple attachment that converts any telephone instrument into a crystal receiver for reception of local broadcasting. Two pins tap the phone wires to serve as antenna and ground. The crystal detector is manipulated by a knob at the top. A bracket holds down the receiver hook



Filings of precious gold that the dentist loses are saved by the new attachment, shown above, designed for use with the ordinary equipment for grinding down inlay and bridge. It catches the costly bits in a hood. The inventor claims it saves ninety percent of the filings. The loss to be overcome is illustrated by the U. S. Mint's recent extraction of $200 worth of gold from a dentist's rug



Here's an easy way to fertilize your garden. An attachment inserted at the faucet contains a "stick" of soluble plant food which is dissolved automatically into the hose stream. Thus the plants are sprayed with a mixture of fertilizer and water



Paddling his paper canoe, Willy Schauer, German inventor, is shown above. The paper is stout, hard and waterproofed. Advocates of such boats say they are lighter than wooden ones, yet equal them in strength, and hence in safety. They also contend the cost of manufacture is lower. The builder says his craft has met all the tests to which wooden or canvas canoes are subjected

"Scarlet fingers of light," 300 feet long, as night signals for English traffic police are advocated by J. W. Blakey, English inventor, shown at left with a new lamp he has devised to project a rocketlike ray. Motorists can see the signal from afar, he says, avoiding traffic tangles



The motor-driven "seasick chair" shown above reproduces the roll and pitch of a ship and is used by French officials to test applicants for navy and merchant marine posts. If they endure this ride, they fear no ocean, for it rivals the roughest sea



A Skyscraper of Glass

A SKYSCRAPER modeled in glass, recently exhibited in New York, shows in a striking way how art and utility will be blended in the giant buildings of the future if those who propose them are true prophets. Masses rising to a dizzy height in vertical lines and elongated towers are features of the proposed new type of architecture. Designed by Hugh Ferriss, noted architect, the ingenious glass model shows more clearly than any set of blueprints both the outside and inside of a new style of skyscraper, that will be supported by steel girders in a circular well at the center. Office suites surround the "hub" in radiating fins.

Squirrel's Memory Tested

CAN squirrels remember where they hide nuts? L. R. Dice, of the University of Michigan, says they can, after testing the nut-finding ability of a fox squirrel that came regularly to his house to be fed. By placing some nuts buried and others uncovered in a box of sand, he found the squirrel discovered only the nuts that were in plain sight. If all were buried, the squirrel would depart without dinner.

This, he says, shows that squirrels do not "smell out" buried nuts, as many persons have thought. "If squirrels do not find buried nuts by use of the sense of smell," Dice declares, "the presumption would be that they remember the place where they have buried each nut that they find. This would require a well developed memory, though not necessarily a perfect memory; for squirrels undoubtedly fail to find many nuts they have buried." His observations confirm the recent similar conclusions of Dr. A. Brookes Klugh, of Cornell University, who has studied red squirrels for eight years, and has watched individual squirrels for as long as two years.

Biggest Family, 44 Children?

NEW interest in the disputed question as to who has the largest family has followed the recent discrediting of the report that a German named Scheinberg is the father of eighty-seven children by two marriages.

Biologists are still uncertain as to the maximum size of a human family. According to Robert Cook, editor of a medical publication in Washington, D. C., the most authentic case of a large family is that of Dr. Mary Austin, a Civil War nurse, who laid claim to a family of forty-four children—thirteen sets of twins and six of triplets. While bringing up her family she found time to study medicine and obtain a doctor's degree.

Seeds Forecast Tree Sizes

THE bigger the seed, the better the tree, is the conclusion drawn from recent tests by the U. S. Forest Service. When seeds of such important western forest trees as the California sugar pine, western yellow pine, and Douglas fir were planted under careful supervision, says E. N. Munns, chief of the office of forest experiment stations, large seeds were found to produce uniformly large seedlings. Transplanting, the tests also showed, nullifies this advantage; for the larger roots of the oversize seedlings are more easily damaged when dug up.

Medal for Purest Insulin

FOR his recent discovery of a way to prepare crystalline insulin of hitherto unknown purity, for treatment of diabetes, and for being the first to prepare the gland extract adrenalin in a form available for treating the blood vessels, Dr. John J. Abel, noted biochemist of Johns Hopkins University, has been voted the man now living who has done most to promote enjoyment of life. The Willard Gibbs Medal, awarded yearly for this service, was presented to him at a recent meeting of the American Chemical Society. "The human body is a walking drug shop," Dr. Abel told the society. "There are, perhaps, seventeen glands in the body which secrete and pass into the body certain substances. We are just beginning to understand a little about these glands and their functions."

Dropper Feeds Tiny Birds

YOU couldn't find a much smaller pet than a baby humming bird. Two of them, "Gay Boy" and his sister "Bee," were recently adopted by Jimmie Mitchell, of Los Angeles, Calif., when he found them lying on the ground, their nest knocked down by a dog. They are thriving on a daily diet of honey and water, fed through a medicine dropper by their twelve-year-old keeper, and soon will be strong enough to fly.

The illustration above shows Jimmy giving "Gay Boy" his lunch. This bird, the livelier, soon began trying his wings every morning, while "Bee" sat on a large pink rose and watched the fellow orphan with keen interest, as if studying for future efforts along the same line.

Garden Is Floral U. S. Map

FLOWER gardens of many shapes have been seen, but so far as known the one shown below is the first of its size patterned on a map of the United States. Forty-eight states will appear in blooming colors at Bay Front Park, Miami, Fla. Made of flowers and shrubs contributed by cities in the various states, the unique floral map will be maintained perpetually by Miami's municipal park division.

Forty-eight states contributed plants for this United States map produced in blossoms in Bay Front Park, Miami, Fla. Miami girls, former residents of the various states, planted the flowers



Magnifier in Pencil Style

ALWAYS handy and easy to use is a powerful new magnifier in a pencil-like barrel, with a clip for carrying in the pocket. Two small lenses in the barrel magnify an object twenty-five times. The enlarged image is seen in the open top of the "pencil," while the lower end is cut away at an angle to permit full illumination of the object examined. Students of natural history in the field, and postage stamp and coin collectors, are among the widely diversified classes for whom the device is designed. Bank tellers might also use it in detecting counterfeits.

Unpacking a 23-Foot Python

WHEN the twenty-three-foot python seen in the photograph below arrived at the Zoological Garden in Philadelphia after its long journey from India, the services of nine men, all of long experience in handling reptiles, were required to unpack the snake and carry it to its permanent quarters.

The zoo keepers were unperturbed enough, because they knew the ways of pythons and held under control the snake that, if unrestrained, could kill a horse. If kept extended at full length the reptile is virtually harmless. It is not venomous, hence its bite has little effect. In its native India it crushes its foes to death in its coils and the powerful muscular folds of its body.

When it realizes it is mastered, the python is not disposed toward futile struggle, particularly if it has been well fed, as this one was. It does not kill except when necessary, for food or to protect itself from those it fears as enemies.

World's Largest Book Is Taller than a Man

TALLER than the average man, this gigantic atlas is said to be the largest book in the world. A gift to King Charles II, ruler of England in 1660, from the merchants of Amsterdam, it now occupies an extensive space in the British Museum in London. Latin inscriptions and text appear on the maps, which are surprisingly accurate in view of their age. The gift was a memento of Charles' visit to the Netherlands where he found friendly refuge after the fall of the British monarchy.



Two men of average size, shown standing beside the 267-year-old atlas, give an idea, by comparison, of its enormous dimensions

Rat-Proof Ships End Plague

RATS on shipboard, responsible for stories and traditions that date from the earliest days of navigation, are soon to be eliminated forever, according to reports from the U. S. Public Health Service. Of seventy-three vessels that have been rat-proofed according to the latest ideas of construction, thirty-one are practically free from the nuisance. Government officials say that in the near future rats will be reduced to a harmless minimum even on grain-carrying ships, and they no longer will spread bubonic plague from one country to another.

The rat-proofing is done, preferably when the ship is built, under the direction of the Government foreman of rat-proofing at the New York Quarantine Station. It consists chiefly of eliminating all hollow walls and shafts, or blocking them off into non-communicating sections; and of using all-metal, instead of wood, construction for cupboards, bins, and pipe casings. In consequence the rats cannot hide, nest, or move about in search of food on the ship. Instead of multiplying, they decrease or die out. The old method of fumigation is expensive and its effects lack permanency. The more efficient rat-proofing was first undertaken in 1924.

Charts Predict Track Record

STAR runners, out for a world's record, should try the 880-yard run. That is the suggestion of Dr. Earle R. Hedrick, mathematician, of the University of California.

After a careful analysis of the present world's records for various distances, Dr. Hedrick concludes that the record of one minute and fifty-two seconds for the 880 is the one most likely to be improved in the near future. It might be lowered a full five seconds and still be consistent with some of the other records now existing—such as that of forty-seven and four tenths seconds for half that distance on a curved running track.

In the course of his unusual studies Dr. Hedrick has discovered that there is an exact mathematical formula which, when he drew it as a curve based on existing records, showed at a glance what a record performance should be in a race of any distance of more than a hundred yards. This curve represents the limit of human endurance, as now established. If future generations break through it, the formula may be adjusted accordingly.

Big Gain in Radio Precision

THE accuracy of radio measurements has increased a thousandfold in four years. Where engineers once were content with an accuracy of one percent, they now measure to a thousandth of one percent, according to Dr. J. H. Dellinger, in charge of the radio laboratory of the U. S. Bureau of Standards.

This amazing gain in precision is partly due to the new quartz-crystal oscillators that can control the wave length of a broadcasting station within extremely narrow limits. Careful control of other factors, however, such as the temperature of the crystal, also plays an important part, Dr. Dellinger says.

So rapidly has the manufacture of apparatus kept pace with the new definition of accuracy that when one of the Bureau's standard crystal oscillators was recently sent to Canada for comparison with the standards of radio authorities there, it was found to agree within one hundredth of one percent.

It took these nine zoo keepers of Philadelphia to unpack the twenty-three-foot python tail first, yard after yard, from the box in which it journeyed from India

They're Off! Eight Balloons Start Race



In the first balloon race in Germany since the war, eight aeronauts started, the winners to compete in America. The gas tank that filled the balloons is in the background

CURIOUS spectators recently thronged the field at Gelsenkirchen, in the Ruhr, as eight aeronauts prepared to leave the ground in Germany's first balloon race since 1914, the three winners to represent Germany in the classic Gordon Bennett balloon race in America. The unusual photograph shows the eight German craft ready to leave the ground. Note in the background the gas tank from which the balloons are filled.

One of the competitors was a distinguished dentist and physician. He recommended ballooning as a cure for shattered nerves, saying many patients have been aided in recovering after breakdowns by riding in the clouds.

"Balloon Bicycle" Invented

NOW we have the "balloon bicycle." Devised by an English inventor, it is supported in the air by a cigar-shaped envelope filled with hydrogen gas. Below, on a lightweight aluminum bicycle frame, sits the pilot-rider, turning with his feet the pedals that operate a propeller at the front. The unique craft has a rudder, worked by handlebars.

Those who have taken up the new sport of balloon jumping, recently described in POPULAR SCIENCE MONTHLY, may resort to the aerial bicycle to speed past their fellows that stride in balloon-supported leaps across the country—much as land cyclists overtake pedestrians.

Bicycles have been designed before to travel on water, snow, and ice; a few inventors have designed flying bicycles with wings and propeller, of which at least one was capable of flight. The new English invention, however, is believed to be the first "bicycle balloon."

Heart Murmurs "Tuned-In"

PHYSICIANS can hear the heart's softest murmurs with a marvelous new electric stethoscope that magnifies them to a roar. The invention, an improvement of the instrument developed in the Bell Telephone Laboratories, and already described in POPULAR SCIENCE MONTHLY, is able to amplify a heartbeat 500,000,000,000 times. "Electric filters" now enable the physician to shut out normal sounds of the heart and study the faint murmurs formerly obscured.

Motors Race to Garage Roof

FROM the bottom of a building to its roof was the course of a remarkable automobile race recently held in Paris, France. There were seventeen curves in the unusual course, which started in the second basement and ended on the roof of a huge seven-story garage equipped with ramps for moving cars from one floor to another. In the illustration below, the foremost competitors are nearing the finish line, their motors laboring from the stiff climb as they swing around one of the curves. Note spectators in the background behind a protecting wall built of sandbags.

From the sub-basement of a seven-story garage in Paris the motorists shown above led a race to the roof. The steep curving ramps between floors formed a hazardous course for the racers



At right: Preparing to test the strange "flying doughnut," built on a design patented in 1897. Four rings of fabric, one above the other, constitute the wings of the device

Fearless Men Vanishing from the Earth?

HUMAN courage is of four distinct types, of which one is fast disappearing under education and industrial life. That is the conclusion of Dr. C. M. Wilson, of St. Mary's Hospital, London, based on his psychological studies of soldiers and of people in civil life.

The vanishing variety, says Dr. Wilson, is that of the person who actually feels no fear—rare in this complex age, when there are so many things to be afraid of. Other types are of those who feel fear but hide it; those who show it, but resolutely carry on; and, lastly, those who are so frightened that their fear is transformed into a reckless frenzy, like that of the small boy who whips the bully who goaded him to desperation.

Turbine Locomotive Tested

NOW turbine locomotives have reached a point of development where they loom as rivals of the conventional piston-and-cylinder engines. The London, Midland and Scottish Railway, of England, is trying a new locomotive that uses a steam turbine. If successful it would be especially useful in mountainous regions, with a claimed fuel saving of twenty-seven percent.

Other turbine locomotives have been designed, but none as yet has proved a successful competitor of the piston-driven type. The new locomotive is of Swedish design and is known as the "Ljungstrom turbo-condenser" engine.

A "Flying Doughnut"

CIRCULAR rings of fabric form the wings of the amazing "flying doughnut," below, recently built by "Doc" Meyers and shown at Curtiss Field, N. Y. It was patented, he says, thirty years ago—nine years before the Wright brothers flew the first successful plane. If the design proves successful, he declares it will prove he was the first to master the basic principles of aviation. The propellers are not greatly different from those used today. The queer looking wing surfaces are intended to serve as do the modern plane's wings.

Bricks Are Now Tested by Their Ring

CARBON for the brushes of electric motors, and brick for building, tell their secrets to the engineer in two novel processes just developed for detecting faulty materials by their "ring" when struck.

Making a musical instrument out of the carbon brushes, rectangular blocks of the hard black substance that carries electricity to the whirring rotor, is the testing scheme used by Dr. G. M. Little, of the Westinghouse Electric and Manufacturing Company. He has constructed a "xylophone" of several standard-sized carbon blocks, of various quality, that range in pitch from the musical tone G sharp to A sharp, a little higher. Test samples are compared in their pitch when struck with a drumstick with those of the "xylophone," and rejected if they fall below G sharp.

Another device, for testing bricks, does not depend upon the trained human ear. The invention of Juichi Obata, of the University of Tokyo, Japan, it photographs the sound of a brick struck by a hammer so that the exact character of the sound can be studied. The sound is picked up by a microphone, amplified by radio apparatus, and used to operate an oscillograph, or sound recorder.

Almost Beats the Camera

WHEN the winner of the recent motorcycle races at Munich, Germany, flashed past on the last lap, a high-speed camera trained on him barely managed to record his passage. The remarkable photograph below, which gives some impression of the speed at which he was traveling, was the result. In the infinitesimal fraction of a second that the camera's shutter took to expose the plate, the cyclist's flying image had moved halfway across it.

The peculiar distortion which resulted is characteristic of pictures of swift-moving objects at close range made with the "focal plane shutter" used in fast cameras. The shutter, a sliding curtain with a slit in it, "wipes" the picture on the sensitive plate a section at a time.



This motorcycle racer at Munich not only defeated his rivals but almost beat the high-speed camera, which in an instantaneous flash could make only this distorted picture of his passage

"Hops Off" from Surf Board

THE remarkable feat of leaping from a surf board behind a fast motorboat to a plane speeding overhead is the recent accomplishment of Mabel Cody, girl "dare-devil" of Tampa, Fla. Throngs of spectators on shore near the Davis Island, Fla., marine speedway, saw her succeed on her 113th attempt after six days of failures. So far as is known, the stunt never has been equaled. The transfer was made by means of a rope ladder dangling from the plane, as the speed photograph below shows. Note the precarious grip she managed to obtain on one side of the rope ladder and the movie camera trained on her as she made her difficult ascent, also the guide rope to keep the ladder from swaying.



Prehistoric Monster Lives

RECENT expeditions into the swampy, almost inpenetrable fastnesses of southern Java have brought back photographs giving the first authoritative evidence that a monster differing little from those of prehistoric times still survives in the moist jungle. It is a one-horned, rhinoceroslike creature, its hairless hide covered with small horny scales, says Dr. P. Vageler, German zoologist, who reported the discovery. Enormous front teeth resemble those of a hippopotamus. Natives call it the "tanggiling."



Man Races Horse

CHARLES W. HART, the English runner who races against horses in London to prove, as he has done, that human endurance is greater than equine, is shown above in white sunbonnet and running pants, at the start of a recent contest. The race continues six days, twelve hours a day. The horse relays with another, while Hart runs alone. He takes his food, most of which is in liquid form, while on the track.

Speed is not attempted in these contests, the only purpose being to test staying power. G. Tyrwhitt Drake, sportsman-zoologist, is riding Hart's opponent. In a similar contest held a year ago, against two horses, Hart was the winner.

Electric Brakes for Autos

ELECTRICITY may stop your car in the future. A new electric brake system, already manufactured for trucks and trailers, is said to use less current to operate a set of four-wheel brakes than is needed to run one headlight or blow the horn once. All the electricity does is to set in motion a mechanical brake which is then applied by an ingenious device that takes its power from the forward movement of the car itself. It is reported capable of stopping the heaviest machine in a short distance; for the greater the momentum, the greater the braking force.

2,000,000-Year-Old Pine Cone

TWO million years ago a pine tree fell before a flow of molten lava in what is now Placer County, Calif. A cone from that tree, preserved by the solidified rock in perfect condition, has just been discovered by a prospector and sent to the department of paleontology at the University of California. Experts vouch for its extreme age, adding the remarkable fact that it is of a species which exists today unchanged through the ages.

Ship Models — Young and Old Find Profit and Joy in Building Them



Bob Nilson, a patient in the Minnesota State Sanitarium, used only files, jackknife and drill to fashion this model, perfect in detail, of "Old Ironsides" from POPULAR SCIENCE MONTHLY's plans





E. L. Redfield, Cloquet, Minn., built his Spanish Galleon so well from POPULAR SCIENCE MONTHLY's plans his father demanded it as a birthday gift. Another hull is now on the stocks

In the circle above, LeRoy D. Bell, of Bristol, R. I., shows the model of an unusual yacht he has invented—a "schooner-sloop." With two masts, the fore-and-aft rigged craft is a schooner; but the foremast can be removed, changing it to a sloop. Thus the craft can be entered in races in two different classes. Bell, a railroad man, builds ship models as a hobby



Henry B. Culver, New York lawyer, who as a hobby employs his delicate touch and historical knowledge to repair old ship models, is seen at the left restoring a copy of the Seventeenth Century frigate, the *Dartmouth*. Col. Henry H. Rogers, owner of the model, has it insured for thousands of dollars

Everyone wanted the models of old ships that Alphonse M. Greis and Karl Bauer built for fun, so they hired assistants and entered business in New York. This view of their shop shows workmen assembling hulls of model galleons. The ships they make are accurate in every detail

You can't begin to learn ship modeling too young, believes Alex H. Sjorlund, of Manchester-by-the-Sea, Mass. In his unique school, the "Dock Yard," boys and girls learn the fine points. Note particularly the large motor boat model in the foreground, a product of youthful skill

Clever Feats of Handicraft

Gus Pufhal, Monona, Iowa, farmer, carves elaborate fans and flowers, each from one piece of wood. He uses only three tools

With five thousand pieces of wood, Henry Bieberich, of Fort Wayne, Ind., made this elaborately inlaid clock case

A miniature Ryan monoplane, shown by Paul N. Edwards, of Denver, its builder, is driven by a one-eighth-horsepower electric motor. Shellacked silk covers its aluminum frame. The Lindbergh plane, *Spirit of St. Louis*, was of this type

With the steering worm from an old motor car attached to the rudder post of his launch, Harland Fancher, of The Dalles, Ore., finds steering a simpler and less tiresome task. Cables connect the shaft and the steering wheel

To view college boat races recently, James Tyson and Theron Howard, University of California students (right), built their own speed boat in a home workshop. Its powerful hydroplane engine produced surprising speed



With front wheel drive, this car will not skid, says Arthur Nichols, Massachusetts Institute of Technology engineering student, who built it of spare parts in 365 hours of spare time. He admits it looks odd, but declares its performance equals that of many "store cars"



The carpentry class of Roosevelt High School, Los Angeles, designed and is building on the school grounds the house shown here in course of construction. When finished it will house the domestic science department and serve as a community center for the school district

Telephone Meter Sells by Word

THE little black meter box atop the telephone illustrated above dispenses telephone service by the word and sentence, charging "a la carte" according to time consumed.

The instrument, called a telechronometer, is the joint invention of Charles M. Beattie, of Rochester, N. Y., and Garrison Babcock, of Seattle, Wash. It has been tried with remarkable success in Everett, Washington, where telephone rates are said to have been reduced forty percent, while the number of subscribers has doubled since its installation. It also discourages useless talk on the wires.

Two units of time—the "telechrone," equal to one minute of telephone conversation, and the "telo," designating fifteen seconds of conversation, have been created for the new service. The device is controlled by electricity through a master clock, and is entirely noiseless. The charges are computed monthly from meter readings, made similarly to those for water, light and gas service.

A New X-Ray Discovery

NOW the killing power of X-rays, used on human tissue as a treatment for cancer, has been shown to depend, not upon the wave length but on their intensity alone. For a long time scientists were in doubt as to whether long-wave X-rays, used for surface skin treatment, had the same curative powers as the penetrating short-wave rays that are employed for deep-lying disorders.

Biologists of the Institute of Cancer Research of Columbia University, New York, recently tested both by exposing female fruit flies to rays of various wave lengths and intensity. Eggs laid by the flies were then tested for fertility; those exposed to the strongest rays did not hatch, while the others did, regardless of the wave lengths of the rays employed.

Live on a Vast Ice Cake

IF AMERICAN climate is too warm, try Northern Siberia—where the earth is frozen the year round, to depths of more than a hundred yards. This icy ground, says Prof. Schostakowitch, of Irkutsk, Siberia, covers two million square miles, equal to half the area of Europe! In Jakutsk a well was sunk 363 feet without reaching unfrozen earth. Directly beneath stove-heated homes, the ground thaws. Sometimes these thawed columns tap underground rivers beneath the ice layer, and veritable Artesian wells spurt into the homes.

Open Door Burglar-Proof

A DOOR so locked that it will open a few inches only, admitting air for ventilation but no burglars, is demonstrated above by Charles Brand, its inventor. A bar extending from the frame is locked to the door so that the man outside cannot reach through and unfasten it as he could the old-fashioned chain and slot guard, which once the door was partly open, was ineffective unless someone inside protected it from the would-be intruder.

Pipe Sweetened by Steam

FOR cleaning old, ill-smelling tobacco pipes, the instrument above has been devised. A teaspoonful of wood alcohol or gasoline, placed in a little cup, heats another little cup which contains water. The steam thus formed enters the pipe through a rubber hose, and after thoroughly penetrating the pipe finally comes out through the bowl.

All the foreign substance is loosened through this method, it is claimed. After the pipe has been steamed for about five minutes, the operator scrapes out the loose stuff in the bowl, leaving the pipe sweet and clean for smoking.

Lifeboat Inflated Like Tire

A MAN jumped overboard in the harbor at Hamburg, Germany. Twenty minutes later he was being hauled over the side of a collapsible pneumatic lifeboat which had been inflated and launched with surprising speed. It was the first test—reported highly successful—of the *Mowe*, first of a new type of craft for rescues at sea. Occupying less space than the ordinary lifeboat, and easily transported when not inflated, the vessel in action can hold sixty persons. Besides those who must be taken aboard because of exhaustion or cold, the craft can keep afloat as many stronger ones as can seize the ropes and grips along its sides.

Hauling a rescued man aboard the inflated rubber boat. Notice the ropes and grips along the side, to which victims of a shipwreck at sea, if they are not too exhausted, might cling

Self-Service Hat Checker

FOR a nickel patrons of a Cincinnati restaurant can check their hats and coats with an ingenious mechanical hat checker. The hat goes over a raised disk mirror in the center; then a hinged ring swings down around the brim, locking it to the coin box below. From the coat hanger, a chain runs through the coat sleeve to the lock. With a key and your coin you unlock your property.

Amazing Locomotive Tested

A NEW turbine locomotive that consumes its own smoke and condenses its used steam into water to be used again and again in the boiler is undergoing tests in England. The condenser is in the rear. The ventilator, which sends smoke back to be burned, is shown on the front in the photograph below. The smoke consumption not only makes the engine cleaner, but it also furnishes additional heat.



Enginemen are adjusting the locomotive's smoke-eating device—a ventilator that carries the smoke back to be reburned





Wakes Up Sleeping Muscles

A NEW exercise device, designed especially for training athletes, is said to develop muscles of legs and back that are not put into play by any other method. It consists of a high chair to which are attached two pedals connected with sliding weights. The exerciser pushes forward with his feet against the pedals. The weights can be varied as desired.

Germs Give Light

THAT certain organisms so small that they cannot be seen through the microscope may play an important part in the amazingly efficient "cold light" of the firefly and other insects and lower animals is the theory advanced by Dr. Umberto Pierantoni, biologist, of Naples, Italy. His experiments, he says, indicate that minute germs introduced into the egg of an insect stimulate the cells in such a way as to create lenses, refractors, and reflectors of light in the insect's body.

Previous evidence has shown that certain deep-sea fishes house colonies of light-giving bacteria.

Fights Skyscraper Fires

FIRE in the top of a half-completed skyscraper apartment hotel in New York City recently did heavy damage because there were no near-by buildings of equal height from which to fight it, and delay was caused by the necessity of hitching two pumping engines together to force water to such a lofty blaze.

Profiting by this experience, the Fire Department had the pumper shown above built to order. With its six cylinders this $14,500 engine can pump 1,000 gallons of water a minute, sending a stream to the top of the Woolworth Building. On its huge pneumatic tires—another innovation—the machine can travel at a speed of forty-five miles an hour.

Uranium Aids Growing Crops

COMPOUNDS of uranium, a radioactive metal closely allied to radium, have a peculiarly beneficial action in growing farm crops, Dr. Keizo Hirai, of the Kyushu Imperial University, Japan, told soil experts recently assembled at Washington, D. C. His latest tests showed that when these compounds were added to the soil, the friendly bacteria that attach themselves to the roots of peas, beans, and clover and make atmospheric nitrogen available as plant food, would work faster and deliver larger amounts of the precious element.

The microscopic bacteria's important part in helping the farmer grow leguminous crops has been known for some time; and "experience has proved the value of inoculation of the seed with these bacteria in obtaining a thrifty growth," according to I. L. Baldwin, bacteriologist at the Wisconsin College of Agriculture. Such germ cultures are said to be an inexpensive form of crop insurance.

Refutes Attack on Oatmeal

WITH the worthiness of oatmeal in diet questioned by a British scientist, an American nutrition expert, Prof. Harry Steenbock of the University of Wisconsin, rises to its defense.

The conclusion that oatmeal not only lacks important vitamins but may contain a poisonous "toxamine," reached by Prof. Edward Mellanby of the University of Sheffield, England, after experiments with puppies, is repudiated by Prof. Steenbock. Repeating the same tests, he concludes that oatmeal is little less effective than wheat cereals in preventing rickets, a childhood bone disease. He doubts the existence of a "toxamine."

Organ Nearly Wrecks Itself

SO MIGHTY are the thunders of this pipe organ, said to be the largest in the world, that it has been necessary to place its console in a sheltered pit more than a hundred feet away from the main part of the instrument.

The organ occupies the center of the Roosevelt Memorial Park, in Torrance, California, near Los Angeles. The organist is seen seated at the keyboard in the foreground, while the instrument itself is housed in the structure beyond.

Previously the keyboard and the organist's bench trembled so decidedly that the player found it impossible to obtain with surety the delicate effects required for fine music. Eventual damage to the keyboard also was feared. The glass-covered pit was then constructed at a distance and connected with the instrument by electrical controls.

Tent Train Saves Pavement

WITH the aid of a unique "cloth train," engineers in Hawaii have at last successfully combated the rain that was wont to ruin their fresh laid concrete roads. New road construction has long been a problem in that country, where the annual rainfall is 200 inches, and where it rains almost every day of the year.

The new apparatus consists of a number of wide, portable canvas coverings stretched on wooden frames and mounted on small wheels. As each new section of concrete road is laid, the "train" of canvas roofing rolls forward to cover it.

What Turns Animals White?

HAVE you ever seen a white woodchuck, or a white robin? Such strange examples of "albinos," snow-white individuals among animals normally dark, were recently described by Dr. R. W. Shufeldt, zoologist, of Washington, D. C., who has made an extensive study of this curious and unexplained freak of nature.

In Virginia, not long ago, a woodchuck was captured that was entirely white. Only a little less rare are the albino weasels and opossums occasionally captured in various parts of the country. Dr. Shufeldt obtained a male robin, partially white, at Stamford, Conn.; he has also found sparrows and finches that come under this name of "partial albinos." Quail, woodchucks and meadow larks are occasionally pure white. "White elephants," though proverbial, are rare; now and then a white squirrel is seen, and white mice are common and familiar pets.

All through the animal kingdom, including man, runs this odd trait, says Dr. Shufeldt. Even flowers show the tendency to produce albinos, as do insects. Albino insects are generally rare, says Dr. Shufeldt. Yet now and then you may see among the common yellow *Colias*, butterflies that haunt clover fields, a single white individual.

Birds' Nest in Mop

THIS unusual location for a nest was selected by a pair of birds that appeared in Chicago and went looking about for a building site. Mrs. William Notacker, having left her mop idle on the back porch for several days, had occasion to use it and discovered that the birds had chosen it as a spot for their home, which was now well on the way to completion. The texture of the mop had saved the feathered settlers labor by constituting a sort of foundation structure for the nest.

The birds showed little fear, and, rather than disturb her tenants and spoil their summer's plans, Mrs. Notacker bought another mop. While raising a family of six the birds became well acquainted with her. In the photograph above, the mother bird is seen bringing home a tidbit to her youngsters.

Mighty Natural Springs Could Supply Cities

NATURAL springs that are harnessed for water power, and others huge enough to supply the largest cities, are disclosed in a recent report of the U. S. Geological Survey. In this country, it states, there are sixty-five springs that could supply Washington, D. C. More than half of them, including many of the largest, occur in limestone; others in volcanic rock, and three in sandstone.

Silver Spring, in Florida, is believed to be the largest of the limestone springs. Each second, 6,149 gallons of water gush from its wide mouth—enough for New York's entire water supply! The water is marvelously clear and glass-bottomed boats are used to obtain a striking view of the fish and underwater vegetation.

From the black lava walls of the Snake River canyon, below the Shoshone Falls in Idaho, spurt the Thousand Springs, whose combined flow is nearly 6,500 gallons a second. High up on the canyon walls, they formed a spectacular waterfall nearly half a mile long and 200 feet high, until they were harnessed for power.

Montana has the only large sandstone springs—Giant Spring, near Great Falls, and the Warm Springs and Big Springs near Lewiston.

"Sidecarette" Carries Three

A WIMBLEDON, England, motorcyclist has built what he calls a "sidecarette," a motorcycle with two streamlined side cars that comfortably carry his small son and daughter, and their jaunts have already covered several thousand miles. The wheels are smaller than those of the ordinary motorcycle. On each side of the vehicle's frame is attached a metal "cockpit" with windshield and seat. In these the children can almost believe they are driving their own little cars along the boulevard.

Streamlined metal cars on either side of this "sidecarette" protect two small children from dust and weather. They have comfortable upholstered seats

Plans Plane to Fly Forward, Backward, Up or Down

AN AIRPLANE which, its designer claims, will reverse its course, going up or down like an elevator and forward or backward like a motor car without turning around or turning upside down, has been developed in Los Angeles, Calif.

Valentine Newbauer, the inventor, exhibits in the illustration at the right, a working model, which has a one-and-one-half-horsepower motor and which he says will lift sixty pounds. The full size plane would have a wing spread of thirty-four feet and a 600-horsepower engine.

In design the unusual machine might be called a combined monoplane and helicopter. The horizontal double wings above, like the blades of a ceiling fan, are designed to whirl in either direction, causing ascent or descent. The propeller in front also is reversible. Newbauer, who has worked on his idea for ten years, says the plane can also be made to stand stationary in the air. In other respects the invention is much like the monoplanes in rather general use.



Valentine Newbauer with a model of his strange helicopter-plane. Reversible movement of rotating wings and propeller, he claims, enables the machine to fly forward, backward, up or down

Flyer Takes His Car Along

A NOVEL plan by which an airplane can carry a motor car so that an aviator, landing on a field, may then drive away to keep an engagement in a near-by crowded city where landing of airships is impossible, was recently demonstrated by a French pilot in Paris. The motor car is equipped with specially designed wheels which have large, heavily flanged hubs. Steel cable slings are attached to the body of the airplane and the slings are threaded around the car flanges. Then the airman soars aloft with the motor car securely suspended.

If the plane becomes disabled, but a safe landing is made and its wheels are intact, the motor car can be used to haul it to the nearest hangar for repairs. Also a damaged part of the plane may sometimes be replaced temporarily by a similar part taken from the automobile. Some engine parts, for instance, are easily interchangeable.



Dr. George B. Emerson and his manikin show the ugly effect of incorrect posture

Manikin Teaches Posture

TO TEACH correct posture and to demonstrate the harmful effects of poor posture, Dr. George B. Emerson, director of physical education for men at Boston University, has devised the manikin pictured at the left. The posture illustrated—shoulders drooping and stomach protruding—is the result, he says, of sitting for hours every day in an office chair, with the weight usually rested on the tip of the spine. It is a frequent deformity among American business men. Dr. Emerson stands beside his manikin in a similar posture. As remedies he advocates exercise and attention to defects, which develop mostly through neglect.

Only Four Basic Odors

THERE are just four fundamental smells, two chemical engineers of Boston, Mass., recently told the American Chemical Society. All the odors, say E. C. Crocker and L. F. Henderson, are blends of these scents, which they name "fragrant," "acid," "burnt," and "caprylic." The last is the odor of certain evil-smelling chemicals. All smells apparently are detected by nerve-endings in the nose. Tastes, physiologists have long agreed, can be reduced to "sweet," "sour," "salt," and "peppery."



How a French aviator carries his motor car with him. Steel cable slings, suspended from the body of the plane, are threaded around flanges on the hubs of the automobile wheels

Are You Planning to Buy an Oil Burner?

AS A result of its investigation of 3,343 oil burner installations, the Popular Science Institute of Standards is prepared to assist readers planning to install this type of heating equipment. Advice on selection and installation to meet your needs will be sent, provided the following information is supplied: (a) Number of rooms in house; (b) Type of heating system; (c) Annual coal consumption; (d) Gas or electricity installed.

No charge will be made for this service. Address your letter: Oil Burner Service, Popular Science Institute, 250-4th Ave., New York.

Improved Tools *to Make* Housework Easy

On the end of a sliding rod running through a hole in the top of this salt shaker is an agate ball. When the shaker is inverted the rod and ball slide forward releasing a sprinkle of salt. With the shaker upright the ball slides down and covers the openings



With this shaker you season your food by pressing a plunger. Press it on one side and salt comes out; on the other side, pepper. Both sides are suitably labeled. Filled from the bottom, the device is said to be proof against moisture

The triangular strainer of the coffee percolator pictured above is an extension of the lid, and fits into the spout. Raising the hinged lid lifts the strainer at the same time, making the spout accessible for washing. An improved type of inner coffee holder is said to give better percolation and fuller flavor, while the strainer is designed to insure clear coffee, free from grounds



You can set this electric iron for any degree of heat you desire, the makers claim, and it will get neither hotter nor colder. Low heat for silks and laces, high heat for coarse materials —either can be obtained by turning a regulator button placed at the back of the plug



You can modernize your candlesticks with a newly invented adapter that makes it possible to burn electric candles in them. The device is an electric light socket, mounted on a rubber base which is inserted in place of the usual tallow candle. The socket then can be used to hold an ornamental "candleflame" bulb which is free from unsightly dripping wax and besides offers no fire hazard

You don't have to use a pad or cloth to avoid burning your fingers if you have these bulldog tongs to pick up hot cooking utensils. They are also helpful for setting pans and dishes in out-of-the-way places, as on the back of a deep shelf



With one hand you can easily pick hot potatoes from the oven, or vegetables from boiling water with the aid of tongs hinged in such a way that pressure on the handles closes them. When pressure is released, a spring releases potato

This odd-shaped ladle has, beside its cup-form bottom, a strainer attachment by which vegetables may be drained on way from pot to dish by a turn of the wrist

This electric coffee percolator can be taken apart for washing. The heating unit is really a separate little stove upon which the perforated and recessed bottom of the pot fits

A handy orange peeler. After you have cut a neat groove around the orange with the small blade at the center of the peeler, the spoon end is inserted under the skin on each side, removing it quickly and easily

These space-saving refrigerator dishes nest together, making the most of room in the ice box. Perforations near the rim of each dish assure ventilation. The contents remain fresh and cool, and protected from contact with other food

In this openwork metal box, that swings out of the way under the sink, is a waterproof paper bag that holds the day's accumulation of waste. The bag, filled and discarded, is replaced by a fresh one



For the picnic lunch this tube shakes salt from one end, pepper from the other. Both ends are covered with caps when not in use



A new serving utensil that prevents spilling food on the tablecloth is a spoon with a cover that you can lift with your thumb. The handle is shaped to fit the fingers. The device also may be used for draining vegetables

To keep pictures straight on the wall, these handy new points are stuck, two to a picture, in the bottom of the frame at the back. Their sharp tips catch on the wall and prevent the frame from twisting awry. The tool that is used for inserting them comes with them



Four slices of bread are turned all at once by this ingenious toaster. The slices are inserted in hinged frames which swing like doors. Turn one by its handle and the other three swing at the same time

What Everyone Asks *about* Flying

Why a Plane Can Rise in the Air—How the Pilot Can Direct Its Course—Other Common Questions Answered

WHAT keeps an airplane in the air?

Air pressure on the wings. The rapid motion of the wings, which are set at an angle, compresses the air below them and reduces the pressure above them. Wings exactly parallel to the line of flight would only cut the air; so the "leading edges" are set a few inches higher. Riding in your car, you would get a lifting effect by raising the front end of the top.

Is the pressure on the underside of the wings enough to keep the airplane up?

Yes, but only one quarter of it is direct "lift." The remainder is the result of the partial vacuum on the upper side, caused by the "slice" which the tipped wing has cut in the atmosphere. As a boat's prow cuts the waves, the parted air is shot upward by the leading edge, leaving a "hole" of thin air on top of the wings. The partial vacuum permits atmospheric pressure to support the wing.

Why is fast motion necessary for flight?

To produce the pressure necessary to lift the plane's great weight.

How can a glider stay aloft without any engine at all?

The glider plane flies like a bird, taking advantage of up-flowing air currents. When the currents cease, the glider comes to earth.

What effect does greater speed produce?

It causes more resistance on all parts exposed. Resistance increases as the *square* of the speed; if you double your speed, you increase resistance four times.

Does more resistance require more power and fuel?

Yes. Fuel consumption increases as the *cube* of the speed; double your speed, and you need eight times the fuel.

Why do not airplanes rise at once from the ground?

For the same reason birds do not—they must attain such a speed that the air pressure and lift will overcome gravity which holds the weight to earth.

How is "see-sawing" prevented?

At the ends of the wings are hinged sections, called ailerons, connected by wires with the pilot's control stick. When a sudden current of air strikes under a wing, the pilot raises its aileron to decrease the vacuum above, and lowers the other aileron to increase the vacuum above it. This action steadies the airplane.

WHY is the "great circle" New York-to-Paris air route the shortest? On a flat map, as below, this route appears to be a curved one. Yet if you stretch a string between the two cities on a globe map, as above, you will see that the string marks a bee line between the two cities. The explanation is that a flat map distorts the curved surface of the globe



When flying out of sight of land, how can I tell whether I am right side up?

A "turn and bank" indicator tells you if the wing is tipped, as when turning. Your inclinometer tells you whether you are headed up or down.

How do I know how high I have climbed?

By looking at your altimeter. This instrument measures pressure of the atmosphere, which decreases as you rise, causing a pointer to travel over a scale that registers the height in feet.

Does this pointer change instantly?

No, it takes some seconds to act, so a rate-of-climb indicator tells you how fast you are climbing or descending.

How can I tell the direction in which I am going?

By watching your magnetic compass and your earth-inductor compass. This last is a new invention, utilizing a generator turned by an air motor. You set the desired course and steer to it, keeping the indicator on zero. Your drift indicator tells you whether a side wind has thrown you off your original course.

Since the airplane does not touch the ground, how is its travel measured?

Your ground-speed indicator measures the miles according to the speed which your plane is traveling. Your tachometer measures the revolutions of your engine and tells you whether it is running properly.

What is the fuselage?

The hull, in which the pilot sits and in which essential parts are inclosed.

Why is the nose of the fuselage usually bluntly rounded, instead of being sharp like a ship's bow?

To get the best streamline effects, with minimum power. Wind resistance is less with this form. The sharp stern enables the parted air currents to flow together smoothly.

What shape is the "fuselage" of a fast flying bird?

The breast is rounded, and the rear is tapered.

Why are the propellers in front of some airplanes, and in the rear of others?

The wing structure can be either pushed or pulled through the air. The propeller in front has an unbroken air stream to work in, and is gaining in favor with aviation men.

Why is the noise made by airplanes so deafening?

Because of the high power and great speed of the engines. Mufflers can be attached, however, and doubtless will be used in the future on passenger planes. Some power is lost thereby, because there is some "back pressure" caused which increases the load on the engine.


CONTROL STICK OPERATES BOTH AILERONS TO TIP PLANE ONE WAY OR THE OTHER
CABLES
LEFT AILERON DOUBLE-END LEVER
QUADRANT
RUDDER BAR OPERATED BY FEET
FUSELAGE
RIGHT AILERON DOUBLE-END LEVER
LEFT AND RIGHT ELEVATOR FLAPS OPERATED BY CONTROL STICK TO HEAD NOSE OF PLANE UP OR DOWN
RUDDER

Skeleton diagram of airplane, showing controls by which a pilot governs his altitude and balance and steers his course



How lifting force is produced by an airplane wing cutting the atmosphere. Pressure of the air stream (indicated by arrows) beneath the wings produces one quarter of the "lift." Partial vacuum above the wing permits atmospheric pressure to supply the additional three quarters

Tricks *of the* Radio Quacks

So-Called Static Eliminators and Battery "Medicines" Prove Worthless in Laboratory Tests

By ALEXANDER E. SENAUKE

The radio fakir with his "cures" is as extravagant as the old-time medicine doctor in his claims, and his goods are just about as worthless

ARE you bothered with static?

Do you suffer occasionally because of an exhausted storage A-battery?

Is your radio set subject to fading?

These and hosts of other real and imaginary radio troubles are easily cured if you believe the claims of radio quacks. No matter what your particular trouble is, there is available a quack expert, who will take your money and guarantee a sure cure. Some of them even offer a single device that is supposed to cure every possible ill. And of course these claims are as worthless as the guarantees.

Devices to eliminate static are the most numerous because static, like hot weather, affects us all—rich and poor. An expensive radio receiver suffers from static just as much as does the cheapest, homemade one-tube outfit. With millions of radio fans enduring the rasping noises of static whenever weather conditions are bad, there is an enormous demand for static eliminators.

BUT so far no really successful eliminator is available. In fact any of the larger radio concerns would pay almost any price for a real solution of the problem of eliminating static. But despite long and patient experiment static has proved a baffling and unsolvable puzzle to our most eminent electrical engineers and radio experts. At worst the so-called static eliminators that are offered for sale are plain fakes. At best they will eliminate the broadcasting as well as the static.

Several varieties of these eliminators have been tested in the radio laboratories of the Popular Science Institute of Standards. Every one has proved worthless.

All sorts of absurd claims are made for some radio cure-alls. In addition to eliminating static, they are supposed to increase the sensitiveness, make the set more selective and make the batteries last months longer!

Storage batteries, like automobile tires, wear out and owners, faced with the prospect of buying new ones, prove easy marks for sellers of battery "rejuvenating compounds." All you need do, according to some of these gentlemen, is pour their magic solution into your old battery and—presto! —it becomes better than new.

Some of these rejuvenating solutions are nothing more than extra strong battery electrolyte, which will spur the battery into action for a short time if there happens to be any active material left on the plates. It is about as effective as digging the spurs into a dying horse to make him go a few steps more before he drops. Other battery rejuvenating solutions consist of powdered salts of various kinds that cannot conceivably do any good and may do harm.

All radio sets need some kind of antenna system and the type of antenna depends on the set, the conditions under which it is to be operated and the type of reception you want. In some cases a loop is used. In others a long outdoor antenna is required for best results. And there are, of course, situations wherein an indoor antenna satisfies every requirement of the set owner.

But in spite of the fact that a piece of plain wire is just as effective as anything else, there are various forms of fancy equipment sold for antenna uses.

For the man who wants to get distance a long outdoor antenna is needed with most types of sets. Frequently there isn't space to erect a hundred-foot antenna in a straight line. The radio fan faced with this problem is offered various kinds of special antennas, in which a wire of the required length is wound into a spaced coil a foot or two long. This coil is to be mounted on the roof and one end of it then connected by the lead-in wire with the radio set. The idea, of course, is that the coil is as effective as the same amount of wire strung out in a straight line. But tests show that it doesn't work out that way. The coil of wire actually is no more effective in bringing in signals than a plain piece of wire as long as the axis of the coil.

THEN there are the special antenna systems consisting of a pole, usually of metal, with a hollow metal piece on top. There is no magic in a metal construction of this type. For all practical purposes it is no more effective than a piece of wire of the same length in the same position.

Another idea for the elimination of static is to bury the antenna under the surface of the ground instead of erecting it high in the air. The theory is that you can receive the ground wave instead of the air wave and that there is little or no static transmitted through the ground. But tests made at the Popular Science Institute do not bear out these theories. Burying the antenna results in weaker signals and exactly the same proportion of static.

Sure Protection

DR. L. W. AUSTIN, in charge of the radio transmission laboratory of the U. S. Bureau of Standards, recently stated that no way of overcoming or eliminating static has been discovered. Money spent on so-called static eliminators therefore is wasted. Before you buy such devices, or other radio equipment, be sure it will do what is claimed.

The Popular Science Institute of Standards maintains large laboratories to protect you in your purchases of radio and other semi-technical products. The advice of its engineers is free to readers of the magazine.

Hints for Radio Beginners

Neat Wiring Made Easier

How to Prevent Loose Connections—New Ways to Better Results

NEAT looking wiring in a radio receiver is an advantage only if the neatness is the natural result of care in making each connection as short as possible. Spacing the wiring so that no two wires run close to each other is necessary only for the grid and plate connections. The remaining wires, which carry power to various points in the receiver, can be bundled together in one cable. Such a procedure is desirable in many hookups because it helps to eliminate stray inductive and capacity effects.

The odd looking device in Figure 1 is designed to facilitate this grouping together. Although at first glance it looks like an over-sized centipede, wiring a multi-tube receiver should be greatly simplified by its use. Essentially it consists of a long, flat strip in which are moulded four thin sheets of brass with a number of lugs on each sheet. These lugs are arranged in such a way that it is possible to make connection to any one of the four connector strips on either side of the form at any point. You will note that the lugs are in groups of four with a separate pair at each end. At one end you connect the plus A and plus B wires from the batteries and at the other end attach the minus A and C wires. Then the terminals of the sockets, transformers and other apparatus that are ordinarily connected to these wires are, instead, connected to the nearest lug. When the wiring is complete the extra lugs are cut off and a neat and efficient job of wiring is the result.



Fig. 1. Wiring is easier and neater with this connecting strip with lugs convenient for all terminals

Binding Posts That Hold

THE manufacturer of a radio set may do a perfect job of wiring a receiver, with all connections correctly made and electrically perfect, but all his attempts to make sure that you will not have trouble will go for naught if you do not see that binding posts are kept tight. Don't take anything for granted. If the set suddenly refuses to function or queer noises develop, check up on every binding post and battery terminal to make sure that they are tightly clamped to the wires.

Figure 2 shows a novel type of binding post that can't come loose. It is made in two pieces, an outer cap that is hollow and an inner solid portion that is fastened to the binding post panel. A hole is drilled through both the cap and the solid portion, but the holes do not line up unless the cap is pressed down against a moderately stiff spring. After the cap is pressed down and the end of the wire inserted in the hole, the spring causes the side of the hole in the cap to exert a constant pressure against the wire and there is no chance for a loose connection.

IF YOU are thinking of building a B-battery eliminator, don't fail to study the article on pages 74 and 75 of this issue, which describes the most improved designs and methods of construction. It will help you to get exceptionally satisfactory results.



Fig. 2. This novel binding post holds the wire by spring pressure from working loose

Locating the B-Eliminator

OFTEN B-battery eliminators are accused of producing a bad hum in the loudspeaker when the trouble really is in the location of the B-eliminator with respect to the radio set. As a general rule, it is a mighty good idea, if a noticeable hum is produced, to move the eliminator away from the radio set and see if this doesn't help the situation.

Of course, the possibility of difficulty depends on the arrangement of the parts in the set and the wiring. However, placing the B-eliminator about three feet from the set is good practice. Don't have the B-eliminator too far away, as other troubles may crop up due to the long leads.

Another good idea is to make sure that the cord connecting the B-eliminator with the light socket is kept away from all other wires. Designers of some types of automatic relays apparently have neglected this point. They have arranged the wiring inside the relay so that there is a definite magnetic pickup between the wires that carry the current through the relay to the B-eliminator, and the filament circuit that operates the relay magnet. If you experience trouble with a hum, be sure to see if leaving the relay out of the circuit will improve results.

Shield the Detector Tube

EVEN a B-eliminator that is practically hum-free will cause a decided hum with some types of sets if the eliminator is placed too close. The hum in such cases is due to the effect of a stray magnetic field which affects the flow of electrons in the vacuum tubes in the set. The detector tube is especially sensitive to this disturbance.

Moving the eliminator a few feet away from the receiver is the simplest way to stop the hum, but if this is not convenient, moving the eliminator may be avoided by carefully shielding the detector tube and grounding the shield. The shield should consist of a metal cylinder just large enough to slip over the detector tube. Of course it should clear the binding post of the tube socket.

A B C's of Radio

THOUSANDS of radio fans get poor results with dry cell B-batteries because they do not realize what happens inside the pasteboard case when the battery approaches exhaustion. When a 45-volt block gets down to 35 volts it should be discarded, the makers claim; but frequently the radio fan finds that reception is fairly good with batteries exhausted considerably beyond this point. And so he keeps on using them, and each night reception is just a little bit worse until it becomes hopelessly weak and noisy.

If you want your set to operate at full efficiency be careful to replace the batteries when the voltage falls to the specified figure. Then you won't have to apologize for the poor results you are getting when your friends drop in for the evening.

Sam Loyd's Page of Posers

Give Your Mind a Speed Test

Five Problems to Measure Your Logic and Ingenuity

UNUSUAL puzzles that not only entertain, but actually test and exercise your mental faculties, sharpening your wits and stimulating your imagination, are presented here each month by Sam Loyd, world famous puzzle maker. They range through many departments of the mind. They run from simple mathematical problems to others that measure your ingenuity or test your powers of observation.

Try your capacities on the varied questions, time your solutions, then turn to page 137 and see how well you have done.

Can You Pen These Pigs?



BARNEY O'MORE went over to inspect the piggery of his neighbor. "How many grunters are you bringing up this spring?" inquired Barney as he peeped into the pens and tried to count the lively inmates. "Exactly twenty-one," replied his friend, Tom McCann, "and they are all doing nicely." "Well, at any rate," continued Barney, "you have just the right number, according to my famous ancestor, Rory O'More, who discovered the luck that lingers in odd numbers. According to Rory's instructions a fellow should have just twenty-one but he should pen them in four groups so that each pen would contain an even number of pairs and one odd pig."

McCann had his pigs in four pens all right; compartments "nested" one within the other, but they were not separated to conform to the famous O'More formula.

Now, how easily can those porkers be redistributed to comply with the rule that there must be four pens, each to contain an even number of pairs and one odd pig?

Here is a little poser that will not yield to orthodox arithmetic. You must exhibit some ingenuity as well if you are to work out an acceptable answer, which is given on page 137. A triumph in ten minutes will betoken a bright mind inclined to a sense of humor.

An Arithmetical Courtship

DANNY went over to urge Kate to name the day.

"This proposal is entirely unexpected," gasped the blushing maiden, "but I will marry you when the week after next is the week before last."

"Had I received this promise yesterday," said Danny, "the waiting would have been six days shorter."

On what day of the week did Danny pop the question?

Danny's reply was instantaneous, because the subject was the most important in the world to him just then and he had always been particularly good in mathematics and in reasoning swiftly and logically. You should be able to answer in ten minutes. See page 137 to find if your answer is correct.

Moving a Pyramid

THE proposition shown below is to transfer the pyramid of six cubes from plate one to plate two, moving the cubes one at a time to any of the plates, but at no time placing a cube upon one of a smaller size. When the puzzle is solved the pyramid will be transferred to plate two and the alphabetical order will be just the same, from top to bottom, A, B, C, D, E, F.

The task can be accomplished in a rather surprisingly small number of moves and the test is for your speed in mastering the situation and determining what moves will most easily effect the transfer.

If your power of analysis is exceptional, you can solve this problem in about fifteen minutes. The solution is given on page 137.



A Rebus Memorandum

I ASKED the sign maker to make a signboard for me exactly four feet in length. Then the fellow, who is a rebus crank, made a little sketch in his memorandum book which corresponded to the design reproduced below. I scratched my head for quite a while before I made out how his notation could be interpreted from a rebus standpoint to indicate four feet.

It did not take the rebus fancier anything like eight minutes to conceive his idea, but if you can, in eight minutes, discover a phonetic translation of that group of letters and one numeral to describe a four-foot dimension, then you are entitled to boast of your imagination and talent for rebus riddling. The answer is on page 137.

The Clock Race



YESTERDAY my clocks started to race. The alarm clock gained one minute an hour on regular time, while the grandfather's clock lost two minutes an hour.

The race ended today when the alarm clock rang eight and the grandfather's struck seven. Who can tell at what time yesterday the race started? A ten-minute canter in mental arithmetic. The answer will be found on page 137.

Another page of Sam Loyd's puzzles to help you test your mental abilities will appear in next month's issue.

A House *with* 30 Servants

Like O. H. Caldwell, Almost Anyone Can Have Electrical Helpers Handy in Every Room—What It Costs to Keep Them

By JOHN R. McMAHON

ARISTOTLE, about 2250 years ago, thought slavery a necessary evil. He pointed to the only alternative:

"If every instrument would accomplish its own work, obeying or anticipating the will of others . . . if the shuttle would weave, or the 'pick' touch the lyre, without a hand to guide them, then chief workmen would not need assistants nor masters slaves."

The other day I asked the spirit of the Greek philosopher to accompany me on a visit to a house in Bronxville, New York. On the way Aristotle said:

"The owner of this house must be a rich man, since you tell me that he has at least thirty domestic slaves."

"He is not rich as we reckon it," I replied, "but in comfortable circumstances. He is widely known in the United States, however, as a member of the Federal Radio Commission—an umpire of the ether. His name is Orestes H. Caldwell."

"The first part of his name sounds familiar," commented Aristotle. "So this is the house. It is modest enough. But where are the slave quarters for thirty servants? Where is the granary for feeding them? And where is their workshop?"

"The servants live in the partitions," I explained, "which saves the expense of housing them outside and also makes them more readily available. The feeding problem is solved by a distant refectory called a power house, and no servant eats except when he works. The units of the workshop are right in the house. Each machine has assigned to it from one to a dozen slaves, who hop from the partitions and get busy at a given signal."

"YOUNG man," said Aristotle sadly, "we had lyres of several kinds in ancient Greece, but none so flagrantly fanciful as yourself. I fear this world has developed backward, since it has not progressed in respect for truth. Kindly permit me to return to Hades, where veracity is yet honored."

There are, of course, millions of homes in America which keep one or two servants lodged in walls and partitions. The distinction of the Caldwell residence is the large number of its equivalents for the slaves of olden time and the hired help of yesteryear, together with the wide, convenient distribution of these mechanical employees through the house. Here is an all-electrical house. Everybody who uses a little current wants to know about the use of a great deal of it, what can be done with it, what it costs and everything.

The meters of the electrical home are housed in a locked box on the wall outside; the meter reader need not bother the occupants

Cost is an early question to which there is often an aggravatingly delayed answer. If the skeptical and somewhat huffy spirit of Aristotle had put this query, I would have given him a frank and prompt reply. The average home in America uses 365 kilowatt hours of current yearly, practically all for light, and at a charge of seven cents plus per kilowatt hour (1,000 watts for one hour) pays an annual bill of $27. In contrast, the Caldwell house uses more than ten times as much, or 4500 kw. h. Of this I figure the lighting component, on the quantity basis of the national average but at a twelve-cent local charge, amounts to $43.80. There is left a power consumption of 4135 kw., which at five cents per kw. adds $206.75. The total annual bill for electricity is $250.55.

It seems a lot of money, but what servant can be hired and fed today at five dollars a week? And the best human servant lacks the versatility and efficiency of the electrical toiler. "Just a minute, ma'am," and "I can't be in two places at one time," are never offered as alibis by the cheerful genii of the partition. We spoke of thirty servants. Doubtless that is a fair comparison with antiquity, perhaps even with our conditions a few decades ago. And it is a large understatement to equalize for our time the multiple labors of the wires in this dwelling with the activity of one person aided with average home equipment.

SEPARATE meters register the current used, one for the lighting system and one for the power line. The meters are neatly housed in a locked box just outside the house and the meter reader does not have to bother the occupants. It is a small but worth while boon that prompts the question:

How about the iceman? That dripping visitor is unknown, and so are the coalman and the laundryman. The intrusion of the grocer and butcher must be borne with for the time being, until the art of conveying food over a wire is developed.

It may be well to emphasize that the Caldwell house is no electrical stunt dwelling. It was equipped gradually for personal use and not to show or prove anything. The owner happens to be an electrical engineer of an inventive turn and he has amused himself with one or two unusual devices, but his chief aim was practical, and almost anyone can have a duplicate of his standard installations. He is on the sunny side of forty, born in Kentucky and educated in Germany and in our Middle West—Purdue University. He has been an editor of electrical and radio magazines since 1907.

After seeing Mr. Caldwell's home workbench with its hand electric drill clamped



The basement includes complete electrical laundry, workshop with a workbench and electric tools, and a gas-heated steam furnace

in a vise and the astronomical toy which he made for his children, I surmised that he sometimes wished he did not have to be an editor, or to spend so much time in Washington acting as a national "traffic cop" of the ether. This man surely has the makings of an inventor, and a notable one at that. When he was just fourteen he invented an underground power system for trolley cars. A traction company bid $50,000 for the invention, which the boy's father declined, believing it worth more. In the end another device was adopted. The loss of money was probably less than the loss of creative stimulus. In high school theatricals the youth officiated as stage electrician. He began to play with radio in its early days and qualifies as an expert.

Most of the wiring and equipment of the Bronxville house was put in by local mechanics under his general directions; but Mr. Caldwell reserved all the radio installation for himself. You may wonder how this could be any kind of a job when you see a quite usual type of cabinet set with indoor aerial standing in the living room. Well, there are some frills. That radio is wired to outlets in every room in the house, including the kitchen.

IF THE cook wants a little music while the chops are broiled by the electric stove, she can don the earphones or turn on the loudspeaker. A clock attachment to the radio gives automatic time control. By this means the children, tucked in bed, receive their allotment of bedtime stories. The parents enjoy the last half hour of a symphony concert after retiring and the music terminates on the predetermined schedule. Likewise the sleeper may be pleasantly aroused to another day by the "Good morning" of the radio voice and he may go through setting-up exercises in the fit costume and place.

Setting the control clock that automatically cooks the meal in the kitchen electric range

Of course, the electrical house has a multitude of outlets. You can plug in most anything anywhere. Take your choice of music, massage or muffins. Cold feet are warmed without a hot water bottle and a feverish head is cooled by the capable servants in the partitions. There are more than a dozen outlets in the living room and not less than twenty in the kitchen, while the total for this house of eight rooms is around seventy-five. The outlets are strategically distributed between ceilings, walls and baseboards, and a very few are in the floors. In comparison, the average house has a third the number of outlets.

"I guess that house was wired when it was built," observes a reader. "Ours wasn't, and it would cost too much to do it now."

BUT it happens that the Bronxville dwelling was bought ready built by Mr. Caldwell some ten years ago, and most of its extensive wiring —in flexible metal cable, by the way—has been put in since. Doubtless it is better and less expensive to wire when building, but the job can be done afterward and the cost is not great. Complete wiring adds inestimable possibilities of comfort, while it enhances the value of every house. It entails just the first cost, upkeep being virtually nonexistent. There are all kinds of useful devices, for regular and emergency purposes, which such wiring makes available. It is also well to be prepared for tomorrow's new invention in machine or appliance: some new current-user on a par with radio and refrigerator and oil burner.

The location of outlets is important. A floor connection is generally undesirable because dirt, water or mechanical interference may cause trouble. The baseboard is safer but may contribute to backache. A wall outlet about three feet above the floor level saves stooping and is most protected. Dining table appliances, as grill, toaster (*Continued on page 136*)



Second floor. The rooms have numerous outlets for all kinds of electrical appliances, such as fans, sewing machine and vacuum cleaner. Bedrooms and sewing room are wired for radio and inside telephone

Of course, everyone cannot have an all-electric home such as this, yet most Americans can enjoy many of the devices for service and comfort which extended wiring makes available



Ground floor. The living room is equipped with thermostatic heat control, electric clock, interior telephone and radio receiver. The dining room and kitchen are electrically equipped throughout

In the living room are more than a dozen electrical outlets; and twenty in the kitchen. Total for this 8-room house is seventy-five

Kinks *for the* Motorist

Simple Ways to Make a Trouble Lamp, Wheel Puller, or a Baggage Rack—Ten Dollars for the Best Idea

O. E. Abernethy, of Hickory, N. C., wins the $10 prize this month for his suggestion of a way to discourage the auto thief (Fig. 4). Each month POPULAR SCIENCE MONTHLY *awards $10, in addition to regular space rates, to the reader sending in the best idea for motorists. Other published contributions will be paid for at our usual rates.*

Headlight Utility

THE socket in many types of auto headlights is a double-ended affair with the bulb plugged into the end inside the headlight and the supply wire from the battery plugged into the other. Such an arrangement permits you to obtain plenty of light for working on either side of the motor with very little trouble. Just remove the headlight rim, take out the bulb, and detach the supply wire. Now plug the bulb where the wire was and put the wire in the end of the socket inside the headlight. You may find it necessary to add a few inches to the length of the wire to make it reach around to the front of the headlight.

Fig. 1. Transposing headlight bulb and feed wire gives light to work on the motor

Old Tube Holds Luggage

THE rubber of which inner tubes are made is of the highest grade and, consequently, it is still springy and full of life long after it has been made useless as an inner tube by many punctures and blowouts.

Of course, it is easy enough to tie luggage on the back of your car with a piece of rope, but the arrangement shown in Figure 2 is much more handy and convenient, and in addition the elasticity of the rubber will keep the luggage tight so that it will not rattle after a few hard jounces. By making the loop of cord and inner tube somewhat smaller than the smallest package you are likely to carry, you will find that any bundle that will go on the luggage carrier can be held in place.



Fig. 2. Elasticity of an old inner tube holds packages tight on the luggage rack

A Wheel Puller

SOME iron bars, a couple of heavy bolts and a piece of copper can be made up into a puller that will serve to remove the rear wheels of any car if the wheels are fitted on the end of tapered axles. Figure 3 shows the construction and the dimensions of the iron bars. The copper plate should be riveted to the bar as shown to prevent injury to the end of the axle. After the bolts are set up tightly, the outside bar should be struck with a heavy hammer on the center over the end of the axle. This arrangement is particularly useful to the service man who may be called on to remove the wheels of cars of old style with odd sized hub cap threads. This wheel puller transmits the strain through all of the spokes to the hub of the wheel.



Fig. 3. Wheel puller made of iron bars, a piece of copper plate and two heavy bolts

Protection Against Thieves

NOTHING is more disconcerting to an auto thief than a noise which will call attention to his activities, and so the simple wiring scheme shown in Figure 4 should prove quite effective while the car is left in a well populated district. All you need is a single pole, single throw knife switch and a few feet of wire. The knife switch should be concealed at any convenient point behind the instrument board. Connect one terminal of the switch to the binding post on the ignition switch, or to the wire that runs from the ignition switch to the spark coil, at any convenient point. Connect the remaining terminal of the switch to the binding post on the horn that is wired to the horn button, or to the wire itself if that is easier. When the switch is closed, turning on the ignition will cause the horn to sound.

Wire Loop Holds Screw

IT ALWAYS is easy enough to remove a screw from an inaccessible place provided you can get at it with the screw driver, but it is not so easy to replace the screw where it belongs after the job is finished. Often there is not sufficient space to hold the screw with the fingers or a pair of pliers. In such cases the job can be accomplished very easily by using a piece of fine wire as shown in Fig. 5. After the screw is started in the thread, the wire can be pulled off. A single strand from a piece of drop cord or ignition cable will serve for small screws. A light wire is best, as it can be pulled off easier after the screw is started in the hole.



Fig. 4. Turning on ignition switch starts the horn sounding continuously, foiling the automobile thief



Fig. 5. Removing inaccessible screws is easy with a small piece of wire, as is replacing them afterward

Some *Fine* Points *of Valve* Grinding

Gus Explains a Few Tricks to Motorist Who "Knew How," but Ruined an Easy Job

By MARTIN BUNN

"You certainly ground 'em aplenty," Gus observed. "The valves and seats are worn down as much as they would be after ten normal grindings"

LATE one afternoon, just before closing time, a customer bustled into the combination salesroom and office of the Model Garage.

"Got any good valve-grinding paste?" he demanded. "I want the kind that has two compartments—one with coarse compound and the other with fine."

"I'm sorry, Mr. Rankin," replied Joe Clark, "but we don't carry that kind. Why don't you try the new water-floated paste? Gus Wilson, my partner, says it does a dandy job."

"Nope!" Rankin growled. "No substitutes for me! I know what I want." And he left the office.

Gus Wilson, who was working on a car near by, had overheard the conversation. "We never seem to have what that pest thinks he wants," he called out to Joe. "I wouldn't shed any tears if he never came near this place again. But I have a hunch he's going to need us to get him out of trouble one of these days."

"He won't get into trouble this time," laughed Joe. "Valve grinding isn't so hard."

"Huh!" snorted the veteran auto mechanic. "Don't fool yourself. Valve grinding looks easy and it *is* easy; but you can make plenty of mistakes if you don't know how to go about it."

Two weeks later the phone rang insistently and Joe clamped the receiver to his ear. A moment later he turned from the phone with a grin.

"Get out the wagon, Gus," he called. "Your hunch came true. Rankin's stuck at the bottom of Marley Hill."

Gus drove off in the service car and in half an hour he returned with the disabled machine on his towrope.

"Now let's see what's the matter with those valves, Mr. Rankin," said Gus as he set to work removing the cylinder head after opening the radiator drain cock.

"See here," snapped Rankin. "I'll admit the car is on the blink, but there can't be anything wrong with the valves. Why, I ground 'em myself just a little while ago.

Gus disconnected the hose connections and removed the cylinder head. Rankin leaned over to look at the valves.

All the exhaust valves appeared badly burned. Several were so warped that they made contact with their seats only at one side. The intake valves, on the other hand, were in good shape.

"Those valves must be defective," Rankin stormed. "I'll make the company replace every one of them!"

"Not a chance," said Gus calmly. "It's entirely your fault. You put the intake valves in where the exhaust valves ought to be, and the exhaust valves are doing intake duty."

"I did it on purpose," Rankin admitted. "The exhaust valves looked blackened, and they were pitted, so I thought I ought to shift them around—to equalize the wear."

"That's where you went wrong," explained Gus. "A lot of cars these days have plain steel valves for the intake and special exhaust valves that can stand a lot of heat without warping. The manufacturers have to save every penny in order to sell cars at today's prices—so there's really nothing to criticize. The intake valves have an easy time of it compared with the exhaust valves that are burned with hot gas on every explosion."

GUS removed the valves and the result was quite evident. Both the surfaces of the valves and the faces of the seats were blackened and corroded.

"How many times have you ground these valves?" asked Gus.

"This is the second time," Rankin answered. "The first time I put the valves back as they were."

"You certainly ground 'em aplenty," Gus observed. "These valves and seats are worn down as much as they would be after ten normal grindings. It isn't necessary to grind so much. You used the coarse grinding paste quite a while before you started to finish them. The more you grind the more you widen out the seat—and a wide seat is bad. A narrow seat is better, because there isn't so much chance for particles of carbon to jam in between the valve and the face of the seat and keep the valve from closing."

Gus held up a valve. "See that ridge? You've ground the valve against the seat so much that the face is worn away, and there's a ridge around the outside edge. If the valve stem is the least bit loose in the valve guide, that edge is going to catch on the valve seat and prevent it from closing gas-tight. The same thing would occur after a number of correct grindings unless you had the valves refaced.

"This valve shows another trouble. The grinding has made the face curved instead of flat. Looks as if the valve guide is loose and the stem wobbled in

Gus says—

"ANYONE can do a good job of valve grinding, but you can't be careless. Each valve must be gas-tight or it will soon be badly burned. First get the valves clean—especially the stems. Then grind them with the right kind of paste. Press lightly and never turn them round and round.

"Be careful not to get any paste in the cylinders. Wipe it all off after grinding each valve. Replace the intake valve guides if loose. No motor runs smoothly at low speeds if the guides let excess air into the mixture. And setting the clearance between valve stem and tappet with care will help get accurate timing and a quiet motor."

the guide while you were doing the grinding.

"We've got an electric valve-facing outfit and I'm going to grind the faces of all the valves. That will make them practically as good as new. Also I'm going to ream out the gas passages a trifle, to narrow the seats, so I can true 'em up without making 'em any wider, and replace one of the valve guides."

"Holy smoke!" gasped Rankin. "I must be some mechanic! If ever I try grinding valves again"—

"I'M NOT trying to scare you out of working on your car," smiled Gus. "There's no reason why you shouldn't do ordinary valve grinding—if you go about it right. It isn't necessary to grind the valves on a special machine and reface the seats every time. Such treatment is only needed after a number of regular jobs.

"Valve grinding should be done every time you scrape out the carbon. Don't let it go until the valves leak so bad the motor begins to lose compression and runs rotten. Once the hot gases begin to get past them, the valves burn and pit much more rapidly. Little and often is the rule for best results. Each time you grind the valves, take off just enough metal so that they seat all the way round; and don't forget to scrape the carbon off the face of the valve before you start grinding.

"Apply the paste evenly, don't press hard, and never rotate the valve all the way around. Turn it back and forth through a part of a circle a few times. Then lift it off the seat, turn it part way round and do a little more grinding."

"How do you know when the job is finished?" Rankin inquired. "I ground 'em a lot just to be on the safe side."

"A GOOD mechanic can tell by the feel of the valve and the look of the seat," Gus replied. "If you're very fussy you can buy a pressure tester like this one." He fished an instrument out of his tool kit. It was shaped like an inverted cup with a gage attached to one side and a rubber bulb connected to it with rubber tubing.

"You press the cup over the valve and squeeze the bulb to pump up a bit of pressure," Gus explained. "If the gage needle stands still, you can be sure that no air is leaking through the valve and it will be gas-tight.

"Here's another simple way to test valves. Wipe off all the grinding paste from both the valve and the seat. Rub enough Prussian blue on the ground part to color it and press it tightly in its seat without turning it. Take the valve out again and if you find a complete ring of blue on the valve seat you may be sure the valve is sufficiently gas-tight."

"Maybe I used the wrong kind of grinding paste," Rankin suggested. "The coarse stuff cut fast enough; but it made deep rings in the metal and I had to grind quite a while with the fine paste to get rid of those rings."

"Joe tried to sell you the right kind of grinding paste, but you wouldn't listen to him," Gus reminded him. "You didn't bother to polish the stems, did you?"

"No," Rankin admitted. "I thought the motion of the valve stem up and down in the valve guide would scrape off the carbon if it got too thick."

"Neglecting that point is what spoils a lot of amateur valve-grinding jobs," Gus asserted. "The carbon gets burned on the stems of the exhaust valves so hard that it forms a little ring on the stem just where it interferes with the valve's closing tightly on the seat. First the motor begins to miss when it's idling, finally it gets so bad that the motor will only fire on all cylinders when the throttle is nearly wide open and the compression is high enough to jam the valves shut in spite of the carbon-caked stems.

"The funny thing is that the valves seem to close all right and the compression is fairly good when you crank the motor over by hand. The valve stems cool off when the motor is stopped and they contract enough to work right.

"After grinding valves you've got to adjust them for proper clearance. If you get 'em too close, the valves won't seat right, the motor may start hard and the valves will need grinding again too soon.

"Of course, reducing the clearance between the valve stems and the tappets will make a motor sound nice and quiet, especially if the parts are badly worn.

"On the other hand, if there is too much clearance the motor will be noisy. It's better, though, to have them a little too loose than a little too tight."

"What's the correct clearance?" Rankin asked.

"Depends on the car," replied Gus. "The service instruction book will tell you what the clearance should be. If you haven't got a book, set the intake valves with about three thousandths of an inch clearance and the exhaust valves at five thousandths—exhaust valves always need more because they get hotter and the stems expand to a greater length. If it's an overhead valve motor the clearance should be greater—about five to seven thousandths for the intake valves and from seven to ten thousandths for the exhaust.

"WHATEVER clearance you use, it's mighty important to have all the intake valves exactly the same; the exhaust valves also should be alike. Then whatever noise is made by the valve mechanism will be smooth and steady. If one valve is a trifle looser than the others you are sure to hear the individual click."

"One other question I'd like to ask," said Rankin. "I've been turning the motor over by hand to find when the valve is closed so I can set the clearance. As soon as I see that the valve is closed I get busy with the adjusting nuts. Is that right?"

"Not quite," Gus answered. "Turn the motor one half a revolution beyond the point where the valve closes. That is especially important in a motor that has been driven considerably, because when the valve closes the valve tappet snaps down on the cam just past the high part that makes the valve open. This pounding has a tendency to wear the cam at that point and if you do your adjusting while the tappet is resting on the worn spot, there won't be enough clearance on the rest of the low part of the cam.

"Don't forget to inspect the valve springs. Weak springs make the motor run rotten at high speed. The trouble is that a weak spring doesn't close the valve fast enough, so that it stays open when it should be closed. The faster you go the worse the valves work. Of course it is easy to test the spring for weakness, because a weak spring always is shorter than a new one. So just compare your springs with a new one, and discard any that are noticeably short."

"Well, if I do a bum job the next time I grind the valves it won't be your fault," said Rankin as Gus finished his explanation, "and if you folks told me that breakfast food made good valve-grinding compound, I'd almost believe you!"



The drawings show how and how not to treat valves if you wish to have a smooth and even-running engine. Reading down, the first column shows valves that must not be switched; unpolished and properly polished stems; and wrongly and rightly ground valves. The second column shows tests for tightness; clearance adjustments; and proper and improper seats

Roosevelt Dam
and Reservoir System



Great American Reservoirs

THE Roosevelt Dam stores up a huge reservoir of water which can be drawn upon as needed. The thirty-five Western Electric distributing houses store up reserves of telephone apparatus and supplies to be drawn on as needed by the telephone companies in constructing lines and maintaining service

Western Electric with this outstanding national distribution system, does this work at substantial economies for the telephone companies and the telephone-using public.

In time of emergency this service, because of its flexibility, aids your telephone company in quickly repairing the ravages of storm, fire or flood.

Distribution thus plays an important part along with manufacturing and purchasing—the three Western Electric responsibilities—in supplying the needs of the Bell System.

Western Electric
Distributing System



After the storm Western Electric stocks enable telephone service to be restored promptly.



Western Electric quickly supplies everything needed inside the telephone exchange too.

A nation-wide service of supply. Western Electric maintains stocks at 35 important points.



Back of your telephone

Western Electric

SINCE 1882 MANUFACTURERS FOR THE BELL SYSTEM

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

No more lost tools!

Make a Tool Chest from Plan No. Se70

A chest keeps tool-edges sharp and surfaces free from rust. It guards against loss. Here's good news: Stanley Plan No. Se71 gives detailed instructions for making a large sized tool chest. Plan No. Se70 is for a smaller chest.

Of course, you realize the savings that come from using *good* tools. The amateur needs good tools even more than the professional. Most carpenters and manual training instructors use Stanley Tools. They know from first hand experience that the Stanley name stands for durability, correct design, and right "feel."

You can buy Stanley Tools separately and so collect your own set. For your convenience in buying there are also complete sets of Stanley Tools in chests at a wide variety of prices from $15 to $95. Or there are assortments in strong cardboard boxes containing directions for making your own tool chest. Priced from $5 to $20.

Your hardware dealer has Plan No. Se71 and Se70 as well as other Stanley Plans for making useful articles, or he can get them for you. The plans cost only 10c each. Ask him also for small Catalog No. Se50—which shows many useful Stanley Tools. It is free. If he cannot supply you write to The Stanley Works, New Britain, Conn.

The best tools are the cheapest to use
Ask your hardware dealer Ⓢ



STANLEY TOOLS

Ⓢ This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.



New Ways *to Paint* Furniture

Five Distinctive Methods of Decorating a Magazine Rack — Color Schemes — Stippling — Transfers

By BERTON ELLIOT

MOST popular of all the unpainted furniture novelties now being widely sold for finishing and decorating at home is the magazine rack.

The reason is easy to see. It is highly decorative and, when gracefully designed, has a charm of its own. It is useful, for there is hardly a household, in this magazine reading age, that does not have a number of magazines about all the time. It is reasonable in price. It looks well anywhere. And it is a simple thing to decorate—one of the easiest for the amateur painter to start with. So its popularity seems to be deserved.

The possibilities for decorating a magazine rack are almost unlimited, when one considers the wide range of colors, shades and tones, the many transfer designs available, and the different types of treatment that may be employed. It may be readily decorated to harmonize with any color scheme.

For those who have not attempted the decoration of furniture, a magazine rack is a good piece upon which to make a beginning. The work is certain to turn out well, if the following suggestions are observed; and then the methods so pleasantly learned in this way may be used to decorate larger pieces.

Five typical schemes of decoration are illustrated. These may be carried out in any colors desired. The color schemes reproduced are attractive combinations; others are suggested in the following paragraphs, which describe in detail each of the five methods of treatment.



1. Plain color

2. Color blend

3. Color print



4. Stipple and transfer

5. Border and transfer

1. Plain color effect with another color on the edges, and a floral transfer decoration. Almost any body color may be appropriately used. Gold is an especially suitable color for trimming, as it harmonizes with most body colors and adds a desirable touch of richness. Lettuce green body color and gold trim, for example, is a pleasing combination. In transfer designs the popular motifs are flowers, ships and birds.

2. Blended effect, graduating from very light at the top to dark at the bottom. Black stippled over green, black over Chinese red, gold over green, gold over black, and gold over red are all good.

3. Plain color effect, decorated with a color print from a magazine, and the entire surface, including the design, coated with clear lacquer. A liquid preparation is now available by means of which printed designs from magazines, newspapers and wall papers may be transferred to any surface. When this method is used, it is not necessary to coat over with clear lacquer unless desired.

4. Stippled effect, blending from dark at the edges to very light at the center. The foundation coating is brushed on as for a plain color effect. The stipple color is applied with an air brush or by pouncing on with a stencil brush (see page 113). A panel of the foundation color is left in the center for the transfer. Lettuce green foundation color, stippled with black and with gold edges and Colonial design transfer, would be a rich and dignified treatment.

5. An oriental effect. The body color—black, for example—is carried to within 1 inch of the edge, the border

(*Continued on page 113*)

How *to Build* a B-Eliminator

Your Choice of Two Practical Designs—A Standard Type or a De Luxe Model for Exceptional Results

By ALFRED P. LANE

THERE are two ways in which you can go about the problem of building a B-battery eliminator. One is to follow standard practice and assemble an outfit according to the arrangement shown in Figs. 1 and 2. This is the circuit used in the majority of factory built eliminators and if you use parts of high grade, your eliminator will be just as good electrically as the commercial product. There will be a slight saving in expense.

The other way is to use a more elaborate circuit arrangement and more expensive apparatus to construct a de luxe B-eliminator. This procedure will appeal to you if you are willing to spend slightly more than the cost of the high grade commercial eliminator in order to obtain extraordinarily perfect results. A de luxe type of B-eliminator is shown in Figs. 3 and 4.

Both these eliminators have been carefully tested by the Popular Science Institute of Standards and the results of these tests are shown in graphic form in Fig. 5.

The quality of any B-eliminator is measured by how nearly it comes to supplying perfectly smooth direct current and by its ability to maintain a constant voltage, regardless of the amount of current drawn from it or the fluctuations in the voltage of the electric light current that is used to operate it.

IF THE pulsations are not removed from the current by the time it goes from the binding posts of the eliminator, a certain amount of hum will be produced in the loudspeaker; and a measure of the severity of this hum is the amount of alternating voltage left in the direct current.

Inability to hold the voltage steady means that adjustments must be provided so that you can regulate the voltage to suit the current requirements of the individual receiver to which the eliminator is connected. Variations in voltage also show up in poor quality when you attempt to operate the receiver at close to maximum volume.

Testing the de luxe B-battery eliminator on the Popular Science Monthly 5-tube receiver—a good combination

The curves marked "standard" eliminator in Fig. 5 show the performance of the B-eliminator illustrated in Figs. 1 and 2. High grade commercial eliminators give about the same results. And any eliminator that tests out as well as this will give good results on almost any type of radio receiver except, perhaps, those using resistance-coupled audio amplification.

If you want still better performance, you can get it by building the eliminator shown in Figs. 3 and 4 and which in the Popular Science Institute of Standards tests produced the curves marked "de luxe" in Fig. 5. Note that the voltage regulation is exceptional. In fact the de luxe eliminator gives better results in this respect than can be obtained from dry cell B-batteries unless they are absolutely new. The hum, as indicated by the alternating current voltage still remaining in the output of the eliminator, has been reduced to an extremely low figure.



Fig. 1. Picture wiring diagram of the standard eliminator, with the theoretical wiring diagram at the left of it. Cases ABC, D and E should be grounded to the minus B wire at any point. The grounding wires have been left out purposely to simplify the diagram



Fig. 2. Two views of the assembled B-eliminator. G controls the voltage on the 90-volt binding post and H controls the detector voltage. Check your wiring several times before you turn on the current

Additional tests were made to determine the effect of using the de luxe eliminator under conditions where the voltage of the electric current was not steady. A current of 42 milliamperes was drawn from the eliminator which represents the amount consumed by a 6- or 7-tube set equipped with power tube. When the electric light line voltage was 117, the voltage developed by the eliminator was 197.5 volts. Reducing the line voltage to 94 caused the output voltage to drop to 179 volts. In other words, a change in the line voltage of 23 only changed the output 16.5 volts. A stand-

ard type of eliminator would show a far greater falling off in output voltage under the same conditions.

To sum up the relative advantages of the two types of eliminator, the standard arrangement shows you how to build the simplest and cheapest eliminator that will give good results. The de luxe type represents a higher class instrument that costs more to build but that gives less hum, a practically constant voltage output, and complete freedom from adjustments of any kind. It will operate perfectly regardless of the type of set or its current consumption. Obviously, it would be foolish to build the de luxe type of eliminator to use with any set of less than five tubes with a power tube of the 171 type in the last audio stage.

WHILE it is possible to get C-voltages out of a B-eliminator, troubles and complications develop in many cases. Such an eliminator is more costly to build and the extra expense is not worth while, especially as a 45-volt battery used to supply the C-voltage required by the 171 tube will last for well over a year.

The list of apparatus needed to build the standard type eliminator in Figs. 1 and 2 is as follows:

A, B, C—Power unit consisting of high voltage transformer and two choke coils.
D—Filter condenser block having terminals giving 2, 2, 8, 1 and 1 microfarads, rated at not less than 160 volts D. C. working voltage.
E—Buffer condenser having two terminals giving .1 mfd. on each, rated at not less than 300 volts A. C. working voltage.
F—Standard X-type socket.
G and H—Variable high resistances, granulated or disk type.
J—Fixed resistance 10,000 ohms.
Type B filamentless rectifier tube, 60 mil. rating.
Four binding posts and wooden baseboard.

It makes no difference whether you buy A, B, C as a single unit in one case or as separate units. Results will be the same. The combined unit is more compact, of course.

The exact wiring arrangements will depend on the individual units you purchase. Fig. 1 shows the arrangement of the wiring of the model eliminator.

To build the de luxe eliminator you will need the following apparatus:

A¹—High voltage transformer with center tap giving 350 volts each side of zero. It is desirable to get one having a filament wiring also, a use for which will be shown in an article in next month's issue.



Fig. 3. This de luxe type of B-battery eliminator has no adjustments. The output voltage is automatically regulated

B¹ and C¹—Choke coils developing not less than 50 henrys inductance at a 50 mil. load.
D¹—Filter condenser block having terminals giving 2, 2, 4, 4, 1 and 1 microfarads capacity, rated at not less than 250 volts D. C. working voltage.
E¹—Buffer condenser giving .1 mfd. on each of two terminals, rated at not less than 400 volts A. C. working voltage.
F¹, K and L—Standard X-type sockets.
M—Fixed resistance 13,000 ohms with tap so that you can divide the resistance into sections of 5000 and 8000 ohms.
One type BH filamentless rectifier tube, 85 mil. rating, and two UX874 voltage regulator tubes.
Four binding posts and baseboard

All apparatus must be exactly as specified in order to obtain the results shown in curves of Fig. 5. In fact, the extremely small hum produced by this eliminator as compared with the standard type lies chiefly in the extraordinarily effective choke coils B¹ and C¹. The excellent output voltage regulation is obtained by developing more power than is required and allowing the excess current to flow through the voltage regulator tubes placed in sockets K and L. By this method of operation, the eliminator always is working under a constant load and the current consumed by the set is subtracted from the amount flowing through the regulator tubes.

Before you start wiring, study Figs. 3 and 4 and be sure that you understand every detail. Note that the parts should be assembled on the baseboard essentially as shown with at least two inches of space between the choke coils B¹ and C¹. You are dealing with relatively high voltages, so be sure to use rubber or enameled fabric insulated wire throughout.

Note that only two terminals are used on sockets K and L, the G terminal and the diagonally opposite filament terminal.

Either type of eliminator will give ample current output to operate at maximum the largest set with a 171-type power tube in the last stage of audio amplification. Use the filamentless type B 60 mil. rectifier tube in socket F of the standard type eliminator. Use an 85 mil. type BH filamentless rectifier in socket F¹ of the de luxe type with the UX874 voltage regulator tubes in socket K and L.

To put the standard type eliminator into operation, connect the binding posts to the similarly marked ones on your radio set, turn on the filament switch of the set, plug the eliminator cord into the light socket and adjust the knobs of variable resistances G and H for best reception results. Always turn the eliminator on after you have turned on the set, and turn off the eliminator before you snap the filament switch on the set. If you don't follow this procedure, excess strain is placed on the filter condensers in the eliminator. Of course, if you use an automatic relay (*Continued on page 107*)



Fig. 4. How to wire the de luxe model. The theoretical wiring diagram is at the right of the diagram above. Be sure to ground the frames of A¹, B¹, C¹, D¹ and E¹, although the grounding wires have been left out to avoid confusion. Wire to point X as shown for a 200A detector tube, but connect to point Y if higher detector voltage is required



Fig. 5. In the upper section of the diagram below is shown the accurate voltage regulation of the de luxe type of eliminator under actual working conditions. Both standard and de luxe type of eliminator are graphically compared in lower section of the diagram





My *Motorized* Shop Cost $20

How an Ordinary Polishing Head Was Developed into an Outfit for Sawing, Turning, Grinding, Drilling and Sanding

By WALTER E. BURTON



The saw table has both a ripping and an adjustable crosscut guide

Side view of the saw table with the dust chute in place



A bent iron bar serves as a convenient rest for grinding tools

SPACE and money are two of the things with which the average home mechanic is not always abundantly supplied. These very limitations resulted in the construction of the small but exceedingly versatile and sturdy motor-driven home workshop illustrated.

The machine itself, without tools and accessories but with a new one-quarter-horsepower motor, cost less than twenty dollars. It is so compact that it could be placed on a table 3 ft. square, yet it will do rip and crosscut sawing, grooving, grinding, polishing, drilling, sanding and turning.

For the main element of the shop a polishing head of fairly heavy construction, costing between four and five dollars, is used. The motor may be of almost any type, providing it has sufficient power and a speed of about 1750 revolutions a minute. A new one, rated at one quarter horsepower, may be purchased for about twelve dollars. A circular saw, 8 in. or less in diameter; a 4-in. grinding wheel, an 8-in. polishing disk, about 10 ft. of ¾-in. or 1-in. angle iron, an assortment of pipe fittings, and miscellaneous screws, bolts, and washers, will be needed.

The saw table, which is 12 by 16 in., is made from two pieces of ¾-in. wood, one 2 by 16 in., and the other 9½ by 16 in. Angle iron is used to bind the ends to prevent warping. The pieces of wood are spaced about ½ in. apart to permit the use of a sliding guide. The larger piece is slotted for the saw blade.



The motor, polishing head and standards



All the parts of the complete motorized workshop except the lathe tool rest

Pipe fittings are used as supports, for several reasons. Nipples of different diameters permit the easy adjustment of the height of the table. The fittings are cheap and rigid, and can be drilled and tapped for set screws easily. When the polishing head is used for purposes other than sawing, the nipples may be unscrewed, leaving only the floor plates, which will not hamper work.

The floor plates and nipples are placed on the saw table and the supporting table or bench as illustrated. When the grinding wheel is used, the two front upright nipples, together with a piece of bent iron rod, form an excellent rest for the work.

It was found best to use as a ripping guide for the saw table a straight piece of wood, held with two iron clamps, because adjusting the table for height causes a slight variation of the position of the saw in the slit. An adjustable sliding guide, made of sheet brass, a set screw and a piece of bar iron or steel is used for mitering.

The lathe bed for supporting the tailstock and tool rest is made of two long pieces of angle iron, spaced with two shorter pieces, the distance between edges of the longer sections being about 2 in.

The tailstock is constructed of ¾-in. pipe fittings, and includes a floor plate, a nipple 2 in. long, and a T. A ½-in. bolt, the end ground to a point, is fixed in the T as

(*Continued on page 100*)

Ride with ETHYL *and get the benefits of High Compression*



ETHYL
BRAND OF ANTI-KNOCK COMPOUND
ETHYL GASOLINE CORPORATION
NEW YORK, U.S.A.
Knocks out that knock

MORE than a million motorists are now enjoying the benefits of high compression through Ethyl Gasoline. In two ways:

1 *Through high compression automobiles.* The advent of Ethyl Gasoline has at last given car manufacturers the opportunity mechanically to raise the compression of their engines. For cars now in use they can offer special high compression cylinder heads which greatly increase performance.

2 *Through carbon formation.* By letting carbon form in the cylinders of a car of ordinary compression, you automatically increase compression. And since Ethyl Gasoline is a high compression fuel, those deposits which heretofore have meant "knocking" and power loss become a source of *extra* power and driving satisfaction.

Ethyl Gasoline is motor gasoline containing Ethyl brand of anti-knock compound, the ingredient which eliminates the "knocking" characteristics of ordinary gasoline and makes it a high compression fuel.

In terms of you and your car, high compression and Ethyl Gasoline mean a more powerful and flexible car, less gear-shifting, faster pick-up, less vibration and lessened depreciation. In short, a performance and economy impossible with ordinary compression and ordinary gasoline.

Ethyl Gasoline is distributed in the United States and Canada by responsible oil companies. ***It has absolutely no ill effect on the motor or its parts.***

The first tankful will prove every claim. On sale at pumps which bear the "ETHYL" trademark shown on this page. There's one near you.

ETHYL GASOLINE CORPORATION
25 Broadway, New York City

ETHYL GASOLINE

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.



System in Surface Grinding

What Wheels to Use—Set-Ups That Simplify Difficult Jobs

By HECTOR J. CHAMBERLAND

EVERY toolmaker and machinist knows the part played by the surface grinder in toolroom production, and the more experience one has had in using this versatile machine, the better one can appreciate its value.

With a magnetic chuck and a set of indexing centers, which should be its regular equipment, the machine can be relied upon in case of a rush job to execute much work ordinarily done on other grinding machines, should the latter be in use.

As in the case of any grinding machine, the choice of the proper wheel for each operation is an important factor, from the standpoint both of economy and of good work.

The wheels recommended in this and in an article to follow are alundum; if wheels of other varieties are preferred, the corresponding grain and grade should be used.

The care of the machine should not be overlooked. The spindle should be tested for wear and end play occasionally and the ways of the carriage kept well lubricated. A daily kerosene bath will save money.

The magnetic chuck should be surfaced off every two weeks by removing .001 in., which is generally sufficient. For this operation a 46-J wheel will give a good finish.

If possible the chuck should never be removed from its position. A convenient scheme that saves much time is to have a plate the size of the chuck to which the centers are fitted. To prevent scratching, thin paper should be used under the plate as well as under any piece to be ground.

Wheels 6 or 7 in. in diameter and from ¼ to ⅜ in. thick are recommended. For ordinary work in grinding tools made of high speed steel it is well to use a wheel one grade softer than that recommended for carbon steel; this is, of course, the general rule in most grinding operations.

The most difficult operations that come within the scope of surface grinding are probably the making of snap gages and dovetail forming tools. These are often more or less complicated, and the average toolmaker, unless familiar with this work, is rather uncertain as to how to proceed.

Grinding a plain snap gage is a common operation, but one like that shown on page 122 requires close attention.



How measuring rods are used to check accurately the lengths in grinding a snap gage. A drawing of the gage is reproduced on page 122

The grinding of the gage is illustrated at the right. This is a typical example of a difficult surface grinding job





A dial indicator is used to measure the depths on a dovetail forming tool (above). Dressing the wheel at an accurate angle (at left)

This gage has seven dimensions on one side and four on the other, all to be ground within close limits.

These gages are ordinarily made in sets of two or four. The blanks are pinned together and milled as one. In this case it is not advisable to pursue this course in grinding, because, owing to the close limits, a slight variation may occur and in that event it would be far cheaper to scrap one than two or four pieces.

An 80-J wheel of proper diameter and width is recommended for this operation. For safety against breakage, smaller dimensions than ⅛ in. should be milled with an allowance of .001 in. for stoning to size.

To attain accurate results, the gage should traverse the wheel all the way across; in other words, the wheel, having been previously dressed and concaved slightly on both sides, should grind on its own two cutting edges in order to hold both ends of each dimension parallel.

The grinding allowance left in making the blanks is generally from .010 to .012 in. For measuring the steps a micrometer depth gage is used; for the lengths, a telescoping caliper may be used, but in this case, owing to the close limits, the measuring rods, as illustrated in one of the photographs above, are the safest. These are made of ⅜-in. drill rod. They are cut off ¼ in. longer than the finished sizes, slightly

(*Continued on page 122*)

MANY time-saving shop ideas are contained in the continuation of the Better Shop Methods Department, to be found on pages 116 to 122.

In Queensland—too
Starrett Tools mean more to a man!

Read the letter reproduced below. It contains a more powerful and sincere argument in favor of a full kit of Starrett Tools than anything we can say.

The catalog which Mr. Hannah requests is the Starrett Catalog No. 23 'W' It contains illustrations, descriptions and prices of more than 2500 fine tools. We will gladly mail you a copy on request.

THE L. S. STARRETT CO.
World's Greatest Toolmakers
Manufacturers of Hacksaws Unexcelled
Steel Tapes—Standard for Accuracy
ATHOL, MASS., U. S. A.

Peeramon
North Queensland
Australia
21/12/26

The L. S. Starrett Co.

Could you send me a catalogue of small machinists tools?

I work in a local shop with a pal who has a complete range of tools bearing your name. It is disappointing when the boss sends him out on special jobs remarking that he can make a better job with the tools of his than I can, when I feel confident of doing the work myself.

I saw one of your ads and took the liberty of writing you.

I remain,

Yours truly,

Geo Hannah Jnr

Use Starrett Tools

976

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.



Lay Creo-Dipts over old side-walls

...save paint...save fuel

DO you want to rebeautify your present home—make it more livable—*more valuable?* Lay Creo-Dipt Stained Shingles right over the old side-walls. Costs only ⅓ more than re-painting; saves its entire cost in paint-bills alone in the first 5 to 7 years.

Saves fuel, too. Most owners estimate from 15% to 25% each year. Side-walls of Creo-Dipts add another protection against winter-cold and summer-heat.

Mail the coupon today for photographs showing this new way of making old homes new. Ask about Creo-Dipts for new homes, new roofs, re-roofing, too. Get the facts *now*—before you turn the page.

Genuine Creo-Dipts are carried in stock by leading lumber dealers everywhere.

CREO-DIPT
Stained Shingles

MAIL THIS COUPON

Creo-Dipt Co., Inc., 1234 Oliver St., No. Tonawanda, N. Y. (In Canada: Creo-Dipt Co., Ltd., 1610 Royal Bank Bldg., Toronto.) Sales offices in principal cities.

Enclosed find 25c for portfolio of large-size photographs of Creo-Dipt homes, booklet of color suggestions, and name of local Creo-Dipt dealer.

Check the use that interests you

☐ Covering old side-walls ☐ New roof
☐ Building new ☐ Re-roofing

NAME.....

ADDRESS.....

Unique Noah's Ark Toy Floats or Runs on Land

By JOSEPH FALK



Latest version of one of the oldest toys—an amphibian ark so large that children can go aboard to play

HERE is a Noah's ark toy built for use on land or water and large enough for small children to get on board with all their pets and animal toys. It is the latest and most novel development of one of the oldest of toys.

The ark is mounted on a simple home-made truck with wheels set off-center so that it will rock realistically as it is pulled along. Then, if there is a shallow wading pool in the neighborhood, it can be wheeled to the water's edge, removed from the truck by loosening four bolts, and launched like a boat.

In building a toy for this dual use, it is important, of course, to have the hull water-tight. Use clear, sound cypress or cedar ⅞ in. thick for the sidepieces and ½ or ⅞ in. thick for the bottom. The latter should be fitted carefully and the joints coated liberally with white lead as the pieces are fastened in place with 1½- or 2-in. galvanized boat nails. The hull should be tight after it has been in the water a short time, but if any cracks develop, they can be caulked with candle wicking or strips of cotton set in white lead. The superstructure should be as light in construction as possible.

If there is no water near by safe enough for using the ark as a boat, the children still can have a great deal of fun playing with it. In that case the sidepieces should be so well rounded that when the ark is removed from the truck it can be rocked in teeter-totter fashion. The narrow bottom boards should be at least ⅞ in. thick to withstand the rough treatment.

Obviously, the toy can be made any size, according to the number of children who are to use it and the materials available, although an over-all length of 6 ft. and a width of 2½ or 3 ft. are ample. The design may be modified in many ways to suit the ideas of the builder. The more doors, windows and such accessories as a bird house and gangplank there are, and the brighter the colors in which it is painted, the better the children will like the ark. The toy can be built, too, in a smaller size—2 ft. long or less—with the same advantage that it can be either drawn over the ground or floated on any shallow pond or stream.

A Handmade Paddle for the Canoeist

SOONER or later, many canoeists who take pride in keeping their equipment in the best of condition, are fired with the ambition to make a paddle of their own. A good model to copy is that illustrated. It is patterned after the favorite paddle



Side and edge views of the paddle, which is a favorite style for long trips and rough water

of a famous Canadian guide and is especially desirable for use on lakes and large rivers where rough water is apt to be encountered.

The paddle may be made of Norway pine, spruce, maple, ash or other tough, strong woods. The piece must be straight grained and well seasoned. The length should be the same as the height of the one who is to use the paddle. Work from the center lines and do the shaping with saw, ax, drawshave and spokeshave. Scrape the wood and rub smooth with a fine grade of sandpaper or steel wool. Finish with linseed oil.—C. A. K.

AFTER I HAD done a careful job of white enameling the interior of our refrigerator, it was allowed to dry thoroughly and well aired. When it was put into use, however, the smell of paint spoiled some of the food. I was told to paint the interior with melted paraffin and then scrub it out with hot water and washing soda. This was tried and removed the odor completely.—FREDERICK J. PEASE.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

H A V E A C A M E L



Camel is as good as the sea is wide

BOUNDLESSLY deep is the quality of Camel. Its cool, smooth smoke is as tasty and fragrant, as restful and friendly as an ocean plunge. Modern smokers, educated by experience to the quality of tobaccos, have made Camel their favorite. In worktime and playtime, Camel is the most loyal smoking companion anyone ever had.

The choicest Turkish and Domestic tobaccos tell in the smoking. Expert blending has its part in making Camel the finished masterpiece of cigarettes. In creating Camels no cost or care is too great to make them the fittest and finest, regardless of price.

If you don't yet know Camels, you are invited to complete taste satisfaction. Camel is the smoking friend that will never fail you. It's first in this modern, particular age.

"Have a Camel!"

R. J. REYNOLDS TOBACCO COMPANY, WINSTON-SALEM, N. C.

© 1927

Luca Della Robbia (1400-1482), the first of the famous Florentine family, developed to a point of artistic perfection the intricate technique of enameling clay.

Borrowing fire from Della Robbia

MASTERS of Art they were. Masters of enameling on clay. Their gems of modeling covered with brilliant colors are unequaled today. And the gifted craftsmen of Venice and Limoges have left us superb proof of their ability to apply enamel to metal.

That enamel can be something besides ornamental, that it can actually be useful, is a discovery and a development of this age of machinery and engineering. Step by step the art has become a science. Better metal, better glazes, better methods, and better heat —electric heat.

The glowing units of the electric furnace give a heat that is perfectly uniform and constant—vital factors if the enamel is to be smooth. And in the electric furnace there is no smoke to mar the glistening surface.

Such stories are legion. With electric heat as an ally, manufacturers offer us today hundreds of well-finished products. Even an army of men using Della Robbia's methods could not do this work at any cost.

General Electric engineers have applied electric heating to processes used for bathtubs and jewelry, for cast iron and bread, for tool steel and glue pots. In the C-E booklet entitled "Electric Heat in Industry" you will get some idea of its range of application and of the possible value of electric heat to any manufacturing business.

GENERAL ELECTRIC

6-3923

Simply Built Reading Tables

One has a roomy magazine rack, the other an accessible book trough and a lamp platform of unique design

By KENNETH R. LAVOY

READING tables, which are a necessity in every home, are doubly desirable when they contain in themselves some storage place for books and magazines. Two exceptionally convenient tables of this type are illustrated. One is a graceful end table with a rack for magazines and papers; the other is a book-trough table of unique design, with a special platform for the reading lamp.

Both tables are of simple construction and involve the making of no difficult joints. They can be built in a relatively short time, at little expense for materials, and finished attractively with one of the new brushing lacquers, which dry quickly and give splendid results.

Complete working drawings for both tables and the full size details necessary for laying out the curves required in the magazine end table are contained in the POPULAR SCIENCE MONTHLY Blueprint No. 68 (see the list on page 103). This sheet will be of considerable help to you if you wish to build either of the tables.

Whitewood, white pine or other easily worked wood should be used, although either table, if preferred, may be made of birch, red gum or other cabinet wood and given a natural finish to match the furniture in the room in which it is to stand.

In making the magazine table, first lay out a pattern for the end on a piece of heavy wrapping paper. The curves may be traced directly from Blueprint No. 68, as they are given full size. Cut out the pattern and use it to mark the outline on two boards ¾ (or ⅞) by 14 by 28 in.

THE quickest method of cutting the curves is, of course, with a band saw, but equally good results may be obtained by using a turning saw. Smooth the edges with spokeshave, file and sandpaper.

Next get out the top, which is ¾ by 18 by 29 in., marking the curved ends directly from the blueprint or from a wrapping-paper pattern.

The magazine holder requires 2 sides, ⅜ by 8 by 19½ in.; 4 ends, ½ by 4 13/16 by 8 in.; 1 center, ⅜ by 11½ by 19½ in., and 1 bottom, ½ by 5 by 19½ in.



The magazine-rack end table. Mr. LaVoy is sandpapering the piece before finishing it with lacquer

Plane the boards to the correct dimensions, mark and cut the curves in the center and side pieces, and plane bevels on both edges of the bottom so that it will fit snugly within the side pieces. Fasten the four end pieces of the rack inside the ends of the table with glue and slanting 1¼-in. brads or with 1-in. No. 9 screws. Leave just enough space between each pair of these pieces to receive the center partition snugly. Then fasten the center with glue and nail it strongly from both sides, driving the nails in a slanting direction or toe-nailing, as it is called. The nails are started in the center piece and pass into the ends, so that there is no chance of marring the outer surface of the ends.

Complete the assembly by adding the bottom and side pieces of the magazine holder and fasten on the top by means of 8-shaped table top clips or a home-made substitute for them.

Smooth carefully with sandpaper, fill nail holes with plastic wood filler, water putty or glue and fine sawdust, and give three coats of brushing lacquer (see page 73).

The book-trough table is intended especially for the student or book lover who wishes to keep a few books beside his chair. None of the book troughs or tables sold commercially combine the same advantages as this table. Whenever the trough is high and accessible, there is no place for the reading lamp, and in the accepted type of combination book trough and table, there is plenty of room for a lamp, but the books are hidden under the long top. At least, this was my own experience and the reason why I set about constructing a table of the type illustrated.

The trough, which is in two parts, will hold twelve books of the average fiction size, and the small platform between them will support an ordinary reading lamp and still leave room for an ash tray. While I did not place a drawer in the table I made for myself, one might easily be added.

WITH the exception of the trough, which is nailed in place, the table is put together with dowels. Screws might be used in places instead of dowels—either round screws with blued heads or common screws with heads set in counterbored holes and concealed with wooden plugs.

The parts required are 4 legs, ¾ by 2 in. by 2 ft. 5 in.; 2 top rails, ¾ by 8 by 8 in.; 2 rails, ¾ by 3½ by 8 in.; 1 top, ¾ by 8 by 13 in.; 1 stretcher, ¾ by 5 in. by 2 ft. 4½ in.; 2 rails, ¾ by 6 in. by 2 ft. 4½ in.; 2 shelves, ¾ by 5½ by 10¼ in., and 2 shelves, ¾ by 9½ by 10¼ in.

The scale drawings of the table and list of the operations or steps in constructing it are contained on our new blueprint (No. 68, page 103)

The book-trough reading table



Side and end views of the magazine table. All the curves are shown full size on our Blueprint No. 68



Working drawings of the table, which has a trough divided in two by a platform for the reading lamp

A Pipe Smoker in Australia Speaks Up

It cannot help but give us a thrill to have someone on the other side of the world write to us in the same pipe-smoker's language that we hear at home.

Hear what the gentleman in South Australia says:

Mount Barker Road
or Crafers P. O.
Sterling West
South Australia
November 18, 1926

Larus & Bro. Co.
Richmond, Va.

Gentlemen:

Having been a smoker for the past twenty-six years, I have never come across any tobacco to compare with your Edgeworth. It is a pleasure to smoke, does not affect the health in any way whatsoever, and is most cooling and tasty to the palate.

Everyone I come in conversation with that is a smoker, I always introduce your Edgeworth and if possible offer them a pipeful.

Once more I say it is a tobacco fit for anyone to smoke.

Yours faithfully,
W. A. Jones

Pipe smokers prefer Edgeworth for various reasons. Some like it because its quality never changes. Some like it because of its flavor. Others smoke it because they can buy it wherever and whenever they like. Perhaps after you try Edgeworth you will discover still another reason for the popularity of this tobacco.



To those who have never tried Edgeworth we make this offer:

Let us send you free samples of Edgeworth so that you may put it to the pipe test. If you like the samples, you'll like Edgeworth wherever and whenever you buy it, for it never changes in quality.

Write your name and address to Larus & Brother Company, 10 S. 21st Street, Richmond, Va.

We'll be grateful for the name and address of your tobacco dealer, too, if you care to add them.

Edgeworth is sold in various sizes to suit the needs and means of all purchasers. Both Edgeworth Plug Slice and Edgeworth Ready-Rubbed are packed in small, pocket-size packages, in handsome humidors holding a pound, and also in several handy in-between sizes.

To Retail Tobacco Merchants: If your jobber cannot supply you with Edgeworth, Larus & Brother Company will gladly send you prepaid by parcel post a one- or two-dozen carton of any size of Edgeworth Plug Slice or Edgeworth Ready-Rubbed for the same price you would pay the jobber.

On your radio—tune in on WRVA, Richmond, Va.—the Edgeworth Station. Wave length (254.1 meters) 1180 kilocycles.

What You Can Make of Stone

How to Cut and Polish Decorative Book Ends and Trays—They Cost Nothing for Materials

By W. E. PYKE
Colorado Agricultural College

THE home workman usually turns to wood as the material for making small articles. It is quite easy, however, to make many useful and unusually decorative articles from stone.

In most communities the raw material is available and needs but a constructive mind and a few simple tools to convert it into beautiful articles for the home.

Ordinary gypsum, especially if it is naturally figured or has been brecciated since its deposition, is easily worked and can be shaped by a novice. Fluorspar, which is used so widely in many industries, is often beautifully banded with exquisite purples, whites and greens. Mexican onyx, which is formed when limestone has been deposited in a cavern, will give effects that are a revelation of beauty; and various chalcedonies, flints, jaspers, and petrified wood can be cut, shaped, and polished.

Mr. Pyke cuts the stone roughly to shape with an ordinary hack saw and finishes the work on a grinding wheel



A book end of brecciated gypsum. The polishing brings out the natural beauty of the figured stone

Another unusually decorative stone book end. Simple shapes such as these are the most effective

It is best for the beginner to start with a stone that is soft enough to be shaped roughly with a hack saw. The final shaping can be done with a carborundum wheel.

In choosing a wheel for this work, one should select a small grinding machine upon which the wheels are easily interchangeable so that several degrees of fineness may be obtained.

The wheels, which need not be expensive, can be purchased at almost any hardware store in various shapes and sizes. It is also possible to obtain a polishing brush to fit the grinding head; this will cut down the handwork in the final finishing process.

Pumice and jeweler's rouge, which is finely ground iron oxide, applied by hand or by means of the polishing brush, will give the final finish.

Articles that the beginner will find easy to shape are book ends, ash trays and pen trays. The shape chosen in each case should be simple rather than fantastic or unusual. The natural beauty of the stone, which is brought out in the polishing, will furnish the decorative effect if the raw material has been carefully selected.

Two designs for book ends are illustrated. These can be executed easily and are especially suitable for the beginner.

It should be remembered that the shaping of stone is much slower on the small scale than woodworking, but it furnishes a desirable outlet of energy in the home workshop, and the reward of the finished article is most gratifying.



Designs for a book end and ash tray

WHEN YOU are trying to open a lower window sash which is badly stuck, remember that you can gain considerable help by making use of the window weights. Pull out both sash cords as far as possible, let go of them simultaneously and push up hard with both hands against the meeting rail of the lower sash. The jerk given by the falling weights will often start the most stubborn sash upward.—L. T. C.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Like to use GOOD *tools?*

Then you need this

400-page Free catalog

GOODELL-PRATT
All Steel Mitre Box—1285. Cannot bend or break, or become inaccurate. Angles more acute than 45° are secured by side attachment. Gauge can be regulated to saw to any desired depth. Equipped with 28 x 5" first quality Back Saw . . $27.50.
Ratchet Bit Brace—7010. 10" sweep. Steel clad head on roller bearings. Head and handle finished with rubber enamel, ebony effect. Chuck sockets and shells of malleable iron; forged steel jaws. Chucks hold all sizes of square shank bits. Beautifully nickeled $3.75
Automatic Drill—185. Mr. Punch. Push, and the tool returns. Drill points carried in handle. Length 10" Beautifully polished and nickeled, including 8 drill points from 1-16 to 11-64" . . $2.75
Two Speed Hand Drill—5½. Black enameled frame. Handle unscrews to hold drills. Takes round shank drills, 0 to 3-8" Steel parts nickeled. 14½" long. Without drills $5.50
Automatic Screwdriver—111. Reversible, for driving or drawing screws. Can be used ratchet or plain. Handle finished in mahogany. Length with blade 19". Including 3 tool steel blades . . $3.10
GOODELL-PRATT
Goodell-Pratt Electric Drill. Sizes from ¼ to 5-8". Light and Heavy Duty, for 110 and 220 A. C. or D. C. Steady drilling doesn't overheat these Drills. Self-oiling bearings require only occasional attention. Vital parts readily accessible. These drills retail from $36.00 to $99.00
Micrometer Caliper—2-R. Graduated to read by 1-1000 from 0 to 1 inch. Ratchet mechanism on the Thimble assures equal pressure, when used by different persons $12.00
Bench Vise—161. Moderately priced. Cut steel feed screw and guide rods insure rigidity. Jaws machined after assembly, so they meet accurately. Steel parts polished, iron parts enameled. 2" jaws, opening 2". Weight 3 3-8 lbs. $2.60
High speed, high power Bench Grinder -485. Handy for bench and household use. Gears are enclosed and packed in grease. High Abrasive Wheel, 5 x 1" Adjustable Work Rest. Finished in red and black enamel, 6½" high above bench . . $10.00
Breast Drill—6. 16" long. Adjustable Breast Plate; Polished Hardwood Handles. Machine-cut Gear Teeth. Two speeds. All-steel Chuck for round shanks 0 to ½" $6.20

Four hundred busy pages, showing the 1500 Good Tools—tools for carpentry, automotive and electrical work—machinists' and builders' tools—in fact, pretty nearly every kind of good tool—for professional and amateur use.

The pages above show only one tool in each line. The catalog shows a complete range of each—65 pages, for instance, of drills alone—hand and automatic drills, breast and chain drills, electric and foot power drills, in every size and capacity.

With this catalog you can select leisurely the tools that will exactly suit your purpose and your pocketbook—then go to your hardware store and buy them.

Write for the catalog—today.

Goodell-Pratt make a complete line of fine tools for carpenters, mechanics and machinists. No better are to be had at any price.

GOODELL-PRATT COMPANY, GREENFIELD, MASS., U. S. A.

MAKERS OF *Toolsmiths* MR. PUNCH

GOODELL-PRATT

1500 GOOD TOOLS

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

4 useful rooms *in place of attic cobwebs*

WHY not *use* your attic? Big panels of Upson Board will quickly build in an extra bathroom, maid's room, play room, or workroom.

Valuable new living space! And at the same time you *insulate*, because an Upson Board lining resists as much cold or heat as 11 thicknesses of ordinary building paper. Saves 20% to 30% in cost of fuel.

One man can apply Upson Board. Little muss or dirt. Use Upson Board for walls, ceilings, partitions—everywhere, round the home, store, or factory. Once up, can't crack or fall. Properly applied, *should never warp*. Ask your Upson lumberman about genuine Blue-Center Upson Board. Or, mail the coupon.

UPSON PROCESSED BOARD

THE UPSON COMPANY
957 Upson Pt., Lockport, N. Y.
Enclosed find 10c for samples, literature, and full size blue print for

.....(Kind of room)

NAME.....

ADDRESS.....

Identify genuine Upson Board by its blue-center edge.

How *to Take Up* Rod Bearings

By RAY F. KUNS

Principal, Automotive Trades School, Cincinnati, O.

CONNECTING rod bearings will fail more often than any of the other bearings of the motor, speaking in general terms and having in mind no make of motor. This is due to the fact that there is such a great variation in the load they carry and the other conditions under which they give service.

After a great deal of service the connecting rod lower bearings will have worn to such an extent that they may give off slight noises or knocks. The piston serves to pull the bearing first to one side of the crank pin and then to the other side of the crank pin, with the result that each time there is a change in direction and the piston is stopped and started, the play in the bearing allows a slight knock.



The cap is removed from the rod bearing, a thin shim is taken out on each side, and then the cap is replaced

Under these circumstances the incipient trouble is remedied by taking up the rod bearings. This is a rather simple task, yet one to be handled carefully. The crank case pan is dropped and then the rod bearing requiring adjustment is located with the throw of the crank for that rod in the down position. The illustration above shows the position for the rod, except that the work is being done in this case with the engine removed from the car.

The actual "taking up" operation consists of dropping the cap from the rod bearing by removing the cotter keys and the castellated nuts from the connecting rod bolts. As the cap comes from the rod, watch the shims carefully. There may be a number of these on each bolt or there may be but one; possibly there is none.

MOST adjustments require the taking out of a single shim on each side of the bearing cap. The shims to be removed are the thinnest ones provided; they ought not be more than .001 in. thick. If one pair is not sufficient, remove another pair and continue until the rod bearing comes up snug on the shaft. If it should be too tight, replace a pair. The setting up of rod bearings until it is impossible to turn the engine over without great effort is no longer considered the best practice. Oil must be allowed to get into the bearing, yet none can do, so until there is clearance. The proper clearance for oil is .001 in. for the splash lubricated bearing and twice that amount for the force fed bearing. These exact limits cannot be obtained in all cases. They are given as the desirable amount and the workman must come as close to them as he can.

Where no shims are provided, the cap face is dressed off with a file or on a sheet of emery cloth lying on a piece of plate glass.

Do not tighten up on the bearing cap bolts and, if you find that the bearing binds, simply back off the nuts a bit to loosen it and call it a job. It isn't. It is trouble in store. Remove the cap and fit thin shims and then draw the cap down on the shims tight. Shims hold the bearing apart and must be gripped tight between the bearing cap and the rod. Place in new cotter keys; don't use the old ones.

Hints on Using Hand Screws for Woodwork

FEW amateur woodworkers, unless they had the benefit of considerable manual training experience at school, make as much use as they might of hand screws, which are especially useful in doing repair work and in gluing up home-made furniture.

To open or close the jaws of a hand screw rapidly, grasp the handles and swing the jaws around and around. When non-adjustable hand screws are used, be sure the jaws are set as nearly parallel as possible, to avoid damaging the screws. A strap wrench made as shown is useful for setting up large hand screws very tight or for loosening a stubborn screw without straining the wrists.—G. A. L.



A simple strap wrench for turning stubborn hand screws, especially of the larger sizes

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Old Briar

TOBACCO

"THE BEST PIPE SMOKE EVER MADE!"

"It came, and is the best tobacco I ever smoked!" Justice———*

Such convincing praise for Old Briar Tobacco from such a pipe smoker means far more to you than anything we can say. Old Briar is bringing back to pipe smokers all of the old peace, contentment, satisfaction and solid comfort of pipe smoking. Vast multitudes—men whose opinions may be divided on a thousand subjects—are united on this wonderful smoking tobacco.

Light up *your* pipe—filled with Old Briar Tobacco. Draw in its ripe fragrance, its full, pleasant aroma. Smoke it awhile. Enjoy its natural tobacco taste, its rich body. Notice how cool it is—and how extra smooth.

Years of scientific knowledge in the art of mellowing and blending and generations of tobacco culture have gone into the production of Old Briar Tobacco. Step by step Old Briar has been developed—step by step perfected.

Of all the pleasures man enjoys, pipe smoking costs about the least.

TO DEALERS: *Old Briar is sold in sealed Pocket Packages at 25c and sealed boxes at 50c, $1.00 and $2.00. If your jobber has not supplied you, write us and we will send you a supply by prepaid Parcel Post at regular Dealer's prices. Every box and package of Old Briar has our unlimited guarantee.*

UNITED STATES TOBACCO COMPANY, RICHMOND, VIRGINIA, U S. A.

*The above unsolicited praise is from a judge who used this coupon ☞

IF YOUR DEALER DOES NOT HAVE OLD BRIAR

Mail this coupon to United States Tobacco Co., Richmond, Va., U. S. A.

SPECIAL OFFER: So many thousands have found so much extra enjoyment in a pipeful of Old Briar, it is a guarantee to you that you, too, will find it is the best tobacco you ever smoked. On receipt of this coupon with your name and address, we will mail you the regular 50c size of Old Briar Tobacco In addition we will send you a 25c package of Old Briar—extra—if you send us your dealer's name. Send no money, but pay the postman only 50c when he delivers the tobacco.



Print Name.....

Address.....

City and State.....

Your Dealer's Name.....

Address.....

If you prefer—send stamps, money order or check with coupon.
Tear out coupon now, while it's handy. P.S. 9-27

Ⓢ This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Cut 6 Times More Metal

At YOUR Hardware Store, you can get the wonderful NEW Atkins Hack Saw Blades of "Silver Steel" for hand use.

Tests show these blades cut SIX times as long, and TWICE as fast, as ordinary hack saw blades. They hold their edge better—cut quicker and easier—save time, money and material.

It pays to be sure the name ATKINS is on the blade. Look for the counter display shown above —*At Your Hardware Store.*

E. C. ATKINS & CO.
Established 1857
428 South Illinois St.
INDIANAPOLIS, U. S. A.

ATKINS SILVER STEEL SAWS

Leading Manufacturers of Highest Grade Saws for Every Use; Saw Tools, Saw Specialties, Plastering Trowels, Machine Knives, Grinding Wheels and Files.

Shelves for a Child's Room

By F. Clarke Hughes

WHAT would delight a small child more than to have for his books and other small belongings a set of hanging shelves which suggest in shape and color a bunny, bird, kitty, clown or fairy? Such shelves are easy to make and form a unique, colorful decoration in the nursery.

Five designs for the end pieces are given in the accompanying illustrations. Other shapes may be devised or copied from toys, and, of course, the size may be whatever the builder chooses.

First make a full size drawing of the chosen design on heavy paper and cut it out for use as a pattern. Trace the outline on soft pine or plywood, either ½ in. or ⅝ in. thick, and cut it out with an ordinary coping saw, or a power jig saw if one is available. Smooth the edges carefully with sandpaper.

"Bunny" shelves. A good color scheme is gray for the body with pink in center of ears, red nose and mouth, and black edges

Next lay out the dadoes or grooves which are to receive the shelves and cut them with a chisel. Be sure not to continue the dadoes entirely through to the front edges as they should not show in the finished work. Stop a little back of the front edges and make the shelves exactly as wide as the grooves are long. A quicker but not so workmanlike a job can be done by omitting the grooves and simply nailing shelves in place.

Perhaps the best finish for the shelves is the new brushing lacquer, which can be obtained in many brilliant colors. Suitable color schemes are suggested in the drawings below.

To hang the shelves make two thin metal hangers about ½ by 1¾ in. These are screwed to back edges of the end pieces at top and engage round head screws or small hooks in wall.



Four more attractive end pieces. The squares will aid you in enlarging the design to any extent desired. Suitable dimensions are 18, 24 or 30 in. high with shelves 10, 12 or 14 in. long

Invisible Springs Keep Loose Windows from Rattling

IN THESE days of poorly seasoned lumber, there is always apt to be some window in the house that rattles when raised for purposes of ventilation. The application of concealed springs, as shown, will hold such a window firmly.

The writer cuts 2 pieces of ¾-in. steel strapping, such as is used for binding heavy packing boxes, each 5 in. long. Two holes are drilled or punched toward one end of each piece, which is then bent as indicated and fastened in place with finishing nails. This method does away with loose wedges.—O. Lovejoy.



Anti-rattlers for sash

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

30 DAYS FREE TRIAL

7 Tube Set
Single Dial Radio

Metrodyne Radio Sets
Are Equipped For
BATTERY or ELECTRIC operation

The Metrodyne
ONLY ONE DIAL TO TUNE

RETAIL PRICE
$75.00
Completely Assembled
Big Discounts to Agents and Dealers

Wonderful offer direct from the factory! The world's greatest radio! A perfect working, single dial control, 7 tube receiver! And just to prove our claims, we will ship it to your home for **30 days' free trial.** Test it under all conditions. Test it for distance, volume and tonal quality—and if you are not convinced that it is the **best single dial set** you ever heard, return it to the factory. We don't want your money unless you are completely satisfied.

Three Year Guarantee

BIG PROFITS TO AGENTS AND DEALERS

Our Agents and Dealers make big money selling Metrodyne Sets. You can work all or part time. Demonstrate the superiority of Metrodynes right in your home. Metrodyne Radios have no competition. Lowest wholesale prices. Demonstrating set on 30 days' free trial. Greatest money-making opportunity. Send coupon, a letter or a postal for our agent's proposition.

Metrodyne Super-Seven Radio

A single dial control, 7 tube, tuned radio frequency set. **Tested and approved by Popular Science Institute of Standards, Popular Radio Laboratory, Radio News Laboratory** and by **America's leading Radio Engineers.** Designed and built by radio experts. Only the highest quality low loss parts are used. Magnificent, two-tone walnut cabinet with beautiful, gilt metal trimmings. Very newest 1928 model, embodying all the latest refinements.

Easiest set to operate. Only one small knob tunes in all stations. The dial is electrically lighted so that you can log stations in the dark. The volume control regulates the reception from a faint whisper to thunderous volume, **1,000 to 3,000 miles on loud speaker!** The Metrodyne Super-Seven is a beautiful and efficient receiver, and we are so sure that you will be delighted with it, that we make this liberal **30 days' free trial offer.** You to be the judge.

6 Tube Set
$48.50
RETAIL PRICE
Completely Assembled

30 Days' Free Trial—3 Year Guarantee

Metrodyne Super-Six

Another triumph in radio. Here's the new 1928 model Metrodyne 6 tube, two dial, long distance tuned radio frequency receiving set. Approved by leading radio engineers of America. Highest grade low loss parts, completely assembled in a beautiful walnut cabinet. Easy to operate. Dials easily logged. Tune in your favorite station on same dial readings every time — no guessing.

Mr. Howard, of Chicago, said: "While five Chicago broadcasting stations were on the air I tuned in seventeen out-of-town stations, including New York and San Francisco, on my loud speaker horn, very loud and clear, as though they were all in Chicago."

We are one of the pioneers of radio. The success of Metrodyne sets is due to our liberal 30 days' free trial offer, which gives you the opportunity of trying before buying. Thousands of Metrodynes have been bought on our liberal free trial basis.

MAIL THIS COUPON or send a postal or letter. Get our proposition before buying a radio. Deal direct with manufacturer—**SAVE MONEY—WRITE NOW!**

MAIL COUPON BELOW

Let us send you proof of Metrodyne quality—our 30 days' free trial offer and 3 year guarantee

Mrs. Wm. Leffingwell, Westfield, N. J., writes: "The Metrodyne Radio I bought of you is a wow! This is as good as any $225 machine I have ever seen."

N. M. Greene, Maywood, Ill., writes: "My time is up and the Metrodyne works fine. I got Havana, Cuba, Oakland, Calif., Denver, Colo., Toronto, Canada, all on the loud speaker."

J. W. Woods, Leadville, Colo., writes: "Received the 7-tube Metrodyne in fine condition. Had it up and working same day received. Was soon listening to Los Angeles, San Diego, Oakland and other California points; also St. Louis, Kansas City and other east and south stations—all coming in fine. Am more than pleased. Sure enjoying it."

We will send you hundreds of similar letters from owners who acclaim the Metrodyne as the greatest radio set in the world. A postal, letter or the coupon brings complete information, testimonials, wholesale prices, and our liberal **30 days' free trial offer.**

METRO ELECTRIC COMPANY
2161-71 N. California Ave., Dept. 51
Chicago, Illinois

Gentlemen:

Send me full particulars about Metrodyne 6 tube and 7 tube sets and your **30 days' free trial offer.**

*Name*_____

*Address*_____

If you are interested in AGENT'S proposition, place an "X" in the square ➡ ☐

METRO ELECTRIC COMPANY

2161-71 N. California Ave. • *Dept. 51* • Chicago, Illinois

Ⓢ **This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS.** **See page 6.**

New Model
Pocket Ben

Hundreds of thousands of men and boys have put their "O. K." on the New Model Pocket Ben.

Good looks, faithful service and low price —it is everything you need in a watch.

Sold everywhere for $1.50. With luminous night-and-day dial $2.25.

WESTERN CLOCK COMPANY
La Salle, Illinois

A Cube for You to Whittle

It's a Queer Puzzle Made of Interlocking Pieces

By Arthur L. Smith

CUBICAL block puzzles are made of blocks of various sizes and shapes. In this article one is offered that consists entirely of blocks ½ in. square and 2 in. long (Fig. 1). Many readers already may have whittled puzzles of this character in other ways; this article merely points out one way of doing it and is presented as a suggestion rather than the last word on the subject.

Twenty blocks (Fig. 2) are perhaps the fewest number which can be employed to bind all together compactly. The cuts are all ¼ in. deep, ¼ or ½ in. wide, and ¼, ½ or 1½ in. long. The distance of the cuts from the ends is either ¼ or ½ in. Larger blocks may be used if the same proportions are observed.



FIG. 1

Each block is ½ by ½ by 2 in.; the cuts are ¼ in. deep, ¼ or ½ in. wide, ¼, ½ or 1½ in. long, and begin ¼ or ½ in. from ends

The illustrations show the character of the cuts more clearly than can be described. Two views each of L and M are given in Fig. 1. The ½ in. square cuts in H and I are larger than necessary and they may be cut on a bevel instead as indicated by the dotted line in the illustration of H. The square cut may add something to the difficulty of the solution since there are many ways in which other blocks may be fitted into it.

Perhaps neater work can be done if all blocks except F are cut slightly longer than 2 in. All measurements then are taken from the center. When the puzzle is assembled the cube can be finished up true with respect to the ends. The F block must be cut exactly to size, for if the square heads are thicker than ¼ in. the blocks cannot be assembled.

If numerical values are assigned to the blocks as described in a former article (May, 1927, issue) it will be found that they total 134 or 6 more little cubes than the cubical contents of 4 solid blocks. Hence, there are internal spaces in the cube amounting to six ¼-in. cubes. These are necessary to allow of assembling.

The first step in assembling is to arrange M K J and L with D and E protruding through the mortised holes as shown in Figs. 4 and 5. Then the other block E is laid in position (Fig. 6), and another tier of blocks KBCJ is built on (Fig. 7). It will be necessary now to arrange the top tier LJKM on this combination (Fig. 8) and raise them so that the block F can be fitted (Fig. 9).

Some manipulation is required to place the H and I blocks (Fig. 10). The H block is slid through the vacant tier so that the projecting head of F will pass through the ¼-in. slot. After it has been brought through as far as the D block will allow, it can be brought around and slid forward so as to occupy the position shown in Fig. 11. The same process is followed with block I. No difficulty should be experienced with the remaining G and A blocks (Fig. 3). G is inserted through the A hole first and slid into place.



Figure 2 shows the assembled puzzle and Fig. 3 is lettered to identify the blocks, each of which is cut as shown in Fig. 1 above. Figures 4 and 5 show the first, Fig. 6 the second step



Another tier of blocks, KBCJ, is built as in Fig. 7; then the top layer, LJKM, is added (Fig. 8) and F placed as in Fig. 9. H and I are added (Figs. 10 and 11) and finally G and A are inserted

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.



Electrol is listed as standard by the Underwriters' Laboratories, and bears their label. Approved by the New York City Board of Standards and Appeals —and by the Commonwealth of Massachusetts Department of Public Safety.

Small Homes or Large— there is an Electrol for All

Electrol engineering experts who produced the outstandingly successful larger Electrol have created the New Model TJ, for homes of average size and smaller.

Now—regardless of the size of homes, from the smallest cottage to the largest mansion, apartment, club, school, library, church or office building—there is an Electrol that will best meet the heating requirements and give uninterrupted service with maximum economy.

The new Electrol, Model TJ, is, of course, *All Electric* and *Entirely Automatic*. Like all Electrol burners, it has the famous Electrol *Master Control* and embodies the proved scientific principles of Mechanical Fuel Atomization and Automatic Electric Ignition. The same high quality materials and workmanship. The same mechanical and operating parts.

During eight years of fine burner manufacture Electrol oil burners have been heating thousands of homes throughout the country. Electrol is the choice of business men and engineers of international reputation. Specified by well-known architects and heating engineers. Write for details of the new Electrol, Model TJ, and other models.

New Model TJ
$395
COMPLETELY INSTALLED
Tank Equipment and Furnace or Boiler Auxiliaries Extra

ELECTROL INC. of Missouri
180 Dorcas St., St. Louis, U. S. A.

ELECTROL

The OIL BURNER with *The Master Control*

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

The "Clock" Helps Hold 'Em To It!

How lost you would feel in controlling your car without an instrument to "clock" your operating speed!

Just so in running *production* machinery:—there's no controlling the rate of operation without a COUNTER to register production.

You can develop the highest production-rate in a machine (*and* its operator) by "clocking." *Be guided* by the production-readings on a

Veeder

The Set-Back Rotary Ratchet Counter below is for machines such as presses and metal-stamping machines where a *reciprocating* movement indicates an operation.



Registers one for each throw of the lever and sets back to zero from any figure by turning knob once round. Supplied with from four to ten figure-wheels, as required. Price with four figures, as illustrated, $11.50 subject to discount. (Cut *less than ½ size.*) Set back *Revolution* Counter of similar model, $10.00 (list). Smaller counters from $2.00 up.

The "Form UM" Magnetic Counter below counts operations or units of output, from any distance that wires connect with machines. Can be placed over desk or on convenient Counter-Board.

Cut ½ Size.

Mechanical contacts on your machine make and break the electrical circuit which operates the counter. The electro-magnetic drive can get its current from your regular lighting circuit (110 volts), or from storage battery.

Write us about that counting problem of yours; ask for the counter catalogue anyway.

The Veeder Mfg. Co.
44 Sargeant St., Hartford, Conn.

Toy Auto Built for Speed

By CARL G. ERICH

MY BOY drives the largest and fastest toy auto in our town, yet its cost was low because I built it mainly from odds and ends. Any reasonable ingenious handy man can make one like it.

Painted orange, with black and white trimmings, this auto would delight any small boy

Strips of white pine 1¼ by 2 in. were screwed together to form the main frame. The radiator frame was cut from 1¼ in. thick pine and heavy, square mesh wire cloth was fastened on the inside.

The back of the seat was built up with wood ribs; thin tin was bent around the outside and upholstery fastened on the inside. The seat cushion was made by upholstering a ½-in. board and laying it in place.

The doors were made of ½-in. white pine, covered with tin outside and cardboard inside. Cupboard catches were attached before the doors were covered.

The steering wheel was cut from a 1-in. black walnut board 8 in. square. To form the spider, a small gas pipe was split and spread out.

For the windshield, a wooden frame was made, the glass being held in with a beading of wood. An instrument board was provided for the light switch and a watch.

Two old bicycle rear-wheel guards were cut and bent to form the fenders. In the process they were flattened somewhat and given a more realistic appearance. Iron brackets underneath the frame support the steps.

The lamps are bicycle headlights wired to a switch on the dash. Two dry cells for the lights are clamped underneath the hood. The rubber-tired ball-bearing wheels are of a type that can be purchased from large mail order houses and some hardware, toy, and manual training supply houses.

The crank hangers are about 7 in. long. The cranks on the rear axle are bent so as to give about a 5-in. stroke. The pedals are 3-in. blocks of hardwood with holes bored lengthwise in them. An inspection of any commercial toy with this type of drive will give a clear idea of the construction to those not already familiar with it.

The bumpers were made from the bows of an old baby buggy top. In place of a tool box, a turtleback, like that of a roadster, might be built, if preferred.

I painted the car orange on the body, except the top of the hood, which is white. The radiator was given several coats of aluminum, the molding around the top edge and the windshield frame were painted black and the fenders, axles and wheels, orange. The instrument board and steering wheel were varnished.

Dusty Gray Finish for Oak

A GRAY antique-looking finish for oak can be had by covering the wood with two coats of a five-percent solution of silver nitrate, followed by a solution of hydrochloric acid. Set aside to dry in a dark place, then neutralize the acid with a coat of ammonia, which should be applied out of doors, as the fumes are very powerful. Do not touch the work with your fingers during the process, for the marks may show. Finish with well-rubbed coats of paste floor wax.—L. D. C.



Side, front and top views of the toy and diagrams of the main frame and wiring. The dimensions may be modified to suit the available materials and the age of the boy who is to drive the machine

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

don't fool yourself



It may get you "fired"

More and more, employers are insisting that people about them be not only neat, but *inoffensive.*

Halitosis (unpleasant breath) is responsible for many a good man and woman being "let out."

Nearly everyone is halitoxic at one time or another and since you, yourself, cannot tell when you have it—and friends *won't* tell—the safe thing to do is to use Listerine every day, especially before personal contacts.

1/3 Had Halitosis

68 hairdressers state that about every third woman, many of them from the wealthy classes, is halitoxic. Who should know better than they?
Face to face evidence

Immediately it destroys unpleasant odors arising from teeth and gums—the most common source of halitosis. And the antiseptic essential oils combat the action of bacteria in the mouth. Better keep a bottle handy in home and office, so that you may always be sure. Lambert Pharmacal Company, St. Louis, U. S. A.

LISTERINE

—the safe antiseptic

FALL IN LINE!
Millions are switching to Listerine Tooth Paste because it cleans teeth whiter and in quicker time than ever before. We'll wager you'll like it. Large tube 25c.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

"I Want A Suit Of Clothes"



The man who simply asks for a suit of clothes and takes what is offered him may find himself dressed in golf togs when he wants to go to a wedding.

Well dressed men, like experienced tool users, specify what they want—and get it.

When the experienced tool user specifies TRIMO, he gets a pipe wrench with a pressed steel frame that never breaks; a wrench with renewable jaws which can be replaced at reasonable cost; a nut guard which keeps the wrench from being knocked out of adjustment.

Hardware dealers can supply you. Always specify TRIMO.

TRIMONT MFG. CO.
Roxbury (Boston), Mass.
America's Leading Wrench Makers for Nearly Forty Years

A Cabinet for Your Curios

How to Build a Hanging Case of Unusual Beauty



THIS wall cabinet, which is intended to hang over a sideboard, between two windows, or on any suitable wall space, may be used for china, curios, or scientific collections or instruments. If the sides and shelf were made of wood, it might even be used as a hanging bookcase.

The pleasing proportions of the cabinet, which was designed by Art Director Doskow of POPULAR SCIENCE MONTHLY, are not the result of chance. They were worked out scientifically upon the basis of the so-called Hambidge theory of dynamic symmetry. That is a remarkable system of *(Continued on page 108)*



Front and end views of the wall cabinet, the method of assembly, and details of the members of side frames, door rails and door frets, and the ornamental features at top and bottom

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.



Ice Cream Plants insure Quality by using *Tycos*-the Sixth Sense

WHETHER manufacturing structural steel, ice cream or other products that go through heat treating processes, you can eliminate loss by spoilage by using *Tycos* Temperature Instruments for Indicating, Recording and Controlling heat.

The adaptability of *Tycos* Instruments in manufacturing is emphasized by the Chief Engineer of one of the largest ice cream companies of the Middle West. On his pasteurizing tanks he has to keep the temperature at exactly 155 degrees. If the temperature goes below 155 degrees, bacteria would not be destroyed—if higher, 500 gallons of cream would be scorched and spoiled. *Tycos* Instruments insure his knowing every minute of the day that the temperature of his tanks is 155 degrees.

In converting the heated cream to frozen ice cream, *Tycos* Instruments are installed on the outside of the brick-walled hardening rooms and the fruit preserving rooms. By making this unique installation the Chief Engineer eliminates the necessity of his men entering these extremely cold rooms, where the temperatures range from 30 degrees above to 15 degrees below zero.

The same economies and efficiencies of manufacturing that this manufacturer has applied in making ice cream are available to every manufacturer using heat treating processes in his plant. Whatever your needs in the Indicating, Recording or Controlling of heat there is a *Tycos* Instrument to serve you. Write us for literature on any instrument or type of instrument and it will be sent promptly. Or, if you prefer, our engineers will consult with you on the application of the *Tycos* Sixth Sense in your plant.

Tycos for the Home

***Tycos** Office Thermometers*
An aid in promoting human efficiency.

***Tycos** Bath Thermometers*
To enable you to get the most good from your bath.

***Taylor** Home Set*
Bake Oven Thermometer, Candy Thermometer, Sugar Meter. The secret of accurate results in Cooking.

***Tycos** Wall Thermometers*
To help you maintain a temperature in your house conducive to good health.

***Taylor** Quality Compasses*
To show you the right way in unfamiliar country.

***Tycos** Fever Thermometers*
A necessity in every home.

***Tycos** Stormoguide*
Forecasts the weather twenty-four hours ahead with dependable accuracy.

***Tycos** Hygrometer*
To enable you to keep the humidity of the atmosphere in your home correct at all times.

Tycos for the Medical Profession

***Tycos** Sphygmomanometer, Pocket and Office types.*

***Tycos** Urinalysis Glassware.*

***Tycos** Fever Thermometers.*

Your dealer will show them to you. Ask us, on a postal, for booklets on any of the above.

Taylor Instrument Companies

Main Office and Factory
ROCHESTER, N. Y. - - U.S.A.
Canadian Plant: *Tycos* BUILDING, TORONTO
SHORT & MASON, Ltd. Manufacturing Distributors in Great Britain

THE ~ SIXTH ~ SENSE ~ OF ~ INDUSTRY

Tycos Temperature Instruments

INDICATING ~ RECORDING ~ CONTROLLING

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

ASK . . . ANY . . . RADIO . . . ENGINEER

The "Mountie" isn't lonely any more

WHEN the supply ship steams south from the last outpost of civilization in September, not to return until the following July, loneliness will never again beset the lives of the Royal Canadian Mounted Police who patrol that vast, wild area.

Radio is now brightening the long winter nights with music, special programs, messages and greetings from their "home folks."

And in the receiving sets of the "Mounties" is the best equipment obtainable. The batteries they use *must* be dependable. They *must* serve until new supplies are brought in a year later.

Ask any Radio Engineer

BURGESS BATTERY COMPANY
GENERAL SALES OFFICE: CHICAGO
Canadian Factories and Offices:
Niagara Falls and Winnipeg

BURGESS
RADIO BATTERIES

Adding a Room to Your House

How to Utilize Space in the Basement if It Is Reasonably Large and Damp Proof

By BRUCE BRIGHTON

This remarkably attractive basement room was recently fitted up in the Detroit home of a friend of Mr. Brighton's. The color scheme is based upon yellow walls, sage green woodwork, and tile red floor

"I HAVE a surprise for you!" exclaimed Mrs. Andrews before we had a chance to settle ourselves in the comfortable wicker rockers on the porch. "We have been doing some decorating. Come inside and let me show you."

Mrs. Andrews led the way through the hall and opened the basement door. The stairway had been newly painted—the walls a cheery, sunny yellow and the woodwork and stairs a sage green. There were rubber treads down the middle of the steps to protect the finish.

We followed her down and at the bottom were astonished to find ourselves in a really wonderful room. And once it had been a commonplace and unattractive basement! It had been exactly the sort found in the average home—a housing place for the furnace, fruit cellar and laundry tubs. But this basement had come into its own.

The room, which was about 14 by 24 ft., had yellow walls, sage green woodwork, an attractive fireplace, window drapes in green and red figured cretonne with curtain poles painted red to match; two handmade benches with wrought iron ends and wooden seats and backs painted in sage green and red, one on each side of the fireplace; a radio cabinet in sage green trimmed with red and a bridge lamp to match. Upon the floor, which was painted in tile red, were several rugs.

After we had congratulated Mrs. Andrews, we asked how she had managed to convert the basement into so bright and comfortable a room.

"I'll tell you the whole thing," she began. "First we partitioned off the room from the remainder of the basement by erecting two-by-four studding, covered with wallboard on the inside, with a doorway out to the furnace and laundry tubs. The ceiling also was lined with wallboard. This proved more of a job than we anticipated, but there was nothing really difficult about it beyond the figuring we had to do to get everything square and straight.

"Next came the fireplace. We used to have many cobblestones in this neighborhood and it so happened that we had stored some in a corner of the basement. We had a mason come in and build the fireplace with these stones. The only other work we had done for us was the making of the benches.

"Then we started the painting and decorating. We gave the wallboard surfaces a coat of flat wall paint mixed with an equal part of wall size, using ivory white for the ceiling and cream for the side walls. A couple of days later, when this coat had dried thoroughly, we filled all holes and cracks with a prepared crack filler. We could, of course, have nailed strips of molding over the joints, but we did not want a paneled effect. Next we gave the wallboard two coats of flat wall paint just as it came in the can. We found that by using zigzag strokes the brush marks were less apt to show."

"What surprises me," I interrupted, "is that you were able to make such a good job of painting the concrete blocks of the foundation on the other three walls."

"It *was* hard to get the surface in shape," Mrs. Andrews admitted. "We used a stiff broom and where there seemed to be some salts or (*Continued on page 116*)

Ⓘ This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

New!

You don't have to be water boy to this battery charger

The Thordarson Battery Charger R-175 employs the Raytheon Rectifying Cartridge guaranteed as above.

3555

THORDARSON
BATTERY CHARGER R-175

Radically new—sound in principle—proven in performance.

The Thordarson Battery Charger makes its bow as a welcome relief to the army of butlers to thirsty battery chargers.

Dry—As dry as they make 'em. In fact the rectifying element is contained in a moisture-proof cartridge.

Silent—No vibrating parts. Current is rectified through a patented electro-chemical process.

Safe—There is no hazard to rugs or woodwork for there is no acid to spill. The tubes of the set are safe even if turned on when charger is in operation.

Compact—Fits into battery compartment easily. Only 2¾" wide, 5¾" long and 4¾" high overall.

Efficient—This charger is always ready for service. No overhauling required. Rectifying element can be replaced in thirty seconds.

Guaranteed—The rectifying unit is guaranteed for 1000 hours full load operation, or approximately one year's normal service. The Transformer will last indefinitely.

Charging Rate—2 Amperes

For Sale at Good Dealers Everywhere or Direct from Factory

PRICE COMPLETE $12.50

THORDARSON ELECTRIC MANUFACTURING CO.
Transformer Specialists Since 1895
WORLD'S OLDEST AND LARGEST EXCLUSIVE TRANSFORMER MAKERS
Huron and Kingsbury Streets — Chicago, Ill. U.S.A.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

After 9 years of Leadership

Nokol brings you final perfection in oil heat

WE realize that "final perfection" is a lot to say for anything. But have you seen the new silent Nokol in action? Have you talked to any of the thousands who invested more than $5,000,000 in this oil burner within 90 days after it was first announced?

They will tell you that with the new silent Nokol a new chapter has been written in the history of oil heat; that with the elimination of the usual oil burning noises, Nokol has removed the last remaining objection; that those who have been waiting "for oil heat to be perfected" need not hold back another day. It's here.

But the elimination of noise isn't the only advantage offered by the new silent Nokol. Efficient as Nokol has always been, there is even a further improvement in combustion. *Thirty seconds* is all it takes to reach the 1600° required to burn oil most efficiently. No time wasted "heating up," no waste of fuel; lowest cost full automatic oil heat known.

Don't go on year after year denying your family automatic oil heat, the greatest home convenience of all. If you only knew what it would mean in comfort, in health, in general satisfaction for all, you'd no more do without Nokol than you would your automobile, the telephone, or electric light. Mail the coupon for interesting booklet and details of our attractive new budget plan.

NEW *Silent* NO COAL NOKOL

REG. U.S. PAT. OFF.

AUTOMATIC OIL HEATING FOR HOMES

FREE—NEW BOOK

AMERICAN NOKOL COMPANY
4180 Shubert Ave., Chicago
Please send me your new book on OIL HEAT FOR HOMES.

Name.....

Address.....

City..... State.....

An Aquarium *at* Low Cost

How to Assemble a Goldfish Tank of Wood and Window Glass

By HI SIBLEY

A neatly made, well kept aquarium adds a bit of life and color to any living room

GOLDFISH aquariums, like house plants, bring a colorful and refreshing bit of outdoor life into our homes. No wonder they are so popular!

The advantag of the aquarium illustrated is that it can be made for about one third the cost of those of equal capacity on sale in pet stock stores. Besides, one has the joy of creative work in making it.

For the base board use a clear piece of dressed wood of tough texture that is not likely to split, and screw two substantial cross cleats underneath. A short length of ⅜-in. brass tubing is driven into a hole bored in one corner of the bottom and a plug made to fit.

For the uprights and sills, use clear, hardwood pieces ⅞ in. square. In my own aquarium the base is 1 by 12½ by 20 in., the four uprights are 15 in. long, two of the sills are 10 in., and two 18 in.

If possible, have the lumber company or sawmill cut grooves in two sides of the four uprights, and one side of the sills. These grooves should be just large enough to receive the thickness of glass you intend to use, either double-strength window glass or plate glass.

The glass should be cut to leave about 1/16 in. clearance between the bottoms of the grooves in the upright wooden members.



Vertical section through one end of the aquarium and details of corner construction

The top strips, which are ⅜ by 1⅛ and ⅜ by ⅜ in., are put on after all the glass has been set. After painting and varnishing, use copper strips to tie the corners together.

It is advisable to varnish the inside of the grooves and set the glass before the varnish dries. An agreeable color for painting the frame is lettuce green. Two coats should be given. Paint close to the glass so that the paint will work into all crevices. Any paint which gets on the glass can be scraped off with a safety razor blade. When thoroughly dry, give all painted portions three coats of spar varnish, allowing plenty of time between for drying.

Now lay a pane of glass on the bottom, having first cut one corner away where the drain plug is placed. Around the edges and at the exposed corner, cover the wood with tar, heated until it is about the consistency of putty. It is not necessary to paint this tar; the sand in the bottom of the aquarium will cover it up.

AFTER everything is thoroughly dry, fill the tank with water two or three times and drain off; fill again and let stand twenty-four hours and drain. Now the aquarium is ready for sand, rocks and plants, *but not for fish;* at least that has been my own experience. Wait a week or so after the plants are installed.

For variety, you can include a small turtle, if you don't mind the plants being sheared off and the fishes' tails scalloped. A small schooner, the hull of which was whittled from a piece of wood 1 by 1½ by 4¾ in., is anchored in the center of my aquarium for the turtle to bask on and from which to "speak" for his meals. Turtles are readily tamed by feeding with small bits of raw beef on a broomstraw.

Select your fish with a view to variety and you will have agreeable entertainment. Name them to suit their appearance and temperament, which you will find varies as much as in domesticated mammals.

The water need be changed only once a week, or at longer intervals.



Counterphase
6-35 Chassis

Your Next Set

What will it cost? How will you decide?

B-T have never built a radio product that was not an outstanding success. They believe this new COUNTERPHASE SIX will prove to the greatest number the most satisfying set they have ever built.



B-T B-Power Unit

The B-T B-Power Unit was designed to eliminate "guesswork" in operation. It has no knobs to turn, no adjustments to make after installation.

Its year and a half of success proves it had the right idea behind it,—although it was the pioneer of its type. This year we believe will see this type displace all others. See Coupon—

Bremer-Tully Say:—

"Here's the best set you can buy for the least it's wise to pay."

B-T build sets for more money, and by leaving out enough could build this one for less. Any manufacturer must decide how high he can go and still find a market, or how little he can put into a product and still make a sale.

B-T believe this is a remarkable set,—and that its excellent selectivity, tone and ease of operation will surprise you.

Go to any B-T dealer and listen to a B-T speaker with this new Counterphase and we're sure you will come away praising them both.

The same set is available in a table model as well as a console, with or without a speaker.

Hundreds of dealers have found that the customer who is "ready for a better set" turns to the B-T Counterphase.

Here's a model good for either first or second choice. If you don't know the B-T Line send for complete literature. The entire B-T history is a record of one success after another.



Counterphase 6-35
Price $110.00

COUPON

Please send me name of nearest authorized B-T dealer and complete literature on B-T products, particularly the new B-T Six Receiver and B-Power Unit.

Name.....

Address.....

Bremer Tully Manufacturing Company

520 So. Canal Street CHICAGO, ILL.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Have you a Wet Cellar?



Dampness and flooding from ground water getting in is easily stopped by filling the cracks and painting over the porous spots in concrete or brick walls and floor with

SMOOTH-ON NO. 7

—the only effective waterproofing material that can be applied *from inside* and to *wet* or *dry* surface.

Excellent also for waterproofing boiler pits, cisterns, tanks, ponds, wash-room, garage, and stable floors, etc. About 25 lbs. required for each 100 sq. ft. of surface and you can do the work yourself.

SMOOTH-ON NO. 1

is the good old standby for stopping leaks in steam, water, gas, oil, or stove pipes; mending cracks, breaks or leaks in furnaces and boilers, radiators, tanks, sinks, pots, and pails, making loose handles tight on umbrellas, knives, hammers, brushes, drawers, etc.; tightening loose screws, hooks, locks, door knobs, etc. Use it on the automobile for stopping leaks in radiator, hose connections, gas tank, gas, oil and exhaust lines, keeping lubricators, hub caps and nuts from loosening and falling off, etc.

The Free Smooth-On Repair Book will show you how an astonishing number of repairs are easy to make, and by doing the work yourself you make big savings. Mail the coupon for a free copy.

Write for FREE BOOK

Get Smooth-On No. 7 in 1 or 5-lb. can, or 25, 50 or 100-lb. keg and Smooth-On No. 1 in 7-oz. or 1 or 5-lb. can. At any hardware store, or if necessary from us direct.

Do it with SMOOTH-ON

SMOOTH-ON MFG. CO., Dept. 58,
574 Communipaw Ave., Jersey City, N. J.
Please send the free Smooth-On Repair Book.

Name.....

Address.....

9-27.....

Return this coupon for a FREE copy of Booklet

Campcraft for Everyone

Making Chairs and Tables—Fishing Tackle Box—Quaint Knocker—Pine-Cone Parrot—Sawbuck

CAMPERS who are able to cut their own oak, hickory or other hardwood poles will find the making of a rustic chair like that illustrated below an interesting project.

If the splints for the seat cannot be purchased locally, wide cane or flat rattan may be used instead, or the seat may be woven with rush, fiber, leather



Substantial and decorative camp chair made of hardwood poles with a woven splint seat

thongs, heavy, narrow webbing, or any other suitable material.

It is always an advantage, of course, in making furniture of this type, to cut the poles in the late fall so that the bark will not peel. If poles with the necessary curves cannot be found, the wood may be bent while green and put away to season.

Assemble the parts with tenons made as shown at A, and glue well. If splints are used for the seat, wet them thoroughly and begin at a corner, as shown at B.

WHEN much firewood has to be sawed up in camp, a sawbuck is essential. One may be made quickly by pointing and notching four short, heavy poles as shown, and driving them firmly into the ground. The joint should be bound with wire or rope.



AN AMUSING novelty for a camper to make in his spare time is the rustic knocker illustrated. The back is a slab sawed diagonally from a white birch or other log. One side is planed, if a plane is available, or else scraped smooth with a jackknife or a bit of glass. The lettering is carved in with the point of a knife, burned in, or painted on, as preferred. A suitable branch is chosen for the striker and mounted as shown so that it will swing.



Rustic knocker

MANY attractive novelties may be made from materials the camper can find all about him. A small sized pine cone, for example, will form the body for a colorful and decorative little parrot.

To the stem end glue an acorn cup or something similar, as shown. Cut the



This tiny parrot with its gay feathers is an amusing and colorful novelty for camp or home

beak from wood, cardboard, or gasket rubber, and glue it in place.

The wire ring represents both perch and feet. Bent as shown, the loose ends are fastened to the cone with a drop of sealing wax or other adhesive. A few colored feathers complete the model. Beak, eye and ring are painted, but not the cone.

At home, the parrot may be hung by means of a silk cord from a window shade, lighting fixture, or other support. —F. CLARKE HUGHES.

HOW often have you wished you had extra tables and chairs for the use of unexpected camp guests? It is easy enough, of course, to purchase various types of folding tables and chairs, if there is a camping equipment store near by, but it is much more fun to make them.

The folding table illustrated on the opposite page has a top of ⅝-in. matched boards, preferably glued together. The wood should be reasonably hard so as to hold the screws. (*Continued on page 99*)

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Campcraft for Everyone

(Continued from page 98)



Side and end views of a light table and underneath view of top when legs are folded

Cleats ½ by 2½ by 23½ in. are fastened under the top with 1-in. No. 9 screws.

Make four legs as shown and two rails ⅞ by 3 by 21 in. and assemble with 1½-in. No. 10 screws and glue. Fasten legs to table with 3-in. strap hinges, using ⅝-in. No. 8 screws. Fasten three blocks A, B, and C, ½ by 3 by 6 in., with glue and 1-in. No. 9 screws. Make spring D of hardwood, 5/16 by 3 by 36 in., and fasten it in the center with one 1¼-in. No. 14 round-headed screw and washer.

When making folding camp stools, you will find that ash, oak, maple or red birch



A sturdy folding camp stool for the outdoor man who never buys anything he can make

are better than the softer woods. A good method of fastening the pins or tenons is to elongate each hole a trifle with a round file, make a cut with a thin saw in each pin and, when the joint is together, drive a wedge to expand the pin. Use glue except in the joints which have to turn. Fasten on a seat of stout canvas, saw off the legs at the correct angle, and finish with paint or varnish.

TWO cigar boxes may be hinged together and fitted up as shown below to make a small but convenient tackle box for the fisherman who has to improvise his equipment on short notice. Scrape and sandpaper the exterior and apply dark green or black brushing lacquer.



How two cigar boxes may be hinged together and partitioned to hold fishing tackle



The body of the "Yankee" Vise with the work in it, is carried to the drill press.

The work is locked in the "Yankee" Vise, at the bench, and center-punched.

Hardened steel block, with V-shaped grooves, holds round or irregular shapes.

The Handiest Vise in the World

Even if you have other vises, you need this "Yankee," because you can do work with it that is impossible with any other—and do it with speed, accuracy and ease.

Not only has a swivel base so you can turn it around in any position, but detaches from its base. You don't have to remove work from vise until entire job is completed—simply lift vise, work and all, off base, and carry to drill press, milling machine, etc.

Sides, ends, bottom and top are machined true. Work is kept in perfect alignment at all times. Cam-throw lever locks vise in any position. You can get the size most convenient for your work.

No. 1994—Jaws open 4 in.
No. 1993—Jaws open 3⅛ in.
No. 1992—Jaws open 1⅝ in.
No. 1991—Jaws open 1½ in.

Some other "Yankee" Tools are: Automatic Feed Bench Drills, Ratchet Breast, Hand and Chain Drills. Ratchet Tap Wrenches. Ratchet Bit Braces. Automatic Push Drills. Plain Screw-drivers. Spiral and Ratchet Screw-drivers, etc.

FREE
New "Yankee" Tool Book

This interesting little book is for all lovers of fine tools. It tells just what you want to know about all the famous "Yankee" Tools for making work easier and quicker. Write for it.

Dealers Everywhere Sell "Yankee" Tools

"Yankee" on the tool you buy means the utmost in quality, efficiency and durability

NORTH BROS. MFG. CO., Philadelphia, U.S.A.

"YANKEE" TOOLS

Make Better Mechanics

Does work of 2 tools!

$2

At all leading hardware dealers. Or write us.

This perfectly balanced 1-pound hammer is made of tool steel. It has chisel-edged claws, without altering the claw feature. It has two small claws right and left to reach close corners next to wall. The head is correctly balanced making it possible to remove 10's at one pull. Write for fully illustrated folder.

Chisel-Edge Claw Hammer Co.
H. A. Ayvad, Hoboken, N. J., Dept. E

CHISEL-EDGE-CLAW HAMMER

The Old Reliable Credit Jewelers **LOFTIS BROS. & CO.** Dept. D-871 108 N. State St. Chicago Ill.

Genuine Diamonds Guaranteed

Diamonds

CASH OR CREDIT

Diamonds Direct From the Importer!

Thousands of customers in every state in the Union make big savings by buying our Diamonds. Our 69-year-old reputation is your assurance of getting more and better value. Our Diamonds are beautiful, blue-white gems of bewitching color and brilliance set in magnificently engraved mountings of solid 18-k white gold.

Satisfaction guaranteed, or money back. Goods sent for your free examination on request. Credit terms: Pay one-tenth down; balance weekly, semi-monthly, or monthly at your convenience. All goods delivered on first payment.

No. 849 $100 $2.50 a wk.

No. 852 $37.50 $1.00 a wk.

No. 850 $125 $3.25 a wk.

No. 847 $150 $3.75 a wk.

Send for Free Catalog

Big 132-page book, illustrating our Diamonds, Watches, Jewelry, Silverware, and gift articles for all occasions, sent absolutely free. Write today.

No. 855 Ladies' Wrist Watch Solid 14-k white gold case, engraved, fancy wing ends, 15-Jewel movement, guaranteed, $2.50 down . . . $2.00 a month

19-Jewel Adjusted Waltham No. 646 — 14-k white gold filled; assorted patterns $42.50 $4.25 down and $1.00 a week

Railroad Watches — Guaranteed to Pass Inspection

HAMILTON NO. 992. 21 Jewels, Adjusted to 5 Positions. Gold filled 25-Year Quality Case . . . $55

ELGIN'S LATEST RAYMOND. 21 Jewels, 6 Adjustments. Runs 40 hours one winding. Gold filled 30-Yr. Gl. Case $55

ILLINOIS "BUNN SPECIAL." 21 Jewels. Adjusted to 6 Positions. Gold filled 25-Yr. Gl. Case. 60 hrs. 1 winding . . . $50

Wedding Rings

No. 836—The "Elite" $7.50 solid 18-k white gold Set with 3 Diamonds, $22.50; 5 Diamonds, $32.50; 7 Diamonds, $42.50; 9 Diamonds, $52.50; 12 Diamonds, $67.50 All platinum, $85. With 3 Diamonds, $50; 5 Diamonds, $70; 7 Diamonds, $90; 9 Diamonds, $100; circled by Diamonds, $200

Credit at Cash Prices

My Motorized Shop Cost $20

(*Continued from page 76*)

follows: A nut is run on the bolt so that it will be inside the T, and the two lock nuts and washers are tightened so that the bolt will be held in the correct position. Melted lead, babbitt, or type metal is then poured through the nipple into the T, so that the bolt is completely imbedded. Powdered graphite, chalk or similar material rubbed into the bolt threads beforehand will allow the bolt to turn easier after the metal has cooled. The assembly is mounted on a hardwood block. It is held to the angle iron bed by a small iron plate and two bolts, which may be loosened for adjusting.



An old plane bit, because of its slot, is an excellent base for the lathe tool rest

The construction of the tool rest is shown clearly in one of the photographs. An old plane bit, a section of pipe with floor plate to fit, a large bolt and nut,



A pointed bolt forms the tail spindle of the lathe



The assembled lathe. The live center is a heavy wood screw held in the drill chuck

a portion of an automobile inner tube valve, an iron rod, and a piece of strap steel are needed. A heavy wood screw, with head removed, is inserted in the drill chuck, and the work to be turned is screwed on. This holds even large pieces.

A sanding disk may be made from hardwood, drilled so that it can be screwed on the polishing end of the spindle, and covered with sandpaper or emery cloth. A simpler method is to cut a disk of sandpaper the size of the grinding wheel and clamp the paper and wheel together by means of the lock nuts.

Simple Straw Instrument Measures Humidity

By H. D. Tiemann

STRAW will make a simple but remarkably sensitive and accurate humidity indicator or hygrometer.

Split lengthwise into about six portions a 4 or 5 in. length of smooth, clean straw, preferably wheat, although any grain will do. This can be done most readily by crushing the straw flat on a table. If the straw is dry, the inner portion is in a state of tension with respect to the outer surface so that the split pieces will tend to curl with the concave side toward the inner or pithy portion of the straw.

Near one end of a smooth board about 4 by 6 in., screw a section of a spool and insert one end of the straw in a narrow slot on the spool, as shown.

Wet the straw in warm water and it will at once straighten out. Place it for not more than two or three minutes in an oven heated to not more than 212 degrees F. and it will curl. Mark the two extreme positions of the end of the indicator 100 and 0 and divide the space between proportionately. This will give a scale for measuring relative humidities.



The straw straightens when the air is moist

Breathing on this instrument will demonstrate how exceedingly sensitive it is. Although it is not, of course, quite as accurate as a wet-and-dry bulb hygrometer, one can detect weather changes just as readily as with an expensive piece of apparatus.

It will be a surprise to many to find how dry their living rooms are during the winter time and how damp the rooms are on a hot summer day, when the interior of the house is cool.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

New Handle Aids in Shooting a Bow

By WILLARD D. MORGAN

Jack A. Hoefer, a California archer, demonstrates a new bow grip that fits the hand

THE revival of the sport of archery has resulted in the designing of an entirely new type of bow handle by Jack Hoefer, of Glendale, California, who says that it distributes the pulling weight more evenly across the palm of the hand than does the English handle. It has been tested out thoroughly at a large university for the past four years and the shooting has been improved greatly.

This handle may be added easily to any bow. On a soft pine block 1⅛ in.



How the wooden handle block is shaped, fitted to the bow, and wrapped with cord

square and 6 in. long, draw a curve like that shown and cut and rasp the bulge to fit the palm of your left hand. Make allowance for the cord wrapping; the tendency is to make the block too thick.

Cut a groove in the underside to fit flush on the "belly" of the bow and glue the block in place with the tapered end just below the shooting center. Hammer in two short brads to hold the handle in position and apply liquid glue liberally on handle and bow.

Start the wrapping ½ in. below the lower end of the handle and continue until you have reached the shooting center. Make an invisible ending with the aid of a tie-in cord. Drive short brads through the ends of the wrapping cord at the start and finish. Use a hammer handle to beat down the cord until it is smooth and even and for the final finish apply two coats of varnish or shellac.



A finished grip showing also the arrow plate, and a handle in the process of being wrapped

Made for You, Sir

Do us the kindness to try it

GENTLEMEN:

One thousand men were consulted as to what they sought in a shaving cream. From them we learned four things in which they said others had failed.

With these as our goal our laboratories started in. Time after time they failed, only to try again. The 130th formula brought success. Brought, too, a fifth feature to assure still greater shaving joy.

Now we ask you to try this shaving cream we've made for you. In simple fairness let us send a 10-day tube to try. We believe we'll win you.

We know how

Our laboratories are competent, superlatively equipped. For 60 years they have studied soap chemistry. The leading toilet soap of the world—Palmolive—is one of our creations.

Before we would consent to put our name on a shaving cream we had to know that, in this highly competitive field, our cream would be outstanding. And today millions are flocking to it, deserting preparations that never quite satisfied.

These 5 advantages

1. Multiplies itself in lather 250 times.
2. Softens the beard in one minute.
3. Maintains its creamy fullness for 10 minutes on the face.
4. Strong bubbles hold the hairs erect for cutting.
5. Fine after-effects due to palm and olive oil content.

Don't buy—yet

Now we ask that for 10 days you shave our way. At our expense. If we have excelled, you will want to know. If we have not, you will know that, too. You can't fool men about shaving.

Do us the courtesy of a 10-day test. Cut out the coupon now.

THE PALMOLIVE-PEET COMPANY, CHICAGO, ILLINOIS

To add the final touch to shaving luxury, we have created Palmolive After Shaving Talc—especially for men. Doesn't show. Leaves the skin smooth and fresh, and gives that well-groomed look. Try the sample we are sending free with the tube of Shaving Cream. There are new delights here for every man. Please let us prove them to you. Clip the coupon now.

10 SHAVES FREE

and a can of Palmolive After Shaving Talc

Simply insert your name and address and mail to Dept. B-1385, Palmolive, 3702 Iron Street, Chicago, Ill.

Residents of Wisconsin should address Palmolive, Milwaukee, Wis.

.....

.....

Please print your name and address

Good News

You don't have to shovel coal and ashes this winter...

PEOPLE all over the country, many right in your home town, have discovered that shoveling coal and taking out ashes is no longer a necessary nuisance for yourself—or your wife. Oil burners have eliminated the work and dirt of heating by coal.

You have heard a lot about oil heat, you have probably talked about oil heat with your neighbors. Now, let us tell you just what oil heat will do for you. First it will mean no more shoveling coal (2) no more taking out ashes (3) no more building fires. These are the three chief things an oil burner eliminates for the home owner.

Now for the positive side. First oil heat means you can run your furnace from your living room (2) you can regulate oil heat (automatically) so it will be nice and warm when you get up in the morning (3) you can have a clean cellar, and more room, because you don't need a coal bin (4) you can have an evenly heated house all day—this means health for your family as well as day in and day out comfort.

And the majority (66%) of owners of Caloroil Oil Burners say that oil costs no more than coal to burn.

The Caloroil Oil Burner has been investigated and is approved by the Popular Science Institute of Standards and is listed as standard by the Fire Underwriters Laboratories. This means that the Caloroil is already giving thorough satisfaction to thousands of users and that it is absolutely safe!

You can now buy a Caloroil Oil Burner the same way you bought your car, vacuum cleaner or phonograph—on monthly payments. May we tell you about the unusual plan by which you can enjoy *this winter* the comfort and convenience of oil heating? Just sign the coupon and sent it to us today.

CALOROIL BURNER CORPORATION
225 West 34th Street New York

Please send me further information about your oil burner and what it will do for me. I live in a.....room house.

Name.....

Address.....

.....

Mystic Lamp Sheds Its Light through a Crystal Ball

By PAUL H. KEATING

A plaster of Paris incense burner and a glass ball were used in making this lamp

WHEN a light is turned on inside the idol illustrated, the ball becomes brightly illuminated and throws a shaft of light upward. The effect is very odd and charming; it is ideal for a smoking room or den and will lend a certain oriental "atmosphere" to any room.

A gilded plaster of Paris idol holding a bowl of incense was obtained. Three holes were cut into the cast, which was hollow—one about ¾ in. in diameter through the bowl, one in the back to hold the electric fixture, and a larger hole in the bottom to give working room for assembling the electric light and socket.



Section through idol showing light socket

A small amount of plaster of Paris was spread around the bowl and a 3½-in. "crystal" ball set into it. When the plaster had hardened, the rough edges were trimmed and painted with gilt to match the rest of the idol.

A 10-watt lamp is about as large as can be inserted in an idol of this size. The total cost was less than eleven dollars.

WHEN WORN hollow, an oilstone may be resurfaced by rubbing it over any flat metal surface, upon which coarse emery or other abrasive has been sprinkled.

How to Turn Brass *into* GOLD

MILLIONS of dollars are paid annually to professional and amateur players of King Brass Band Instruments.

Much of this money is earned outside of regular working or school hours. You, too, can enjoy the social benefits and extra money that come from being able to play a King.

It's easier to learn to play King Band Instruments because they are built scientifically—each instrument laboratory tested.

Mail the coupon and learn how the magic that is built into the brass of a King can be turned into gold by you. Do it *now*, lest you forget.

KING THE H. N. WHITE CO.
5237-91 Superior Ave., Cleveland, O.

☐ Saxophone ☐ Trumpet ☐ Trombone ☐ Alto ☐ French Horn ☐ Baritone ☐ Bass ☐ Bugle

Please send me free copy of your illustrated magazine "The White Way" and your Handy Reference Catalog. I have checked at left, the instrument I prefer.

My Age.....
Name.....
Address.....
City.....State.....

BETTER ENGLISH!

Improve your speech! You are judged by your use of language. Instead of taking expensive courses, merely read these pocket-sized Little Blue Books—self-teaching manuals—your choice 5 cents per book. **Order by number.** 5¢

821 How to Improve your Vocabulary
25 Rhyming Dictionary
56 Slang Dictionary
367 How to Improve Your Conversation
6974,000 Words Often Mispronounced
696 How to Pronounce Proper Names
734 Handbook of Useful Phrases
855 How to Write Letters
82 Common Faults in English
681 Spelling Self Taught
682 Grammar Self Taught
683 Punctuation Manual
75 How to Choose Books
822 Rhetoric Self Taught
78 Public Speaking Guide
192 Book of Synonyms
86 Reading Guide
112 Self-Development
1244 How to Write Love Letters
89 Model Love Letters
1174 How to Write Business Letters
125 Wilson's Best Speeches
166 English As She Is Spoke. Mark Twain
326 Short-Story Writing Hints
186 How Poe Wrote "The Raven"
214 Lincoln's Best Speeches
986 How to Talk & Debate
708 Romance of Words
639 Most Essential English Words
1023 Popular Recitations
815 Familiar Quotations
902 Foreign Words & Phrases
499 Classical Dictionary
905 Biblical Allusions
1002 Dictionary of Sea Terms
816 Shakespearian Quotations
972 Popular Joke Book
1093 Book of Puns
276 Washington's Best Speeches
342 How to Report News
364 How to Argue Logically
435 100 Best Books Outlined
1131 Writing for the Market
437 Scenario Writing Guide
764 Writing Book Reviews
496 Writing One-Act Plays
514 Writing Poetry
556 Etiquette Hints
629 Legal Forms
831 Crossword Puzzles
894 Writing Advertising
971 Funny Anecdotes
1003 How to Think Logically
1009 Typewriting Manual
1097 Memory Improvement

GREAT BARGAIN! Any book 5c plus 1c per book for carriage charges—order by number. Canadian and foreign 7c per book. Catalog free on request.

Haldeman-Julius Publications, Dept. S-89, Girard, Kansas

PRINT YOUR OWN Cards, Stationery



labels, paper, circulars, tag menus, book etc. Save money and time, cut cost in half. Sold direct to you from factory. **Print for Others, Big Profits.** Complete Outfits, $8.85 up. Job Presses $11 up, Rotary $149. All easy, rules sent. Pays for itself in short time. Write for catalog presses, type, paper, cards etc.

THE KELSEY CO., B-33, Meriden, Conn.

Learn Advertising at HOME

Many of the highest paid men in the world are advertising men. You can learn easily and quickly at home during your spare time. We guarantee satisfaction. Bigger opportunities now in advertising than ever before. Constant demand for our graduates at splendid pay.

Send for FREE Book. Giving interesting information and vital facts—just what you want to know about advertising. Write today.

PAGE-DAVIS SCHOOL OF ADVERTISING
Dept. 1366, 3601 Michigan Ave., Chicago, U. S. A.

A 2c STAMP —will start you on the road to success. See Money Making Opportunities on pages 124 to 151.

Blueprints for Your Home Workshop

Nos. 2 and 15

ANY ONE of the blueprints listed below can be obtained for 25 cents. The blueprints are complete in themselves, but if you wish the corresponding back issue of the magazine, in which the project was described in detail, it can be had for 25 cents additional so long as copies are available. The editor will be glad to answer any specific questions relative to tools, material, or equipment.

POPULAR SCIENCE MONTHLY
250 Fourth Avenue, New York

GENTLEMEN:

Send me the blueprint, or blueprints, I have underlined below, for which I inclose.....dollars.....cents:

No.	Title	Described in Issues of		Price
1.	Sewing Table	Feb.,	'22	25c
2.	Smoking Cabinet	Mar.,	'22	25c
3.	End Table	Apr.,	'22	25c
5.	Kitchen Cabinet	May,	'22	25c
8.	Shaving Cabinet	June,	'22	25c
9.	Arbor, Gate and Seats	July,	'22	25c
10.	Porch Swing	Aug.,	'22	25c
11.	Bench and Tilt Table	Sept.,	'22	25c
12.	Electric Washer	Oct.,	'22	25c
13.	Tea Wagon	Nov.,	'22	25c
14.	Christmas Toys	Dec.,	'22	25c
15.	Workshop Bench	Jan.,	'23	25c
16.	Inlaid Radio Cabinet	Feb.,	'23	25c
17.	Cedar Chest	Mar.,	'23	25c
18.	Phone Table and Stool	Mar.,	'23	25c
19.	Grandfather's Clock	Apr.,	'23	25c
20.	Flat Top Desk	Apr.,	'23	25c
21.	Colonial Desk	Apr.,	'23	25c
22.	Cabinet and Desk	Apr.,	'23	25c
23.	Pergola Garage	May,	'23	25c
24.	Gateleg Table	June,	'23	25c
25.	Canoe Sailing Outfit	July,	'23	25c
26.	Baby's Crib and Pen	Sept.,	'23	25c
27.	Kitchen-Cabinet Table	Oct.,	'23	25c
28.	Pullman Play Table	Nov.,	'23	25c
29.	Toy Tea Cart, etc.	Dec.,	'23	25c
30.	Tool Cabinet, etc.	Jan.,	'24	25c
31.	Sewing Cabinets	Feb.,	'24	25c
32.	Chinese Game Table	Mar.,	'24	25c
33.	Dining Alcove	Apr.,	'24	25c
34.	Garden Trellises	May,	'24	25c
35.	Simple Radio Cabinet	Oct.,	'24	25c
36.	Rush-Bottom Chair	Nov.,	'24	25c
37.	Simplified Bookcase	Dec.,	'24	25c
38.	Sheraton Table	Jan.,	'25	25c
39.	Salem Chest	Feb.,	'25	25c
40.	Desk in Sheraton Style	Mar.,	'25	25c
41.	One-Tube Radio Set	May,	'25	25c
42.	Three-Stage Amplifier	June,	'25	25c
43.	Four-Tube Receiver	July,	'25	25c
44.	Pirate Ship Model—Hull	Feb.,	'26	25c
45.	Pirate Ship—Details	Mar.,	'26	25c
46.	Galleon Model—Hull	May,	'26	25c
47.	Galleon Model—Details	June,	'26	25c
48.	Sailing Yacht Model	July,	'26	25c
49.	Broom Cabinet	Aug.,	'26	25c
50.	Airplane Model (Flying)	Sept.,	'26	25c
51.	Clipper Ship Model—Hull	Oct.,	'26	25c
52.	Clipper Model—Details	Oct.,	'26	25c
53.	Clipper Model—Rigging	Nov.,	'26	25c
54.	Five-Tube Radio Set	Oct.,	'26	25c
55.	Five-Tube Set—Details	Oct.,	'26	25c
56.	Bird and Animal Toys	Dec.,	'26	25c
57.	*Constitution* Model—Hull	Jan.,	'27	25c
58.	*Constitution*—Rigging	Feb.,	'27	25c
59.	*Constitution*—Rigging	Mar.,	'27	25c
60.	Welsh Dresser	Mar.,	'27	25c
61.	Viking Ship Model—Hull	Apr.,	'27	25c
62.	Viking Ship—Details	Apr.,	'27	25c
63.	Toy Motor Boat—Hull	May,	'27	25c
64.	Toy Motor Boat—Details	May,	'27	25c
65.	Six Simple Block Puzzles	June,	'27	25c
66.	Ship-Model Weather Vane	Aug.,	'27	25c
67.	Toy Model of Lindbergh's New York-to-Paris Plane	Aug.,	'27	25c
68.	Magazine-Rack Table and Book-Trough Table	Sept.,	'27	25c

Name.....
(Please print name and address very clearly)

Street.....

City and State.....

HARDEST AND SHARPEST
REG. U. S. PAT. OFF.

Home Craftsmen need Sharp Edge Tools

Keep a Carborundum Combination Stone Handy

NOT how cheap, but *how perfect*, is the big consideration when Father builds a doll-house for Daughter. Or a boat for Sonny, or a sewing stand for Mother. His is a labor of love.

Keen cutting edges on all edge tools are always essential on any job. It is easily possible to keep tools ready with a perfect, keen smooth edge. Carpenters have learned to depend upon the Carborundum Combination Stone to get a better edge—quicker—so should the Home Craftsman.

This "double duty" Carborundum Combination Stone completes your tool kit. It is made of Carborundum—the manufactured abrasive—harder, sharper, faster-cutting than any other material. Made with one side coarse grit to start your edge, and reverse side fine grit to finish off. Every stone uniform in grit and grade. Does not readily fill nor glaze over. Wears evenly. Lasts a lifetime. Use dry or with oil.

Carried by Hardware Dealers Everywhere

WE SUGGEST
No. 108—8 x 2 x 1 inch
No. 109—6 x 2 x 1 inch
No. 110—7 x 2 x 1 inch

THE CARBORUNDUM COMPANY
Niagara Falls, N. Y.

CANADIAN CARBORUNDUM COMPANY, LTD.
Niagara Falls, Ont.

Sales Offices and Warehouses in New York, Chicago, Boston, Pittsburgh, Cleveland, Detroit, Cincinnati, Philadelphia, Grand Rapids, Milwaukee; The Carborundum Co., Ltd., Manchester, Eng., Deutsche Carborundum Werke, Dusseldorf, Germany.

Carborundum is the Registered Trade Name used by The Carborundum Company for Silicon Carbide. This Trade Mark is the exclusive property of The Carborundum Company.

Send for Catalog P-1 for Complete List of Carborundum Products



Carborundum
REG. U. S. PAT. OFF.
ABRASIVE PRODUCTS



"There's the 'B' for Your Set"

$28.50

with Raytheon B Tube

IF YOUR SET has five tubes or five and a Power tube, you can now get a Sterling Raytheon-equipped "B" for it at $28.50—why spend more? Think of it! For less than $30 you can get rid of "B" batteries once and forever and in their place be sure of full-powered Sterling-filtered "B" current right from the light socket.

Sterling Model RT-81 has an output at 35 mills of 135 volts. Detector and Medium voltages are each adjustable and the high tap takes care of the Power tube on most sets. This assures plenty of voltage and exact power regulation for your particular set. RT-81 is no larger than one dry "B" battery, and fits right into the console cabinet or into Radiolas 25 & 28.

RT-81

Another Popular Sterling Model for Larger Sets, R-98 "B-C" Power Unit

A "Universal" "B-C" model for high class sets. Output at 35 mills, is 180 volts. Has four "B" terminals, two of which are independently variable. All four voltages are variable through primary control. Variable High "C" voltage. On and Off switch. Uses Raytheon B or B H Tube. List price; without Tube, $33.50.

Sterling

"B" POWER UNITS

THE STERLING MFG. CO.

2831 Prospect Avenue - Cleveland, Ohio

DESIGNED FOR USE WITH Raytheon TYPE B H LONG LIFE RECTIFYING TUBE

A Dressing Table for Baby

It Fits into Small Bathroom—Quickly Removed After Use

By CONSTANCE J. WARDELL



This safe and roomy table on which to dress a baby may be erected without marring bathroom fixtures

IN THESE days of modern efficiency and short cuts, we have dish washing machines and vacuum cleaners, but mother's knee is still very often the chief dressing station for wee babies. That is all wrong, because it is a nervous strain on mother and an uncomfortable position at best for baby.

The solution is to erect an easily removable dressing table in the bathroom in such a way as not to mar the woodwork or fixtures. All this we accomplished with only a saw, hammer, chisel, screw driver, a few ¾ in. thick boards, and some nails and screws. Anyone who is handy with tools can acquire an equally satisfactory "baby board" by applying the ideas outlined in the accompanying sketches to the particular arrangement of his own bathroom.

In our own case, the board itself is ¾ by 27 by 35 in., with cleats across the ends. It was necessary to notch out the right-hand front corner to suit the woodwork around the doorway, but this notch, being tight fitting, helps to steady the board considerably. It is supported at this corner by means of a bracket screwed to the door trim as shown.

The left-hand front corner rests upon an upright support, which passes through slots in two wooden braces attached to the bathtub by the simple method illustrated. Each of these braces consists of two pieces suitably notched and shaped to fit the bathtub and the pipes and then fastened together with nails. Note that the upper end of the upright enters a mortise or slot cut right through the left-hand cleat under the table top.

An ordinary leather or fabric strap may be nailed across the width of the top with both ends free for buckling around the baby's waist, and two screw eyes are inserted, one on each side of the board to which the baby's safety strap may be snapped. These are for use when the baby has to be left temporarily on the table, for instance, when answering telephone calls.

The rear of the board merely rests upon the water tank. It can, therefore, be lifted up bodily and put aside when not in use. The upright also may be withdrawn from its sockets, so that nothing is left in place except the bracket attached to the door trim and the tub braces.

If no other provision has been made for toilet articles, a shelf may be attached to the wall, just out of baby's reach.


SCREW EYE
DOOR FRAME
BABY BOARD ¾"x 27"x 35"
RECESS
SUPPORTED ON TANK
UPRIGHT SUPPORT ¾"x 4"x 38"
SCREW HOLES
INTERLOCKING BRACE FOR UPRIGHT SUPPORT
PIPES IN NOTCHES SIMILAR TO UPPER BRACE
NOTCHED CLEAT AND BRACKET HOLDS CORNER OF BOARD

How the table is constructed. Note particularly the way braces are attached to pipes

How to Insert Flashing under Old Shingles

WHILE a new rear porch was being added to a shingled residence recently, the question arose as to how to place flashing at the junction of roof and wall without removing and replacing a number of the wall shingles. Pieces of thin wood, cut from cigar boxes, were driven up under the shingles with a piece of thin hardwood until they were 1½ in. above the butts of the next higher course, as illustrated. A mark on the hardwood strip made it easy to place the pieces accurately.



Spacing strips allow the flashing to slide in

The flashing was then bent lengthwise on a straightedge so that the bend would come even with the roof. The flashing slipped into place easily; a few nails held it until the roof could be finished. This was done, of course, before the porch rafters were put in place.—ALVIN M. GULLY.

Making Blocks for Ship Models

By F. L. Coes

BEFORE I was bitten by the model-making bug, I often saw fellow commuters unostentatiously whittling little slips of boxwood (old 2-ft. rules, as I afterward found out) into what seemed to be tiny wooden seeds. Inquiry elicited the information that these mysterious seeds were blocks for ship models.

My first need for anything of this kind was for two pairs of blocks for a "watch" tackle to swing the captain's gig on davits over the stern of a model motor boat. These I made from aluminum wire, in the same sequence as did the commuters, with the advantage that the metal, while harder to work, has no grain and may be drilled easily without danger of splitting. When I came to build a model that required many blocks of three sizes, this



How dies may be made for stamping ship-model blocks quickly from aluminum wire

method seemed far too slow and I devised an infinitely faster one.

On one end of three rods of high-grade tool steel of suitable sizes, I formed a half block. These punches then were hardened and drawn to a brown-blue.

Next I obtained two blocks of steel 1 by 1 by 3 in., produced a flat surface on one side of each, clamped these surfaces together and drilled for guide rods. Then I annealed the blocks, laid out three parallel lines on each, working from a center line, and, placing the blocks on an anvil, set the three impressions into each with heavy hammer blows. After a little "slicking up" with a file, the two dies were hardened and tempered to a deep straw.

In use, this forming tool is clamped in a solid vise or used on an anvil. Two springs may be inset, as shown, to open the tool after each blow. A rod of aluminum wire, hard solder, annealed yellow brass or other soft alloy is put into the impression and a blow struck on the upper block. If necessary, turn the rod over, set it in the impression and hit it a second time. Don't close the dies fully with the rod in the impression, but keep the block on the rod so that it can be finished with a fine file before being (*Continued on page 106*)

for Precision Construction

Mechanics Use

BROWN & SHARPE TOOLS

"World's Standard of Accuracy"

The moderate priced motor car could not roll on the roads today were it not for the precision tools which make quantity production possible.

Precision construction plays just as important a part throughout hundreds of industries as it does in the manufacture of automobiles.

Mechanics in all these industries place complete reliance in the performance of Brown & Sharpe tools. They know that this performance sets a standard of accuracy throughout the mechanical world.

Hardware dealers can supply you with Catalog No. 30 or, we will send you one direct.

DEPT. P S
BROWN & SHARPE MFG. CO.
Providence, R. I., U. S. A.

YOU Must Make Your Own Future

For Young Men of 16 to 20 THE BROWN & SHARPE APPRENTICE SCHOOL *Offers Unusual Advantages*

"Earn While Learning to Earn"

Write for Illustrated Booklet "APPRENTICESHIP"

The CROSMAN .22 RIFLE

If You Are a Real Judge of Guns You Will Appreciate

The Wonder Gun

"Power without Powder"

Here is the most remarkable gun that has appeared in years—a .22 rifle that uses no powder, has accuracy not obtainable in any other gun, abundant power, never needs cleaning, silent, scientifically correct. The delight of men who glory in precision shooting and the ownership of a handsome powerful gun.

Unsurpassed Accuracy

Experts find this new gun accurate beyond anything in their experience. By its use amateurs become experts in a short time. Absence of powder deposit in rifling keeps it true, from first shot to last—like shooting a newly cleaned gun every time. Put bullet after bullet through same hole, establish new high records and astonish your friends. Perfected by a West Pointer. Used and endorsed by men like Richard L. Sutton. Army men delighted with its marvelous accuracy and self-cleaning feature. Knocks down quickly to fit 22-inch suitcase.

Never Needs Cleaning

Powderless, smokeless, noiseless. Never needs cleaning. Every bullet passing through barrel acts like swab and leaves it brighter and cleaner. Shoot all day, put gun away and rest while your friends mess around with oily, blackened rags. Next day outshoot them again with your wonderful Crosman.

Do Target Shooting at Home

Set up range in your attic, cellar, yard, or even in your apartment—if you live in a crowded city. Power adjustable for indoor shooting with same superb accuracy. No smoke to annoy, no noise to disturb anyone, no shells dropping over floor. Simply shoot to your heart's content any time you feel like it. Gets all kinds of small game, pests, rats, sparrows, etc.

Send for This Booklet

FREE Target and Game Shooting

CROSMAN ARMS CO., INC.
413 St. Paul Street
Rochester, N. Y.

70 West King St., Toronto, Canada

How to "Frame" Pictures with Wallboard

FRAMES for the pictures you may cut from magazines can be made from scraps of fiber wallboard, as shown below. They may be painted, gilded or varnished. In some cases I have even grained the frames with good results.

As the saw leaves rather rough edges, it is necessary to smooth them carefully with a sharp knife and sandpaper.

When the surface of the frame has been finished, the edges may be painted with



When the wallboard has been cut out and decorated, the print and back are glued on

black, gold or silver. Some frames will be improved by painting an unobtrusive but decorative design on them with artist's oil colors.

The picture is merely glued to the frame and backed up with cardboard, which is also glued. A wide board then is placed over the frame and heavy weights are piled on it. Allow at least twenty-four hours before removing the frame, which will be found perfectly flat.—HAROLD JACKSON.

RECENTLY I desired to carve my initials on a tool chest. In looking for artistic letters to copy, I came across a sheet of embroidery initials intended to be transferred to linen by means of a moderately hot iron. I discovered that these designs, which may be purchased in fancy goods stores, can be transferred perfectly to oak and mahogany.—A. S. J.

Making Ship-Model Blocks

(*Continued from page 105*)

cut off. The rod serves as a handle.

If you prefer, you can drill the block at this time. I do this on the smallest size of block, but for the larger sizes I hold them with a spring wooden clothespin, in the jaws of which a partial impression of the block has been burned.

My preference for the strap is soft brass wire except on the smallest block. After the hole is drilled and the strap bent on, I dip the finished block in bicycle enamel, shake the excess off and dry for forty-eight hours, or hang in a tin can and set on a radiator for six or eight hours.

If you happen to know a good blacksmith, you can have the dies made in the form of a spring set, similar to the old bullet swages used by Kentucky riflemen for making round bullets "slick" after they had been molded.

Keep Your Copies of "POPULAR SCIENCE" in the New Big-6 Binder

There is so much useful information in Popular Science Monthly that many readers have asked us to supply them with a binder in which they can keep a permanent file.

To meet this demand we have had designed the binder pictured above. Bound in two-tone Artcraft (looks like leather—lasts forever) with the name of the magazine stamped in 24 Carat Gold on the cover, this binder will securely hold 6 copies of Popular Science Monthly.

New copies can be slipped into the Big-6 Binder as easy as inserting a letter in an envelope.

There is nothing to get out of order—no screws to work loose, no keys to get lost. This binder will last a lifetime.

The binder is as beautiful as it is useful—it will be an ornament to any library table.

Only $2.00--Postage Prepaid

Bought in a store this binder would cost you $3.00 or more. Because we are having them made in quantity for our readers we can make you the special price of $2.00 including all delivery charges.

Popular Science Monthly,
250 Fourth Avenue,
New York, N. Y.

Please send me your Big-6 Binder bound in two-tone Artcraft with "Popular Science Monthly" stamped on the cover in 24 Carat Gold. I am enclosing $2.00 and it is understood that there is to be no further charges of any kind.

Name.....

Address.....

.....

What Do You Want to Make?

IF THERE is anything you wish especially to make in your home workshop or any repairing or painting you need to do about your house, and you don't know exactly how to go about it, perhaps POPULAR SCIENCE MONTHLY can help you. Don't hesitate to write to the Home Workshop Editor.

Your idea will, perhaps, form the starting point for developing an article that will help and interest many readers, so please be as definite as possible. Send rough sketches or a picture of what you wish to construct, if you can do it conveniently.

Similarly, if you wish to obtain materials or tools which are not stocked by your local dealers and cannot be obtained through any ordinary channels, POPULAR SCIENCE MONTHLY will be glad to suggest sources of supply.

Look upon the Home Workshop Department as a clearing house for ideas and send in not only questions but also any kinks you have found useful.

How to Build a B-Eliminator

(*Continued from page 75*)

you do not have to think about this point.

To put the de luxe type into operation, plug the specified tubes into the sockets and wire the binding posts of the amplifier to the similarly marked posts on your set. When you plug the cord from the eliminator into the wall socket, you will note a dim blue-purple glow in the tubes in sockets K and L. This glow indicates that the eliminator is operating properly. Now go ahead and tune-in your set; your eliminator will supply just the voltage required without any attention on your part.

While no excess voltages are developed with the de luxe eliminator if you leave it running when the set is turned off, it should be disconnected from the electric circuit when not in use to save current and wear on the rectifier and voltage regulator tubes.

The Popular Science Institute of Standards has prepared a special list of apparatus suitable for use in constructing either of these two types of B-battery eliminators. You can obtain this list by writing to the Radio Editor, POPULAR SCIENCE MONTHLY, 250 Fourth Avenue, New York. If any details about the construction, wiring or use of the eliminators are not clear to you, include these questions in your letter and they will be answered without charge.





Care for Your Car in Comfort!

You know how the best of intentions vanish in a cold, cheerless garage. The car needs greasing, washing—a dozen little attentions—but never gets them, because the garage is too cold.

Line the garage with Sheetrock. Make it comfortable. Make it better for the car itself and a better place to work.

Sheetrock is fireproof. Sheetrock is insulating. Sheetrock comes in broad, ceiling-high sheets [6 different lengths] and saws and nails like lumber. Made of gypsum, mill-cast between tough fibre coverings. Full three-eighths of an inch thick. Patented square, folded edges for extra nailing strength. Every board branded on the back. Exclusive Sheetrock Reinforced Joint System makes paneling unnecessary—seals all joints.

There is a Sheetrock dealer near you.

UNITED STATES GYPSUM COMPANY
General Offices: Dept. 48, 300 West Adams Street, Chicago, Illinois

Reg. U. S. Pat. Off.

SHEETROCK

FIREPROOF . . . INSULATING

Made by the United States Gypsum Company

USG

UNITED STATES GYPSUM COMPANY
Dept. 48, 300 West Adams Street, Chicago, Illinois
Send me free booklet, "Sheetrock Walls."

Name.....

Address.....

"Why Don't You Speak For Yourself, John?"

The human voice is so well synchronized with the moving picture that all of the characters of the silver screen now can "speak for themselves."

What has this to do with NICHOLSON Files? Simply this—nearly every step forward taken by science and industry develops new uses for files.

NICHOLSON Files will be made to meet these future needs—just as they are made for every filing job today — throughout industry and the home.

Would you like us to name some? Sharpen dull saws, axes and hoes, help build a radio, fix locks that stick, clean electrical contacts, smooth down warped bureau drawers.

Others? Send for our booklet "Files and What They Will Do For You." No charge — what's your name and address?

NICHOLSON U.S.A. TRADE MARK

NICHOLSON FILE CO.
Providence, R. I., U. S. A.

— a File for Every Purpose!

A Cabinet for Your Curios

(Continued from page 92)

design developed through a mathematical analysis of Ancient Greek architecture.

The constructional features are so simple as to bring the project well within the reach of most amateur woodworkers.

First, make the two side frames and bore the holes for the metal shelf blocks or supports, if the shelf is to be movable; otherwise it can be supported on small nickel-plated angles. Next, get out the stock for top, bottom and back—preferably ⅜-in. plywood, as it does not shrink. After boring and countersinking all screw holes, glue and screw the top and bottom to the sides; then glue and screw the back to the sides, top and bottom. Care should be taken to get the cabinet perfectly square. After the glue is dry, the edges of the top, bottom and back should be planed flush with the sides.

The frames for the doors are next made and fitted. The rabbet is ⅝ in. wide (⅜ in. deep) because it must hold, in addition to the glass, a fretted panel simulating leaded glass. These fretted panels should be made of plywood, preferably only 1/32 in. thick. The pieces to be removed are sawed out carefully with a coping saw or a fine keyhole saw and the edges smoothed with file and sandpaper. After the doors are hung, the left one is fitted with a flush bolt on top and bottom, and the right one with a small lock.

The top and bottom should be planed and scraped flush with the face of the doors; then the scrolled pieces on top and bottom are glued in place. Slender screws are driven through the narrow parts of the pieces and small triangular blocks placed behind them reinforce these joints. A fillet 1/16 by ⅜ in. is mitered around the front and sides of the top and bottom and held in place while the glue is setting with very fine brads.

The glass in the sides and doors is held in place by a small quarter-round molding nailed to the frame. The plate glass shelf is supported evenly on four shelf blocks, with a small piece of felt or cork between the glass and each block.

Instead of the turned ornament suggested, a brass ornament, such as an eagle, may be purchased from a firm specializing in metal furniture fittings.

The cabinet is supported by mirror hangers and a strip of 1-in. molding fastened to the wall.

Stock Bill for Wall Cabinet

No. Pcs.	T.	W.	L.	Part
2	¾	11	25	Top and bottom
1	¾	20⅞	25	Back
2	⅝	15⅛	20⅛	Sides
2	⅝	1¼	20⅛	Sides
4	⅝	1¼	9¼	Sides
4	⅞	1¼	20⅛	Doors
4	⅞	1¼	10⅞	Doors
2	⅞	10⅛	18⅜	Doors
1	½	5	25	Top scroll
1	½	3	25	Bottom scroll
1	1/16	⅜	10 ft.	Fillet
1		9⅜	23⅝	Plate glass shelf
2		8¼	18¼	Window glass sides
2		10⅛	18⅜	Window glass doors
2 pair		1¼	1½	Hinges
2				Flush bolts
1				Lock
4				Shelf blocks

All dimensions are in inches except as otherwise noted.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.



30 Days Free Trial

Now! A Real Electric Radio Set

Three Year Guarantee

Shipped direct from our factory at rock bottom prices—cost less than most battery sets

No Batteries, Chargers or Eliminators

No Acids; No Liquids—Plug In—Press Button—"Tune In"

Metrodyne

ALL ELECTRIC RADIO

Agents! Dealers—Big Profits!

Make big money taking orders for Metrodynes. All or part time. Metrodyne All Electric Radios are in a class by themselves. Unequalled for quality, performance and price. Demonstrate at home and take orders. Lowest wholesale prices. Your demonstrating set on 30 days' free trial. Mail coupon below for details.

7 Tubes—Single Dial Set

100% Electric Radio

At last! The radio you've dreamed about! If you have electricity in your home you can now really enjoy **Long Distance** radio reception without the care, bother and muss of batteries, chargers, eliminators, etc. The **Metrodyne All Electric** is a real, genuine **batteryless** radio set. Simply insert the plug in the socket, press the switch button and "tune in." You could not possibly buy a better radio set than the **Metrodyne All Electric**, no matter what price you paid.

BEAUTY—EFFICIENCY DEPENDABILITY

The Metrodyne All Electric Radio is a 7 tube, single dial set. Only the highest quality low loss parts are used throughout. Solid walnut cabinet, beautiful two-tone effect, with handsome gilt metal trimmings. Size of cabinet, 28 inches long, 13 inches deep, 10 inches high. Has electrically lighted dial so that you can log stations in the dark. Only one dial to tune in all stations. Excellent tone qualities — wonderful volume — very selective.

Gorgeous Console Electric Radio

Here is the Metrodyne All Electric Console Radio — a gorgeous, genuine walnut cabinet, in a beautiful two-tone finish. Has a built-in genuine Metro-Cone large size speaker. Brings in programs with great volume, reproducing the entire range from the lowest to the highest notes with remarkable clearness and distinction. All metal parts are finished in old gold. Wonderful electric radio, in a cabinet that will beautify the appearance of any home.

Costs Less Than Most Battery Sets

Do not confuse the Metrodyne electric radio with ordinary light socket sets, because the Metrodyne is truly an **all electric radio** — consumes less than 2c worth of power a day. Comes to you **direct from the factory.** Its low cost brings it down to the price of an ordinary battery set. We are so confident that you will be delighted with this wonderful, easy-to-operate **batteryless radio** that we offer to ship it to your home for **thirty days' free trial** — you to be the judge.

Mail This Coupon

We are one of the pioneers of radio. The success of Metrodyne sets is due to our liberal **30 days' free trial offer,** which gives you the opportunity of trying before buying. Thousands of Metrodynes have been bought on our liberal free trial basis — **WRITE TODAY!**

METRO ELECTRIC COMPANY
2165 N. California Ave. *Dept.* 621 Chicago, Illinois

METRO ELECTRIC COMPANY
2165 N. California Ave., Dept. 621
Chicago, Illinois

Gentlemen:
Send me full particulars about Metrodyne All Electric Radio and your **thirty days' free trial offer.**

Name_____

Address_____

If you are interested in AGENT'S proposition place an "X" in the square → ☐

MAIL COUPON NOW!

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Keeping an Auto-Set sharp is child's play

THE thin chromium steel cutter of a Sargent Auto-Set Plane is as tough and as keen as they come. It doesn't nick easily; it keeps its edge for a long time. But when it does need to be sharpened, it can be taken out, sharpened, and put back at its former place with no fussing to readjust whatever. This is an exclusive Auto-Set feature. You can imagine the time it saves, and the better work it means.

The Auto-Set and the small Sargent Steel Block Plane should be on every home and school bench. They cost much less than you would expect the tools of professional carpenters to cost. They are so strongly made that you should never have to replace them. With them any job is quickly finished. See them at dealer's. Write for booklet. Sargent & Company, *Manufacturers*, 50 Water Street, New Haven, Conn.

SARGENT

PLANES

Sargent Steel Block Plane No. 5206

Sargent Auto-Set Bench Plane No. 714

BUILD YOUR OWN GRANDFATHER'S CLOCK

We furnish blue prints and instructions. Buy the works and dial from us at surprisingly low prices. Make fine profit building artistic clocks for your friends. **Plain works as low as $5.00. Others with Chimes at all prices. Ask for attractive free offer.**

AMERICAN CHIME CLOCK CO.
1691 RUFFNER STREET PHILADELPHIA

Own a CORONA

The portable typewriter built like an office machine. Has four-row keyboard and big-machine features throughout.

Write to
L C Smith and Corona Typewriters Inc
913 E. Washington St., Syracuse, N.Y.

Exceptional Quality is found in every
Gerstner Tool Chest
For Machinists and Toolmakers
A postal brings free catalog which tells about them.
H. GERSTNER & SONS
545 Columbia St., Dayton, O.

100 SCALE PLANS OF OLD and MODERN SHIPS

Easy to build and sell ship models. Send 6 cents for catalog of over 100 plans, books, prints, maps and other things that smack of the sea.

SEA ARTS GUILD
405-N ELEVENTH AVE. MILWAUKEE, WIS.

Combination Awning and Shutter for Bungalow



Wooden shutter for a bungalow porch which also serves the purpose of a cloth awning

ON THE South Shore of Long Island the "bungaloafers," as they sometimes call themselves, have evolved a combination awning and shutter of wood for inclosed porches. It is made as shown, of 3 or 4 in. wide tongue-and-groove pine boards, and painted to look like a cloth awning. When the bungalows are closed for the winter, the shutters are closed and fastened.—MALCOLM MACDONALD.

Making Garden Hose Washers



Guide for cutting washers off the hose

TO MAKE washers of any size and thickness to fit standard garden hose couplings, cut slices from the hose itself or from an old piece of hose of the same size by the method illustrated. The guide is made by boring a hole through a block of wood. Cut with a wet knife and then scale off some of the outer rubber.—A. OSWALD.

Replacing a Broken Glass Knob

Paper and tape serve as a temporary knob

WHEN a glass knob breaks or pulls out of the metal socket, the sharp edges of the socket are apt to lacerate the hand. To make a temporary repair until a new knob can be obtained, roll up a compact wad of paper slightly smaller than the original door knob and press it into the metal socket. Cover the paper with friction tape and sprinkle liberally with talcum powder to prevent stickiness.—H. S.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

The Shipshape Home

Iron Holder and Stand

THE simple one-piece electric iron stand illustrated serves two purposes. It is a convenient rest for use on the ironing board, and, when the ironing is done, it is merely turned over to convert it into a holder by which the hot iron may be hung up immediately in a cupboard.

The stand used as a rest for the iron (above), and as a holder for hanging it on the wall (at left)

It will be noted that the bent parts of the stand, which form its feet, act as clips for holding the iron in place when the holder is hung on the wall. There is also a hook to receive the coiled electric cord.—GEORGE D. HUGO.



By an ingenious method of cutting and bending, the holder is made of one piece of metal

Tightening Loose Casters

FURNITURE casters which, because of age or defects, have a tendency to fall out of tables, chairs, beds, and the like, may be made to hold by wrapping a rubber band around the shank. Rubber is better than string or friction tape because it is soft and pliable and has a high coefficient of friction.—W. F. S.

Simple caster repair

SHAVE . . .

SHOWER . . .

RUB-DOWN . . .

Even *then*

this pink cream rolls pore-dirt free

Tomorrow morning, *after* you lather your face, *after* you shave, *after* you shower, let this cream prove that your face is still only half clean.

Pore-dirt hides in every face. It gives you a gray, lifeless tone instead of the ruddy glow you might well show the world.

Pompeian Massage Cream will remove pore-dirt from the clearest complexion. That's our *claim*. But the *test* that convinces thousands is this:

Send us the coupon for a FREE tube. Wash your face as clean as you know how. Then massage Pompeian into the pores. What happens?

***The cream rubs in* pink, *but* ROLLS OUT DINGY GREY!**

The picture below, taken under a powerful microscope, shows a section of skin before using Pompeian Massage Cream. The light area at the side shows the cream spread on the skin.

Compare it with the picture at the right. That's skin that is really clean! Those dark marks are the dried pellets of cream, black with the pore-dirt that has been rolled free. Dirty, aren't they? And remember, that embedded dirt could never have been washed out!

Give yourself a Pompeian Massage. Free your pores of sallow-toned dirt. Show the world a face alive with the athletic glow that clean skin boasts. A Pompeian massage is a great start for a busy, successful day!

FREE test convinces thousands

Test the benefits of Pompeian Massage Cream on your face FREE. Fill in the coupon and mail it to us—right now, while you are reading this magazine.



Photograph taken under the lens of powerful microscope showing section of skin before using Pompeian Massage Cream. The light area at the right shows the cream spread on the skin.



Photomicrograph of the same section of skin after using Pompeian Massage. Compare the skin tone. Note the dried pellets of cream, dark with the pore-dirt that has been rolled free.

POMPEIAN MASSAGE CREAM

The Pompeian Company, Dept. 301-I, 595 Fifth Ave., New York. Gentlemen: Please send me a generous trial tube of Pompeian Massage Cream . . . enough for three facial massages.

Name_____

Street_____

City_____ State_____

VERSATILE!

Does everything a novelty saw can do—but does it better.

SIMONDS

PLANER SAW

This saw will produce quickly and economically with either soft or hard wood. Whether ripping, cutting off or mitering, it will stand fast hand feed without rubbing or overheating. The successful performance of Simonds Saws, Knives and Files is due to the fact that they are made of scientifically tempered steel and that behind them is Simonds' near-century of experience in making the finest cutting edges. When buying cutting tools, specify "Simonds"!

SIMONDS SAW AND STEEL COMPANY

"The Saw Makers" Fitchburg, Mass. Established 1832

Branch Stores and Service Shops in Principal Cities

BECOME A MAKER OF USEFUL THINGS



Materials
Designs
Castings
Blue Prints

Bearings, Belting, Books on Mechanical and Scientific Subjects, Castings for Small Engines, Compressors, Gears, Lathes, Motors, Saws, and Supplies of All Kinds.

Complete Catalogue 25c which is allowed on first $2 order.

Amalgamated Sales and Service Corporation

327H South LaSalle St., Chicago, Ill., U. S. A.

It's E-Z

WITH A BUESCHER True Tone

Like music? Learn to play a Buescher Saxophone. Easy. Sweetest music. Only the Buescher (original American Saxophone) has simplified keys, perfect tone, easy blowing. 3 lessons given on request with each new Sax. teach scales in an hour. Play tunes first week. Many join Band or Orchestra in 90 days. Make real money. Travel. Work is all play. 6 days' trial. Easy terms. Send postal for Beautiful Free Book. Explains everything. Write Today.

Buescher Band Instrument Co.

2021 Buescher Block (17) Elkhart, Ind. Free Book

PARKS

Manual Trainer

$35.00

without motor

For your home shop! Combination 11-inch band saw and 11-inch wood-lathe. If you have a knack for woodworking you can turn out first-class bridge lamps, cabinets, furniture, ship models, etc., in fast time. Get one!

Write for specification circular.

THE PARKS WOODWORKING MACHINE CO.

1547 Knowlton Street Cincinnati, Ohio

Canadian Factory: 208 Notre Dame, E. Montreal, Can.

TISIT

Solders

Aluminum, Agate ware, iron, china, wood, glass

Not affected by heat. Can be used to repair steam pipes, wash boilers, automobiles, motor-boats, etc. Applied cold with a stick. No soldering iron necessary. Sets in 20 minutes. Efficient. Positive. Anyone can use it. No experience necessary. Makes soldering a pleasure instead of a hard job.

50c at your dealer's. If he cannot supply you, send us 50c—we will ship you bottle direct, postpaid. Money back if dissatisfied.

Letellier Laboratories, Inc.

187 Main St. E. Rochester N. Y.

Representatives wanted everywhere. Big profits. Write today.

The Shipshape Home

Linoleum Drainboards

INLAID linoleum may be used to cover wooden drainboards, and will give years of service. A remnant 1 yd. square will cover a good sized board.

The linoleum may be bent and carried up the wall to which the board is fastened so as to form a continuous water-tight covering of all surfaces subject to the splashing of dishwater.

Before the linoleum is placed, a strip of wood about ½ in. thick should be nailed face down around the outer edge and end of the board. A few—the fewer, the better—galvanized or copper



How an old-fashioned wooden drainboard can be modernized by covering with linoleum

nails with washers under their heads hold the linoleum in place. The edges of the drainboard also may be covered with a narrow strip of linoleum, giving the effect of a solid slab of composition material.

To cover the cut edges of the linoleum on top, a strip of brass or aluminum, such as used for the edges of automobile running boards, will be found suitable and inexpensive. On the edge of the drainboard next to the sink, the metal stripping should be *under* the linoleum so that water cannot seep under and leave a damp place. It is, indeed, possible to eliminate this joint by bending the linoleum carefully over the edge and nailing it as suggested in one of the accompanying views. The finished covering should be given two coats of first class varnish.—O. K.

Puttying Sash Lights

WHEN replacing broken window panes or reputtying sash, be sure to notice whether the glass rabbet requires a coat of paint or linseed oil. If the old putty flaked off by itself, it is a certain indication that the rabbet should be repainted before attempting to putty in the glass. Putty will not stick permanently to unpainted or unoiled wood.

Glazing is often avoided by handy men because it seems difficult to make the putty lie smoothly. A little trick that will help the amateur is to dip the putty knife in water. Then it will slide better over the putty and leave a smooth surface.

Use only the best grade of commercial putty or mix bolted whiting, a little white lead and boiled linseed oil. Cheap varieties of ready-made putty often contain marble dust, coarse whiting and adulterated linseed oil, and will not last.

New Ways to Paint

(Continued from page 73)

How a stencil brush is used to pounce one color on another in producing a stipple

all around being in any tint that will set off the black panel attractively. An oriental transfer pattern is used.

These are typical methods of decorative treatment. Compare them with the corresponding illustrations on page 73.

Brushing lacquer is generally used for the finishing because it is easily applied on small objects of this kind and dries quickly.

As wooden articles are not generally smooth enough for fine finishing, the surface should be sandpapered with the grain of the wood to as nearly absolute smoothness as possible. Use very fine sandpaper—No. 00 or No. 0000. Dust off clean.

If the wood is whitewood or poplar or any very soft wood, it is a good idea to apply a coat of shellac, which seals the surface and keeps the lacquer from sinking in. On this foundation two or three coats of lacquer will produce a first-class finish. There is another advantage in the use of a priming coat of shellac. The grain of many woods is raised by the application of painting materials, and when shellac has been applied directly to the wood, this raised fuzz may be sandpapered off and the surface restored to a perfectly smooth surface before any lacquering is done.

Apply the lacquer with a reasonably soft brush such as a fitch or bear hair brush—not a hard, coarse bristle brush. Do not keep brushing it, and do not spread it out thin. Work quickly and use a full brush at every stroke, without scraping most of the lacquer off on the edge of the tin. Do not sandpaper between coats unless you use very fine waterproof sandpaper, wet with water.

Combed Stencil Effects

PAINTED stencils as used by amateur decorators are apt to appear somewhat hard and a bit too regular and uniform for the most artistic effect. This can be overcome with the aid of a painter's graining comb containing teeth not more than 1/16 in. wide. As soon as the stencil color has been applied and before the stencil is removed, the comb is drawn over the stencil once lengthwise and once crosswise. This gives the wet paint a texture somewhat resembling a fabric and relieves any appearance of harshness or too great regularity.—J. M. T.

FOOT STOOL
See LePage's Book, page 23.

END TABLE WITH BOOK TROUGH
See LePage's Book, page 22.

HANGING BOOK SHELVES
See LePage's Book, page 25.

BACK REST
See LePage's Book, page 24.

Handiest tool in your shop

PERHAPS you have never thought of the special advantages of using LePage's Liquid Glue. It is always ready for immediate use. No weighing, soaking or heating is required. The quality is always the same. It "sets" slowly enough so that you have plenty of time to place the joints together exactly as they should go. Slow setting also allows LePage's to penetrate the wood, increasing the strength of the joint. LePage's Liquid Glue is equal in strength to any animal glue. Buy a can for your work shop. It is the easiest, quickest, handiest form of glue. Insist on LePage's.

LE PAGE'S GLUE
BOTTLES, TUBES, CANS

How to make attractive Gift Furniture

LePage's NEW Home Work Shop Book will show you how

NOW with the coming of fall and the home work shop season, comes this NEW LePage's Home Work Shop Book to show you how to make 20 different pieces of gift furniture, designed by an expert—attractive, artistic, useful, practical and easy to make.

New Book—greatly improved

THE first LePage's Home Work Shop Book, published a year ago, proved so popular that, though advertised only a few times, over 30,000 copies were sold—an enormous edition for a book of this kind. Now the new book, just off the press, represents a wonderful improvement over the old one. Of its 20 complete projects, 16 are entirely new and never offered before.

Each project is presented in three parts— a photographic illustration of the finished project, a complete dimension drawing of its parts, and simple, easy-to-follow directions, for making, given step by step from start to finish.

Designed by Expert

FOR each of the 20 gift furniture projects, the design, dimension drawings and photographs, as well as the actual articles, were made by William W. Klenke, Instructor in Woodworking, Central Commercial and Manual Training High School, Newark, New Jersey. Assurance is therefore given that each project and the directions for making it are perfectly practical.

In addition to the four pieces illustrated above, the projects include the following: Table with side flaps and two drawers, Spanish Ship model, folding sewing screen, fernery stand, tilt top table, piano bench, costumer, Priscilla sewing box. Cedar chest, smoking cabinet, table desk, desk chair, card or console table, book stand, turned bench, dressing glass. Where else could you get complete directions for making all these things for only 10 cents?

This new LePage's book also shows you how to make strong joints with glue in its most convenient form—LePage's Liquid Glue. It also tells you a lot of craftsmanship possibilities with a new product, Gesso, in making joints, covering up small defects, etc.

Send 10 cents for this NEW LePage's Home Work Shop Book

JUST write your name and address on the coupon below, tear it out and mail to us today with 10 cents in coin or stamps, and we will at once send you a copy of LePage's New Home Work Shop Book, postage paid. Address LePage's Craft League, 556 Essex Ave., Gloucester, Mass. Tear out the coupon now so you won't forget it.

MAIL THE COUPON

LEPAGE'S CRAFT LEAGUE
556 Essex Ave., Gloucester, Mass.

Gentlemen: Enclosed please find 10 cents (coin or stamps) in payment for LePage's New Home Work Shop Book. Please send a copy of this book to:

Name.....

Street.....

City.....State.....

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

IT'S THE *YOUNGER CROWD* THAT SETS THE STANDARD!

Go to the younger crowd if you want the *right* word on what to wear or drive or smoke. And notice, please, that the particular cigarette they call their own today is one that you've known very well for a very long time.

FATIMA



What a whale of a difference just a few cents make!

THE REAL ESTATE EDUCATOR

The New Revised Edition, 1927, contains Questions and Answers; Brokers' License Law; Dictionary of Words and Phrases in Real Estate and Construction; How to Appraise Property; Law of Real Estate; How to Advertise Real Estate; Legal Forms; Commissions to Agents; Savings and Loan Associations; "Don'ts" in Contracts, etc., and other useful information. 288 pages. Postpaid $2.00. Cloth.

Popular Science Monthly, 250—4th Ave., New York.

A 2c Stamp

—will start you on the road to success. See Money Making Opportunities on pages 124 to 151.

POPULAR CHEMISTRY

A Monthly Chemical Magazine

Latest chemical news, laboratory methods, experiments, formulæ, book reviews, etc. Three trial copies 30 cents. $1.00 per year. Solubility chart and book catalog sent free to immediate subscribers.

Popular Chemistry Company
Dept. D Swedesboro, N. J.

FREE Facts About Gland Failure

DO you know why many men are old at 40, while others are young at 70? Do you know why the prostate gland slows up and why it causes bladder weakness, sciatica, pains in the back, feet and legs? Write today for scientist's new book FREE. Learn just what these symptoms mean. Learn of a new kind of drugless treatment. Learn how 40,000 men past 40 have found quick relief without medicine. Learn facts of priceless value to you. Write now for an interesting illustrated and copyrighted book, "Why Many Men Are Old at 40." Address W. J. Kirk, 4073 Main Street, Steubenville, Ohio. Western address, Suite 40-S, 303 Van Nuys Bldg., Los Angeles, Cal.

RADIO AGENTS Make Big Money

EASY to sell American Radios and Supplies. Nationally advertised, high quality merchandise at wholesale. Big profit on every sale. No capital to invest. No stock to carry. Order direct from my huge warehouse as you sell. Get My Liberal Offer and also Big New 132-page Catalog and Guide—"How to Sell Radios"—Free. Full of Bargains—all latest in Radio. Write today.

AMERICAN AUTO & RADIO MFG. CO.
HARRY SCHWARTZBERG, PRES.
Dept. 286 American Radio Bldg., Kansas City, Mo.

FREE BIG BARGAIN CATALOG

Home Workshop Chemistry

Simple Formulas that Will Save Time and Money

AMMONIA is a colorless gas primarily obtained as a by-product in the manufacture of coke and illuminating gas. Water absorbs about 700 times its volume of this gas at room temperature. As a rule a ten percent solution is known as a concentrated solution. Since it is one of the fundamental chemicals, it may be obtained even in grocery stores.

Large quantities of ammonia are used in the household for cleaning purposes because it acts on grease. Household ammonia may be prepared by dissolving 5 oz. soap in 1 pt. water by heat and adding 2 oz. concentrated ammonia. To make the solution cloudy, add a pinch of potassium nitrate.

Floor wax, to give a polished surface to floors, should be applied in thin coats and



A laboratory rocking device made of toy parts and used in this instance to churn a soap solution for household ammonia

rubbed well in with a weighted floor brush. When a good grade of commercial floor wax cannot be conveniently obtained, a wax may be prepared by dissolving 4 oz. beeswax in 1 pt. turpentine with the aid of heat until the wax melts. Remove from the heat and add 3 oz. of ammonia and about 1 pt. of water. Stir vigorously until the mass is creamy.

A varnish which will withstand the action of ammonia fumes may be prepared by dissolving amber in raw linseed oil at a temperature of 390 deg. C. Heat the linseed oil to this temperature in a sand bath and place a thermometer in the oil. Then add the crushed amber and stir until dissolved. Cool the solution and thin with ozonized (oxidized) turpentine. Such a varnish is useful where the ammonia process is used in freezers.

Use this label as a reminder:

Ammonia
NH_4OH

Keep ammonia in glass-stoppered bottles. Rubber stoppers may be used, but these swell on continual exposure to ammonia. Keep in cool place, as heat tends to drive the gas out of the water.

Ammonia will remove grease and, unlike other caustics, any surplus is dissipated by decomposition and evaporation.

A floor wax may be made by dissolving 4 oz. beeswax in 1 pt. turpentine and adding 3 oz. ammonia and 1 pt. water. Stir until creamy.

Household ammonia consists of 2 oz. concentrated ammonia to 1 pt. thick solution of soap in water and, if desired, a pinch of potassium nitrate to make the solution cloudy.

How to Prolong the Life of a Wooden Miter Box

A WOODEN miter box will last longer and allow more accurate work to be done if holes are bored where the saw cuts



Hardwood dowels are inserted just where the saw kerfs are to be cut in the miter box

are to be placed and hardwood dowels are glued into them, as illustrated. When the glue is hard, the guiding saw kerfs are made vertically through the dowels.—IRVIN L. MORROW.

Adding a Room to Your House

(*Continued from page 94*)

effervescence on the cement, we scraped it off and washed the surface with a solution of zinc sulphate and water—three pounds of zinc sulphate to a gallon of water. When the walls were dry, we applied three coats of concrete building paint, tinting it to match the wall paint used on the wallboard. For the first coat we thinned the paint with about twenty-five percent of turpentine, and each coat was allowed forty-eight hours to dry.

"Then there remained the woodwork—window frames and sashes, doors, stairway and also the radio cabinet, benches and tea cart which had been delivered to us unpainted. These were done in enamel. For the first coat we used flat wall paint of a sage green color similar to the enamel that was to follow. For the second coat we used half flat wall paint and half enamel, and for the finishing coat, enamel.

"For the floor we used concrete floor paint—three coats, the first being thinned liberally with turpentine. It was given a final finish with floor wax. And that is about all there was to it," she concluded. "Our card club had its meeting here last night, and everyone thought it was a wonderful room."

We agreed heartily with this verdict.

"It is a wonder," I said, "that more home owners who have reasonably large, dry and airy basements, don't try to do something with them. If there are boys in the family, the basement can be made into a comfortable and attractive place for them to work and play."

"Yes," rejoined Mrs. Andrews, "when you are hard pressed for an extra room, the basement is the place to look."

MANY times it is necessary to cut down a cork to fit a bottle or plug a hole. A smoother job can be obtained by rubbing the cork over a piece of coarse emery cloth than by attempting to cut it with a knife. If a hole has to be made through a cork, a good tool is a sharp piece of tubing.—RUSSELL W. FOWLER.



for the
LINDBERGHS *and*
CHAMBERLINS
of **America**

TO you young men of the type that gives to America its Lindberghs and its Chamberlins, the motorcycle has a special appeal. It appealed to Col. Charles Lindbergh, who is a motorcycle enthusiast, and Clarence Chamberlin, who was a Harley-Davidson dealer, because the motorcycle is a spirited mount. It has personality. It inspires clear thinking and clean living. It appeals to red blood, a love for action, and a healthy spirit of adventure.

A ride on a Harley-Davidson is recreation in one of its most healthful and pleasant forms. Ride a few miles and see!

Prices as low as $310 for the Twin—$235 for the "80 miles per gallon" Single, f. o. b. factory. See your dealer for demonstration. Send coupon for catalog.

HARLEY-DAVIDSON MOTOR COMPANY
Department P. S. Milwaukee, Wis.

Plenty of room in the sidecar for your outfit or a pal.

HARLEY-DAVIDSON
Motorcycles

Twins and Singles in a wide range of prices.

Harley-Davidson Motor Company
Dept. P. S. Milwaukee, Wis.
Interested in ☐ Twin ☐ Single
Send catalog and full details.
Name
Address

Worn Roofs
made watertight

IT'S easy now to keep your roofs watertight. Rutland No-Tar-In Roof Coating makes an old roof as good as new. No trouble at all to apply—costs little—and makes a *lasting* job.

Rutland No-Tar-In provides a perfect coat of asphalt and asbestos—*a tough mineral covering*. Not a drop of tar in it. It will not crawl, sag, harden, peel or blister. For any roof or surface.

Insist on Rutland at your hardware or paint store. Save money by mailing the coupon today. Rutland Fire Clay Co., Dept. R-13, Rutland, Vermont.

Rutland
No-Tar-In
ROOF COATING

RUTLAND FIRE CLAY CO.,
Dept. R-13, Rutland, Vermont.

Send me more information about No-Tar-In.

Name .....

Address .....

.....

It's Easy to Build Things!
—when your ripping, mitering, grooving, etc., are done on the
Boice-Crane Handisaw

Made in two sizes. Swings saws as large as 8" to cut 2½" stock. Attachments for grinding, dadoing, sanding. Driven by any ⅛ to ½ h. p. motor. Attaches to light socket. Sold with or without motor. Send 10c for descriptive catalog of bench saws, drills, jointers, band saws, and lathes.



W. R. & J. E. Boice
Dept. P.S.9-C
Toledo, Ohio

Sport Bodies for Fords
at FACTORY PRICES!

This Model in Grey Prime $39.50
Write for Booklet A-10 Showing Other Models.

SPORT FACTORIES, Aurora, Illinois

Draft Regulator Protects Boiler

By P. T. Saul

AS A protection for the boiler of a high school heating plant, an automatic draft regulator was installed as shown below. Such a device would be a valuable addition to any similar plant where there is danger of a mishap occurring while the engineer is attending to duties away from the boiler room, or, indeed, as a protection for the boiler of a low pressure heating system. This installation was designed after an accident happened. A fuse blew, the electric boiler feed pump stopped, and all the water



If the feed pump fails, pail A fills with water and causes the draft door to close

evaporated and wasted through the air relief valve when no one was watching the boiler. As a result, the crown sheet cracked.

When the feed pump fails to operate for any reason, the water now backs up the return lines until it escapes through the air relief valve of the heating system. If as much as a quart of water escapes into the small pail A, it overbalances the weight B and trips lever C, which releases the draft door so that it shuts.

A very small hole in pail A allows the water to flow out slowly after the draft has been closed; weight B raises the pail, and lever C can be again hooked up.

Milling Cutter Acts as Guide in Drilling an Index Plate

RECENTLY I was given an order to make as cheaply and quickly as possible a 3¾-in. index plate with 34 holes for experimental work. Variations of .015 in. on the entire circle would be acceptable.

Plate with milling cutter clamped to it

First I found in the tool crib a milling cutter that appeared to be a good milling job and was of the right diameter and number of teeth. Then I turned the

(*Continued on page 117*)


The SOLDER of 1000 uses
YES, and even more than a thousand uses. Kester Metal Mender solders metal as easily as glue sticks to paper. The skill is all in the solder—requires only heat.
In the average home there are innumerable metal articles from attic to cellar. Some are absolutely unserviceable for the lack of a touch of Kester Metal Mender.
You know these things need attention, and yet to have some one fix them would probably cost as much as replacing the articles.
A touch of heat and a touch of Kester and the job is done. It's so easy to use Kester that soldering has become an interesting and profitable fad for thousands of people.
Buy a can from your hardware dealer, general store, auto supply shop or druggist.
Free Sample upon request
KESTER METAL MENDER
The Household Solder
CHICAGO SOLDER COMPANY
4209-09 Wrightwood Ave.
Chicago, U. S. A.

DYKE'S AUTOMOBILE ENCYCLOPEDIA

Entirely Rewritten, Rearranged and Illustrated. Greatly Enlarged; 1238 Pages, 4143 Illustrations.

A PRACTICAL BOOK FOR EVERYBODY

The Repairman will find this book a ready reference and guide.
The Auto Owner will know how to diagnose troubles and know when repairs are done *right*.
The Student learns the fundamental principles, the key to a successful repairman.

This Book Will Teach you to Become

An *Expert Automobile Repairman*, not only on *testing, adjusting and repairing* engines, carburetors, ignition, rear axles, differentials, tires, etc., but an *Electrical Expert* on ignition, generators, starting motors, storage batteries, etc. Diagnosing any trouble will be easy.

DON'T WAIT—*Order Now!*

Cloth $6
Limp American Morocco $7.50
Postpaid

POPULAR SCIENCE MONTHLY
250 Fourth Ave. New York City

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Milling Cutter Acts as Guide

(Continued from page 116)

plate and clamped both together on a short ¾-in. stud. I set the combination on two parallels on a small drill press and, using the bottom of the teeth as a guide, located the holes with a center drill.

The milling cutter was removed and the plate drilled with holes of the proper size. Work indexed with the plate was tested and the variation was found to be only .007 in.—H. C.

Simple Shop-Made Chuck for Hole Grinding Operations

IN THE illustration is shown a finished circular stamp, the hole of which had shrunk so that it had to be ground out. To hold it a chuck was made that has since proved practically indispensable.

Two pieces of machine steel, one 4 in. in diameter and 3 in. long, and the other



The grinding fixture with disk removed to show how the work is located and held

3½ in. in diameter and ⅜ in. thick were turned, bored and finished on their faces. The main member has three equally spaced 5/16-in. pins for keeping the disk concentric. In the disk are two small pins to hold the work as the screws are tightened. Two headless screws placed in the two extra holes serve the same purpose when work with a larger hole is held.—O. S. MARSHALL.

Uses Old Automobile Motor for Building Hoist

FROM a discarded automobile motor which cost twenty dollars and other parts worth less than five dollars, plus twelve hours' work, I constructed the



Constructed at a cost of $25, this hoist is used to pull coal in cars up an incline

hoist illustrated. This cost did not, of course, include the rope.

The hoist has been used to pull coal in cars up an incline as well as for other purposes.—C. E. WALTON.



All for One

An Advertisement of the American Telephone and Telegraph Company

A SLEET storm descends, carrying down trees and wires. A wind turns outlaw and blows down a pole line. Or some swollen river rampages through a circuit of destruction.

But wherever angry nature attacks the Bell Telephone System there are repairmen trained to meet the emergency, and everywhere trained in the same schools to the use of the same efficient tools. Supplies of surplus equipment and materials are kept at strategic points whence they may be rushed by train or truck to the devastated area.

Throughout the Bell System, all construction and practice are standard, so that men and supplies, when necessary, may be sent from one state or company to another.

There are twenty-five Bell Companies, but only one Bell System—and but one Bell aim and ideal; stated by President Walter S. Gifford as:

"A telephone service for this nation, so far as humanly possible free from imperfections, errors and delays, and enabling anyone anywhere at any time to pick up a telephone and talk to anyone else anywhere else in this country, clearly, quickly and at a reasonable cost."



SPECIAL
Porcelain Enameled SINK $28.25
One of many bargains
Write for Plumbing Catalog. Save 40%
B. KAROL & SONS CO.
Dept. 36, 800 So. Kedzie Chicago

ZIP-ZIP SHOOTER
CAMPERS AND TOURISTS:
Here is the very thing for you; campers tell us that this is the greatest weapon to be had where fire arms are prohibited. Zip-Zip Shooter is noiseless, powerful and effective and is used by a great number of tourists and campers. Thousands of boys are made happy with this wonderful Zip-Zip Shooter. If your dealer happens not to have them order from us. Zip-Zip Shooter 35c or three for $1.00. Send stamps, coin or money order.
Automatic Rubber Co.,
Dept. B.B., Columbia, S.C.

BURN YOUR NAME ON TOOLS
WITH THE
ARKOGRAF
Protect Your Tools From Theft. Write with electricity any name or design on the hardest and finest tools and instruments, or any metal, like writing on paper with pen or pencil. Complete Outfit $3.50 Prepaid Anywhere. Interesting illustrated circular free. Write today. Agents wanted.
ARKOGRAF PEN CO.
1171-A East Stark St., Portland, Oregon

TWO FREE BOOKS
Breed squabs and make money. Sold by millions at higher prices than chickens. Write at once for two free books telling how to do it. One is 40 pages printed in colors, other 32 pages. Ask for Books 3 and 4. You will be surprised. Plymouth Rock Squab Company, 616 H Street, Melrose Highlands, Massachusetts.

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

STAR Hack Saws are known the world over to be good and they are used in every country on the globe.
They will meet your requirements also, even on your toughest jobs. You can prove that Star blades are what you need for we will send you sample blades to try.

FREE:—Let us mail you our large hack saw chart to be placed on the wall for handy reference.

TRADE MARK

HEADQUARTERS for HACK SAW BLADES
Since 1883
CLEMSON BROTHERS, INC.
MIDDLETOWN, NEW YORK

STAR HACK SAW BLADES

Illuminated Table for Tracing Blueprints

TO MAKE a tracing on either cloth or thin paper from a blueprint, especially from a blueprint that has been made from a pencil drawing, is always difficult. The work becomes relatively easy, however, if the blueprint is laid out



Sectional view and sketch of the top of a shop-made table for difficult tracing jobs

on a sheet of glass and illuminated from below.

A glass table for this purpose was built in one drafting room, as shown in the accompanying illustration. A sheet of transparent paper was tacked beneath the frame to diffuse the light. The size and method of construction, of course, can be varied to meet individual needs. —E. L. GARFIELD.

Pencil Holder for Dividers Made from Washer

RECENTLY, when I lost the elaborate pencil attachment ordinarily used with my dividers, I made another from a washer as shown. A notch was filed inside



How the washer was filed to fit the dividers and fastened in place with the pencil and a match-stick wedge

the washer to fit a leg of the dividers and part of the outside circumference was filed off to reduce the size of the attachment. It is held in place by the simple expedient of wedging a bit of match stick tightly against the pencil.—F. B.

The Vest Pocket Lawyer

A complete law course—clearly analyzed in understandable English. It is a daily guide—a manual of reference for the business man—the law student—the justice of the peace—the notary public—the farmer—the clergyman—the merchant—the banker—the doctor.

360 pp. Price $1.50, postpaid

POPULAR SCIENCE MONTHLY
250 Fourth Avenue, New York City

FREE TO BOYS

"THE SHOOTER'S ART" Send Now!

Tells how to hold, aim and handle rifles; helps you guide others in correct knowledge of guns. **Gives facts that make crack shots.** Contains safety and common sense instruction every parent and boy should have. **Helps to make boys leaders.** Your copy Free. Write at once.

The Shooter's Art

The NEW BENJAMIN AIR RIFLE Outshoots All Others

America's Original Air Rifle

$5 *at your dealer's or sent postpaid. Write!*

BENJAMIN Air Rifle & Mfg. Co., 629 N. Broadway, St. Louis, Mo.

NEW MODEL 9-in.
South Bend Jr.
Back Geared, Screw Cutting, Precision BENCH LATHE Complete with Plain Rest, Countershaft, and Equipment $160

Truing Commutators One of Many Auto Service Jobs for a Lathe

Illustrated above is a lathe tool truing an armature commutator. This job is only one of hundreds that can be done quicker, better and with greater profit on a South Bend Junior Lathe. The Junior Lathe is today the outstanding tool for the auto service shop. Sold complete with countershaft and equipment, or may be had with complete motor drive that plugs into ordinary lamp socket.

FREE—NEW BOOKLET

24-page booklet No. 22-K, dealing exclusively with the 9-in. Junior Lathe. 159 photographs; actually illustrates more than 30 auto jobs. *Mailed free to any address.*



South Bend Lathe Works
830 E. Madison Street
South Bend, Indiana

Time Payments if Desired

You Asked For It—Here It Is!

What the Radio Buyer Should Know

a radio booklet that tells How to Buy, Install and Operate for Best Results

Do you know just what you can expect in the way of radio reception, how much you must pay, how you can cut down this cost, and what equipment is reliable?

These are some of the questions answered in the new radio booklet just published by the Popular Science Institute of Standards after numerous requests from readers.

Full instructions on installation are included and ten pages of hints on operation tell you how to operate and care for your set so as to get utmost out of your radio investment.

Price 25 Cents

Popular Science Institute
250 Fourth Ave., New York City

IS This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Compact Angle Iron Rack Holds Great Many Tools

THE tool rack illustrated is used to hold a large number of tools such as hammers, tongs, and wrenches over a small floor space.

It is built of angles, the posts being 2 by 2 in. and the other members 1½ by

A rack 6 ft. long and less than 7 ft. high used as storage place for 2 tons of various tools

1½ in. The cross angles are double, with a space between to receive tool handles. The slots are staggered so that long handles hang down between the slots of the row beneath. Between the uprights is a space that may be used for crowbars.

The dimensions of the rack will be determined, of course, by the space available and the tools to be cared for. That in the illustration is 6 ft. long and less than 7 ft. high, yet it holds more than two tons of miscellaneous tools, including more than 1200 hammers.—O. H. K.

Simple Method of Indexing Welded Gear Teeth

WELDING shops not equipped with milling machines or index centers will find the kink illustrated useful for laying out teeth on gears which require some of their teeth to be replaced with welded metal.

A short piece of rod that fits the tooth space is held in two clamps on a surface



A rod held in two clamps on a surface plate aids in indexing new teeth on a welded gear

plate. The gear is rested on the plate and on the rod. The surface gage is set to the center line of one of the good teeth, after which the gear is indexed so that another space rests on the rod. Then the surface gage may be used to scribe the center line of one of the teeth to be cut.—H. M.

NOW! MAKE THINGS AT HOME
WITH THE NEW RED JACKET HOME WORK SHOP

SENT ON TRIAL



only $10.00 down

THE HOME CRAFTSMAN'S LATHE WILL MAKE YOU A CRAFTSMAN

A COMPLETE SET OF PRECISION TOOLS electrically driven that will make you an accomplished workman. It is a chest full of tools that has been designed by a master for the private use of tool lovers and men who want to build, construct, invent and create at home. You will be able to make everything—attractive odd furniture, toys, home and garden improvements, all around manufacturing, repairing.

The WACO Guarantee
If It Is Not What You Want When You Get It—Send it Back

Special Crafts Course
And blueprint service is free to Red Jacket Shop owners—all that there is to know about handicraft methods, raw materials, woods, carving, sawing, turning, designing, carpentering, decorating, is taught by special correspondence.

Buy on your Own Terms
Only $10.00 down. Liberal discounts for cash. Easy monthly payment plans. It is no hardship to own a Red Jacket.

Interesting Literature Free
Just send the coupon. You will be surprised with all it contains. Beautiful, Instructive, Fascinating, Interesting.
Everything Explained in Our Literature

free CRAFTS COURSE

free BLUE PRINTS

The complete equipment consists of the powerful Red Jacket Motor, with direct drive to an accurate wood turning lathe (capacity 9 in. x 34 in.); a bench saw, that has depth and side gauges; scroll and jig saw; and all accessories for both portable and stationary power drilling, buffing, grinding and cleaning. Attaches to any light socket and converts your work bench into a complete private tool and machine shop.

10 DAYS' FREE TRIAL
Our literature tells you how to start a job of your own. If you are not pleased return the Shop.

2 OUNCES
of interesting reading will be sent you gratis. Send the coupon below. Sit back—see what we send you. It's free.

Turning
Sawing
Winding
Spinning
Grinding
Buffing
Polishing
Cabinet Making
Scroll Sawing
Drilling
Repairing
Dove tailing
Pointing
Jointing
Sharpening
Sanding
Scratching
Carving
Successful Masterpieces

WACO TOOL WORKS, Inc.
542 No. Parkside Ave., Chicago, Illinois.
Manager, Dept. 9. Please send me particulars about 10-day free trial, free blueprints, and $10 down payment.

Name .....

Address .....

MAKE MORE MONEY READ MONEY MAKING OPPORTUNITIES ON PAGES 124 TO 151 OF THIS ISSUE

Build and Fly a 3-ft. Model of
LINDBERGH'S
NEW YORK—PARIS
MONOPLANE

This IDEAL New York-Paris Monoplane is a perfect copy, 3-ft. size, of the machine in which Lindbergh crossed the Atlantic Ocean. Any bright boy can build this model: The IDEAL Construction Outfit contains everything needed; all parts, fittings, materials and supplies, including careful instructions, plans and diagrams. The model is wonderfully has many features of the original and is guaranteed to fly. Complete Construction Outfit..... $7.50
[West of Denver, Colo., and in Canada, price is $8.00]
Ask your dealer or order direct. Plans and instructions Only (No materials included) Postpaid 25c

Plans for Other Model Airplanes 25c per set
FOKKER North Pole Plane
CURTISS J N 4 D-2 Plane
DeHAVILLAND World Flyer
NC-4 Naval Seaplane
Bleriot, Nieuport or Taube Monoplanes
Cecil Peoli Racer Plane
[All 8 plans for $1.50]

IDEAL AEROPLANE & SUPPLY CO.
163-165 Spring Street, New York City

Catalog of Model Airplanes, Parts, Supplies, etc., 5c postpaid

before
you buy a home movie camera
see Pathex
AUTOMATIC CAMERA AND PROJECTOR
MADE BY PATHÉ
better results-less cost

Demonstration at your Dealer
free booklet
PATHEX INC.
35 W. 45th ST., NEW YORK CITY

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Licensed by Rider
Radio Corporation
Pats. Pending
Pat'd 5-8-'16; 7-27-'26

Modernize Your Set

PHASATROLS

An Effective Stabilizing Device for Radio Frequency Amplifiers

Price $2.75

Thousands of fans are solving their problems of R. F. oscillation by installing Phasatrols. By controlling oscillations this instrument suppresses the squeals and noises they cause. Applicable to most R. F. receivers. Very simple to install.

At Your Dealer

Send for special pamphlet listing various circuits.

Dept. 64A
175 Varick Street, New York, N. Y.

ELECTRAD

Victoreen "112"
Audio Transformer Unit

New, because for the first time two scientifically developed audio transformers are successfully combined into one unit, giving utmost simplicity and efficiency.

Different, because of its radically different design and the recommended use of two "112" tubes, with high plate voltage.

Better, because for the first time, broadcast programs are reproduced with the same clarity and naturalness as is heard in the original.

Simple to install in either new or old sets

Price $22.00

Victoreen R. F. Transformers, Master Control Units, Rheostats, Potentiometers and Audio Control Units are the recognized standard of quality. Send for complete folder.

The Geo. W. Walker Co.
Merchandisers of Victoreen Radio Products
6528 Carnegie Avenue, Cleveland, Ohio

How to Obtain a Light Driving Fit Quickly

CAREFUL work and considerable time often are required to get the dimensions just right for a light driving fit in order to obtain the desired amount of friction. In many cases the expense of obtaining such a fit is inordinately high.

One method that will solve the problem in a good many instances is illustrated below. It cannot be applied where the outer piece is hardened or has a considerable wall thickness, but there are innumerable cases where it can be used to advantage. It consists in compressing



A plain compression fit is illustrated below and a light compression "key" at right

a small portion of the outer part down upon the internal piece. This can be done easily in a vise by using a stout nail set with a large point, or a pin punch with a slightly concave end. The heavy pressure concentrated upon the small surface so compresses the metal locally that the pieces are held firmly together.

The same method can be used to key two pieces together by providing a groove in the internal piece of a width equal to or slightly less than that of the point of the tool, the displaced metal thus being pushed into the groove. In either case the hold can be increased by compressing the metal at several different points.

This method can be used wherever the thickness of the outer wall does not exceed ¼ in. It can be applied to work having even thicker walls by first drilling a hole until between ⅛ and ¼ in. of wall is left and then applying the pressure.

Clamp for Holding Small Round Finished Parts



A tool used in the vise for holding parts which require to be filed, threaded or slotted

THE tool for holding small round finished parts, illustrated above, is ½ by 2 by 4 in. with holes from 3/16 to ⅝ in. in diameter. After the holes are drilled and reamed, the plate is milled in three sections with a 1/16-in. saw. The ¼-in. holes at the ends are counterbored to 5/16 in. diameter and ¼ in. deep to receive the springs.—H. J. C.

Build This Gorgeous SPANISH GALLEON

Complete Instructions and Plans Only $1.00

One of the most colorful and beautiful of ship models—designed for Popular Science Monthly by the famous model builder Captain E. A. McCann. Anyone can make it who can use tools. We supply complete description and instructions, together with photographic reprints of important parts, and a reproduction of the galleon in full color, complete detail charts, together with two full size Blue Prints. All mailed postpaid in a handsome container for only $1.00.

Materials will cost only about Five Dollars. Your model, when completed, may be worth $250.

Send check, money order or dollar bill.

Book Department
POPULAR SCIENCE MONTHLY
250 Fourth Ave.
New York



THIS 100 PAGE RADIO CATALOG FREE

Contains
75 Radio "Hook Ups"
500 Illustrations
Over 1,000 Articles

"Build your own with "RASCO" Parts"
Radio Specialty Co., 96-P Park Place, New York, N.Y.

BIG RADIO CATALOG
From the "Big, Friendly Radio House"

NEW 1928 Book offers finest, newest well-known sets; parts, eliminators, accessories at lowest prices. Set-builders, dealers, agents—WRITE for this CATALOG!

Western Radio Mfg. Co.
130 West Lake Street—CHICAGO, ILL.

The Electrician's Wiring Manual

By F. E. SENGSTOCK, E. E.

Contains all the information needed for the proper installation of lighting and power systems in houses and other buildings.

It completely covers inside electrical wiring and construction in accordance with the National Electric Code. *Pocketsize—flexiblebinding*

448 pp. **Price, $2.50**

POPULAR SCIENCE MONTHLY
250 Fourth Ave., New York City

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Triple Center Punch for Laying Out Dies

WE HAVE used center punches with two points for some time on die work. Still better is a punch with three points; by its use the scribing of one line may be avoided.

The illustrations show the manner of

Center punch with three points, which saves time in marking the centers of holes to be drilled close together in a die for removing the waste metal core



laying out holes preparatory to drilling out the center of a die when using the three-point center punch. The punch is held with two points on the line and struck lightly, making three marks. It is then turned to bring the inner point on the outside line. As one point remains in the mark previously made by it, the tool, when struck again, makes two additional marks. This process is repeated all along the line.

To make the tool, three small center punches are required. They must be exactly alike and hardened and ground all over. These are forced into one end of a sleeve, and a rod is driven into the other end so as to touch the upper ends of all three punches.—H. MOORE.

Welding Torch Used to Bush Holes in Foundry Flasks

FOUNDRIES specializing in high class castings must have flasks with accurately fitting pins, or else there will be an objectionable offset on the castings. Small steel flasks are frequently used for this work; however, in time the pinholes must be refitted.



Flask hole to be repaired by welding

Rather than bush these holes, one foundry found that it could ream out the pinholes and fill them up solid with steel or bronze welding rod more economically. Afterwards a new pinhole is drilled in the welded metal.—A. S. JAMIESON.

AN OLD piston ring, if slipped over line shafting in a shop will move from end to end and scrape the shaft clean.—GLENN L. BROWN.

The Outstanding Radio Power Units

What does it mean to you that over fifty leading manufacturers of light socket power units submitted their designs to the Raytheon research laboratories for approval and right to use Raytheon long life rectifying tubes? Just this—that Raytheon's technical personnel and unusual scientific facilities in conjunction with the use of the Raytheon rectifier are invaluable aids in the making of a *reliable* radio power unit.

Look over the Raytheon-approved devices. They are the outstanding radio power units by reason of their highly dependable performance. Today, over 700,000 receivers are performing at the height of their efficiency by being powered with Raytheon-approved light socket power units.

Your dealer can show you a Raytheon-equipped unit exactly suited to the needs of your receiver.

RAYTHEON MANUFACTURING CO.
CAMBRIDGE, MASS.

DESIGNED FOR USE WITH Raytheon LONG LIFE RECTIFYING TUBE

When you see this green Seal of Approval on a power unit you know that it is a Raytheon-approved unit and can buy it with full confidence in the integrity of its makers and the performance of the device.

Raytheon
THE HEART OF RELIABLE RADIO POWER

CARTER
as usual
is ready for the latest developments in the Industry.
R. C. A., Cunningham and other A. C. Operated Tubes.
Rheostats, potentiometers, and adjustable resistors (semi-variable).
In Canada, Carter Radio Co., Limited, Toronto
MEMBER RMA Carter Radio Co. CHICAGO

More than HUMAN
The only automatic self adjusting filament control, supplying at all times just the current your tubes require. Insures 100% tube performance. Safeguards against damage. Eliminates hand rheostats. Simplifies wiring. Insist on Amperite. Refuse substitutes claimed just as good. Price $1.10 complete.
Radiall Co., 50 Franklin St., New York City
Write Dept. PS9 for FREE Hook-Ups
AMPERITE
REG. U. S. PAT. OFF.
The "SELF-ADJUSTING" Rheostat

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Dubilier

Light Socket Aerial



All You Need Today—

Five years ago we needed all the aerial we could swing to bring in uncertain broadcasting on our little two tube sets—but today it's different!

Screw a Dubilier Light Socket Aerial into the nearest 110 D.C. or A.C. outlet. Connect it to your receiver and listen! The static is about gone, interference is reduced and you've done away entirely with sooty aerials, lead-in wires, ground switches and lightning arresters. The device consumes absolutely no current and needs no attention whatever.

Price $1.50



The New Dubilier Micadon

The famous "Standard Fixed Condenser of Radio" in a more modern shape, and more efficiently insulated by its new case of molded Bakelite. Terminals are adaptable to either screwed or soldered connections.

Lowest dielectric loss
Lowest variation in capacity
In all capacities . . . Prices $.45 to $.85

Dubilier Condenser Corp.
4377 Bronx Blvd. New York

Dubilier

System in Surface Grinding

(Continued from page 78)



The snap gage selected as an example of the problems encountered in surface grinding

centered, and both ends hardened. Then they are ground cylindrically straight and finished to the exact lengths in a V-block.

The operator should study his drawing and check up all dimensions for stock, as removing too much off one side may have some effect on the dimensions near by and perhaps spoil the gage. Each length should be ground a snug fit to the rod and slightly stoned to the proper finish.

The procedure in this case is as follows: After grinding the thickness of the gage so as to have a parallel surface to start with, the regular gage grinding wheel is mounted and dressed as described before. Do not stop the wheel, if it can be avoided, once it is ready for grinding.



This dovetail forming tool involves the additional problem of grinding angles exactly

As indicated in the drawing of the gage, the top A-B is ground first, then steps C-D-E; side F is merely squared up and the 2.470 dimension is finished at the opposite side. By retaining the measuring rod in position and using a plug gage, the .343 dimension is finished from H. Next, side I is ground until the 4.281 dimension is obtained. If these three lengths are correct, evidently the length 1.468 is also. The other side is ground as previously outlined after squaring end J. Naturally, when grinding small surfaces such as H, one must feed very lightly.

Dovetail forming tools, although made of specially selected steel, will be changed more or less through hardening. It is necessary, therefore, to grind them all over.

The correct wheel is absolutely necessary, as sharp corners must be maintained. The wheel must be of a very fine grain, hard enough to stay sharp but still not heat the tool in the least. For high speed steel tools a 100-J is satisfactory, as no more than .001 in. should be removed at a time. In close quarters it is often necessary to feed downwards instead of using the cross-feed. The amount allowed for grinding should be about .006 in.

A dial indicator is used for taking the depths; the widths are measured with plug gages. In this case a wheel 3/16 in. wide is used. It is advisable to dress the wheel after grinding each dimension so as to have square corners at all times. Before beginning, however, the bottom and two sides of the form must be squared up with a 60-G wheel and the form checked for stock on all dimensions.

As shown in the drawing of the tool, the top A is ground first, removing .006. Depth B and width C are finished next, then depth D and width E. F is then spotted on the inside and the wheel worked downwards to the proper depth G. In feeding downwards, no more than .0005 should be removed at a time. Depth G and width H are finished and the top of F ground to the correct step (J). In grinding depths D and G, measurements are taken from A.

The two angles now remain to be ground. An illustration on page 78 shows how the angle is formed on the wheel. If a wheel has already been used for this purpose, it should be used again, if available, to reduce the cost. The wheel should be wide enough so as to have ½ in. flat after forming.

The fixture used, which is shown in detail below, is set at the proper angle with the protractor. It should be as nearly as possible radial with the wheel.

When the dressing operation has been completed, the wheel is dropped so that it comes barely in contact with depth D, and is worked towards angle K until the flat surface left by grinding width E is removed. The wheel is then reversed and the angle touched up again by clamping the fixture upwards at the same angle.

Angle I is now finished as previously outlined. The forming tool is next laid on the side and the total width M is finished from what is the right-hand end in the drawing. This last operation also finishes width F. If all dimensions are ground exactly, including both angles, the top and bottom dimensions of the angular section should be relatively correct.

Another article by Mr. Chamberland on the surface grinder is scheduled for early publication.



A tool used for forming angles on grinding wheels. It is illustrated in use on page 78

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6.

Blasts That Saved a City

(Continued from page 22)

Great Northern Railway completes the Cascade bore in Washington, it will be the longest railroad tunnel in the western hemisphere, 7.79 miles from portal to portal. Here two crews in a bore eight feet by nine feet race toward each other, one recently making a world's record of 1,157 feet, almost four city blocks, in thirty-one days.

Every second, somewhere in this country, twenty pounds of explosive is fired. Sometimes it strikes back at those who make and use it. It must be treated with respect, especially during the processes of manufacture. The base of dynamite, for example, is ordinary glycerin. When this is mixed with nitric and sulphuric acid, heat is formed; even a slight jar would set it off. The operator glues his eyes to the thermometer until mixing is completed. Even more hazardous is the separating process, done by two men in an isolated house, surrounded by earth barricades, to which the nitroglycerin is run in lead-lined troughs. Here the mixture can be agitated with compressed air to cool it. The men who carry small tanks of this mixture in so-called "angel buggies" break no speed laws. It becomes insensitive to shock when forty percent or more is mixed with wood pulp, cornstarch, cotton or other cushioning elements. Straight dynamite, the most shattering, is the most sensitive, containing ninety-two percent of nitroglycerin.

THE mixing is done under roller wheels. In the packing house an automatic machine tamps the brown, sugary mass into paraffined shells of paper, and twenty-five to fifty pounds are placed in a box. One large plant ships sixty million pounds annually. Dynamite produced today will withstand zero temperature, and dangerous thawing is eliminated.

"The normal hazard of making dynamite," Charles S. Hurter, a technical expert, told me, "compares favorably with that of other large industries. But an accident in a dynamite factory naturally makes more noise. Millions of pounds are mixed, beaten, washed, moved, shaken, tamped and transported safely.

Dynamite even goes to sea, I was informed by Mr. Russell. "As much as half a million pounds have been shipped to South America on a single ship, with no special precautions beyond packing the boxes close together and labeling them. Not long ago a cargo of potash caked in the hold of a ship was dynamited loose—perhaps the first such instance in history. In the sea lanes dynamite is often used against small icebergs and derelicts. A Newark, New Jersey, shark-leather concern tried hunting sharks with dynamite, using raw meat for bait. The first shot brought a dozen large sharks to the surface, dead, and dynamite is now used exclusively. Whalers use a 'killing lance' with a small explosive in its tip."

Nor are mosquitoes immune from this universal weapon; New Jersey salt marshes are drained by ditches made with dynamite.

EMERGENCY or unusual uses of dynamite often save lives and property. Snow in high mountain passes has been removed. Huge caissons have been jarred into their holes by small charges. Nuts and bolts have been removed from tight places in machinery, wells have been sunk, and others made to flow more freely. Woodchucks, prairie dogs and gophers have been killed. For motion pictures dynamite furnishes smoke screens, shell fire and artificial geysers.

Drilling oil wells, especially dry ones, costs fortunes; a well reaching down two miles may cost $300,000. The use of dynamite in the oil fields, however, removes much of the risk.

Truly, dynamite is the modern genie of the bottle, willing to burrow in the earth, lift rock under water, even quench roaring fires, at the bidding of its masters!

21 JEWEL~Extra Thin

STUDEBAKER

The Insured Watch

Sent for Only $1 DOWN

Direct from Factory



You Save 30% to 50%

An amazing offer! Just $1.00 down brings you the famous 21 Jewel Studebaker Watch direct from factory. Balance in easy monthly payments. You save fully 30% to 50%. Lowest prices ever named for equal quality. Send coupon below for catalog of Advance Watch Styles and full particulars.

This amazing offer enables you to pay for your watch while wearing it. Studebaker Watches have 21 Jewels, genuine rubies and sapphires, 8 adjustments—for heat, cold, isochronism and five positions. Insured for your lifetime! Insurance Policy given FREE! Ladies' Bracelet Watches, Men's Strap Watches, Diamonds and Jewelry also sold direct to you at lowest prices and on easy monthly payments. Open a charge account with us. Send the coupon.

WRITE for FREE CATALOG

The coupon below will bring you a copy of our beautiful, new six-color catalog showing 80 magnificent, new Art Beauty cases and dials. Latest designs in yellow gold, green gold and white gold effects. Exquisite thin models. 12 size and 16 size. Buy a 21 Jewel Studebaker Insured Watch direct from the maker—save big money and pay for it in easy monthly payments.

Special Limited Offer: Watch Chain Free

For a limited time we are offering a Magnificent Watch Chain Free. To all who write immediately we will include particulars of this astounding special offer. This offer is limited. Send the coupon at once—before it expires.

STUDEBAKER WATCH COMPANY

Directed by the Studebaker Family—three-quarters of a century of fair dealing

WATCHES DIAMONDS JEWELRY

Dept. V-805 • South Bend, Indiana

Canadian Address: Windsor, Ontario

Save on Ladies' Bracelet Watches and Strap Watches for Men. Both are sold on the easiest kind of payments!

Mail Coupon at Once While This Offer Lasts

Studebaker Watch Co. Dept. V-805 South Bend, Indiana

☐ Please send me your free catalog of Advance Watch Styles and details of your $1.00 down offer. ☐ Please send me free catalog of Jewelry and Diamonds.

Name .....

Street or R. F. D. .....

City ..... State .....

An *Easy-to-build* Bookcase

IF YOU have not had much experience in woodwork, you will find the bookcase illustrated one of the few really attractive and useful pieces of furniture that you can construct without a single difficult joint. The parts are put together with butt joints such as are used in making common boxes; there is not a dowel, a mortise and tenon, nor a dovetail used in the construction.

The unique methods by which the construction has been simplified are not apparent, however, in the finished bookcase. The design is good and will stand comparison with the better class of bookcases sold in furniture stores.

Blueprint (No. 37) of the bookcase will be sent on receipt of 25c.

POPULAR SCIENCE MONTHLY, 250 Fourth Av., New York

This seal on a radio, tool or oil burner advertisement signifies the approval of the INSTITUTE OF STANDARDS. See page 6

Money Making Opportunities
for Readers of Popular Science Monthly

Advertising Services

ADVERTISE in 24 metropolitan dailies, 24 words, $15.00. Helpful Guide listing 1000 publications, 4c stamps. Wade Company, Baltimore Bldg., Chicago.

24 WORDS,-151 rural weeklies, $6.04. Ad-Meyer, 4112P Hartford, St. Louis, Mo.

ALL Advertisers should not be without the important facts on Money Making. Write today for the "Quick-Action Advertising Rate Folder" which contains information of value to you. If you are anxious for quick profit returns, do it now! Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Ave., New York.

EFFECTIVE letters and advertisements for honest propositions. Edwin Brown, Box 95, Oak Park, Sacramento, Calif.

FOUR Hundred Rural Newspapers, 30 Words, $12.65. Thompson Service, 818 Oak St., Cincinnati, O.

40 WORDS insert 60 magazines $2.00. Empire Agency, Shawano, Wis.

Authors, Song Poem Writers, Manuscripts

SONG Poem Writers—Send for proposition. Ray Hibbeler, D10, 2104 N. Keystone Ave., Chicago.

SHORT stories, articles, etc., revised, typewritten, marketed. Hursh Service, Dept. 3, Box 1013, Harrisburg, Pa.

I WANT song poems. Casper Nathan, J-3544 No. Racine, Chicago.

"MUSIC Composed" to words. Bauer Bros. (formerly of Sousa's Band), Oshkosh, Wis.

SONG Poem Writers. Address, Monarch, 236 W. 55th, Dept. 126, New York.

WRITERS: Send in your song poems and let us arrange the kind of melody the public likes. Free examination, satisfaction guaranteed. Address: A. S. Glogowski M. P. Co., 1316 Wentworth Ave., Chicago Heights, Ill.

SONG Poem Writers, write Sequoia Songwriters Service, Sherman Branch, Los Angeles, California.

Automobiles and Accessories

DELIVERY bodies for Ford Model T. Chassis with inclosed cab, suitable for Contractors, Grocerymen and Farmers. Three styles. Price $49.50. Write Daniel Zimmerman, Craigville, Indiana.

MR. ADVERTISER: Ask today for a copy of the "Quick-Action Advertising Rate Folder." It contains some really important facts which will prove interesting and valuable to you. It also tells "How You Can Use Popular Science Monthly Profitably." You'd like to know, wouldn't you? Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Avenue, New York.

JUST patented—Most beautiful spinning red, white and blue automobile light—turns with wind—used anywhere on car. Installed 2 minutes. Beats flags. Get one—be first—mail, $2.00. Money back guarantee. Agents wanted. Box 202, Midland Park, N. J.

THE tell tale Calculator tells you the time and speed on any given trip, carry in pocket and every motorist should carry one 25c each—5 $1.00. P. O. Box 293, DeKalb, Illinois.

Aviation

THE American School of Aviation announces a new correspondence course in mechanics of aviation. A thorough training in practical aeronautics. American School of Aviation, Dept. 6741, 3601 Michigan Ave., Chicago, Illinois.

BIGGEST, Best Catalog Model Airplanes, Parts, Supplies; 5c postpaid. Ideal Company, 163½ Spring Street, New York.

LEARN to fly, courses from $100.00 to $200.00. New Standards OX5 Motor $900.00 to $1,200.00. Less Motor $700.00. Ready for delivery. OX5 Motors $100.00 up. Write for catalogue. Nicholas Beazley Airplane Co., Marshall, Mo.

SEND dime for 12 inch mounted propeller and circulars on free three foot model aeroplane. No selling. Aero Shop, 3050 Hurlbut Ave., Detroit, Mich.

IMPORTANT to advertisers! Are you deriving profit from your advertising? Write today for a copy of the "Quick-Action Advertising Rate Folder" showing "How You Can Use Popular Science Monthly Profitably." Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Ave., New York.

NATIONAL Institute of Aviation offers newest and latest home study course for thorough and practical training in Aeronautics. National Institute of Aviation, Dept. B., Louisville, Ky.

Bending Machines

THE Famous Hossfeld "Wrenchless" Universal Iron Bender is the last word in bending machines. Bends metal cold or hot into most any conceivable shape including Eye Bolts and Automobile Spring Eyes. Bends up to 1-inch Bars or 1½-inch Pipe, cold. Used by all classes of trade, from the smallest shops to the largest Railway systems. Write for Circular and prices. Hossfeld Mfg. Co., Winona, Minn.

ALL Advertisers should not be without the important facts on Money Making. Write today for the "Quick-Action Advertising Rate Folder" which contains information of value to you. If you are anxious for quick profit returns, do it now! Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Ave., New York.

Rates 30 Cents a Word. A 10% discount is allowed on all contracts for six consecutive insertions. Advertisements intended for the November, 1927, issue should be received by September 5th.

"The Greatest Number of Inquiries"

Produced through

POPULAR SCIENCE

When an advertiser expresses himself in the superlative, there can be little doubt as to the quality rating which the classified columns in POPULAR SCIENCE MONTHLY have.

Read what Mr. G. C. Robinson, president of the Suburban Orchards, says about the producing power of Popular Science—

Gentlemen:

> We have always rated your magazine very highly as an advertising medium, and our inquiries show that your readers are composed of a high grade class of people, the kind we have been trying to interest in our proposition.
>
> When we tell you that on the 26th of this month, Dept. "S" (your magazine) shows the greatest number of inquiries of all the mediums we used during this month, little more need be said.

Very cordially yours,

G. C. ROBINSON
President & Manager.

It is paying 250 classified advertisers to use POPULAR SCIENCE MONTHLY—it will pay you. May we send you further information and closing dates? Address your inquiry to—

Manager Classified Department
POPULAR SCIENCE MONTHLY
250 Fourth Avenue: New York

Blue Prints

TO THE man who has a Home Workshop and likes to work with tools, Popular Science Monthly offers the opportunity to purchase blue prints giving details of the construction of useful articles for the home. The following are a few of the blue prints available: No. 15, Workshop Bench, No. 17, Cedar and Mahogany Chest, No. 41, One-tube Radio Set, No. 42, Radio Receiver with three stages of amplification, No. 43, Four-tube Radio Receiver, 44 and 45, Model Pirate Ship, 46 and 47, Spanish Galleon, 48, Model Sailing Yacht, No. 50, Airplane model, 51, 52 and 53, Clipper Ship, 54 and 55, Five-tube Radio set. Send 25c for each blue print you wish to Popular Science Monthly, 242 Fourth Avenue, New York, N. Y.

Boats and Launches

HUBBELL Marine Coolers convert Ford engines into marine motors. Booklet free. Ford speedboat, easily built, blue print and directions, sixty cents. C. C. Hubbell, 14C Cottage St., East Norwalk, Conn.

BUILD your own boat. Outboard motor speedster, runabout, cruiser, row or sail using our knock-down materials. 55 Models. Send 25c for catalog. Brooks Boat Co., Inc., Salt Street, Saginaw W.S., Mich.

Books

A PERFECT Life-Book—Write Art Card Co., Omaha, Nebr.

IMPORTANT to advertisers! Are you deriving profit from your advertising? Write today for a copy of the "Quick-Action Advertising Rate Folder" showing "How You Can Use Popular Science Monthly Profitably." Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Ave., New York.

Business Opportunities

LEARN the collection business. Good income; quick results. Interesting booklet, "Skillful Collecting," free. National Collector's Association, Science Building, Newark, Ohio.

BECOME a Foot Correctionist. A New Profession, not medical nor chiropody. All the trade you can attend to; many are making $3,000 to $10,000 yearly, easy terms for training by mail, no further capital needed or goods to buy, no agency or soliciting. Address Stephenson Laboratory, 10 Back Bay, Boston, Mass.

PATENTS procured; Trade Marks Registered—A comprehensive, experienced, prompt service for the protection and development of your ideas. Preliminary advice gladly furnished without charge. Booklet of Information and form for disclosing idea free on request. Richard B. Owen, 44 Owen Bldg., Washington, D. C., or 41-Z Park Row, New York.

MINIATURE die-casting machines, $50.00. Byrd—318 Reed, Erie, Pa.

USED correspondence school courses sold on repurchase basis. Also rented and exchanged. Money-back guarantee. Catalog free. (Courses bought.) Lee Mountain, Pisgah, Alabama.

INVENTIONS commercialized. Patented or unpatented. Write Adam Fisher Mfg. Co., 183 Enright, St. Louis, Mo.

IF YOU are tired of working for others, and are looking for something to do during your spare time, write us. Service Box 531, Lake Forest, Illinois.

BIG business producer. A dollar bottle of our famous Vanilla and one dollar set of LaBohme Pearls both for One Dollar. You make 50c on every combination. Big flash, best quality goods, and everybody buys. Mystol Co., Dept. A5, Glens Falls, N. Y.

OPERATE Chewing Gum Machines. Large profits. Small Capital. Particulars free. Robbins Company, 23 Dodworth St., Brooklyn, N. Y.

SELL by Mail!—Books, Novelties, Bargain! Large Profits! Particulars FREE! C—Elfco, 525 South Dearborn, Chicago.

YOU Are Now Reading an Advertisement which may make you Thousands of Dollars if you'll send for my "Eye-opening" Literature and Lists of Guaranteed Formulas for making the World's Biggest-Selling Specialties in all lines, right in your own Home, Shop, Office, etc. Write today for this Free Money-Making Information. Dr. Liscomb Miller, Chemist, Tampa, Florida.

WE START you in business, furnishing everything. Men and women, opportunity to earn $35 to $100 weekly operating Ragsdale's original "New System Specialty Candy Factories" anywhere; wholesale or retail. Big commercial candy book free. W. Hillyer Ragsdale, Drawer 19, East Orange, N. J.

JUST $1 started one man making $18 daily, particulars free. Delhenty, Webbwood, Ont., Can.

SIGNS and showcards easily painted with letter patterns. Large variety of styles and sizes. Samples for stamp. John Rahn, B2120 Neva Ave., Chicago.

MR. ADVERTISER: Ask today for a copy of the "Quick-Action Advertising Rate Folder." It contains some really important facts which will prove interesting and valuable to you. It also tells "How You Can Use Popular Science Monthly Profitably." You'd like to know, wouldn't you? Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Avenue, New York.

START yourself into Business Guaranteed. Six Lessons Real Estate. Six House Plans and Building cost. How to Finance Super-Salesmanship and Million Dollar New Idea. Price $2.00. Caste Realty System, 814 Miller Ave., Columbus, Ohio.

CAPITAL furnished for new or established enterprises through sale of securities, by Investment House having nation-wide sales organization. Companies organized. Patents sold. Diana Syndicate, 81 Wall, New York.

PRINT 250 signs or pictures an hour without press, type or machinery. Sample and particulars 10c. Sarton, 1014, Springfield, Ohio.

START your own business; remunerative, interesting; little capital, learn privilege trading. Paul Kaye, 149 Broadway, N. Y.

YOU are wanted to resilver mirrors at home. Immense profits plating auto parts, tableware, etc. Write for information. Sprinkle, Plater, 94, Marion, Indiana.

PRODUCE perfect products yourself. Thirty Formulas, Processes, Trade-Secrets show the way. All lines. Modern master methods. Catalog, circulars free. C. Thaxly Co., Washington, D. C.

ADVERTISE—In 275 country newspapers; 23 words, $10.00. Lists free. Keator, Hartford Bldg., Chicago.

ONE of the biggest mails on earth. Sent to any address for 10c. Louisiana Distributing Service, Dept. PMX, Harmon, La.

$8,500 in 17 weeks! That's what Charles F. Worthington made after reading my free book. Do as he did. Be a Real Estate Specialist. Use my successful system. Start at home in spare time. No capital or experience needed. Free book shows how. Address President, American Business Builders, Room 34—3, 18 East 18 St., New York.

$50.00 weekly, your own business. We furnish everything. Samples 10c. Whitney, Station C, Cincinnati, Ohio.



Amazingly Easy Way to get into ELECTRICITY

Don't spend your life waiting for $5 raises in a dull, hopeless job. Now . . . and forever . . . say good-bye to 25 and 35 dollars a week. Let me show you how to qualify for jobs leading to salaries of $50, $60 and up, a week, in Electricity—NOT by correspondence, but by an amazing way to teach, that makes you an electrical expert in 90 days! Getting into Electricity is far easier than you imagine!

Learn Without Lessons in 90 DAYS

LACK of experience—age, or education bars no one. I don't care if you don't know an armature from an air brake—I don't expect you to! I don't care if you're 16 years old or 48—it makes no difference! Don't let lack of money stop you. Most of the men at Coyne have no more money than you have. That's why I have worked out my astonishing offers.

Railroad Fare Allowed

I will allow your railroad fare to Chicago, and if you should need part-time work I'll assist you to it. Then, in 12 brief weeks, in the great roaring shops of Coyne, I train you as you never dreamed you could be trained . . . on the greatest outlay of electrical apparatus ever assembled . . . costing hundreds of thousands of dollars . . . real dynamos, engines, power plants, autos, switchboards, transmitting stations . . . everything from doorbells to farm power and lighting . . . full-sized . . . in full operation every day!

No Books—No Printed Lessons

No dull books, no baffling charts . . . all real actual work . . . building real batteries . . . winding real armatures, operating real motors, dynamos and generators, wiring houses, etc., etc. That's a glimpse of how we make you a master electrician in 90 days, teaching you far more than the average ordinary electrician ever knows and fitting you to step into jobs leading to big pay immediately after graduation. Here, in this world-famous *Parent school*—and nowhere else in the world—can you get such training!

Prepare For Jobs Like These

Here are a few of hundreds of positions open to Coyne-trained men. Our free employment bureau gives you lifetime employment service.

Armature Expert $100 a Week
Substation Operator $65 a Week
Auto Electrician $110 a Week
Inventor - - Unlimited
Maintenance Engineer $150 a Week
Service Station Owner $200 a Week
Radio Expert - $100 a Week

Jobs, Pay, Future

Don't worry about a job, Coyne training settles the job question for life. Demand for Coyne men often exceeds the supply. Our employment bureau gives you lifetime service. Two weeks after graduation, Clyde F. Hart got a position as electrician with the Great Western Railroad at over $100 a week. That's not unusual. We can point to many of Coyne men making up to $600 a month. $60 a week is only the beginning of your opportunity. You can go into radio, battery or automotive electrical business for yourself and make up to $15,000 a year.

Get the Facts

Coyne is your one great chance to get into electricity. Every obstacle is removed. This school is 28 years old—Coyne training is tested—proven beyond all doubt—endorsed by many large electrical concerns. You can find out everything absolutely free. Simply mail the coupon and let me send you the big, free Coyne book of 150 photographs . . . facts . . . jobs . . . salaries . . . opportunities. Tells you how many earn expenses while training and how we assist our graduates in the field. This does not obligate you. So act at once. Just mail coupon.

Now In Our New Home

This is our new, fireproof, modern home wherein is installed thousands of dollars, worth of the newest and most modern Electrical Equipment of all kinds. We now have the largest amount of floor space devoted to the exclusive teaching of practical electricity in the world. Every comfort and convenience has been arranged to make you happy and contented during your training.



Get this FREE Book

COYNE ELECTRICAL SCHOOL
H. C. LEWIS, President, Dept. 67-73
500 S. Paulina St., Chicago **Established 1899**

Mr. H. C. Lewis, Pres.
COYNE ELECTRICAL SCHOOL, Dept. 67-73
500-524 S. Paulina St., Chicago, Ill.

Dear Mr. Lewis:

Without obligation send me your big free catalog and all details of Railroad Fare to Chicago, Free Employment Service, Radio and Automotive Courses, and how I can "earn while learning." I understand I will not be bothered by any salesman.

Name.....

Address.....

City.....State.....

Business Services

RAISE necessary capital. Incorporate! And sell shares in your business. 27 years organising and raising money for businesses of merit. Terms reasonable. Prompt and confidential service. W. Harrison Cole, 507 Fifth Avenue, Suite 508, New York.

Chalk Talks

LAUGH producing program, $1.00. Catalog free. Cartoonist Balda, Oshkosh, Wisconsin.

Chemists

OUR new catalog listing 5000 chemicals, 2500 illustrations, Laboratory Apparatus and 1000 Books sent on receipt of 50c. Laboratory Materials Company, 641 East 71st Street, Chicago, U. S. A.

Dogs, Birds, Fish

BEAUTIFUL registered bull pups, $15. Bulldogs, 501 Rockwood, Dallas, Texas.

HUNDRED Hunting Hounds Cheap. Trial. Catalog. Kaskaskennels, CA31, Herrick, Illinois.

Education and Instruction

DON'T prepare for any Civil Service examination without seeing our free catalogue. Columbian Correspondence College, Washington, D. C.

CARTOONING and Commercial Art. 25 lessons, 300 illustrations, 2 clothbound volumes and drawing outfit $5 postpaid. Catalog Free. Nu-Way Art School, 220 Graham Ave., Brooklyn, N. Y.

"DOUBLE entry bookkeeping mastered in 60 hours with 8 keys; guaranteed; diploma." International Bookkeeping Institute, Desk 10, Springfield, Mo.

HOME Study: High School, Normal, Business, Law, and Engineering courses. Tuition only $3.00 per month. Address, Carnegie College, Rogers, Ohio.

(1001001001001) „BRIEF numerals. Enclose self-(– – – – –) addressed stamped envelope for other samples. Address Hyrum Alpha Thomas, Box 69, Glenwood, Iowa.

LABORATORY experts earn $300 to $500 monthly. Study microbiology, bacteriology, sanitation. Degrees granted, 71-piece outfit free. Free prospectus. Int. College of Microbiology, 722 Calumet Ave., Hammond, Ind.

Electrical

THE Electrician's Wiring Manual, By F. E. Seng, stock, E. E. Contains all the information needed for the proper installation of lighting and power systems in houses and other buildings. It completely covers inside electrical wiring and construction in accordance with the National Electric Code. Pocket size—flexible binding. 448 pp. Price $2.50. Popular Science Monthly, 250 Fourth Ave., New York City.

Financing and Investments

MANUFACTURERS needing capital on small bond issues, investigate my proposition. Extensive clientele. Commission basis. Write G. Pickhardt, 4631 N. Racine Ave., Chicago.

For Inventors

UNPATENTED Ideas Can be Sold. I tell you how and help you make the sale. Free particulars (Copyrighted). Write W. T. Greene, 805 Jenifer Building, Washington, D. C.

INVENTIONS Commercialized. Patented or unpatented. Write Adam Fisher Mfg. Co., 183 Enright, St. Louis, Mo.

I AM in touch with hundreds of moneyed men and manufacturers who wish to buy good inventions. Hartley, 38 Court St., Bangor, Maine.

INVENTORS' Universal Educator—contains 900 mechanical movements; 50 perpetual motions. Tells how to obtain and sell patents. Suggests new ideas. Explains how to select your attorney and avoid patent sharks. Special Price, $1.00 postpaid. Albert E. Dieterich, 681 Ouray Bldg., Washington, D. C.

GET your own patents. Forms, complete instructions, $1. Cooperson, Campbell, Calif.

INVENTIONS helped along, we help perfect them if necessary, promote, patent, and market them, send us your ideas and problems, you pay us nothing if patent fails to make money. The Iler Electric Service Co., 917 Hillman St., Youngstown, Ohio.

For Men and Women

DETECTIVES—Work home or travel. Experience unnecessary. Particulars free. Write, George Wagner, 2190-P Broadway, N. Y.

Formulas

DON'T Buy Formulas till you've read my Valuable, "Eye-Opening" Literature for producing Guaranteed Money-Making Specialties in all lines. Mailed Free. Address Miller, Manufacturer's Chemist, Tampa, Florida.

DUCO, lacquer, and baked-enamel polish. A remarkable formula. Easiest, quickest, best. Result of one year laboratory experiment. Easy made. Only $1. C. F. Roll, 1127 N. Main, Tulsa, Okla.

SUBSTANTIAL business building Formulas. Selected best sellers. List free. Specialty Mfg. Service, 801 So. Farragut, Bay City, Mich.

For Sale

FOR Sale—Patent, Improved Flour Sifter, outright or Royalty Basis. Harry Nakagawa, Tanana, Alaska.

For the Home

HOT water on tap, $6. Make your own Automatic. Write John Kirkeby, San Luis Obispo, Calif.

GRANDFATHER clock works, $5.00. Build your own case, instructions free; make good profits selling your friends. Clock works with chimes for old or new cases. Write for full particulars. Clock Co., Nicetown, Penn.

TO THE man who likes to work with tools, Popular Science Monthly offers the opportunity to purchase blueprints giving details of the construction of useful articles for the home. The following are a few of the blueprints available: No. 1, Sewing Table, No. 5, Kitchen Cabinet, No. 13, Tea Wagon, No. 15, Workshop Bench, No. 17, Cedar and Mahogany Chest, No. 43, Four Tube Radio Receiver, 44 and 45, Model Pirate Ship, 46 and 47, Spanish Galleon, 48, Model Sailing Yacht. Send 25c for each blueprint that you wish to Popular Science Monthly, 242 Fourth Avenue, New York, N. Y.

CEDAR chests only $11.65—"Red-i-Kut" complete with rich copper trim—you assemble and save half—send for pictures. "Red-i-Kut" Kuempel, Guttenberg, Iowa.

MR. ADVERTISER: Ask today for a copy of the "Quick-Action Advertising Rate Folder." It contains some really important facts which will prove interesting and valuable to you. Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Avenue, New York.

Help Wanted

EARN $25 weekly, spare time, writing for newspapers, magazines. Experience unnecessary. Details free. Press Syndicate, 971, St. Louis, Mo.

STEAMSHIP positions—Europe. Orient. Good pay. Experience unnecessary. List of positions free. Box 122-Z. Mount Vernon, N. Y.

SILVERING Mirrors, French plate, easily learned; immense profits. Plans free. Wear Mirror Works, Excelsior Springs, Mo.

MEN, get Forest Ranger job: $125–$200 mo. and home furnished; permanent; hunt, fish, trap. For details, write Norton, 254 McMann Bldg., Denver, Colo.

IF YOU Are A Man Worthy of the name and not afraid to work I'll bet you $50.00 you can't work for us thirty days and earn less than $200.00. Think I'm bluffing? Then answer this ad and show me up. Openings for managers. Wonder Box sells on sight. The best selling proposition in America today. Write Tom Walker, Dept. 111, Pittsburgh, Pa.

WANTED—Live foreman or mechanic or clerk in every factory in the United States to act as subscription representative for the most popular magazine in the world. Address Manager of Representatives, Popular Science Monthly, 250 Fourth Ave., New York.

HOW to obtain positions in South America, $1.00. Box 342, South Bend, Ind.

SECRET Service Badge Free. Be a Detective. Travel, Big Pay. Send $2 for year's membership to Continental Secret Service System, Box 81K, Waukegan, Illinois.

BEGINNERS for hotels. Carolinas, Bermuda, Florida. Fares paid. Write Hotel Institute, Drawer 1508, Boston.

Help Wanted Instruction

DETECTIVES Earn Big Money. Excellent opportunity. Travel. Fascinating work. Experience unnecessary. Write, George Wagner, 2190-P Broadway, N. Y.

MEN wanting outdoor work, qualify for forest ranger position. Start $125 month; cabin and vacation; patrol the forests, protect the game; give tourists information. Write Mokane, Dept. M-29, Denver, Colo.

U. S. GOVERNMENT Jobs. Men—women, 18 up. $1140 to $3300 year. Steady pleasant work. Paid vacation. Short hours. Experience unnecessary. Common education sufficient. List positions and sample coaching with full particulars—Free. Write today sure. Franklin Institute, Dept. N30, Rochester, N. Y.

Incorporations

DELAWARE Incorporator, Charters: Fees Small; forms. Chas. G. Guyer, 901 Equitable Bldg., Wilmington, Delaware.

Insects Wanted

WHY Not spend Spring, Summer, Fall gathering butterflies, insects? I buy hundreds of kinds for collections. Some worth $1 to $7. Simple outdoor work with my instructions, illustrations, price-list. Send 10c for Illustrated Prospectus. Sinclair, Dealer in Insects, Dept. 7, Box 1424, San Diego, Calif.

Inventions Wanted

INVENTIONS commercialized. Patented or unpatented. Write Adam Fisher Mfg. Co., 183 Enright, St. Louis, Mo.

I BUY meritorious inventions, write, George Ross, 159 N. Queen St., Lancaster, Pa.

Laboratory and Chemical Services

YOUR chemical problem solved and working formula or process furnished for $5.00. Write me. W. Stedman Richards, Industrial Chemist, Box 2402, Boston, Mass.

FREE chemical service: Any formula or chemical process printed free in "Popular Chemistry" for subscribers. Subscription $1.00 year. Three trial copies, 30c. Department D, Swedesboro, N. J.

Machinery and Tools for Sale

CONCRETE Building Block Machines and Molds. Catalog free. Concrete Manufacturing Co., 5 N. Main, St. Louis, Mo.

NO. 60 HEALD Cylinder Grinders. Fine condition, $350. Lucas & Son, Bridgeport, Conn.

Magic Tricks

NEW 1927 "Fun-Magic-Mystery" now ready. 100 pages, profusely illustrated. Over 750 tricks—illusions—jokes—puzzles—books—European novelties at reduced prices. Postpaid, 10c. Lyle Douglas, Station A-1, Dallas, Texas.

DISAPPEARING Spots. Magic catalogue free. Cigarette Vanisher 25c. Swivel, 114 Huntington, New Brunswick, N. J.

Manufacturing

WIRE: Steel, Aluminum Copper and Brass. Wire goods manufactured to order. Cooley Manufacturing Co., 528 N. Western Ave., Chicago, Illinois.

TO ORDER: Metal articles, Models, Tools, Patterns, Experimenting. Manufacturing. Inventions developed. Parma Engineering Works, Brooklyn Station, Cleveland, Ohio.

Miscellaneous

FORMS to cast Lead Soldiers, Indians, Marines, Troopers, Animals, 151 kinds. Send 10c for Illustrated Catalogue. Henry C. Schiercke, 1034 72nd St., Brooklyn, N.Y.

MR. ADVERTISER: Ask today for a copy of the "Quick-Action Advertising Rate Folder." It contains some really important facts which will prove interesting and valuable to you. It also tells "How You Can Use Popular Science Monthly Profitably." You'd like to know, wouldn't you? Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Avenue, New York.

TATTOOING—Learn how with my outfits. Descriptive circulars sent anywhere. Sergt. Bonzey, 367 South Main, Providence, R. I.

Models and Model Supplies

SPECIAL Machinery or parts, Dies, Tools, Model Specialties, Model special gears, stock gears and Model Supplies. Send 5c for Catalogue. The Pierce Model Works, Tinley Park, Ill.

WOODS for Models, Scroll Work and inlaying. Free Wild, 510 East 11th St., New York.

SHIP Model Fittings and readycut hulls. Send dime for list. Roy Hancock, 323 Douglas, Portsmouth, Va.

SPECIAL machine builders, tool and die makers, inventor's models, production work of all kinds. Dept. I. Quality Hardware & Machine Co., Ravenswood and Thorndale Avenues, Chicago, Ill.

MODEL steam engines and boilers. Boat and boiler fittings. Send 10c stamp for catalog. Refunded with first order. Model Machine Shop. 212 Price St., Railway, New Jersey.

SHIP Models: Complete parts and blueprints for Three Masted Chinese Junk, 60c postpaid. Cosmo-Craft, Framingham, Mass.

LET our experience be your guide. Models that get models; Tools and equipment for economic manufacture. Patterns of all types; manufacturing in all branches. Satisfaction guaranteed. United Machinery Company, Engineering Dept., Cincinnati, U. S. A.

AIRPLANE models, build and fly them. Our large catalogue illustrating 21 finest models, complete line of supplies sent postpaid for 10 cents. U. S. Model Aircraft Corp., 341-P-Monroe St., Brooklyn, N. Y.

WE MAKE models, dies, manufacture your invention, help perfect it. Do experimental work. Free information. Strand Mfg. Co., 642 West Randolph, Chicago.

Motorcycles

MOTORCYCLE bargains. Used, rebuilt. Guaranteed. Shipped on approval. Catalog free. Floyd Clymer, 812 Broadway, Denver, Colo.

Motors

MOTORS—New GE 110 or 220 volt 60 cycle Single Phase, ¼ HP $11.90, ½ HP $28.53, 1 HP $38.50. Mail $3 Check or Money Order. We will ship C.O.D. anywhere. Motor Specialties Co., Crafton, Penna.

NEVER before, never again—18-inch Restaurant Exhaust Fans—Brand New—only $50.00; also 1/4 H.P. A.C. motors, $5.00. 25% required, balance, C.O.D. Elle & Co., 1018 W. Lake St., Chicago, Ill.

Music and Musical Instruments

SAXOPHONISTS — Clarinetists — Cornetists — Trombonists—get "Free Pointers." Virtuoso Music School, 36, Buffalo, N. Y.

Office Devices

ADDRESSING machines, multigraph, duplicators, folders, check writers, sealers, dictating machines, at about half new cost. Pruitt, 117 N. Market St., Chicago.

ALL ADVERTISERS should not be without the important facts on Money Making. Write today for the "Quick-Action Advertising Rate Folder" which contains information of value to you. If you are anxious for quick profit returns, do it now! Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Ave., New York.

Patent Attorneys

PATENTS—Time counts in applying for patents. Don't risk delay in protecting your ideas. Send sketch or model for instructions or write for FREE book, "How to Obtain a Patent" and "Record of Invention" form. No charge for information on how to proceed. Communications strictly confidential. Prompt, careful, efficient service. Clarence A. O'Brien, Registered Patent Attorney, Security Bank Building (directly across street from Patent Office), Washington, D. C. (See page 130)

Patent Attorneys

PATENTS. Booklet free. Highest references. Best results. Promptness assured. Watson E. Coleman, Patent Lawyer, 724 9th Street, Washington, D. C.

UNPATENTED Ideas Can Be Sold. I tell you how and help you make the sale. Free particulars (Copyrighted). Write W. T. Greene, 811 Jenifer Building, Washington, D. C.

MILLIONS spent annually for ideas! Hundreds now wanted! Patent yours and profit! Write today for free book—tells how to protect yourself, how to invent, ideas wanted! How we help you sell, etc. American Industries, Inc., 501 Victor Bldg., Washington, D. C.

PATENTS, Trade-Marks, all countries. Ten years' experience examining applications in Patent Office. Consultation invited. George Beeler, Patent Attorney, 11 Park Place, New York.

MONROE E. MILLER, Ouray Bldg., Washington, D. C. Patent Lawyer, Mechanical, Electrical Expert. Booklet and Priority Record blank gratis.

PATENTS Procured: Trade Marks Registered.—A comprehensive, experienced, prompt service for the protection and development of your ideas. Preliminary advice gladly furnished without charge. Booklet of information and form for disclosing idea free on request. Richard B. Owen, 44 Owen Bldg., Washington, D. C., or 41-2 Park Row, New York.

RICHARD E. BABCOCK, Patent Lawyer, Washington Loan & Trust Bldg., Washington, D. C. Booklet.

PATENT, trade-marks, copyrights. Reliable services by an experienced practitioner devoting personal attention to each case. Inquiries invited. References furnished. B. P. Fishburne, Patent Lawyer. 525-C McGill Building, Washington, D. C.

LANCASTER AND ALLWINE, 232 Ouray Building, Washington, D. C. "Originators of the Form Evidence of Conception." Before disclosing your invention to anyone send for blank form to be signed and witnessed. Form and patent information bulletin free.

EDWARD C. SASNETT, Formerly a Principal Examiner U. S. Patent Office, Attorney-at-Law. Strictly personal service. Correspondence invited. 516 McGill Building, Washington, D. C.

MR. ADVERTISER: Ask today for a copy of the "Quick-Action Advertising Rate Folder." It contains some really important facts which will prove interesting and valuable to you. It also tells "How You Can Use Popular Science Monthly Profitably." You'd like to know, wouldn't you? Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Avenue, New York.

INVENTOR'S Advisor, valuable patent book, sent free. Lobtzer, Three Parkrow, New York.

PATENTS of careful protection by registered attorney. Former examiner Patent Office. Albert Jacobs, Barrister Building, Washington.

ADAM E. FISHER, Registered Patent Attorney in business 25 years; references; personal attention and promptness assured; Dept. E, 183 Enright, St. Louis, Mo.

PATENTS secured for inventors on our new financial plan. Inventors Service Bureau, Box 1648, Washington, D. C.

FREE information, advice on inventions, patents. Immediate personal service. J. E. Trabucco, Hobart Bldg., San Francisco.

CARL MILLER, Registered Patent Attorney, McGill Building, Washington, D. C. Write for Instructions.

Patents for Sale

INVENTORS: Use our special service for presenting your invention or patent to manufacturers. Adam Fisher Mfg. Co., 183-A Enright, St. Louis, Mo.

PATENTS listed for sale. Inventors Service Bureau, Box 1648, Washington, D. C.

Photographs and Supplies

HAVE you a camera? Write for free sample of our big magazine, showing how to make better pictures and earn money. American Photography, 117 Camera House, Boston, 17, Massachusetts.

MAKE money in Photography. Learn quickly at home. Spare or full time. New Plan. Nothing like it. Experience unnecessary. American School of Photography, Dept. 1743, 3601 Michigan Avenue, Chicago.

Photoplays Wanted

$1250.00 FOR a Photoplay story by an unknown writer and sold through our Sales Department. We retain copyright and market. Located in the heart of Motion Picture Industry. We know the demand. Established 1917. Send Manuscript for free criticism. Booklet mailed on request. Universal Scenario Company, 254 Western & Santa Monica Bldg., Hollywood, Calif.

Printing and Engraving

BETTER Printing for Less Money. Write us about your printing needs, and you will save money. Ernest Pantos Company, 525 South Dearborn Street, Chicago.

200 SHEETS and 100 Envelopes printed, $1.00. Write for samples. J. Brooks, Printer, Glasgow, Ky.

200 LETTERHEADS and 100 Envelopes, $1.00, postpaid. Oberman Company, Box 1268, Chicago.

MR. ADVERTISER: Ask today for a copy of the "Quick-Action Advertising Rate Folder." It contains some really important facts which will prove interesting and valuable to you. It also tells "How You Can Use Popular Science Monthly Profitably." You'd like to know, wouldn't you? Address your inquiry to: Manager, Classified Advertising, Popular Science Monthly, 250 Fourth Avenue, New York.

Printing Outfits and Supplies

PRINT your own cards, stationery, circulars, paper, etc. Complete outfits $8.85; Job Presses $11, $29; Rotary $149. Print for others, big profit. All easy, rules sent. Write for catalog presses, type, paper, etc. Kelsey Company, F-3, Meriden, Conn.



The Temple of Heaven, Peking, China

Originally built in 1420 A. D., this magnificent edifice is believed by the Chinese to cover the exact center of the earth.

FOR MEN AND YOUNG MEN
World Travel With All Expenses Paid!

How often you've longed to see for yourself the awe of Egypt's pyramids—the beauties of the gorgeous Mediterranean sunset—the squalor of China's ancient cities! Now you can do it—travel the whole world at will, all your expenses paid. Every one of your expenses of travel will be paid for you—you won't be out a cent of your own. And you can draw a good salary besides!

There is a big demand for men to handle the Radio operating on board the ships of the world. Practically every vessel must carry one man—many of them two or three or more. Radio operating is easily and quickly learned—and the work is very interesting and pleasant. There is no other work like it for the man who wants the experiences and pleasures of world-travel.

Radio operators aboard ocean liners live luxuriously—they rank as officers of the ship. Meals, a private cabin, all other living needs are furnished free, and besides, the operators draw a good salary. You don't have to sign up for a long term—you can change ships as often as you like, so as to go to any part of the world you prefer on each voyage.

Book with Full Information Sent Free

My free 64-page book gives all information about this field of work, and the opportunities for travel, fascinating work and advancement. Send for it today—get all the facts. You can learn in your spare minutes at home to qualify for a Radio Operator's position. Just a few months of my practical training in your spare time at home and you'll be prepared to start on your travels.

My methods of training are recognized by the U. S. Government. My graduates are all over the world. My Employment Department, which keeps in touch with employers and supplies them with Radio Operators, is at your service without charge when you complete your training.

No special education is necessary—lots of men I've trained didn't even finish the grades. Read about it for yourself in my big free book—learn how I'll prepare you quickly and easily at home for these big opportunities. Send Coupon TODAY! Address: J. E. SMITH, President, National Radio Institute, Washington, D. C.

The "Sailaway" Coupon—Mail it now!

J. E. SMITH, President,
National Radio Institute,
Dept. K-87 Washington, D. C.

Dear Mr. Smith: Please send me your free 64-page book, with all information about learning Radio for bigger pay, and as a means to world-travel at will, all expenses paid. I understand this places me under no obligation.

Name _____

Address _____

Town _____ State _____

Radio

HOW to Buy, Install and Operate for best results. A new 20-page booklet published by the Popular Science Institute gives full details that will help you get the most out of your radio investment. Price 25c. Popular Science Institute, 242 Fourth Ave., N. Y. City.

Real Estate—Orchards—Farm Lands

PECAN—Orange—Fig Groves "On the Gulf." Monthly payments. Guaranteed care. Fig, quick returns. Suburban Orchards, Dept. "S," Biloxi, Miss.

Salesmen and Agents Wanted

AGENTS—Clever invention! Inkspoon makes every pen a fountain pen. Fast office seller, big profit, demand increasing everywhere. Exclusive territory offered. Sample free. H. Marul Company, Tribune Bldg., New York.

GET our free sample case, toilet articles, perfumes and specialties. Wonderfully profitable. La Derma Co., Dept. F., St. Louis, Missouri.

AGENTS. $60—$200 a week. Genuine gold letters for store windows easily applied. Free samples. Liberal offer to general agents. Metallic Letter Co., 434-A. N. Clark, Chicago.

BANKRUPT and Rummage Sales. Make $50.00 daily. We start you, furnishing everything. Distributors Dept. 34, 609 Division, Chicago.

$10 DAILY silvering mirrors, plating and refinishing lamps, reflectors, autos, beds, chandeliers by new method. Outfits furnished. Write Gunmetal Co., Ave. F, Decatur, Illinois.

AGENTS—Best seller; Jem Rubber Repair for tires and tubes; supersedes vulcanization at a saving of over 800 per cent; put it on cold, it vulcanizes itself in two minutes, and is guaranteed to last the life of the tire or tube, sells to every auto owner and accessory dealer. For particulars how to make big money and free sample, address Amazon Rubber Co., 504 Amazon Building, Philadelphia, Pennsylvania.

BIG money and fast sales. Every owner buys gold initials for his auto. You charge $1.50; make $1.35. Ten orders daily easy. Write for particulars and free samples. American Monogram Co., Dept. 47, East Orange, New Jersey.

A BUSINESS of your own—Making Sparkling Glass Name and Number Plates, Checkerboards, Signs. Big Book and Sample free. E. Palmer, 513, Wooster, Ohio.

AGENTS—Make a dollar an hour. Sell Mendets, a patent patch for instantly mending leaks in all utensils. Sample package free. Collette Mfg. Co., Dept. 467, Amsterdam, N. Y.

EARN $10 daily silvering mirrors, plating and refinishing metal ware, headlights, chandeliers, bedsteads. Outfits furnished. F. Decie Laboratories, 1133 Broadway, New York.

POLMET Polishing Cloth cleans all metal. Sells fast at 25c. Sample free. F. C. Gale, 15 Edinboro St., Boston.

AGENTS: Make $500.00 Monthly. Pay daily. No investment. Rhinestone initial buckles and novelties. Sell easy everywhere. Exclusive territory. Chaton Novelty Co., 606 Blue Island, Chicago.

DON'T sell for others. Employ agents yourself. Make your own products. Toilet articles, household specialties, etc. 500% profit. We furnish everything and show you how. Valuable booklet free. Write at once. National Scientific Laboratories, 1994W Broad, Richmond, Va.

AGENTS, both sexes, we manufacture and control new household article. Fast seller. Big profits. Exclusive territory. Write now, Connolly, 123 Liberty St., N. Y.

$50.00 WEEKLY easy, Applying Gold Initials on Automobiles. No experience needed. $1.45 profit every $1.50 job. Free samples. "Ralco Monograms," 1041 Washington, Boston, Mass.

35% COMMISSION selling $1.50 boxes Monogram Stationery. New. Write. Wolfeprint, Lawndale, Philadelphia.

CALIFORNIA perfumed beads selling like hot cakes. Agents coining money. Big profits. Catalog free. Mission Factory, R2328 W. Pico, Los Angeles, Calif.

SIMPLEX Vaporiser. 25 to 60% increased mileage guaranteed. Retails $1. Thirty days free trial. Exclusive territory. American Fixture Co., 232 West Water, Milwaukee, Wis.

MISTER Agent let me tell you how to make the World's Biggest-selling Specialties as, Sealatite, puncture-proofing liquid for tires; Solvit Hand Cleaner; Mendit, Fabric Patching Liquid; Cellu-lac Automobile Finish—all colors; Bugacide, Fly-killing Spray; Non-Thermic Ice Saving Cloth; Tufnit, for quadrupling life of Silk Hosiery; Ducopol Guaranteed Most Efficient Automobile Polish. Fifty other equally Big Money-Makers. Investment Small. Profits Great! Let me tell you how to get the profit you're entitled to. Miller, Industrial Chemist, Miller Chemical Building, Tampa, Florida.

AT LAST! Reasonable priced Auto Emblems for every Lodge. Sells for only $1.25. Write for attractive selling proposition and FREE sample case offer. North Central Distributors, Department 10, Ashland, Ohio.

AGENTS. We have a whirlwind seller. Get details. Webster, 608 Wrightwood, Chicago, Ill.

WALKER made $165 first day selling Collection System to doctors and merchants. Retails $6.50. Collects $65.00, costs $1.50. Adjustment Assn., Mobile, Alabama.

AGENTS: Sensational profits taking orders for Taylor made-to-measure caps for men, and women's Bobbette hats with purse to match. $75 to $150 every week. Pay in advance. We deliver. Outfit free. Write quick. Taylor Cap Manufacturers, Desk R-12, Cincinnati, Ohio.

JUST Out—New Patented Apron. No strings or straps—$20.00 a day every day; over 100% profit; commissions daily. Write for free offer. Sta-Put Co., Dept. 909, St. Louis, Mo.

HOLLYWOOD California Hat. Latest Movie Star Sensation. Men and women wanted in every county. Free Sample. Enclose addressed envelope. 5621 Sunset Blvd. Hollywood, Calif.

FROM the Argentine, South America. Latest Novelty, marvelous sales possibility, most unusual, write for full particulars. Write Don Francis X. Cassera, Dept. 117, 23 Washington St., New York City.

AGENTS sell our line high class printing at half price appeals to every one in business. Liberal commission with order. Samples free. Free cut service. R. Williams Co., Aurora, Indiana.

Salesmen and Agents Wanted

REPLATE brassy worn-off automobile parts, reflectors, bath room fixtures, worn spoons, forks, etc., with pure silver. Looks like new. Use U-Kan-Plate Polish. Positively no mercury. $1.00 half pint. Postpaid. Satisfaction guaranteed. Agents wanted. Dept S. U-Kan-Plate Co., Philadelphia.

TEST big money-maker at our risk. Will send sample patented wringer mop on approval. Many eager buyers. Kleanezy Mop Co., Dept. L-8, Delphos, Ohio.

SALESMEN—Make $44 weekly and expenses; $1 hour part time; sell "Mason Shoes;" 91 styles; easy sales; big repeat business; free selling outfit. Write Mason Co., Box 1223, Philadelphia, Pa.

AMAZING advertising service, sells every merchant. 70% commission! $150.00 weekly easy! Write today! National, 1271 California St., San Francisco, California.

AGENTS: Make $100 Weekly selling "Gray Seal"—Automatically, instantly and permanently seals all tire punctures. Gives longer life to tires and tubes. Demonstration closes sale every time, with $1.50 to $3.00 profit for you. Exclusive territory given. Money-back guarantee. Write today for our very liberal offer. Gray Seal Products Corp., 206 Rutger St., St. Louis, Mo.

AGENTS $300 month. Sell guaranteed silk hosiery. Must wear 7 months or replaced. New selling plan. We furnish auto. Free silk hosiery for your own use. Write for samples. Betterknit Textile Co., Silk 632, Greenfield, Ohio.

WE HAVE a line of goods for which every man in America is a prospect. Can be handled with tremendous profit by any salesman now selling to men. $20.00 Outfit Free. Address Dept. 533, William C. Bartlett, Inc., 850 West Adams, Chicago.

SALESMEN—You can make $130 extra each month selling only one policy a day. Policy pays $5,000 death; $25 weekly benefit for injury or sickness. Entire cost $10 yearly. Salary and commission. Permanent income from renewals. $100,000, Deposit with State. Address Underwriters, 701 Bonnell Bldg., Newark, N. J.

MAKE $100 a week up, selling better-quality, all-wool made-to-measure suits and overcoats. Biggest values. Highest commissions, paid in advance, and extra bonus for producers. Large swatch samples furnished free. Write W. Z. Gibson, Inc., 161 W. Harrison, Dept. J-521, Chicago.

WE WANT men and women who have distributed free samples and advertising matter. New Offer. Steady Work. Good Pay. Write immediately. American Products Co., 9451 Monmouth, Cincinnati, Ohio.

$2,731.00. THAT'S what Chas. Hickey's Commissions amounted to for only 60 days work this spring selling Face-a-Lites. This amazing device needed by every car. Wonderful tourist line. Good distributors wanted in open territory. Either sex. Short hours. Big commissions. Experience not a requirement. Write or wire to W. M. Willy, President, 332 Logan Building, Mitchell, So. Dakota.

RADIO Agents—Make Big Money—Easy selling Marvelous New Sets and accessories. Buy from factory at lowest prices. Get Big New Catalog with thousands of nationally advertised bargains. Free Call Book. Write today. American Auto and Radio Co., Dept. 288, Radio Bldg., Kansas City, Mo.

TIRED of working for other people? Without experience, training or capital I'll show you how you can become financially independent. Easy, pleasant work. $100 profit every week. Free automobile. Write today for particulars. Albert Mills, Mgr., 9218 Monmouth, Cincinnati, Ohio.

BIG bunch mail. Year 15c. Magazines, catalogues. Kentucky Agency, Covington, Kentucky.

PRODUCE perfect products yourself. Thaxly Formulas, Processes, Trade-Secrets show the way. All lines. Modern master methods. Catalog, circulars free. C. Thaxly Co., Washington, D. C.

BIG pay every day! Complete guaranteed line direct to wearer—Dress Shirts, Work Shirts, Flannels, Overalls, Pants, Leather Coats, Sweaters, Playsuits, $10-$25 daily! Experience unnecessary. Big Outfit Free! Nimrod Co., Dept. 25, 4922-28 Lincoln Ave., Chicago.

GOLD leaf window letters and script signs. No experience: 500% profit. Samples free. Consolidated, 69-Y-West Van Buren, Chicago.

FIFTEEN Dollars a day. Sell Harrison's "New York Style" suits and overcoats. Tailored of 100% virgin woolens. Priced $19.75 to $34.75. Highest commissions paid daily. Experience unnecessary. Valuable exclusive territory now open. Send for expensive sales portfolio with many selling features. It's free to men who mean business. De Luxe Harrison raincoat line included if you write now. Harrison Bros., Inc., Dept. 876, 133 West 21st St., New York, N. Y.

100% PROFIT on every sale selling Christmas greeting cards in box assortments. Our wonderful Christmas box assortment is the finest ever published. Agents earn $2. to $4 per hour. We have a magnificent box assortment containing 21 high-grade Christmas greeting cards and folders, each with an envelope. Steel engraved, colored, paneled, and bordered. Sells for $1.00; costs 50 cents. Nothing ever sold begins to compare with the sale of Christmas box assortments. Write immediately for particulars and free samples. Waltham Art Publishers, 7 Water St., Dept. B-27, Boston, Mass.

AGENTS—new plan, makes it easy to earn $50.00 to $100.00 weekly, selling shirts direct to wearer. No capital or experience needed. Represent a real manufacturer. Write now for free samples. Madison Company, 566 Broadway, New York.

WONDERFUL new moisture gas saver. All cars. 400% profits. Doubles Mileage. 1 free. Critchlow, A1-120, Wheaton, Ill.

MAKE $100 before Christmas selling exclusive personal Christmas cards in distinctive steel engraved designs. Expensive sample book free. Wetmore, Janes and Sugden, Rochester, N. Y.

DISTRICT Salesman—All wool, Union made suits, overcoats, $23.50. Liberal advance commission, bonus. Write for expensive free outfit. Harvey Bros., Dept. 514, Box 00, Chicago, Ill.

LAMB'S Wool polishing mittens, brushes. Newhall, 358 Broad, Lynn, Mass.

BIG winner for Agents. New patented cigarette case. Holds package cigarettes and box safety matches; beautiful, compact, flexible container; large profits; write for liberal proposition. All-In-One, Dept. S-9, 2810 Portland Ave., Minneapolis, Minn.

AMAZING new device. Sharpens everything, even scissors. Over 100 big uses in every home. Also sells fast to garages, shops, etc. Many now making $3-$9 an hour. Everything furnished. Write for Free Outfit Offer. Central States Mfg. Co., Dept. L-1040, St. Louis, Mo.

Salesmen and Agents Wanted

$30.00 A DAY guaranteed to workers taking orders for Goodwear tailored-to-measure clothes at sensational new low price. Tremendous assortment Virgin Wool fabrics. Biggest cash commissions paid daily and special cash bonus besides, makes ours best paying line in history. Write at once to Dept. 148, Goodwear Chicago, Inc., 844 West Adams, Chicago.

AGENTS $260 month. Bonus besides. Introduce finest line guaranteed hosiery you ever saw. 126 styles, colors. New sales plan a wonder. No experience needed. No license to pay. Auto furnished. Credit given. Spare time satisfactory. Samples furnished. Wilknit Hosiery Co., Dept. 1832, Greenfield, Ohio.

WANT $15 A Day? New way to make quick cash profits, selling fine shirts. Actual samples sent free. Write Fashionwear Shirt Co., L-363 Jackson St., Cincinnati, O.

AGENT: Be a thousand miles ahead of competition. Patented product housewives want. 100% profit. Commission in advance if wanted. Manager Box 929, New Orleans, La.

Sales Promotion

EXPERIENCED promoter new products personally writes folders, letters, complete campaigns. Reasonable. Box 56, S. Orange, N. J.

Shop Equipment

EVERYTHING for Battery and Tire Shops at wholesale. Our new catalog on request. Investigate. Adams-Barrs, Columbus, Ohio.

Stamps and Coins

STAMPS, 100. All different, 3 cents. Lists free. P. S. Quaker Stamp Co., Toledo, Ohio.

STAMP Collectors—Phillips Monthly Bulletin (illustrated) offers over 2000 special bargains, sets, packets, etc. each issue. Free. Phillips, Box 1012, Hartford, Conn.

OLD coins, large Fall selling catalogue of coins for sale free. Catalogue quoting prices paid for coins, ten cents. William Hesslein, 101B Tremont Street, Boston, Mass.

CALIFORNIA gold $\frac{1}{4}$ size, 27c.; $\frac{1}{2}$ size, 53c. Wheat cent and catalogue, 10c. Norman Schultz, Box 765, Salt Lake City, Utah.

150 GOOD mixed foreign stamps, 3c. Stanton (166), Niantic, Conn.

20 VARIETIES unused free. Postage 2c. P. S. Miami Stamp Co., Toledo, O.

500 GOOD mixed stamps, bargain lists, magazine, catalog, packet hinges, all 25c. Approvals for beginners. Harvey Teeple, Decatur, Indiana.

MINT—$5 revenue free to applicants with references. Foreign revenues, telegraphs, locals, etc. Intriguing, educational, different, cheap. E. R. Vanderhoof, 1114 Logan Street, Denver, Colorado.

500 DIFFERENT 40c; 1000, 80c; 2000, $3.50. Fred Onken, 630 79th Street, Brooklyn.

UNITED STATES and Foreign Coins. Military Decorations. Catalogue and 500,000 mark bill, 10 cents. Alexis Mengelle, Colorado Springs, Colorado.

FREE! Beautiful unused set 10 Jugo-Slavia 1926, cataloging $1.81, to approval applicants. Pennsylvania Stamp Co., Greensburg, Pa.

STAMPS, 105 China, etc., 2c. Album (500 illustrations) 3c. Bullard, Station AA, Boston.

300—300—300. ALL different stamps (cat. over $6.00); 300 hinges; 5 approval sheets; duplicate stamp album; perforation gauge; millimeter scale and ruler to approval applicants only for 20c. Edgewood Stamp Co., Dept. S, Milford, Conn.

BIG Bargains, $\frac{1}{4}$c up. Babcock, 409 E. Fort, Detroit, Mich.

1c, 2c, 3c, 4c, 5c and 10c approvals offered stamp collectors furnishing satisfactory references. Send for one and get three good stamps Free. Humboldt Stamp Co., Arcata, California.

100 DIFFERENT U. S. stamps $1.00. U. S. stamps sent on approval. Ref. please. M. G. Hanna, New Kensington, Pa.

Stories Wanted

STORY Ideas Wanted for photoplays, magazines. Big demand. Accepted any form for revision, development and submission to markets. Estab. 1917. Send manuscripts for free criticism. Booklet mailed on request. Universal Scenario Company, 402 Western & Santa Monica Bldg., Hollywood, Calif.

Technical Schools

CHICAGO Technical College offers short, intensely practical courses in Drafting and Engineering—civil, mechanical, electrical, structural—Architecture, Building Construction, Plan Reading, etc. Courses fitted to your needs. No time wasted. Instructors are experts. Graduates in demand at big salaries. Opportunities for part-time work while studying. Day and evening classes. 24th year. Enter any time. No special preliminary training required. Low tuition—easy terms. Write for 84 page illustrated Blue Book, describing opportunities open to our graduates. Chicago Technical College, 23 Chicago Tech. Building, Chicago.

Typewriters and Supplies

"RENT a typewriter." Any make. If you pay its price in rent, we give machine free. Catalog free. Pgh. Typewriter Supply, Suite 543, 339 Fifth Ave., Pittsburgh, Pa.

Wanted

DETECTIVES needed everywhere. Experience unnecessary. Particulars free. Write, American Detective System, 2190-P Broadway, N. Y.

WANTED—Live foreman or mechanic or clerk in every factory in the United States to act as subscription representative for the most popular magazine in the world. Address Manager of Representatives, Popular Science Monthly, 250 Fourth Ave., New York.

America Takes to the Air

(Continued from page 11)

Leaving out the purely military aviation fields, operated by the Army, Navy and Marine Corps, there are thirty-one fully equipped airports now in operation. These are equipped with revolving beacons to guide the flyers by night, with partial or full equipment of floodlights for landing, flood-lighted buildings, boundary lights and danger lights, as well as necessary hangars and other buildings, oil and gas tanks and staffs of mechanics.

That is a pretty substantial beginning toward the establishment of national airways. But airports are not all that go to make up a modern airway. There must be beacons all along the route, indicating not only the route but safe landing places; and other means of aiding the flyer to keep on the course in fog or storm, such as radio direction finders.

More than 2,500 miles of our national airways system are already completely lighted. By November 1, the Department of Commerce announces, another 4,800 miles and more will be similarly defined for night flying. That is essential; for if aviation is to be merely a daytime affair there is no such great gain in time and speed of communication as to warrant the effort to compete with the railroads.

THE airways now completely lighted are those from New York to Boston, 220 miles, New York to Salt Lake via Chicago, 2,041 miles, and Chicago to St. Louis, 278 miles. The airways to be lighted before the end of 1927 are those from Jacksonville to Atlanta, Atlanta to New York, Chicago to Dallas (via Kansas City), Cheyenne to Pueblo, Chicago to Twin Cities, Salt Lake to Pasco, Wash., Los Angeles to Salt Lake, San Francisco to Salt Lake, and Los Angeles to San Francisco, a total of 4,813 miles.

And the Government's program of airway development does not end with the list of airways now being lighted. Look at the map. The airways defined there are only a beginning.

It works out this way, the Government's new policy for the encouragement of commercial aviation. A city or a group of individuals or some civic organization like a Chamber of Commerce decides that the community wants to be a station or terminus on an airway. Sentiment is aroused and land is set aside or purchased for an airport. Then the Post Office Department is prevailed upon to promise air mail service from the nearest point at which air mail service is already in operation. The Post Office advertises for bids for carrying the mail by air between these two points. These mail-carrying contracts are the American substitute for the Governmental subsidies which have been chiefly responsible for the great development of commercial aviation in Europe. Over routes between populous centers between which considerable commercial business is exchanged, the volume of air mail may quickly be built up to a point where the charge for its transportation will cover the operating costs of the air line, leaving the revenue from passengers and express matter as the basis for possible profit. And the Post Office helps in every way, as by advertising and the placing of air mail boxes at convenient points, to develop the business for the contractors. In Europe mail-carrying is a minor consideration of commercial aviation, in which very little mail is carried.

EIGHTEEN air mail contractors are now either carrying mail over established airways or awaiting the completion of airports and intermediate lighting before beginning operations. You will find the routes of these mail lines on the map on pages 10 and 11. And over most of these airways passenger lines will be running before the end of 1927. Last year only six of the airway lines carried passengers; there are seven regular (Continued on page 130)

We Guarantee Both -Training and -Employment Service

Training—preparation for a better job and a raise in pay . . .

If you are now earning less than $40 a week

I guarantee to *prepare* you for a fine Drafting position, right in your home, in your spare time; then I guarantee to help you find such a position paying at least 50% *more than you earn today*, within 60 days after you complete this training, or I will refund the small amount you pay for tuition.

O C Miller
Director Extension Work

Jobs! pay $60 to $125 a week!

Go *into* Drafting!

Learn Drafting—how to *make* and *read* plans, and the doors of opportunity in all mechanical, building and engineering lines swing open for you! There are more well-paid Drafting jobs open today than in any other one profession or trade. There's a variety, a fascination to Drafting that will grip you. No other work is so interesting, *so well paid*—no other field offers equal opportunities for quick promotion.

Free Job Service

The American School is the first in the home-study field to recognize the need of guaranteeing its courses with a money-back contract, if the training fails to accomplish the benefits you expect. Thus all risk and doubt are eliminated—**either the training will help you to a better job and a raise in pay or it will cost you nothing.** To better carry out this important service, we maintain a **National** employment department which keeps in touch with the employers of Draftsmen all over the U. S. All this without extra charge to our students and graduates.

The Draftsman is the Boss of the Works!

Destroy blue-prints and plans, and the wheels of all Industry will stop until new ones can be made. Every move of every workman on the job is controlled by the Draftsman through his plans. Railroads, public works, buildings of a hundred sorts, machinery, electricity, automobiles—all manufacturing and construction start on the Drafting table! That's the kind of work to get into, friend. Where you have the same chance as anybody else to make a quick success!

3 Drafting Lessons Actually FREE!

to prove you can learn at home in spare time!

Employment —*helping you find a job or money refunded*

You'll be surprised how quickly you can learn Drafting by our new one-step-at-a-time method. We start you off doing actual Drafting room jobs from the very beginning. Before you know it, you are batting out professional plans like a veteran. Get the first three lessons — the coupon brings them free. Do them. Test your ability to master Drafting at home. Without cost or obligation.

PROFESSIONAL

OUTFIT GIVEN!

You will naturally expect the American School to give you the best kind of instruments and tools with the best kind of training. This outfit is good enough to use professionally after you finish your training.

A Million Dollar Institution Back of This Guarantee

Get this straight—the American School was chartered in 1897 as an **educational** institution, **not for profit.** So you will find the same standards of service here as in the best resident schools and colleges. Over 200 of the leading Engineers, Executives and Educators of the U. S. prepared the instruction we offer. Their standing vouches for its **quality.**

O. C. MILLER, *Director Extension Work*

The American School

Dept. D-675, Drexel Ave. and 58th St., Chicago

O. C. Miller, Director Extension Work
American School, Dept. D-675
Drexel Ave. and 58th St., Chicago

Your offer to send me 3 lessons free and facts about the opportunities in Drafting and about your course, looks good to me. It is understood I am not obligated in any way in making this request.

Name.....

Address.....

Occupation..... Age.....

Hidden Gold!

Above Your Eyes!

IF YOU'RE earning a cent less than $60 a week—*clip coupon now!* Get my big new *Free Book*, "Auto Facts." Find out about the wonderful opportunities for quick success that the Auto Business offers you! You're worth only $2.50 a day from the neck down, but in the Auto Field the money you can make *with your brains* is *limitless!*

The AUTO BUSINESS pays for Brains!

Get into the world's *biggest* Business—it needs you! Never before were there greater opportunities for the trained Auto man—never before a better opportunity for *you* to dig out the hidden gold that lies above your eyes. Even the untrained mechanics are making a good living in the Auto Business—The trained man is cleaning up!

earn up to $150 a Week!

Don't sell your time for low pay! You don't have to! Send for this amazing Free Book right now! See how hundreds of men are boosting their salaries, making big, extra spare-time money, and getting into their own Money-Making Businesses NOT IN YEARS—but almost right from the start—*in a few short weeks*—or months!

4 TESTING & REPAIR OUTFITS INCLUDED

Send coupon for full particulars of my big outfits offer. You get a complete set of Master Mechanic's Tools, Tool Bag, Portable Electrical Test Bench, Electrical Experimental Outfit, and 360 Auto Wiring Diagram Charts, all absolutely Free of extra charge!

I train You AT HOME!

Learn how you can master every branch of Auto work right in your own home—Electrical and Mechanical! Get all the facts about this new easy method. Common schooling all you need. No previous experience required. I help you do it. I give you lifetime Employment Service. Lifetime Consultation Service, too! Coupon brings full details absolutely Free!

Send Coupon Now!

No strings attached to this offer whatever. This same amazing book that has shown thousands the way to big pay is yours *free* and without the slightest obligation!

MAIL THIS COUPON!

FREE AUTO BOOK!

B. W. COOKE, Directing Engineer,
CHICAGO MOTOR TRAINING CORP.,
Dept. 625, 1916 Sunnyside Ave.,
Chicago.

Send me your book, "Auto Facts" absolutely Free. Also full particulars of "Job-Way" Training. Also send your 4 Outfits offer. It is understood that this obligates me in no way whatever.

Name.....

Address.....

America Takes to the Air

(*Continued from page 129*)

passenger routes by air operating now, and five more have been announced for early installation of passenger service.

One can ride for an average cost of fifteen cents a mile over these airway routes. From New York to Boston, 220 miles, the fare is $30. To fly from Cheyenne to Pueblo, Colorado, 200 miles, costs $45 for the round trip. For the flight between Seattle and Los Angeles the fare is $132 each way. Between Salt Lake and Los Angeles round-trip air tickets are $150. Only one air line so far sells commutation tickets; that is the line between Detroit and Grand Rapids, on which one can buy a ten-trip book of tickets for $160. Over the Chicago-Twin Cities Airway the fare is $75 for the round trip.

ON JULY 1 passenger service was inaugurated over the Chicago-San Francisco air route, and on August 1 the New York-Chicago section of the Transcontinental Airway also began passenger service. Five triple-motored planes are under construction for the service. Each will carry twelve passengers, a pilot, navigator, and a steward. The one-way fare will be in the neighborhood of $60. Four hundred dollars is the price of a transcontinental air ticket; the rail and Pullman fare is $140. But it takes from eighty-seven to ninety-six hours to make the trip by the fastest trains, while the air service flies it in thirty-one to thirty-two hours. For a man whose time is valuable $260 is not a high premium to pay for saving from fifty-five to sixty-four hours.

One limitation of transcontinental passenger service is that as yet passengers cannot be provided with sleeping quarters, and probably few will undertake the strain of a thirty-hour or longer flight, sitting up, even with half a dozen stops en route for refreshment and relaxation. No airplane pilot is required to make these long through flights; they are relieved at frequent intervals, as are the crews of railroad trains. Secretary Hoover suggests that an air passenger service starting from New York or San Francisco to overtake the farthest passenger train that can be reached in eight or ten hours may be the first important development of cross-continent air travel. The saving in time would be material and the cost approximately the same per mile flown.

THERE is an American program of commercial aviation which is already challenging Europe's supremacy and which, now that America has at last become air conscious, is certain to make this country the greatest flying nation in the world. For that matter, we are already in that position, in the present availability of air passenger service and perfected airways, so recently achieved. I am comparing America now with any individual nation of Europe, not with Europe as a whole, as the comparison is usually made; for we have more airways, more available equipment and pilots, more facilities of every kind for air passenger service than any one European country has, and with the rush of Americans to avail themselves of these new facilities we shall soon have more people flying from point to point, not as a stunt but as a means of getting somewhere in a hurry, than fly in all Europe in the same period of time. Last year, while 5000 passengers flew across the English channel, 795,000 went by boat and rail.

Undoubtedly there are thousands to whom the possibility of flying to Boston from New York in two hours and a half, transacting a day's business and flying back before bedtime would easily be worth the $40 or so of extra cost over railroad fare. The best railroad service between New York and Chicago takes twenty hours from station to station. With a plane equipped with even modest sleeping con-

(*Continued on page 131*)

POPULAR BOOKLETS OF SCIENCE

Little Blue Books at Amazing Bargains—About 15,000 Words in Each Book—Your Choice 5 CENTS EACH

—*Order by Number*—

806 Nature of Science
776 Foundations of Science
409 Great Men of Science
493 Novel Discoveries in Science
1000 Wonders of Radium
1050 X-Ray, Violet Ray, etc.
408 Einstein Relativity Explained
238 Reflections on Modern Science, Huxley
133 Principles of Electricity
510 Electric Energy
722 Electricity & Life
419 Origin & Nature of Life
779 Fitness of Life
778 Environment of Life
895 Astronomy for Beginners
557 Is the Moon a Dead World?
607 Solving the Mystery of the Comets
608 Origin of Atomic Theory
609 Are the Planets Inhabited?
837 Greek Physics & Modern Science
728 Life Among the Bees
796 Life Among the Butterflies
818 Life Among the Dragonflies
833 Life Among the Ants
885 Life Among the Spiders
827 Life Among the Apes and Monkeys
873 Dwellers of the Ponds
874 Lower Invertebrate Animals
725 Zoology Self Taught
710 Botany for Beginners
679 Chemistry for Beginners
994 Physics Self Taught
603 A-B-C of Electron Theory
227 Introduction to Zoology
703 Physiology Self Taught
808 Man's Debt to the Sun
1185 The Weather: What Makes It and Why
853 How to Know the Song Birds
811 Genetics for Beginners
189 Eugenics Made Plain
812 Introduction to Heredity
93 How to Live 100 Years
467 Evolution Made Plain
321 History of Evolution
686 Records of Evolution
694 Evidence for Evolution
695 Embryology & Evolution
568 Darwin & Evolution
597 Haeckel's Evolution
49 Controversy on Creation, Haeckel
191 Evolution vs. Dogma
13 Man & His Ancestors
42 Origin of the Human Race
47 Animals of Ancient Seas
274 Animals of Ancient Lands
826 More Animals of Ancient Lands
275 Building of the Earth
415 Age of Mammals
555 Structure of the Earth
202 Survival of the Fittest
327 The Ice Age
481 The Stone Age
928 Religion of a Darwinist
71 Poems of Evolution
1064 Simplicity of Ra in
1139 Photography Self Taught
491 Psychology for Beginners
782 Psycho-Analysis
53 Insects & Men, Clarence Darrow
784 Tests Used in Psycho-Analysis
800 Six in Psycho-Analysis
417 Nature of Dreams
804 Freud on Sleep & Sexual Dreams
904 Sex Symbolism
1052 Nature of Instincts & Emotions
1094 Insanity & Other Mental Disorders
1097 Memory: What it is
524 Death & Its Problems
693 Experiments in Animal Psychology
720 Intelligence of Invertebrate Animals
721 Intelligence of Vertebrate Animals
727 Psychology of the Affections
861 Behaviorism: Normal Psychology
996 Dual & Multiple Personality
1063 Psychology of Laughter
1069 Conquest of Fear
1051 Cause & Nature of Genius
648 Facts About Rejuvenation
761 Food and Diet
1126 Eating for Health
688 Teeth & Mouth Hygiene
794 Truth About "Patent Medicine"
136 Measles, Diphtheria, Scarlet Fever, etc.
870 Tuberculosis: Cause & Prevention
875 Diabetes: Cause & Treatment
1091 Facts About Cancer
726 Facts About Venereal Disease
983 Syphilis: Brief Treatise
74 Physiology of Sex Life
692 Homosexual Life
950 Determination of Sex
1070 How to Fight Nervous Troubles
486 Hints on Soils & Fertilizers
860 Our Insect Enemies
939 Tales of Imagination Science, Poe
680 Louis Pasteur: Chemist of Human Ills
567 Darwin as a Naturalist
485 Voyage to the Moon, Verne
926 Obliterated Man, etc. H. G. Wells
927 The Stolen Bacillus, etc. H. G. Wells
566 Ernst Haeckel: Struggling Youth
598 Ernst Haeckel: Philosopher
445-446 Psychical Research (2 vols.)

ORDER BY NUMBER: If you want "The Ice Age" put down "327." Your choice 5c per book, as many or as few as you like. Add 1c per book for packing and carriage charges or your order will be shipped express collect. Canadian and foreign price 7c per book. New Catalogue, listing 1,200 different Little Blue Books, included with all orders or free on request.

HALDEMAN-JULIUS PUBLICATIONS
Dept. S-12 GIRARD, KANSAS

Wrestling Book FREE

WRESTLING FOR HEALTH

Learn to be an expert wrestler. Know scientific wrestling, self-defense, and Jui-Jitsu. Develop a splendid physique, and have perfect health. Join this popular school and learn by mail. The famous world's champions—the marvelous

Frank Gotch and Farmer Burns

offer you a wonderful opportunity. Wrestling is easily and quickly learned at home by men, lads and boys write now for splendid free book. Learn all the science and tricks. Be able to handle big men with ease. Accept this wonderful offer NOW. Send for free book today, stating your age.

Farmer Burns School of Wrestling, 3396 Range Bldg., Omaha, Neb.

DRAW CARTOONS

Turn Your Talent Into Money

Cartoonists earn from $50 to $300 per week—some even more. Remarkable new Circle System of Drawing teaches you in half the usual time. Send for booklet and sample lesson plate explaining full details of the Course.

THE NATIONAL SCHOOL OF CARTOONING
615 Penton Building Cleveland, Ohio.

Make More Money

Read the Money Making Opportunities on pages 124 to 151 of this issue.

America Takes to the Air

(*Continued from page 130*)

veniences a passenger could leave New York with the night air mail at 8 o'clock, breakfast in Chicago, spend an entire business day there, leave at 8 that evening and be back at his desk in New York at 9 o'clock the next morning. And it would cost him about $240 as against about $100 by rail.

That, of course, is in the future. But the Pullman Company already has plans for "sleeping planes." And Bellanca, designer of the Chamberlin monoplane, has plans for an American luxury service as exemplified in the "Silver Wing De Luxe" service between London and Paris, on which eighteen passengers, seated in luxurious wicker chairs, are carried in a three-propeller plane at 100 miles an hour and are served with meals *en route*.

LAST year the principal European air companies carried, on regular traffic routes, 140,000 passengers over a total of 12,000,000 miles, with only thirty-five fatalities. The air map of Europe is a perfect network of airways, centering chiefly in London, Paris, Amsterdam, Berlin, Frankfort, Basel, Stuttgart, Hamburg, Prague and Vienna, and with regular services extending eastward to Moscow and southward to Naples and Sicily, with at least one line crossing the Mediterranean to Africa, at Tunis. There are about 30,000 miles in this great European system. And in the last year particularly there have been great improvements in lighting facilities and arrangements at airports for the comfort of passengers. An important development is the increase in express and freight service—a phase of commercial aviation still in its infancy in America. The only important demonstration in America of the freight-carrying possibilities of the airplane has been by the Ford Motor Company, which operates the air mail lines between Detroit and Chicago and Detroit and Cleveland. These lines carry no passengers, but during 1926 carried 1,033,338 pounds of express matter over the Chicago route and 696,197 pounds between Detroit and Cleveland. A total of 3,155 pounds of express matter carried in 1926 between Detroit and Grand Rapids by the Stout company is the only other record of air express service in America.

The American habit of mind in considering aviation has been to compare the airplane with the automobile—as a device primarily for private, individual use rather than as a common carrier. I have tried to point out that Europe takes the opposite view, and that it is the regular, scheduled flights over definite, protected airways which our Government is trying to encourage, and which we must develop to compare our aviation situation favorably with that of Europe. There will always be individual aviators, and their number will increase; but that the time is close at hand, or even within reasonable speculative distance, when flying by individuals will become popular enough to call for aerial traffic cops is seriously to be doubted. But five railroads are already considering extending their service with airplane lines.

AS A matter of history, new inventions do not displace the old so much as they supplement them. So it is coming about with air travel, now in America—as for several years in Europe. The thing we have been talking about for twenty years is upon us. Our young men, emulating Lindbergh, are eager to fly. Our capitalists for the first time see aviation as a practical business enterprise. Our plane builders are giving us better planes than ever, our engine designers more reliable engines. Our airports are established and more are on the way. Our airways are lighted. Everything is set for America to take to the air. And America does.

You Daring Young Men Seize Life's Biggest Thrill!

The famous "Spirit of St. Louis" which flew from New York to Paris in the memorable non-stop flight May 20-21 *Wide World Photo*

Get into Aviation

WHAT thrill could compare with this—what sport could bring you the tingling, breath-taking adventure of this fascinating, new occupation—the game for men with sporting blood! See life—win applause—thrills—big money—step into a field of excitement and daring—away from the monotony of tame, narrow humdrum everyday life!

Think what Aviation offers you. Thrills such as you never had before! The praise and plaudits of the multitude. And a chance to get in on the ground floor where rewards may be unlimited!

Amazing Opportunities

Aviation is growing so swiftly that one can hardly keep track of all the astonishing new developments. Air mail routes have just been extended to form a vast aerial network over the entire U.S. Airlines and airplane factories are springing up all over the country. Men like Henry Ford are investing millions in the future of commercial Aviation in America! The possibilities are so tremendous that they stagger imagination!

Everything is set for one of the greatest booms in history. Big fortunes came out of the automobile industry and out of motion pictures. Big fortunes will also come out of Aviation. The development of Aviation as an industry is bringing with it a call for trained men. Those who qualify quickly should find themselves on the road to unusual earnings—success—popularity—and prominence.

Pick Your Job!

- Airplane Repairman
- Airplane Mechanician
- Airplane Inspector
- Airplane Salesman
- Airplane Assembler
- Airplane Builder
- Airplane Pilot
- Airplane Instructor
- Airplane Contractor
- Airplane Engineer
- Aerial Photography
- Aerial Advertising

Easy to Become an Aviation Expert

Get into this thrilling business at once while the field is new and uncrowded. Now—by a unique new plan—you can quickly secure at home, during spare time, the preliminary training necessary to get a start in the Aviation Industry. Experts will teach you the secrets—give you the inside facts that are essential to your success. And the study of Aviation by our method is almost as fascinating as the actual work itself. Every lesson is chock-full of interest—and so absorbing that you actually forget you are studying. But best of all are the ultimate rewards you are fitting yourself to gain.

Send for FREE Book

Send the coupon for our new, free booklet—*Opportunities in the Airplane Industry*. It is unusually interesting, reads like a romance, and gives vital facts about Aviation you probably never even dreamed of. You owe it to yourself to at least read it. We offer you a free copy now. No obligation. Mail the coupon for yours today.

AMERICAN SCHOOL OF AVIATION
Dept. 1366, 3601 Michigan Ave., Chicago, Ill.

American School of Aviation,
Dept. 1366, 3601 Michigan Ave.,
Chicago, Ill.

Without any obligation please send me your FREE book, Opportunities in the Airplane Industry. Also information about your course in Practical Aviation.

Name.....Age.....

Address.....

City.....State.....

SHOW CARD LETTERING
Learn at Home

HERE is the very course you need if you want to get a good paying position as a Show Card Letterer or Sign Letterer, or have a business of your own. This course is complete and practical and especially arranged to meet the needs of the student who studies at home. It was written by E. L. Koller, Principal of the School of Art of the International Correspondence Schools, member of the American Federation of Arts, and The National Society of Craftsmen.

Mr. Koller has had twenty years' teaching experience, and his success in helping other men and women is an indication of what he can do for you.

H. L. Wood, a clerk, made more than $700 "on the side" before he had completed his course and also won $125 in prizes. Harry William Lord writes that he has more than doubled his salary as a result of studying this I. C. S. course in spare time. William Whitman, a former wagon builder, now has a sign painting business of his own and is earning *nearly three times* as much as he did before enrolling with the International Correspondence Schools.

There is no doubt that Show Card Lettering and Sign Lettering offer a real opportunity to ambitious men and women. Just mark and mail the coupon and we'll gladly send you a booklet telling all about the I. C. S. course in Show Card Lettering, or any other subject in which you are interested.

INTERNATIONAL CORRESPONDENCE SCHOOLS
Box 7640-E, Scranton, Penna.

Without cost or obligation on my part, please send me one of your booklets and tell me how I can qualify for the position or in the subject before which I have marked an X:

☐ SHOW CARD LETTERING

☐ ILLUSTRATING	☐ CARTOONING
☐ Business Management	☐ Advertising
☐ Business Law	☐ Better Letters
☐ Banking and Banking Law	☐ Stenography and Typing
☐ Accountancy (including C.P.A.)	☐ Business English
☐ Nicholson Cost Accounting	☐ Civil Service
☐ Bookkeeping	☐ Railway Mail Clerk
☐ Private Secretary	☐ Common School Subjects
☐ Salesmanship	☐ High School Subjects

TECHNICAL AND INDUSTRIAL COURSES

☐ Electrical Engineering	☐ Surveying and Mapping
☐ Electric Lighting	☐ Architect
☐ Mechanical Engineer	☐ Architects' Blueprints
☐ Mechanical Draftsman	☐ Contractor and Builder
☐ Machine Shop Practice	☐ Architectural Draftsman
☐ Railroad Positions	☐ Structural Engineer
☐ Gas Engine Operating	☐ Chemistry ☐ Pharmacy
☐ Civil Engineer	☐ Automobiles
☐ Steam Engineering ☐ Radio	☐ Mathematics

Name.....

Street Address.....

City.....State.....

Canadians may send this coupon to International Correspondence Schools Canadian, Limited, Montreal, Canada



FREE BOOK Tells How

You can quickly qualify for big-paying positions in Motion Picture, Portrait, Commercial or News Photography, or start your own business. No experience needed.

CAMERA FREE Learn at home or in our great New York Studios. Earn while learning. Write today for Free Book, Job Chart and Free Camera offer.

NEW YORK INSTITUTE OF PHOTOGRAPHY
Dept. 5 10 West 33rd St. New York

Why We Mob Heroes

(*Continued from page 26*)

makes the touchdown brings the whole student body to its feet with a roar. But his exploit is useless. The students don't cheer madly their college professor who has made a lasting contribution to mankind through some arduous bit of research work.

What is the answer? The reason again is to be found in the primitive source of hero worship. It isn't based on a mental calculation of our idol's contribution to human welfare. It arises from the opportunity our idol's exploit offers us to express socially-balked energies.

Modern life affords few outlets of a practically useful kind to the reserves of emotional power we have inherited. But contests of endurance and physical prowess do bring them out. In a game of tennis you use up more energy than in painting the porch floor. But a hard game of tennis makes you feel fine, and painting the floor tires you.

IN OTHER words, the emotions of the tennis contest tap your energy reserve; and likewise the emotions of watching Lindbergh contending for supremacy with other men and with the elements pleasurably releases your emotional reserves.

But had one of the other contenders, Chamberlin or Byrd, flown first, our enthusiasm—and the consequent publicity—would have been something less than it was in Lindbergh's case. To understand why Lindbergh was called "the greatest hero of the age," we may neglect the features of the Paris hop that would have made any one of the flyers famous.

Let's forget the international rivalry, the fate of Nungesser and Coli which harrowed our feelings and dramatized the peril of the flight. Forget Lindbergh as a sort of aerial ambassador of good will, and forget the thrill to our national pride which came with the announcement of Lindbergh's dramatic arrival. All these things built up the total effect to an unparalleled peak of popular enthusiasm. But they might have done the same had Byrd been the first flyer.

Consider Lindbergh the individual.

Lindbergh is unmarried. The other flyers have families. Women could more easily think of themselves as the possible Mrs. Lindbergh than they could fancy themselves ousting Mrs. Byrd from her rights.

Lindbergh is ingratiatingly youthful. Boys want to be heroic young men. Older men want to be heroic young men. Women want the attention of heroic young men. The whole populace could give vent to a deep desire by self-identification with Lindbergh.

It chances that Lindbergh's personality is just the kind in which we could most gratifyingly picture ourselves. He is the typical American boy. He isn't too handsome, too remote, too polished. He is one of us. He is self-made. He comes out of the heart of the country. He has tinkered with motorcycles; he has been kicked out of college; he has been a regular boy. In his failings he typifies our own failings, and in his merits he typifies those we long for.

THUS it is comparatively easy to identify ourselves with him, and it is especially pleasant to do so because of his dramatic entry into the race. He swooped into it unexpectedly, in two hops across the continent. When the mile runner comes up from behind and beats the leaders out at the tape, we burst our lungs in cheering. The trailing contender who passes the others in a final gruelling spurt thrills us because he symbolizes our own situation in life. We are always trailing; somebody is always ahead of us. We long to put forth superhuman efforts and dash into the van. We applaud the man who does; in him we see ourselves doing the same thing.

But most important of all, Lindbergh, coming up from behind, flew alone. His backers kept completely out of the picture. We barely know their names. Hence our interest was not divided, as it was in the case of the other fliers.

Now in coolly hopping off all alone Lindbergh impressed us as being immeasurably heroic. Not only because he would have no assistance in an emergency, but also because of our unreasoning fear of solitude. Man has never been able to fight nature alone. A man condemned to solitude often goes crazy.

Lindbergh flew alone! But in fancy we all flew with him, or rather each of us was Lindbergh, making that flight through fog and darkness in the solitude which we dread, particularly, when confronting the elements. The cave man could fight his battle single handed against a wild beast; but when the thunder roared he felt his helplessness and wanted company. Those of us who fear thunderstorms today are unreasoningly happier if we have company.

THUS, when Lindbergh "made it," each of us felt vaguely as if we had come through with him, and pulled off a feat of unique courage. In celebrating his success we were figuratively patting ourselves on the back as well; and less fancifully we were glorying because *one of us* had succeeded.

As a matter of fact, if Byrd in his polar flight had fallen in the Arctic he would have been more hopelessly lost than had Lindbergh fallen into the ocean where a chance ship might conceivably have rescued him. But Byrd was not alone. It was Lindbergh the freelance, the "flying fool," who fascinated us.

We can't divide our enthusiasm over several people. The returning general must share his glory with an entire army. Even Peary, in his final dash to the pole, had to have support. He took a man of another race, which helped us to concentrate our enthusiasm upon him. But there was nobody at all to share Lindbergh's triumph. Hence the intensity of hero worship that engulfed him.

Once the outburst is over, the hero is soon forgotten. Who were the round-the-world fliers? Who made the daylight non-stop flight from coast to coast? The popular hero must keep "doing his stuff." When Jack Dempsey was champion and didn't fight, the fans turned against him. When he put on the gloves again they rallied around him. Gertrude Ederle, performing in a tank in vaudeville, is not making the financial success predicted. Even Lindbergh's day is already passing.

IN CROWD hysteria over each successive hero, we exhaust the energies which his feat typified, and for the time being are satisfied. Another hero, who represents another of our ideal selves, replaces him. The secret of it all is the innate wish to escape inexorable reality by annihilating time, space and mortality. Lindbergh had his day because he approximated two out of these three desires.

Microphone Beats Ear

WHEN English radio engineers recently attempted to broadcast a nightingale song from a microphone concealed in a thicket, they thought the attempt a failure; the seldom-heard birds apparently had failed to perform. But their doubts were quickly dispelled by radio listeners, many miles away, who heard perfectly the song of a bird inaudible at the transmitting end. So much more sensitive was the transmitter than the human ear that it was able to pick up a distant nightingale's song without the engineers' knowledge.

Airships 2,000 Years Old!

(Continued from page 42)

invented by the magicians, in their efforts to create miracles, are known to have existed, but no more than casual mention of them can be found. For instance, the diving suit of Alexander the Great, in which he investigated the bottom of the sea, in 320 B.C., is frequently mentioned by ancient historians. But descriptions of it differ. Some claim it to have been a diving suit in which the wearer could walk along the ocean bed, while others have it a diving bell built of glass.

We know that asbestos was worn on the soles of the feet of the priestesses of Diana, in 600 B.C., when they walked over red-hot coals at the annual festival in the Greek Temple of Apollo at Bastabala. We also know that the ancients had a method of fireproofing wood, never yet rediscovered; and that the priests of most countries were familiar with a secret ointment which protected their bodies in fiery ordeals.

WE ARE sure that the magicians resorted to fumigation to rid their temples of fires. A well-known example of this was in the Temple of Hercules, on Mt. Oeta, Greece, where the gods had been invoked to free the building of pests.

We have read that on Mount Larysium, in the southeastern district of Peloponnese, which was called Laconia, the feast of Bacchus was celebrated in the early spring, and that ripe grapes were produced in testimony of the favor of the goddess. Now we learn that hothouses were responsible for that pretended miracle.

And—of interest to this generation—Plutarch, a Greek writer under the Roman Empire, tells us that the physicians of the Roman Emperor Tiberius (14–37 A.D.) were familiar with the use of bitter almonds to prevent drunkenness. The presence of prussic acid in the almond has a sobering effect.

Plows 1000 Acres a Day

(Continued from page 28)

planted, cultivated and harvested at the right time. Engines are faster than men and horses."

Electricity is playing an increasingly important rôle in agriculture. The individual electric plant has found countless farm customers. More and more power lines are being run through the country. Electric motors even for such heavy power requirements as feed grinding and ensilage cutting are not infrequent. Lighted barns spot the countryside at night, and literally millions of hens are awakened early on winter mornings when an alarm clock throws an electric switch, and hop off their roosts to eat food and lay more eggs.

Fewer farmhands are necessary when one man with a tractor can plow four to eight times as much as he could with a team. In 1830 one farmer could handle twelve acres in crops; today he can take care of thirty-four acres. A bushel of wheat under primitive methods required three hours of human labor; now ten minutes suffice.

Other inventions soon will make it possible for still fewer farmers to do the same work. Engineering students at Iowa State College, under the direction of Prof. J. B. Davidson, have nearly perfected a plow that will run without any human attention other than to supply fuel and oil. Automatically it crosses a field, reverses, shifts and recrosses. Another manless plow invented by F. L. Zibach, of Grand Island, Neb., and demonstrated at the University of Nebraska, was described in POPULAR SCIENCE MONTHLY for August.

As more farms adopt the proved mechanical advantages of the day, a reduction of at least twenty-five percent in the number of agricultural workers will be possible without reducing food production.



LOOK WHAT I'VE DONE FOR THESE TWO MEN

$65 A Day!

"Dear Chief: If it hadn't been for your wonderful Course I wouldn't now be making as high as $65 a day. It makes me proud to have your Diploma. And believe me I am a booster for your Course." Jacob Lens, 1223 1st Ave., Hillsboro, Ore.

$75 A Week!

"Dear Mr. Cooke: I was working in a store for $18 a week when I started your Course. Then I began doing Electrical Work in my spare time. Now I average as much as $75 a week." J. Wollaston, 104 Robin St., Dunkirk, N. Y.

Free of EXTRA COST
6 BIG OUTFITS

The BIG PAY FIELD

GET a real job—be able to afford the better things of life—learn to make $70 to $200 every week instead of a mere $25 to $35—jump into Electricity and join my thousands of "boys" who are now earning $3500 to $10,000 a year! You can do it—it's easy—I'll show you how in so short a time you'll be amazed!

Electrical Men in Big Demand

Even ordinary electricians—the common "screw driver" kind are making big money. But the Trained Man—the man who can plan and boss and supervise the work of others—is needed everywhere today at $300 to $900 a month! And thousands of "Cooke" Trained Men are getting this big money right along! Don't YOU be satisfied with anything less!

Learn at Home

You don't need a College education nor a High School diploma to learn Electricity from me. And you don't have to quit your job nor even lose a single hour's pay! With my famous "Work Sheet" and "Job Ticket" Method I train you at home. And I train you right! You get not only theory but practice! I give you Six Big Working Outfits without extra charge so you learn by doing! That means you learn Electricity **right**—learn it so you can quickly become a Big-Pay Man in this Big-Pay field!

Earn While You Learn

Not only do I give you an Electrical Training that is thorough and complete—the training that Electrical Experts recommend and Electrical Companies select for their employees—but I show you, right from the start, how to make spare time money doing little electrical jobs that more than pay for the entire Course! Later comes the Big Job and the Big Pay—an income large enough to make you independent the rest of your life!

Get Started—Mail Coupon!

You want big money—you want to get into work where men are in constant demand. Then act! Get my Big Pay-Raising Book. It's free. Shows why "The Cooke Trained Man is The Big Pay Man" everywhere and always! Shows how easily YOU too can become a "Cooke" Trained Man with a real honest-to-goodness income. Get started. Mail coupon at once!

L. L. COOKE, Chief Instruction Engineer
L. L. COOKE SCHOOL OF ELECTRICITY
Dept. 36 2150 Lawrence Ave., Chicago, Ill.

FREE BOOK COUPON *MAIL IT!*

L. L. COOKE, Chief Instruction Engineer
Dept. 36, 2150 Lawrence Ave., Chicago, Ill.

You may send me, entirely Free and fully prepaid, your book, "Secrets of Success in Electricity," together with facts about your Home Study Course in Electricity.

Name_____

Address_____

City_____

Residents of Canada may send this coupon to R. A. Farrow, Special Representative, 7 Medbury Lane, East, Windsor, Ontario, Canada.

The "Cooke" Trained Man is the "Big Pay" Man

Make More Money Read the Money Making Opportunities on pages 124 to 151 of this Issue.

TRAVEL - for 'UNCLE SAM'

RAILWAY POSTAL CLERKS
MAIL CARRIERS—POSTOFFICE CLERKS
$1700 to $2700 a Year for Life

No "lay-offs" because of strikes, poor business, etc.—sure pay—rapid advancement. City and country residents stand same chance. Common sense education sufficient—no political influence.

STEADY WORK Cut coupon and mail it before turning the page.

MEN—BOYS
18 to 45
Use Coupon Before You Lose It

"COUPON"

FRANKLIN INSTITUTE, Dept. M-264, Rochester, N.Y.
Rush to me, entirely free of charge, 32 page book with (1) A full description of the position checked below: (2) List of jobs now obtainable.

☐ Railway Mail Clerk ($1900 to $2700)
☐ Postoffice Clerk ($1700 to $2300)
☐ City Mail Carrier ($1700 to $2100)
☐ Prohibition Agent ($1800 to $3000)
☐ Rural Mail Carrier ($2100 to $3300)

Name.....
Address.....

"Student Receives $250 For a Few Cartoons"

JUST read the following "straight from the shoulder" letter and you'll see why we say that the Washington School of Cartooning can prepare you for the big pay field of Cartooning, in your spare time, at home, by mail.

"The enclosed cartoons," says O. A. Pokrandt, a Wisconsin student, "are samples of my progress in drawing. I have received $250 for these and the enclosed letter will show that I have a ready market for my work in the future. The making of cartoons has been one round of pleasure and enjoyment as well as profitable to me."

Cartooning Pays Big

There's no more attractive or highly paid profession today than Cartooning. Millions of dollars are spent every year on cartoons. Capable cartoonists earn from $50 to $250 a week. Learn to draw side-splitting comics—right at home in spare time through this amazing method that has already been tested and proved by many Washington School Graduates. No special talent or previous training needed. No drudgery. And in a very short time you should be ready to make money drawing cartoons.

Send for FREE Book

A new handsomely illustrated book has just been printed, which gives all the most up-to-date information on the wonderful opportunities in Cartooning, and shows how this startling method enables you to enter this field. It tells all about our students—their success—what they say—actual reproductions of their work—how they made quick profits while studying. This attractive book will be sent without cost or obligation. Send for it. Mail coupon NOW. **Washington School of Cartooning,** Room 249E, 1113-15th St., N. W., Washington, D. C. No obligation. (No salesman will call.)

Washington School of Cartooning,
Room 249E, 1113-15th St., N.W., Washington, D.C.
Please send me without obligation, your illustrated FREE BOOKLET on Cartooning.

Name.....
(Write Name Plainly) State whether Mr., Miss or Mrs.

Address.....

City.....State.....

Age.....

When Neptune Scowls

(*Continued from page 36*)

appeared leaving no clue as to their fate.

On this night, when the moon smiled down on tranquil water, the captain never left the bridge. Hydrographic reports stated that icebergs were adrift here.

A few minutes after two o'clock the captain's quick eye saw what appeared to be a huge silver cliff arising from the sea. In another instant he realized it was an iceberg that had sneaked upon his course.

He remembered the *Titanic*. He remembered the 750 souls in the berths below. He knew it would be impossible to swing his ship about quickly enough to miss the jagged glacial mountain.

Within two seconds he had ordered full steam astern, changed his course and headed the *Grampian* straight for the floating terror. They crashed! The vessel's bow caved in as if made of paper. Ice, tons of it, tumbled upon the deck.

THE crew discovered that the upper part of the bow had struck an overhang of the berg which had stuck out, like a balcony. This made a great gash just above the water line. If it had crushed the entire bow, even below that line, the ship still would have remained afloat, as the captain figured, because of the water-tight bulkhead placed about twenty feet aft the bow by the builders for just such an emergency.

The stem of the *Grampian* was driven back forty feet, and two of the crew were caught and killed in the wreckage, but the captain, by sending his craft head-on into the berg, had saved 750 passengers.

The bridge is no place for a slow thinking man when two ships collide. Had the captain of the Ward liner *Sagua* thought sluggishly when his craft was mortally wounded in a collision with the *Bing*, a small freighter, off Barnegat Shoals one March night in 1917, Davy Jones would have claimed him and his ship.

The *Sagua*, homeward bound, was feeling her way through the fog-blanketed waters when the *Bing* stuck its nose into the liner's stern, tearing a hole big enough for a rowboat to enter. The *Sagua* staggered and trembled. Before she was back to an even keel the captain directed the closing of the bulkhead doors of the water-tight compartment just aft the engine room, but the inrushing water threatened to buckle the doors.

BELIEVING the doors would hold long enough to make New York Bay, the captain headed there and managed to beach the *Sagua* on the flats on the south shore of Bedloes Island.

Some of the most costly accidents occur not on the high seas but when ships are in friendly harbors. There was the German ship, *Burgomeister Hackman*, for instance.

With 120,000 cans of oil she was tied up at her pier in New York taking on the last few thousand pounds of cargo. Then: Bang! The wheel of a stevedore's hand truck struck the wheel of another stevedore's truck. Two boxes of inflammable liquids toppled from one of the loads and one went hurtling into the hold. Twenty-five feet below, it hit another box with such force that sparks flew. Instantly there was an explosion. The cargo was destroyed and the ship badly damaged.

One would hardly expect a million-dollar accident to happen to a steamship unless by fire, explosion or collision. But that is approximately what it cost the U. S. Government to recondition the steamship *St. Paul* after she went down in forty feet of water at her pier in the Hudson River in 1918.

The Government had just taken over the *St. Paul* for transport service. She was being towed into her slip when 400 men working aboard her noticed a decided list to starboard. The men scuttled for their lives.

Just as the last of the workmen reached the open deck the *St. Paul* keeled over on her side. Her masts and superstructure crashed against the pier, then snapped, and a moment later she sank. The exact cause of the *St. Paul's* capsizing was never satisfactorily explained, although investigations were made.

There are "good dog Trays" in the world of ships, as well as in the canine world. These "innocent bystanders" often are victims of peculiar accidents.

The steamer *Curaca* was one of these unfortunates. On the night of December 6, 1917, she was one of a score of ships in Halifax harbor. Members of the crew were in the forecastle sleeping or writing Christmas letters when the French munitions ship *Mont Blanc* collided with the steamer *Iowa*, laden with Belgian relief supplies.

IN THE resultant explosion which took 2,000 lives and wrecked an enormous amount of shipping, the *Curaca's* superstructure was blown away and her hull badly damaged. Towed to New York, she was found to sag eight feet in the middle. She seemed hopelessly broken. But she was too valuable a bottom to give up without a fight.

With infinite patience and skill shipyard engineers set about to straighten her keel. And how they succeeded is well worth passing along to others. When the *Curaca* was placed in a graving dock, care was taken to align the keel blocks so the ship could be brought back to a straight line keel. A careful survey was taken to make sure that the vessel was over the position as laid out for her. The great problem was to bring the portions of the hull—bow and stern—in perfect alignment so as to allow for a patch over the break.

To relieve the strain on the material as much as possible, workmen with torches were set to cut the steel plates at the break in the hull, thus allowing the two ends of the ship to settle toward the keel blocks as fast as the water was pumped from the dock.

After seven and a half hours of pumping the dock was entirely free of water and the two ends were resting on the blocks. The *Curaca* had been brought back to a straight line keel. Shipping men who watched the work on the *Curaca* pronounced it one of the most difficult repair feats ever performed.

The hurricane that visited the south Atlantic last summer, piling harbor craft high upon the sands at Miami and other ports, kicked up nothing more than a little "ground swell" compared to the tidal wave which followed an earthquake that hit the harbor of Pisco, Peru, back in '68.

THE *Wateree*, a double-ended gunboat which had seen service in the Civil War, anchored in twenty fathoms of water, was farthermost from the Pisco piers and consequently was the first to feel the full force of the mountainous wave that came in from the sea.

The wave hit the *Wateree* full on her port side. The chains snapped like strings. The next instant the gunboat was lifted high into the air, to the very crest of the great sea wave, and started on its mad journey inland.

Over the piers she went with a rush and a roar, across and above the waterfront shanties, through the municipal plaza, on and on across the lowland town like a frenzied leviathan, hitting a tree here, a house top there, tumbling, twisting, turning, until, at last, she brought up with a crash against a hillside three miles from her original anchorage.

When the waters subsided, almost immediately, the *Wateree* was no longer a denizen of the sea, but a mute monument to the mighty, and sometimes wrathful, gods of the ocean.

Next We'll See to Paris

(Continued from page 23)

ingenious and original method of scanning.

You will recall that in the method employed to send the face of Herbert Hoover from Washington to New York, the face was scanned by an arc light beam, which swept across it in a series of fifty parallel lines. This was accomplished by means of a whirling disk punctured with a spiral of fifty holes, through which the beam passed.

BAIRD employs not one, but three rotating disks. Instead of sweeping a narrow beam across the face in a succession of lines, he illuminates the entire face with filament lamps of 300 candlepower. The first of his disks, turning 800 revolutions a minute, contains sixteen lenses placed in staggered arrangement so that each focuses on the photo-electric cell a different section or strip of the face. The lenses are arranged in two sets of eight, dividing the face into eight strips. But interposed between the lens disk and the photo-electric cell is a second disk punctured with numerous apertures and turning 4,000 revolutions a minute. These swiftly moving slots interrupt the light rays from the lenses, and thus have the effect of breaking the image into smaller fragments. To give a still finer grain to the image, a third disk with a single spiral slot rotates at 200 revolutions a minute between the second disk and the light-sensitive cell.

The combined effect of this complicated arrangement of revolving disks is to cause the image of the face to fall upon the photo-electric cell in a succession of tiny squares of light of varying intensity. Instantly the cell translates them into a fluctuating electric current of corresponding intensity. This changing current then is amplified and transmitted.

Picked up at the receiving station, the current is amplified again and led to a tube filled with neon gas, causing it to glow with varying intensity, corresponding to the fluctuations of the current. The light from the tube passes first through a disk with a spiral slot, then through lenses in a second rotating disk. Both disks are exact duplicates and rotate at precisely the same speed as the corresponding disks in the transmitting station. The lenses focus the successive patches of light on a ground glass screen, thus building up and reproducing complete images of the original face. All this is done so rapidly that to human eyes not only does the succession of light patches become a complete image instantaneously, but the successive images themselves blend together into lifelike motion.

AS IN the Bell Laboratories television system, the entire success of this method depends on the perfect timing, one with the other, of the rotating disks in the transmitting and receiving stations. This demands that the motors which drive the disks in both stations be perfectly synchronized. Baird accomplishes this by coupling to the transmitting apparatus an alternating current generator, from which current is transmitted to the receiving station. There it is amplified and controls the speed of a synchronous alternating current motor.

Baird is confident that television service over the sea soon will be established on a commercial basis. Faces, he says, will be flashed across the Atlantic on a wave length of forty-five meters. Of his visit to America, Baird said recently:

"This will be almost the last phase in the development for world-wide broadcast purposes. All that will remain will be the actual perfection of a seen image, which is approaching completion. Improvements which I have effected make it mainly a question of greater power to be able to see a person or scene thousands of miles distant."

PATENTS TRADE-MARKS AND COPYRIGHTS

OUR OFFER:

Your first step—

The inventor should write for our blank form "RECORD OF INVENTION." This should be signed, witnessed and returned to us together with model or sketch and description of the invention for INSPECTION and INSTRUCTIONS FREE.

Our Four Books Mailed Free to Inventors

Our Illustrated Guide Book

HOW TO OBTAIN A PATENT

Contains full instructions regarding U. S. Patents. Our Methods, Terms, and 100 Mechanical Movements illustrated and described.

OUR TRADE-MARK BOOK

Shows value and necessity of Trade-Mark Protection. Information regarding *Trade-Marks and unfair competition in trade.*

OUR FOREIGN BOOK

We have Direct Agencies in Foreign Countries, and secure Foreign Patents in shortest time and at lowest cost.

Progress of Invention

Description of World's Most Pressing Problems by Leading Scientists and Inventors

ALL COMMUNICATIONS AND DATA STRICTLY CONFIDENTIAL
INTERFERENCE AND INFRINGEMENT SUITS PROSECUTED

IMPORTANT

TO MAKE YOUR CASE SPECIAL AND AVOID DELAY YOU SHOULD HAVE YOUR CASE MADE SPECIAL IN OUR OFFICE to secure protection, save correspondence and obtain early filing date in Patent Office. To secure special preparation of your case send $25.00 on account with model or sketch and description of your invention.

Highest References—Prompt Attention—Reasonable Terms

Private Office, Victor J. Evans, with View of Patent Office Through Window

WRITE TODAY

Free Coupon

VICTOR J. EVANS & CO.

Patent Attorneys

Main Offices: 760 Ninth St., Washington, D.C.

New York Offices 1007 Woolworth Bldg. | Philadelphia Offices 518-519 Liberty Bldg. | Pittsburgh Offices 514 Empire Bldg.
Chicago Offices, 1114 Tacoma Bldg. | San Francisco Offices, Hobart Bldg.

Gentlemen: Please send me FREE OF CHARGE your books as described above.

Name..... Address.....

"His Tail Between His Legs"

What most men would see if they could see themselves

MOST men are being whipped every day in the battle of life. Many have already reached the stage where they have THEIR TAILS BETWEEN THEIR LEGS.

They are afraid of everything and everybody. They live in a constant fear of being deprived of the pitiful existence they are leading. Vaguely they hope for SOMETHING TO TURN UP that will make them unafraid, courageous, independent. But it never does. They continue to work and sweat and—MAKE OTHERS RICH AND HAPPY.

Some men, however, after years of cringing, turn on life. They CHALLENGE the whipper. They discover, perhaps to their own surprise, that it isn't so difficult as they imagined, TO SET A HIGH GOAL and reach it! Only a few try—it is true—but that makes it easier for those who DO try.

What about YOU? Are you ready to admit that you are through? Are you satisfied to keep your wife and children—and yourself—enslaved? ARE YOU AFRAID OF LIFE?

Success is a simple thing to acquire when you know its formula. The first ingredient is a grain of COURAGE. The second is a dash of AMBITION. The third is an ounce of MENTAL EFFORT. Mix the whole with your God-given faculties and no power on earth can keep you from your desires, be they what they may.

You can develop these God-given faculties as SIX HUNDRED THOUSAND other people have done—through Pelmanism.

Pelmanism is the science of applied psychology, which has swept the world with the force of a religion. It has awakened powers in individuals, all over the world, they did not DREAM they possessed.

Famous people all over the world advocate Pelmanism, men and women such as these:

T. P. O'Conner, "Father of the House of Commons."
The late Sir H. Rider Haggard, Famous Novelist.
General Sir Robert Baden-Powell, Founder of the Boy Scout Movement.
Judge Ben. B. Lindsey, Founder of the Juvenile Court, Denver.
Frank P. Walsh, Former Chairman of National War Labor Board.
Jerome K. Jerome, Novelist.
Gen. Sir Frederick Maurice, Director of Military Operations, Imperial General Staff.
Admiral Lord Beresford, G. C. B., G. C. V. O.
Sir Harry Lauder, Comedian.
W. L. George, Author.
Baroness Orczy, Author.
Prince Charles of Sweden

—and others, of equal prominence, too numerous to mention here.

A remarkable book called "Scientific Mind-Training," has been written about Pelmanism. IT CAN BE OBTAINED FREE. Yet thousands of people who read this announcement and who NEED this book will not send for it. "It's no use," they will say. "It will do me no good," they will tell themselves. "It's all tommyrot," others will say.

If you are made of the stuff that isn't content to remain a slave — if you have taken your last whipping from life,—if you have a spark of INDEPENDENCE left in your soul, write for this free book. It tells you what Pelmanism is, WHAT IT HAS DONE FOR OTHERS, and what it can do for you.

The first principle of YOUR success is to do something radical in your life. You cannot make just an ordinary move, for you will soon again sink into the mire of discouragement. Let Pelmanism help you FIND YOURSELF. Mail the coupon below now—now while your resolve to DO SOMETHING ABOUT YOURSELF is strong.

THE PELMAN INSTITUTE OF AMERICA
Approved as a correspondence school under the laws of the State of New York.
71 West 45th Street Suite 879 New York City

The Pelman Institute of America,
71 West 45th Street, Suite 879, New York City.

I want you to show me what Pelmanism has actually done for over 550,000 people. Please send me your free book, "Scientific Mind-Training." This places me under no obligation whatever.

Name.....

Address.....

City.....State.....

A House of 30 Servants

(Continued from page 67)

and percolator, are often connected by cord to an overhead lighting outlet, which is a poor makeshift, or to a wall outlet, which is better. In high-class installations there are no exposed cords, the "juice" traveling through the hollow center leg of the table and the outlets being countersunk in the table surface.

The size of wires is even more important. It would seem that we might leave this detail to the building code and to electricians. But the owner who does this often gets about as much satisfaction as a hungry man who enters a restaurant and asks for "a plate of food." With 110-volt service the ordinary lighting circuit will take care of all small appliances between vacuum cleaner, dish washer, fan and refrigerator. More current is needed for heating and cooking apparatus, which require heavier wire.

EVERY appliance is or should be marked by the maker with its watt consumption. Divide the number of watts in a given device by the voltage and the result is amperes, from which the proper size of wire can be determined. For example, the total load on one circuit is four 660-watt units or 2640 watts; dividing by 110 gives 24 amperes, for which the necessary size of rubber insulated wire is No. 10. Here is a table of wire sizes as prescribed by the National Electrical Code:

Amperes	B. and S. gage wire
3	No. 18
6	No. 16
15	No. 14
20	No. 12
25	No. 10
35	No. 8

Perhaps some one who has no wire gage—and not every electrician has one—will appreciate being told that the wire numbers indicate thickness or diameter in very nearly corresponding fractions of an inch; as No. 8 is close to one eighth inch, No. 10 is about one tenth inch, and so on.

How much apparatus does the Caldwell house contain? About everything you ever read of or saw at an electrical show; but everything has its place and the casual visitor hardly notices the difference between this and any other tastefully furnished dwelling. As we enter the living room we glance at a small mantel clock. Is that the right time? It has to be, since the clock is electrical and ruled by Washington. No winding and no setting. It is forever and almost monotonously correct. What is this other little clock? The radio control, which doses out sleep-music and exercises. On the wall is a neat thermometer—of course, a thermostat at second glance—which keeps the house temperature within one degree of the desired point throughout the winter. With clock control the heat is lessened to any point at night and brought back in the morning. A bell tinkles faintly. The hostess picks up a miniature receiver and talks with a daughter upstair. This is an interior telephone that connects the principal rooms and saves steps.

THE dining room has all the apparatus for quick and easy breakfasts with interior phone and music thrown in. The kitchen contains an electrical clock, a fan to mitigate summer heat, a choice of radio earphones and loudspeaker, interior phone, electric refrigerator and dish-washer, a little machine that does the work of several "slaveys" in grinding coffee, beating eggs, chopping meat, slicing vegetables, mixing batter, making ice cream, sharpening and polishing knives; and finally a large electric range with oven and clockwork attachment. You may put the raw materials of a dinner in the oven in the morning and leave the house for the day. At four p. m. the clock turns on 1000 watts of current. Meat and vegetables are brought to a roasting temperature in half an hour, when the current automatically switches off. Cooking continues for an hour and a half with the heat stored in the oven by walls heavily insulated with mineral wool. When you return home at six o'clock dinner is ready to serve. Take a frozen dessert from the refrigerator, make coffee at the table. The cost of cooking that meal, at a power rate of five cents per kilowatt hour, has been exactly two and one half cents!

"Yet some people say electric cooking is expensive," I remarked.

"Yes, I know of a family that gave it up when the monthly bill ran to fifty dollars," replied Mrs. Caldwell. "The reason was that the servants used the elements on the stove to heat the kitchen. Of course it is expensive to use electricity for heating in that way."

"Can a servant be trusted to manage an electric range properly?"

"OURS have had no trouble. We had a Negro maid who not only did everything correctly, but taught herself, after a year, to make small adjustments and rewire any kitchen plugs that needed it."

The current cost for apparatus in general is surprisingly low. That versatile kitchen "slavey" unit costs about half a cent an hour. A refrigerator averages around seventy-five cents a week. An electric fan is half a cent an hour, while a radiant heater or a hand iron uses about four and one half cents' worth of current in the same time. Plenty of toast and coffee can be had for two cents, dishes are washed for half as much, an hour of vacuum cleaning is done for a penny. The larger apparatus, as full size range, refrigerator and kitchen unit, are relatively expensive in first cost while moderate in power consumption. It is interesting to note that operation cost has led to greater efficiency in the electric range, through timing and insulation features, than is found in the ordinary gas or other fuel cookstove. Waste and inconvenience go with cheap fuel.

Heating a house and water in quantity are two things which electricity cannot do with any approach to economy. The Caldwell house is heated with gas used with a steam boiler. It is an absolutely automatic system, noiseless and dustless. It ranks mechanically above oil and just below electricity. Its cost is another story, although the owner does not think it excessive compared with the high local price of coal, which he formerly used.

There is a complete electrical laundry in the Caldwell basement and the visitor notices here as elsewhere those little pilot lights which locate fixtures in the dark and also give warning that an appliance is using current, whether a hand iron, washing machine or other device.

SINCE Mr. Caldwell is an amateur astronomer, it seems appropriate that he should have fixed up a celestial ceiling for the children's room. Small golden stars dot the blue-white ceiling and constitute an accurate astronomical map with the Great Bear, the Little Bear and all the other sky animals and persons just where they belong. The sun is represented by a large frosted globe light at the wall.

It occurs to the visitor that there may be a minor serpent, as it were, lurking in the electrical Eden. With apparatus, motors and devices galore, there should be quite an item of upkeep and a source of considerable expense. But Mr. Caldwell attends to most of the upkeep himself, spending an hour a month in mending wires, scraping contacts and so on. The vacuum cleaner has a general overhauling once a year. The electric range has needed renewal of heating elements once in four years. A washing machine has been used for eleven years and its total repairs have cost under $25.

Answers to the Sam Loyd Puzzles on Page 65

Can You Pen These Pigs?



The diagram shows how the plucking of one porker from the outer pen and depositing it in the center will present an arrangement which by a little play of the imagination can be made to fit the famous Rory O'More formula: that each pen must contain an even number of pairs and an odd pig.

The central pen containing five pigs fills the bill. Now comes the playful feature of the puzzle as hinted. The second inner pen must be regarded as containing all the pigs within its borders; in other words it contains a total of nine pigs—an even number of pairs and an odd pig. Viewed in the same way, the next pen will contain thirteen pigs and the pen which embraces all the others must be credited with holding the entire twenty-one pigs.

An Arithmetical Courtship

On Sunday, the first day of the week, Kate promised to marry Danny "when the week after next is the week before last." Therefore, if Kate lives up to her promise she will marry Danny in four weeks, or twenty-eight days. Had Danny proposed a day earlier and Kate had made the same reply, then on Sunday, twenty-two days later, her promise would have fallen due.

Moving a Pyramid

The pyramid of cubes may be transferred from Plate No. 1 to Plate No. 2 in 17 moves as follows: A to 2, B to 3, C to 4, B to 4, A to 4, D to 2, E to 3, D to 3, F to 2, D to 1, E to 2, D to 2, A to 1, B to 3, C to 2, B to 2, and A to 2.

A Rebus Memorandum

The sign-maker's memorandum indicated four feet for the reason that it was "3 inches over an L." An ell is a measure of forty-five inches in length.

The Clock Race

Grandfather's clock lost two minutes every hour and the alarm clock gained one minute, so it is evident that the alarm clock in an hour's time gained three minutes upon the other. Therefore, in twenty hours it gained 60 minutes. During those twenty hours the alarm clock gained 20 minutes upon correct time, from which we deduce that the race must have started the previous morning at 20 minutes to 12 o'clock.

Insane Sleep in Sawdust Beds

SAWDUST beds for insane patients are the rule at the Eastern State Hospital, Lexington, Ky. According to Dr. William R. Thompson of that institution, helpless patients cannot fall out of the oblong wooden troughs filled to within six inches of the top with fresh sawdust. The beds are comfortable, and "changing the linen" is a matter of renewing the sawdust filling.

Zoo Sells Elephant Hides

SELLING patches of elephant hide is the unusual but profitable business recently established at the London Zoo. The skin of mounted elephants in museums suffers extremely from the weather; and worn-out spots must be covered with patches of the same material. The zoo has just filled a large order for patches to restore the hide of Indarani, an elephant that died a few weeks ago.

PATENTS

TRADE-MARKS ·· DESIGNS
FOREIGN PATENTS

MUNN & CO.

PATENT ATTORNEYS

Associated since 1846 with the Scientific American

1583 SCIENTIFIC AMERICAN BUILDING
24 WEST 40th STREET
New York City

522 SCIENTIFIC AMERICAN BUILDING
Washington, D. C.

1311 TOWER BUILDING
Chicago, Ill.

664 HOBART BUILDING
San Francisco, Cal.

519 VAN NUYS BUILDING
Los Angeles, Cal.

Books and Information on Patents
and Trade-Marks By Request.
Associates in all Foreign Countries.

INVENTIONS Commercialized
ON A CASH OR ROYALTY BASIS
PATENTED or UNPATENTED
In Business 25 Years - Complete Facilities - References.
Write ADAM FISHER MFG. CO.
183-D Enright Ave. ST. LOUIS, MO.

INVENTORS who derive largest profits know and heed certain simple but vital facts *before* applying for Patents. Our book *Patent-Sense* gives those facts; sent *free*. Write LACEY & LACEY, 648 F St., Washington, D. C. Established 1869.

INVENTORS PROTECT YOUR IDEAS

Send for our Guide Book, **HOW TO GET YOUR PATENT,** and Evidence of Invention Blank, sent Free on request. Tells our terms, methods, etc. Send model or sketch and description of your invention for **Inspection and Instructions Free. Terms Reasonable. Best References.**

RANDOLPH & CO.
Dept. 130, Washington, D. C.

NAME.....
STREET.....
CITY.....STATE.....

Mechanical Engineering

Learn at Home

MECHANICAL Engineering embraces the design, construction and operation of machines and machine tools.

It is a profession which offers almost unlimited opportunities to men who combine natural mechanical ability with technical training.

For this is The Age of Machinery. Almost every convenience, luxury or necessity which we enjoy depends on machinery for its production or adaptability to our needs. Every new invention multiplies the opportunities for competent designers, builders, erecting engineers, etc.

One of the best ways to train yourself to secure a position as a Mechanical Engineer is through the home-study courses of the International Correspondence Schools.

These courses are complete and up-to-date, and they are especially arranged to meet the needs of the student who studies at home.

They are particularly helpful because they are written by well-known mechanical engineers who have had years of practical experience in this field and who know the quickest, best way to solve every problem.

Just mark and mail the coupon and we'll gladly send you Free Booklets describing the I. C. S. courses in Mechanical Engineering or any other course in which you are interested.

Mail the Coupon for Free Booklet

INTERNATIONAL CORRESPONDENCE SCHOOLS
Box 7639-E, Scranton, Penna.

Without cost or obligation, please send me one of your booklets and tell me how I can qualify for the position or in the subject *before* which I have marked an X:

☐ Mechanical Engineering	☐ Toolmaking
☐ Mechanical Course	☐ Blacksmithing and Forging
☐ Drafting	☐ Patternmaking
☐ Mechanical Drawing	☐ Foundrywork
☐ Complete Shop Practice	☐ Machine Shop Practice
☐ Electrical Engineering	☐ Architects' Blueprints
☐ Electric Lighting	☐ Contractor and Builder
☐ Radio	☐ Architectural Draftsman
☐ Railroad Positions	☐ Concrete Builder
☐ Civil Engineer	☐ Structural Engineer
☐ Surveying and Mapping	☐ Chemistry ☐ Pharmacy
☐ Metallurgy ☐ Mining	☐ Airplane Engines
☐ Steam Engineering	☐ Agriculture and Poultry
☐ Architect	☐ Mathematics

BUSINESS TRAINING COURSES

☐ Business Management	☐ Spanish
☐ Industrial Management	☐ French
☐ Personnel Organization	☐ Advertising
☐ Traffic Management	☐ Better Letters
☐ Business Law	☐ Show Card Lettering
☐ Banking and Banking Law	☐ Stenography and Typing
☐ Accountancy (including C. P. A.)	☐ Business English
☐ Nicholson Cost Accounting	☐ Civil Service
☐ Bookkeeping	☐ Railway Mail Clerk
☐ Private Secretary	☐ Common School Subjects
☐ Salesmanship	☐ High School Subjects
	☐ Illustrating

Name.....

Street Address.....

City.....State.....

PATENTS

Trade-marks, Copyrights, Patent Litigation, Handbook with illustrations, 100 mechanical movements. Sent free on request.

ALBERT E. DIETERICH

Formerly member Examining Corp. U. S. Patent Office
Patent Lawyer and Solicitor
27 years' experience

681-A Ouray Bldg. Washington, D. C.

PATENTS

BOOKLET FREE **HIGHEST REFERENCES**
PROMPTNESS ASSURED **BEST RESULTS**

Send drawing or model for examination and advice

WATSON E. COLEMAN, Patent Lawyer
724 Ninth Street Washington, D. C.

Explorers of the Sky

(*Continued from page 31*)

balloons" carry self-recording thermometers and barometers to great heights, until they burst. Then a parachute swings the instruments gently to earth, to be examined. "Pilot" balloons carry no instruments; they are watched as they rise by special telescopes known as "theodolites." They show how the wind blows miles above the earth.

In Germany, a sounding balloon reached twenty-two miles before it burst. A pilot balloon soared to a record height of twenty-four miles. This is probably the greatest altitude a man-made device has ever attained.

A projectile from a gun could be shot much higher if the gun were pointed straight up. Havoc would follow its fall. When Capt. Gray tossed overboard a twenty-pound oxygen cylinder, a parachute checked its descent. Otherwise it would have hurtled like a falling meteor through eight miles of space.

ROCKETS may send instruments even higher. Prof. R. H. Goddard, who has proposed to construct a rocket capable of reaching the moon, already has designed a small one to explore the upper air. A Viennese engineer, von Hoefft, proposes also to explore space to a height of sixty miles with an instrument-carrying skyrocket. This seems the only way to reach the upper levels; rockets need no air to fly, depending on their own "kick-back" for propulsion. At lower levels, says A. J. Mitchell of the U. S. Weather Bureau, helicopters may eventually replace balloons.

Eight-mile pilots and twenty-mile balloons have already told amazing things about the upper air. For instance, they have found out that our atmosphere is at least a two-layer affair.

You know the "troposphere"—the "ground floor" of the air, in which you walk daily. Put on your flying togs, and look at its ceiling. Twenty thousand feet—time to start taking oxygen. Going up now, and it's getting colder—two degrees for every thousand feet on the altimeter.

Look, now—the thermometer needle has stopped going down. It's cold enough here at 35,000 feet, goodness knows—nearly eighty below, but it's not getting any colder. You're still going up—climbing now into the most exclusive known region, the "stratosphere." The few men who have been here you could practically count on the fingers of one hand—Gray, Macready, Callizo, and a few others.

YOU could climb to the "ceiling" of your plane, and it would get no colder; possibly a few degrees warmer. There the thermometer remains stationary, regardless of height; though we know it would vary from day to day. And sounding balloons record the same state of affairs up to an altitude of twenty miles or more.

After this "stratosphere," what next? That is where experts disagree. The whole atmosphere extends five hundred miles, or more, above the earth, latest measurements of the aurora tell us. Somewhere, very likely, the stratosphere ends. All we are sure of is that any air above it is nothing like the air we know.

From their studies of the flight of meteors—which first flash into brilliance 100 miles above the earth—the astronomers Lindemann and Dobson conclude that a warm layer of air exists above the stratosphere, starting about forty miles above the earth. Its temperature they put at eighty degrees. Support for this theory comes from an unexpected source. A physicist, F. J. W. Whipple, studying the peculiar way that sound waves from an explosion are often heard better at a distance than near by, found that a warm upper air layer through which sound waves might recurve back to earth would account for this oddity. His calculations place the beginning of the third air layer at only twenty miles high, and give it a still higher temperature.

Again, Abbe Moreaux, director of the Bourges Observatory in France, is convinced the stratosphere ends fifty miles up, and at its top consists mostly of nitrogen gas, the heavier oxygen having sunk toward the earth.

Abbe Moreaux thinks hydrogen encircles the stratosphere. Only traces of hydrogen appear in the air you breathe; the rest may be miles up. Studies of the aurora's spectrum indicate that this is true. This hydrogen might be the warm layer the other investigators suggest.

ABOVE that, from a height of eighty miles up to the five hundred or so where the air ends, we are in the greatest doubt. Some unknown gas, says Abbe Moreaux, possibly the "coronium" observed in the spectrum of the sun, may be here. Dr. L. Vegard suggests that crystalline frozen nitrogen at 350 degrees below zero may encircle the air as a sort of shell.

When Capt. Gray listened to the radio receiving set he took with him on his record flight, he heard clearly music and voices from near-by stations up to a height of 35,000 feet, when they signed off. At this altitude he had evidently not reached the "radio roof" that is believed to reflect radio waves back to earth from some point in the upper air. This was to be expected, for the height of this layer is estimated at forty to ninety miles. Ozone formed by the sun's ultra-violet rays is now thought to cause it by breaking down into charged electric "ions"; and its height varies from day to night.

A radio roof, other mysterious layers—these await future explorers. But there is yet another fascinating possibility in the upper air. The earth may have captive meteors. It is likely, many astronomers believe, that some meteors shooting past our globe were swung out of their course by its gravity and now revolve about us as tiny satellites. One may have been seen.

AT A flying field in San Antonio, Texas, some years ago, Corley McDarment, an aviator, noticed an object that resembled a balloon at a great height in the southwestern sky. Through field glasses, the resemblance vanished. The peculiar object had a dark triangular streamer like a shadow pointing to the west. No balloons had been sent up near by, investigation showed; moreover, as far away as New York observers saw a similar object but mistook it for a balloon. The phenomenon remains a mystery.

One of the first altitude flights of any magnitude was that of Gaston Tissandier in 1875. With two companions, he rose over Paris in the spherical balloon *Zenith* to the then extraordinary height of 28,000 feet. Tissandier alone survived, his companions dying in mid-air. He was rendered unconscious.

This was before oxygen tanks were a part of every altitude flyer's equipment. Glaisher and Coxwell, two English balloonists, barely missed death a few years before. At 29,000 feet both became unconscious; Coxwell, fainting, set his teeth in the valve cord and released the gas that brought the men alive to earth.

Many years elapsed before further attempts; then, in 1901, two German balloonists, Suring and Berson, startled the world by reaching 35,424 feet.

What new upper-air explorations will disclose we can only guess. The upper void remains still a challenge to daring pilots. New inventions and new aircraft may enable them to go higher and higher still. Gradually, as they skim farther and farther beyond the world, we are learning more about the least known region of all—the upper air.

UNITED STATES CAPITOL

PATENTS

DON'T LOSE YOUR RIGHTS TO PATENT PROTECTION

Before disclosing your invention to anyone send for blank form **"EVIDENCE OF CONCEPTION"** to be signed and witnessed. As registered patent attorneys we represent hundreds of inventors all over the United States and Canada in the advancement of inventions. The form "Evidence of Conception," sample, instructions relating to obtaining of patents and schedule of fees sent upon request.

LANCASTER & ALLWINE
274 Ouray Building
WASHINGTON, D. C.
Originators of forms "Evidence of Conception."

PATENTS

To the Man With an Idea

I offer a most comprehensive, experienced, efficient service for his prompt, legal protection and the development of his proposition.

Send sketch, or model and description, for advice as to cost, search through prior United States patents, etc. Preliminary advice gladly furnished without charge.

My experience and familiarity with various arts, frequently enable me to accurately advise clients as to probable patentability before they go to any expense.

Booklet of valuable information and form for properly disclosing your idea, free on request. Write today.

RICHARD B. OWEN
Patent Lawyer
6 Owen Building, Washington, D. C.
41-D, Park Row New York City

TRADE-MARKS
REGISTERED

1000 NEEDED INVENTIONS!

Here is the most remarkable book ever offered to inventors. One Thousand needed inventions listed and described. Arranged as follows: General Problems; Automotive; Mechanical; Electrical; Chemical; Radio; Marine. Separate chapter on the Ten Most Needed Inventions. This book may give you one idea that will win you a fortune. Nothing else like it has ever been published. Compiled at enormous expense. Edited by Raymond Francis Yates, formerly Managing Editor of a leading scientific magazine. Over 100 pages, durably bound. Send no money. Pay postman only $1.00 plus postage on arrival (*Outside U. S. $1.20. Cash with Order*). Money back after 10 days' examination if desired. Limited edition. Write NOW.

BUREAU OF INVENTIVE SCIENCE
Dept. 39 Rochester, New York

Make More Money

Read the Money Making Opportunities on pages 124 to 151 of this issue.

Schedule or—

(*Continued from page 16*)

"'Tis that I wish to speak a wurrd to ye about."

"What's the trouble? Still worrying about the engines?"

"That I am, an'—"

"Isn't there an expert up ahead to ride with the engineer, to see—"

"Yes, but 'tis no blood ye can git from a turnip, an'—"

"Oh, nonsense, Marley!" McCutcheon's face darkened. "Hasn't this thing soaked into your head yet? What's become of your native intelligence—and your hearing? Don't you know my hands are tied on this engine proposition, tied with the rope that Sylvester's going to hang himself with? I've been told to let Sylvester handle these trains, and I know as well as you know that he can't. *I* can't convince the others—but tonight's performance *will*. Then, when one of the gentlemen higher up realizes we don't need this high-salaried bungler, maybe we won't be bothered with him."

"YES, but how about the trains tonight? We can't leave—"

"*Awww Booorrd!*"

Passengers and visitors scrambled up and down the car steps as trainmen gave the signal to start. Marley moved toward the engine like one in a daze.

"Pretty fast schedule for this type engine," Atkins, the locomotive expert, remarked when Marley dragged his weary form into the gangway and had slumped down on the fireman's seatbox.

Bewildered by what McCutcheon had said to him, Marley sat and stared at the varicolored lights as the train clattered out into the seeming tangle of speeding trains and engines in the crowded traffic stream.

"Schedule pretty fast," the man repeated as he clung to the cab window at the superintendent's side.

"Hey? What's that? Fast!" Marley gave him a hard look. "Fast, yer grandmother! Why, an ingine like this wan can—"

"Well, I thought you said, er—I was given to understand—"

"Tut, tut, Mr. Atkins." Marley was all railroad man now. "Ye can't be payin' no 'tention to switch shanty gossip. Jist listen to the old girl bark, an' look at that steam gage!" he shouted above the noise of the laboring engine.

LEAVING Bonaventure Station at 9 o'clock, the train bore down through St. Henri and Ste. Annes and finally thundered past Coteau Junction. Lights of the city behind, the powerful headlight pierced the slight haze from the St. Lawrence River, and to Marley, the "Frontier Special" seemed to speed along, propelled by its own momentum. Green lights on railside and station semaphores gleamed their messages of a clear track ahead, but those safety signals brought no joy to the superintendent as, with cigar clamped between his teeth, he sat staring into the swift-moving tunnel of light. For Marley was wrestling with the tremendous problem created by McCutcheon's words, trying to fathom the general manager's exact meaning, and at once resisting with all the effort of a man given to viewing every angle of a question, the indirect suggestion contained in those words.

Did McCutcheon mean that failure to make the time with the new train was the end he sought? Would the general manager sacrifice the sacred prestige of the A. & P. Railroad merely to rid the service of a man whom he deemed unnecessary to its personnel?

"Be gar, an' I don't believe it!" he muttered, "I don't believe it!"

But the more he thought of McCutcheon's final words, the

(*Continued on page 140*)

PATENTS

Inventors: Protect Your Ideas — Take First Step Today

If you have a useful, practical, novel idea for any new article or for an improvement on an old one, you should communicate with a competent Registered Patent Attorney AT ONCE. Every year thousands of applications for patents are filed in the U. S. Patent Office. Frequently two or more applications are made for the same or substantially the same idea (even though the inventors may live in different sections of the country and be entirely unknown to one another). In such a case, the burden of proof rests upon the last application filed. Delays of even a few days in filing the application sometimes mean the loss of a patent. So lose no time. Get in touch with me at once by mailing the coupon below.

Strict Secrecy Preserved — Write Me in Confidence

All communications, sketches, drawings, etc., are held in strictest confidence in strong, steel, fireproof files, which are accessible only to authorized members of my staff. Feel free to write me fully and frankly. Your case will have my personal attention. It is probable that I can help you. Highest references. But FIRST—clip the coupon and get my free book. Do THAT right now.

No Charge for Information on How to Proceed

The Booklet shown here contains valuable information relating to patent procedure that every inventor should have. And with it I will also send you my "Record of Invention" form, on which you can sketch your idea and establish its date before a witness. Such evidence may later prove valuable to you. Simply mail the coupon and I will send you the booklet, and the "Record of Invention" form, together with detailed information on how to proceed and the costs involved. Do this NOW. No need to lose a minute's time. The coupon will bring you complete information entirely without charge or obligation.

CLARENCE A. O'BRIEN
Registered Patent Attorney
Member of Bar of: Supreme Court of the United States; Court of Appeals, District of Columbia; Supreme Court, District of Columbia; United States Court of Claims.

Practice confined exclusively to Patents, Trademarks, and Copyrights

Mail Coupon Now!

Clarence A. O'Brien
Registered Patent Attorney
88-V Security Savings & Com. Bank Bldg.,
Washington, D. C.

Please send me your free book, "How to Obtain a Patent," and your "Record of Invention" form without any cost or obligation on my part.

Name.....

Address.....

.....

(Important: Print or Write name clearly)

Learn at Home to Make Clever SHOW CARDS

A Profitable Business of Your Own for full or spare time. Earn $25 or more a week in spare time. Double your full time pay. This practical method of home instruction has simplified everything.

Why work for low-pay? Clever "sales-increasing" display material is always needed by progressive business enterprises of every description. $10 to $20 is often paid for a single attractive show card. Skilled Show Card Writers command high salaries—right from the start.

Prepare now. No special ability needed. Learn at home in spare time through this most complete, practical method. Student R. A. Hart writes: "I make not less than $2.00 an hour making show cards in spare time." Ray Underwood (while still a student) wrote: "Am with large sign Co. People ask me to do work after regular hours and I clear $25 to $35 a day."

Many others have learned Show Card Writing by this method. So Can You, if you will simply apply yourself as they did.

Take advantage of the money-making opportunities open in the Show Card field. Make Show Cards for your present employer or for several merchants at one time. Have a profitable business of your own. Earn up to $100 a week—more if you're ambitious.

Send for FREE BOOK

Get busy. Boost your pay. Don't delay another hour. Send coupon now for big, Free, Illustrated Book and full information. Mail coupon **now.**

(No salesman will call.) Dept. 249E
WASHINGTON SHOW CARD SCHOOL
1117 - 15th Street, N. W., Washington, D. C.

Washington Show Card School, Dept. 249E
1117 - 15th Street, N. W., Washington, D. C.

Please send me FREE and without obligation, a copy of the new 32-page book, "Quick Success in Show Card Making."

Name .....
(Write name plainly and state whether Mr., Mrs., or Miss)

Address .....

City ..... State .....

Age .....

ELECTRICITY

Practical-Technical Courses

Great demand for practical-technical electricians and engineers. A brilliant future awaits you. A high salaried position or a profitable business of your own; these may be yours through our PRACTICAL-TECHNICAL courses. Opportunities unlimited. Finlay condensed method now in 25th successful year trains head and hand. Thousands of high salaried graduates throughout the world testify to the success of Finlay training. Extensively equipped laboratories and shops. Faculty of recognized experts. One and Two-Year courses in Electrical Engineering open in September; 12-Week courses in Practical Electricity and Power Plant Operation open at any time. Degrees, diplomas and certificates of efficiency awarded. Students assisted to positions. SEND FOR FREE CATALOG.

FINLAY ENGINEERING COLLEGE

Fall term starts September 15th

59 Finlay Bldg. Kansas City, Mo.

Schedule or—

(Continued from page 139)

stronger grew the conviction that he did believe it; that he *had* to believe it.

It was then that he turned his mind to a phase of the problem which never before had been considered. Would he execute McCutcheon's subtly communicated orders? Could any man, either general manager or superintendent, be a party to an enterprise designed to cast reflections upon the ability of those charged with the operation of the A. & P. Railroad?

Marley slid the cab window wide open, and with head and shoulders projecting muttered into the night: "An' I *will* not! Not fer annything will I dirty me record wit' such tricks! 'Tis no change I be makin' in me plans!"

The chilling air stung his flushed face.

"'Tis me job I be losin'," he moaned, and the words seemed to issue from a desolate heart. A moment of silence. Then: "To th' divil with the job which is kept by playin' scurvy tricks!"

Having thus set himself right in the matter, he faced the operating difficulties before him in characteristic fashion. Turning to Atkins, who stood swaying in the gangway, he remarked significantly: "'Tis me orders ye will be carryin' out this night—if ye ever expect to sell us anny more ingines."

The man gave him a puzzled look.

"CERTAINLY, Mr. Marley. I'm on here to help all I can."

"Then why don't ye be usin' yer nose, to smell that burnin' oil?" Marley snapped.

"By George, you're right, sir." Atkins sniffed the unmistakable odor coming in the cab window. "Must be a driving box running hot."

The train was crossing the Beaudette River, which marked the line between Quebec and Ontario.

"Stop at the water crane at the next station," Marley shouted to the engineer. "Be fillin' the tank wit' water while I be speakin' a wurrd to the dispatcher."

"We've got a full tank of water, Mr. Marley; we don't need—"

"Shut up! Do what I be tellin' ye. Ain't all thim passengers awake yet? We got to be takin' water, to show what we stopped fer, in case anny o' thim gits off to see."

He turned to Atkins.

"Put a Keeley on the hot box soon as we—"

"We ought to stop right now," Atkins objected. "We may have to put in a new brass, Mr. Marley. That'll take an hour if—"

"'Tis no new brasses we be puttin' in on *this* train!" Marley turned upon him fiercely. "'Tis more instructions I'll be havin' fer ye whin I have a wurrd wit' the dispatcher."

When the train slowed for the stop at the water tank Marley swung from the engine and disappeared in the telegraph office. In a moment he rejoined them, where water hissed from the heated journal.

"Let's go!" the superintendent snapped.

"WE'LL have to change this brass when we get it cooled off," Atkins said.

"'Tis trains ye'll be changin', if ye don't climb on." Marley reached for the throttle.

"But, Mr. Marley," Atkins swung up the steps of the moving locomotive. "You'll ruin that journal in another ten miles—it'll be cut to pieces if you run it in that condition. These low-wheeled engines were never meant for such fast runs, anyway."

"An' did ye be tellin' thim facts to Mr. Sylvester whin he bought thim?" Marley asked with biting sarcasm.

Atkins threw a surprised glance at Marley.

"I had nothing to do with the sale of these engines. I'm only on here—"

"Save yer breath fer puttin' in the brass whin I cut the ingine out at Lancaster," Marley snapped. "Take it aisy, lad." He gave the engineer a slow signal. "'Tis no wheels we wish to be droppin'."

While the "Frontier Special" slipped along through the night, Marley unfolded his plan.

"Put in a new brass whin she cools off," he instructed Atkins. "Run her around the wye, so she'll be ready for the eastbound in the mornin'. I'll leave the fireboy wit' ye to help. See the ingine is drippin' wit' oil whin the other train comes—she's going back to Montreal on the train that's comin' from Toronto. An' mind ye," he warned, catching Atkins' arm in a vicelike grip, "not a wurrd to anny one o' what is takin' place this night."

The locomotive expert gave Marley a quizzical grin but said nothing. The train ground to an almost noiseless stop opposite a lone engine on a siding. Marley was on the ground, attending steam hose and air pipe between tender and baggage car. Grasping the pin-lifter he gave the engineer a "go-ahead" signal. Driving box now ablaze, the new engine was side-tracked, to make way for the 951. Panting from the effort of coupling up the stiff hose, Marley hurried along the side of the tender. Nearing the gangway he paused.

"BE GAR, 'tis a fine job o' paintin' thim boys have done!" he muttered happily as the words "Frontier Special" adorning the side of the relief engine caught his eye.

On their way again, Marley and the engineer were the sole occupants of the cab of the substitute engine. And as the superintendent felt the handle of the fireman's scoop in his hand a glad cry escaped him. Some glorious challenge flung back by the walls of a hundred yesterdays sounded in his ears, and as he shoveled coal into the roaring maw of the throbbing locomotive, worry and misgiving slipped from him like the perspiration rolling from his face.

For several minutes Marley attended his firing. Then he sank heavily to the seatbox where his coat and vest had been thrown, and dragged from a pocket a coal-grimed timetable. In the dancing light from the open firebox door he studied the figures of the schedule. Consulting his watch, he stumbled to the engineer's side to announce: "Fifty-five minutes behind time we be, me lad!"

The engineer nodded. "Yep, I know, boss, an' I could clean up that time if I had far enough to go; but my run ends at Kingston Junction. West of there you'll have 'Careful Charlie' Jones. Don't see much chance to make Toronto on time."

MARLEY slammed the fire door shut with a violence that caused the engineer to give him a quick look. Leaning against the coal gate he lost himself in troubled thought. He hadn't counted on the possibility of catching an engineer who was afraid to run. He recalled Sylvester's words, now, when it was too late..."if your men are afraid to run..." He wondered vaguely why he had not given some thought to the matter. But he had so few of that kind in the service, the kind that was afraid to run. Jones was one of the few; a stolid plodder who could not be stirred to fast running.

"'Careful Charlie'," he muttered in disgust. "'Tis no time at all I have fer the likes o' him this night. If I could be takin' this lad through to Toronto wit' me, I could—"

His eye caught sight of the needle on the steam gage and he reached for the scoop. Backward and forward he swung his rugged body as with heaping shovel he scattered the coal upon the broad bed of flames in the furnace. The speed of the train was terrific, and as the engine rounded sharp curves he found a precarious footing

(Continued on page 141)

Most Amazing INVENTION in 25 years

"Cleans Up" for Agents

FREE MACHINE FOR AGENTS

$90 WEEKLY IN SPARE TIME!

Men, here is a wonder—the most sensational invention of the age! If you're looking for a rapid fire seller—an item that nets you 100% profit—an item that sells itself to 7 out of 10 men on demonstration—I've got it in Ve-Po-Ad, the amazing new vest pocket adding machine!

Sells for $2.95—You Make $1.65

This most remarkable invention does all the work of a $300 adding machine, yet fits the vest pocket and sells for only $2.95! It sells on sight to storekeepers, business men, and everyone who uses figures—and makes you over 100% profit on every sale! Ve-Po-Ad does any kind of figuring in a jiffy, yet weighs but 4 oz. Counts up to a billion. Shows total visible at all times. Perfectly accurate, lightning fast. Never makes a mistake or gets out of order. Over 100,000 in daily use!

Get Your Machine FREE

Live wire salesmen are dropping everything else and flocking to Ve-Po-Ad. Ve-Po-Ad brings them quick money and lots of it. Shapiro out in California made $475 in one week! You can "clean up" too! Only 10 sales a day in spare time will bring YOU over $95.00 a week! You need no previous sales experience—Ve-Po-Ad sells itself! If you are really interested in earning a steady, substantial income, write at once for full details of my MONEY-MAKING PLAN and FREE VE-PO-AD given to new Agents. Do it NOW—TODAY!

C. M. CLEARY, Dept. 15 C
211 W. WASHINGTON ST. CHICAGO, ILL.

It's Easy to Earn

$2.50 An Hour

DURING YOUR SPARE TIME

No Experience Necessary

Hundreds of men and women throughout the country are making good money during their spare time by taking subscriptions for

POPULAR SCIENCE MONTHLY

You can do it too! And we will gladly help you. For information, just fill out and mail the coupon today.

POPULAR SCIENCE MONTHLY,
250 Fourth Avenue,
New York City, N. Y.

Please tell me how I can earn $2.50 during each spare hour.

Name .....

Address .....

City ..... State .....

Schedule or—

(*Continued from page 140*)

upon the threshing apron of sheet iron which covered the space between engine and tender.

"Tunnel!" yelled the engineer.

With a single movement Marley slammed the firebox door and dived for the seatbox just as the train roared into the black pit. Weak and a little sick he slumped, his heart thumping violently. He had forgotten about the tunnel, how the flight of the train into that tube under a short hill would draw the fire through the open door of the firebox, to burn and sear whatever substance it met.

Now that the danger was passed, he commenced to feel the effects of the strenuous toil. His muscles ached from the unaccustomed strain of firing, and his eyes were almost blinded from the glare of the firebox. Hazily he tried to figure the distance to Kingston Junction, where another fireman would relieve him of his back-breaking labor. As nearly as he could estimate he had still a hundred miles of gruelling toil before he would be free to surrender his scoop to a man hardened to the work.

"ONLY forty-five minutes late, Mr. Marley," the engineer called as the train flashed through Moulinette. "Means we'll be about twenty minutes late into Kingston, and about the same into Toronto, if you don't have any delays west of Kingston."

"No, 'tis on time we'll be into Toronto," Marley declared doggedly.

"But you know 'Careful Charlie', the hog-head you're goin' to get—"

The rest of the engineer's statement was lost on Marley. For with an excited shout he leaped for his coat, to drag out a notebook. Muttering aloud the words of his message as he set them down, he addressed the train dispatcher:

"Hand up train orders on the fly at Kingston Jct. Frontier Special makes no stop for fresh engine crew or nothing. This crew goes through. Clear line for on time arrival Toronto."

Carefully wrapping the note around a small lump of coal and covering it over with a thin layer of waste, he threw it from the train at Farran's Point.

"Ye're goin' through to Toronto!" he called to the engineer.

"That'd be a violation of the engineer's agreement, Mr. Marley," the engineer grinned happily.

"An' we won't even slow down at Kingston Junction."

"Well, it'll cost you a couple hundred miles' pay for old 'Careful Charlie'."

"An' 'tis right glad I'll be to pay him—to stay to home," Marley announced grimly.

"It'll be a long hard grind for you, Mr. Marley—it takes a *man* to fire an engine with a scoop for three hundred miles."

"HUH, an' will ye listen to the lad!" Marley snorted. "Do ye believe I earned the name of 'Mile-A-Day' Marley wearin' kid gloves an' sittin' in a rockin' chair?"

"'Mile-A-Day' Marley will have to become 'Mile-A-Minute' Marley if we land this train on the advertised," the engineer boomed. "An' you'd better load that fire. We'll burn about a ton of lignite on these next hills."

The hours that followed were hours of physical agony for Marley. Painfully weaving on uncertain legs, every muscle crying out in fatigue, even his calloused hands blistered and bleeding from contact with the rough handle of the scoop, he stoked the engine to maintain steam pressure sufficient to meet the demands of an engineer whose soul seemed obsessed with the identical idea which drove himself, that of making Toronto on time.

Then they were entering the yard limits at Kingston Junction. (*Continued on page 142*)

They Make $20,000 a Year!

"$1000 a month is what I make!" A. H. Brown

"I Make $8000 a Year!" Lewis Black

They Both Learned Drafting At Home

So Can You!

Here are two successful Dobe-trained draftsmen. Their yearly earnings total $20,000. Both of them took Dobe's Simple, Easy, Quickly-learned Drafting Course. No other man and no other institution trains draftsmen like Dobe trains them.

And you learn all this at home in your spare time. You don't travel a long way to a distant city. You don't give up your present job. No matter what your job is now, you should write for Dobe's great book, "Successful Draftsmanship" and the names and addresses of many other big-earning Dobe trained men. Before the men pictured above began to earn the real money Dobe trained them for, they were making from $12 to $25 a week. Think that over. How much are you making today?

Maybe you can't do as well as these men have done—but you've got to admit that it is worth a try. Don't you think so?

Mail this Free Coupon or Write Today for FREE Book!

They asked for the Free Book first. Will you ask for it today? Certainly you are not obligated at all by writing for "Successful Draftsmanship." Get it and read it. Then make up your mind how successful you can be. This man is making real money and you know the old adage "What man has done man can do." So mail the Free Coupon below—or write a letter or a post card. Do that now. No man who is dissatisfied with what he is making now should fail to get and read "Successful Draftsmanship."

DOBE EASY DRAFTING
1951 Lawrence Ave.
Div. 13-66 Chicago

Dobe Easy Drafting
1951 Lawrence Ave., Div. 13-66 Chicago

You may send me free your book "Successful Draftsmanship" and names and addresses of more Dobe winners.

Name..... *Age*.....

Address .....

Post Office..... *State*.....

Want Some Money?

Here's a wonderful way to get it

Our beautifully illustrated book tells how. It tells all about our new methods of art decoration, art treatment and how anybody can learn without previous training or experience. It contains page after page of handsome color illustrations of what you can make and sell. You can make good money and this book is **FREE** Our system is amazingly easy to learn and the profits are larger than in almost any other business. You can produce beautiful finished art objects almost from the beginning. You don't have to know how to draw or have any experience. Begin making money now. All supplies are sent by us with the instructions and many have made $25 the first week. Some society women have taken up this work for their own amusement.—Either way, pleasure or profit, it's the most delightful home work you can imagine. Write Now for your copy of this valuable book; it's FREE.



Fireside Industries

DEPT. 51-M ADRIAN, MICH.

Make $40 a Day

Introducing MASTERLITE POCKET LIGHTER

Lights On New Marvelous Principle—Without Flint

Attracts crowds everywhere. Works every time in any weather. Sells for only 50c. Equal to $10 and $30 lighters. Every smoker instantly appreciates its wonderful convenience. No wind can blow out the flame.

Every Smoker Buys on Sight!

100% Clear Profit. Repeat Business Guaranteed

Sells instantly to smokers and dealers at big profits. Guaranteed for 10 years. Each sale builds an everlasting repeat business. $3.00 brings sample dozen in handsome display box with our sure-fire selling plans. Masterlite retails at 50c. ***Sells on a Flash Demonstration at over 100% Profit***

Sample 50c

Radio Gas Lighter

Lights Gas Without Flame

No friction, spark, or flame. Lights instantly mantles, gas stoves, jets and heaters. Held directly over gas flow. Flame appears instantly. Absolutely safe. Banishes danger from matches.

PROTECTION CAP FREE

Make $26 a Day

A big 25c seller, paying 300% clear profit. A gross easily sold in a day brings $36.00 and costs $10.00—**$26 a day clear.** Rush $10.00 for gross or $1.00 for sample dozen, with amazing new sure-fire self-selling plans.

Masterlite Mfg. Co., Dept. J-27
110 East 23 St., New York

WANT MORE MONEY?

Easy to Earn with a TYPEWRITER

Write like a business man and turn spare time hours into dollars—right at home. Own a standard ***remanufactured*** typewriter—Underwood, L. C. Smith, Royal, Remington—***at saving*** of ***40*** to ***60%***. Latest models. Look like new. Instructions in rapid touch typewriting Free to purchaser. Easy to learn.

10 Days' Free Trial

REAL TYPEWRITER BARGAINS

Write today for free catalog and learn of our Ezpay-like-rent plan.

YOUNG TYPEWRITER CO.
Typewriter Headquarters
654 West Randolph St., Dept. 1429, Chicago

Four Vital Subjects~

The Lord
The Holy Scripture
Life . Faith

by EMANUEL SWEDENBORG

Book of 634 pages, clear print, good paper, substantially bound in stiff paper covers. Endowment enables us to send this book to any address without further cost or obligation on receipt of only

Five Cents

The American Swedenborg Printing and Publishing Society
Room 330 16 E. 41st St., New York

LIGHTNING PROFITS
TOURISTS PRIDE
Tire Plugs "The Instant Inserting Instrument"
ENORMOUS DEMAND – EASILY SOLD – SURE REPEATER

Sell Dealers

FASTEST SELLING Necessity Known

Every Vulcanizer, Garage, Repair Shop, etc., is a prospect and can be sold.



Inexperienced salesmen sell 10 to 12 orders per day with profits of $15.00 to $22.00 per day. Martin's sales one week $702.20. Mr. Pim's sales six months $14,000.00. Territories closing fast. Write for full particulars. **Tourists Pride Mfg. Co.**
Dept. 10-I, Minneapolis, Minn.

AGENTS 500% PROFIT

GENUINE GOLD LEAF LETTERS

Guaranteed to never tarnish. Anyone can put them on stores and office windows. Enormous demand, large profits, Paul Clark says: smallest day $28.70. R. L. Reel made $920 in two months. Write today for free sample and liberal offer to general agents.

METALLIC LETTER CO., 433A N. Clark Street, Chicago.

"Patents of commercial value financed on royalty basis without expense to inventor. Mail models and copies of patents or full details to Kamstone Holding Corp., 41 East 42nd Street, N. Y. C."

Want $158 Month Commence?



Railway POSTAL CLERKS

Steady Work—No Layoffs—Paid Vacations
Travel — See Your Country
Common Education Sufficient
MEN—BOYS—18 UP. Act Immediately.

GET U. S. GOVERNMENT JOBS

MAIL COUPON BEFORE YOU LOSE IT

Franklin Institute, Dept. M266, Rochester, N. Y.

Sirs: Rush to me without charge, (1) 32 page book, "Government Jobs"; (2) tell me how to get a U. S. Government job; (3) Send list of positions obtainable.

Name .....

Address .....

Schedule or—

(*Continued from page 141*)

The engineer sounded the whistle for the station, to which he added a shrill message for the conductor: "Pick up train order without stopping."

Down a lane of leafless trees standing stark in the moonlight they rumbled at fifty miles an hour. Leaning from the cab window, Marley hooked his arm through the train order hoop held aloft by the operator. Then Kingston Junction was left behind, its station platform filled with a noisy group of people who had gathered to view the new train.

An hour later a short stop was made at a coal chute. Marley attempted to climb to the top of the tender to pull down the water spout, but he sank exhausted to the coal pile.

"Rest yourself a moment, Mr. Marley," advised the engineer, as he sprang to attend the water spout. "You're about done for."

"Done fer!" Marley shrilled. "Is it spoofin' me yer tryin' to do?"

THEY were gliding along again, now to flash by a speeding train on the opposite track with a deafening roar.

"Must have been Number 12," the engineer remarked. "They're right on time. Didn't they have one of the new engines out of Toronto?"

"They did," Marley gasped, "but 'twas no chances I take wit' thim, me not bein' able to ride two trains at onct. I have the 950 ready at Scarboro Junction, an' make the change there, before they lose much time wit' hot drivers."

"Then they'll change again at Lancaster—pick up the one we left there?" questioned the engineer.

"They will, an' we change at Scarboro Junction, git the wan which they left—which gives the both of us new ingines into Toronto an' Montreal, an' Sylvester an' the rest o' thim smart fellers thinks they've wint all th' way," he explained.

"Some schemer you are, Mr. Marley," the engineer grinned. "You can ease off a bit on that fire now. We're right on time."

Marley grinned proudly as the train glided along the arrowlike roadbed paralleling the lake.

"'Tis glad I am to hang up the old scoop. But if ivver I become a fireman, John, 'tis fer the likes o' you I'd want to fire," he added enthusiastically.

Scarboro Junction. The success of the run was now practically assured. Hurting in every bone, Marley climbed stiffly from the engine and boarded the locomotive which was to pull the train into the city a few miles distant.

TORONTO at 3:58 in the morning, with two minutes to spare! The "Frontier Special" was now in the keeping of railroad officers of the connecting division.

Then a coal-grimed man dragged his weary body toward the telegraph office.

"An' will ye ask the dispatcher how Number 12 wint into Montreal?" he begged diffidently.

The operator spoke into his telephone.

"Right on time, the dispatcher says," the man replied, "he asks who it is that wants to know."

"Meself, Marley."

"I thought it was you, Mr. Marley," grinned the operator. "The dispatcher says Mr. McCutcheon wants you to call him on the telephone at his home, right away."

So it had come, the call for a resignation that couldn't wait until business hours! Ah, well, he had been between two fires, anyway. If he had failed with the new train, Sylvester would have demanded his pound of flesh. And, now that he had put the two trains across the Ontario division on time, he had defied the general manager. In winning, he had lost. But the victory,

(*Continued on page 148*)

Follow This Man!

Secret Service Operator 38 Is On the Job!

Follow him through all the excitement of his chase of the counterfeit gang. See how a crafty operator works. Telltale finger prints on the lamp stand in the murdered girl's room! The detective's cigarette case is handled by the unsuspecting gangster, and a great mystery is solved. Better than fiction. It's true, every word of it. Get the facts in the case.

Free The Confidential Reports No. 38 Made to His Chief

And the best part of it all is this. It may open your eyes to the great future for YOU as a highly paid Finger Print Expert. More men are needed right now. This school has taken men just like you and trained them for high official positions. This is the kind of work you would like. Days full of excitement. Big salaries. Rewards.

Earn $2500 to $10,000 a Year!

Any man who can read and write can make good in this new profession. You can learn in your home in your spare time. It's a fascinating study, too. And think of the opportunities to travel, see the world and make big money. But you must ACT NOW.

Write and we'll send you the Free Reports—also a wonderful, illustrated book telling of the future awaiting you as a Finger Print Expert.

University of Applied Science
1920 Sunnyside Ave. Dept. 13-66 Chicago, Ill.

AUTO-INTOXICATION

When you feel depressed, tired all the time; sleep does not refresh you, and yet you have no pains or organic troubles, you are probably suffering from AUTO-INTOXICATION. This serious condition has baffled many physicians, but after intensive studying of this subject over a long period of years, Dr. Frank McCoy, internationally famous health specialist, has discovered the amazing secret of restoring health in such cases. He has watched thousands of people successfully eliminate the deadly poisons after following his simple directions. This secret may now also be yours. This is the same information for which thousands of Dr. McCoy's private patients are daily paying thousands of dollars to learn. Nothing else to buy. Send only 50c coin or money order today for the complete confidential instructions.

McCOY HEALTH SERVICE,
1363 Brack Shops Bldg., Los Angeles, Calif.

HERE'S HOW

AGENTS MAKE BIG MONEY!



They merely show the DUO-COOKER (condensing), explain its features and use, and a quick sale results. A great utensil. Nearly every American household wants one. No failures. Big margin of profit for you. Write for details.

DUO-COOKER CO. (Condensing)
4304 Duncan Ave. St. Louis, Mo.

Electrical Engineering Course for men of ambition and limited time. Over 5000 men trained. Condensed course in Theoretical and Practical Electrical Engineering including the closely related subjects of Mathematics and Mechanical Drawing. Students construct motors, install wiring, test electrical machinery. Course designed to be completed in *one college year.*

BLISS ELECTRICAL SCHOOL
Prepare for your profession in the most interesting city in the world. Catalog on request.
109 Takoma Ave., Washington, D.C.

Schedule or—

(*Continued from page 142*)

disastrous as it would be to his future, was not without its sense of triumph. He had kept faith with himself and had safeguarded the sacred reputation of his beloved railroad.

"But 'tis no surprise to me at all at all," he muttered as he sought a telephone booth. "'Tis what I'd be doin' me own self if wan of me min refused to obey me orders. Be gar, 'tis a job on the section I'll be lookin' fer this day," he prophesied, as grimly he gave the number to a yawning telephone attendant.

Marley was clinging to the instrument for support, but when he heard McCutcheon's voice coming to him across the distance he snapped erect.

"Well, Daniel," the general manager began, "you turned the trick."

"'Tis no tricks I be turnin'—an' ye ought to knowed I wouldn't."

McCutcheon's delighted laugh stayed the bitter words Marley would have uttered.

"I MEAN you put 'em over on time," the other explained. "A splendid job you made of it, Daniel. I knew you'd do it, but I wanted to make sure. That's why I said what I did to you there in the station."

"Ye mean ye . . . "

Marley's weariness slipped from him like a garment. A feeling of happy anticipation possessed him.

"I mean you aren't as slick as you think you are, Daniel," McCutcheon laughed. "You might have known you couldn't keep all those fine plans under cover. I knew all about those engine changes you had lined up. That locomotive expert you had out of Montreal was a man selected by Sir Samuel and myself. Of course, he confirmed what you have been telling me. Sir Samuel has been watching the performance of the two trains here with me. We've been talking over your mile-a-day record in track laying and . . . "

"Be gar, that ain't nothin' compared to me latest record, mile-a-minute firin', an' . . . "

"I know," McCutcheon chuckled, "so we've decided that you know best how to run your railroad—without Mr. Sylvester and those new engines, so . . . "

"But, Mr. McCutcheon," Marley interrupted, "keep 'em both, the mutt o' a Sylvester an' the ingines too. We can use 'em. Thim ingines will be fine fer mountain service farther west, an' I've a hunch Mr. Sylvester would be a grand success in the traffic . . . "

"You think you can get along with Sylvester?"

"Sure an' isn't it plenty experience I be havin' in bossin' me superior officers?" he questioned joyously.

Roman "Cannon Ball" Found

EXCAVATIONS of the third wall of the city of Jerusalem have unearthed relics of the siege of that city by the Romans, among them a stone ball shot out of a catapult by the Roman besiegers. It also has been discovered that the wall consists of two courses, which were apparently built at different times. It is thought that the lower course was built by King Agrippa, the upper course being added during the war with the Romans.

Grasshoppers in a Glacier

A GLACIER full of grasshoppers is the unusual sight that confronts stray tourists from the Yellowstone National Park at the near-by mining town of Cooke City, Mont. The mile-long snow-covered formation known as Grasshopper Glacier, pure white with blue ice beneath, is filled to a considerable depth with countless numbers of the frozen insects. At times specimens from this novel cold storage are fresh enough for angler's bait!

If You Want a Job

or a Hobby

that Pays Well

Where You can be Your Own Boss

and Keep Your Own Hours

learn Illustrating

Send for our free catalog "A Road To Better Things.' Learn how former Federal School graduates now earn big money. See the work and comments of famous artists like Clare Briggs, Norman Rockwell, Fontaine Fox, Neysa McMein and over fifty others.

Opportunities in drawing have never been better. The Federal Course includes illustrating, cartooning, lettering, window card illustrating, etc.

Many people have a talent for art and do not realize it. That is why we inclose a test chart with our catalog. It finds out your ability. Fill out the coupon now.

Federal School of Illustrating

FEDERAL SCHOOL OF ILLUSTRATING
9147 Federal School Bldg., Minneapolis, Minn.

Name.....Age.....
Occupation.....
Address.....
.....

Reading Architects' BLUE PRINTS



Learn at Home!

THE building trades are booming. Employers everywhere are looking for men who can read architects' blue prints. Splendid salaries and rapid advancement are offered men who have this special training.

There is an easy, delightful way to learn. The International Correspondence Schools will teach you right at home in an hour a day of the spare time that now goes to waste.

You will like the course because it is so PRACTICAL. You work on actual blue prints—the same blue prints a contractor would use if asked for an estimate, or a foreman would receive from a contractor.

In a surprisingly short time you can acquire a knowledge of blue prints that will be of great value to you in a salary way the rest of your life.

Mail the Coupon for Free Booklet

INTERNATIONAL CORRESPONDENCE SCHOOLS
"The Universal University"
Box 7641-E, Scranton, Penna.

Without cost or obligation on my part, please tell me how I can qualify for the position or in the subject *before* which I have marked an X:

☐ **READING ARCHITECTS' BLUE PRINTS**

☐ Architect	☐ Electrical Engineering
☐ Contractor and Builder	☐ Electric Lighting
☐ Architectural Draftsman	☐ Mechanical Engineer
☐ Concrete Builder	☐ Mechanical Draftsman
☐ Structural Engineer	☐ Machine Shop Practice
☐ Chemistry ☐ Pharmacy	☐ Railroad Positions
☐ Airplane Engines	☐ Gas Engine Operating
☐ Automobile Work	☐ Civil Engineer
☐ Agriculture and Poultry	☐ Surveying and Mapping
☐ Mathematics	☐ Metallurgy ☐ Mining
☐ Radio	☐ Steam Engineering

BUSINESS TRAINING DEPARTMENT

☐ Salesmanship	☐ Business Management
☐ Advertising	☐ Industrial Management
☐ Better Letters	☐ Personnel Organization
☐ Foreign Trade	☐ Traffic Management
☐ Stenography and Typing	☐ Business Law
☐ English	☐ Banking and Finance Mana'm't
☐ Civil Service	☐ Accountancy (including C.P.A.)
☐ Railway Mail Clerk	☐ Cost Accounting
☐ Common School Subjects	☐ Bookkeeping
☐ High School Subjects	☐ Private Secretary
☐ Illustrating	☐ Spanish ☐ French

Name.....

Address.....

City.....State.....

Occupation.....

Persons residing in Canada should send this coupon to the International Correspondence Schools Canadian, Limited, Montreal, Canada.

PREPARE FOR AN
ART CAREER

—thru the *only* school operated as a department of a large art organization. Commercial Artists trained the *"Meyer Both Way"* earn as high as $10,000 per year. We today have hundreds of students who had previously studied in other art schools. Why? Because your instruction is based upon our everyday experience in meeting the art needs of leading advertisers. Home study instruction. Write for illustrated book telling of the success of our students.

MEYER BOTH COMPANY
Michigan Ave. at 20th St. (Dept. 35) Chicago, Ill.

How Animals Make Love

(*Continued from page 20*)

up a great foam, all the while bellowing at the top of his thunderous voice. And, as if this were not enough, he meanwhile gives off a sickening "perfume" of musk.

The Malayan lizard sits on a leaf before his mate and sings her a silent love song, while he delights her eye with an exhibition of vivid colors in the pouch which is suspended from his throat. He nods his head and opens and closes his mouth, but never makes a sound.

Because most fish hatch large numbers of eggs at once, few of them have much courtship, Professor Huxley explains. The fiddler crab, a small crustacean which scurries about the sandy beaches and salt flats, possesses one greatly enlarged claw, which he uses to flirt with. Professor Huxley has seen a male fiddler stop in his tracks as an eligible young female passed by, raise himself on tiptoe and hold his big claw straight in the air. If the female crab passed, he would run ahead of her and assume his pose again. This flirtation continued until he received some attention or gave up in disgust.

BUT to find the prettiest courtships in all creature life, we must go to the birds. One of the most romantic lovers among them is the bower bird, an inhabitant of the tropics. This esthetic bird starts constructing an elaborate bower, or tunnel, as the mating season approaches. He clears a space and lays a carpet of twigs or moss. Into this floor covering he weaves various colored objects, such as bright flowers, feathers, berries, polished bones, or shiny sea shells brought from long distances. One species of this remarkable bird always mats his carpet with large leaves, their silvery under surfaces scrupulously turned upwards. If wind blows them over, he turns them up again; and he replaces the leaves as they wither. Above this artistic carpet the male erects a tunnel, which he weaves from carefully selected twigs. One species of the bower bird uses only delicate stems from the orchid—the most exquisite of all flowers! And still a different species builds a hut eight feet high around a center column gaily decorated with fruit and flowers. Such is the bower, which gives this astonishing bird its name. The bower is quite distinct from the nest, which is not built until after mating.

When these extravagant preparations are completed, the male preens himself for inspection and stations himself before his bower. He drops one wing, then the other, all the time keeping up a concert of curious whistling notes intended to engage the attention of the female. He also pretends to pick up food, as if the appeal to appetite might intrigue the exacting spouse. Finally, when she approaches, the pair enjoy a hilarious game of hide-and-seek.

THE courtship of the dignified crane, though, is a stately minuet. He wheels around in front of his ladylove, making a low bow with his head nearly touching the ground, and ends the first figure by leaping high in the air. He pirouettes again with a still deeper bow, and trails his wings loosely at his sides. His lady then responds with several bows and a hop. Finally the pair execute a series of figures not at all unlike the minuet.

If the cranes' nuptial dance is a minuet, then certainly that of the lesser bird of paradise is a fancy dress ball. The dazzling display which these beautiful birds make when they are wooing probably is the most colorful in all the feathered kingdom. During the mating season the males perch on horizontal tree branches which are more or less barren of leaves, while the females watch from near by. The ball opens with a vocal chorus of some twenty males, who work themselves into frenzied excitement by shrilling, "Walk-walk-walk-walk-walk," while they quiver their wings. When the music has reached the proper pitch, all the males suddenly lift their wings on each side, raise their tails, and with a quick rustle thrust up and forward the shimmering golden side plumes, which are the pride of the species. For about twenty seconds the males exhibit their superb adornment, rigidly holding their positions and delicately quivering their wings to give a sparkle to their translucent feathers. The show is finished by a mad, excited scamper back and forth along the tree limbs.

MONOGAMY is the rule among birds, at least for one season, or, as in the case of the American wren, for a single brood. The monogamous instinct is frequent also throughout the other realms of creature life, although promiscuity is by no means uncommon. It has been left to the ruff, or fighting sandpiper, however, to establish a society in which the female does the courting. The males of this species at mating time sprout magnificent ruffs or collars, and ear tufts, each male distinctly different from every other. Edmund Selous, European naturalist, tells how he has watched the male sandpipers assemble in a cleared space, known to ornithologists as "the hill." Here they spar and joust with one another or whirl about while alone, but the moment a female approaches each bird drops to the sand, spreads his wings, and remains immobile. The female may find a mate to her liking, or she may preen herself, stroll around, and fly away—on which the cocks arise from the ground rather sheepishly, pretending they have been entirely unconcerned about the whole affair.

In some bird species the females actually fight for their mates. The European warbler is one of these. The males of the species, according to Eliot Howard, English ornithologist, migrate northward a week or so before the females and each establishes himself in a restricted zone, in which no other male is tolerated. Then the warbler begins singing both to advertise himself to eligible females and to warn off neighboring males from his territory. When the mate arrives, the two pair for the season. But if two females happen to arrive at once in the same zone, they settle their rival claims by fighting it out. The male hovers by, watching with interest, but never interfering. Neither does he make love to any female until after his matrimonial choice is decided for him.

SONG, among the birds, is generally believed to be a love serenade, even though some varieties sing throughout the year. Dr. Ludlow Griscom, of the American Museum of Natural History, however, offers it as his opinion that bird notes constitute a language expressive of widely different emotions.

An ingenious simile on human marriage has been discovered in the wedded harmony practically universal among the birds, according to Charles A. David, American ornithologist. The consistent happiness of the mated birds, he declares, results from the unflagging devotion of the male, who never tires of his mate, nor ever fails to save for her the choicest morsels of food throughout the summer, even until their brood is feathered and ready to fly.

Instead of interpreting animal courtships in terms of human behavior, however, Professor Huxley wonders how our own love-making would look to an external intelligence, and asks if it would not be wiser for us to forsake our assumed superiority and frankly interpret much of human behavior from the animal side, rather than the animals' behavior from ours.

Biologists agree that the instinct for procreation of the species is one of the most primitive and compelling motives in all life, and that, after all, there is not much difference between mankind and the insects, including all life between, when it comes to making love.

Makes $150 IN A WEEK!
Opening Cans a Funny Way

Here's an amazing new way to make big money—easy as A-B-C! So surprising that R. A. Stewart cleaned up $151 in a week! All due to a startling little device that banishes old style can openers to the scrap heap.

MEN, this almost magical device is a real "million dollar" can opener. Imagine a little, inexpensive, automatic machine that opens any can, round, square, or oval at the turn of a crank! Cuts the entire top out slick and clean in a couple of seconds. No more snagging your fingers on jagged tin edges! No more fishing around with a spoon to get all the food out of a can! Speedo ends this bother and danger forever. No wonder women simply go "crazy" over this new wonder-worker! And no wonder that agents everywhere clean up $7 to $12 in an hour, steady as clockwork!

Agents! Distributors!

Write quick for exclusive territory and generous FREE TEST OFFER. Act today while the enquiry is hot. Write to—

CENTRAL STATES MFG. CO.
4500 Mary Ave. Dept. L-840
St. Louis, Mo.

Big Pay!

"I MADE $21.00 IN FIVE HOURS"

Writes Peter Werner, Ill. Sell Madison "Better-Made" Shirts for Large Manufacturer direct to wearer. No capital or experience needed. Spare or full time. Cash bonuses.

WRITE FOR FREE SAMPLES
MADISON SHIRT MFRS., 562 Broadway, New York

LEARN TO FLY

Billions of dollars will be created and spent through the development of aviation. Thousands of positions will be open for those who are prepared.
Prepare now! Complete Home Study Course in Aviation arranged by America's foremost aeronautical society. Authentic yet inexpensive.
Course complete with blueprint of airplane $5.00.
Send money order or check or write for further information.
The American Society for Promotion of Aviation
Dept. Y
1123 Fifth Ave. New York

"STAMMERING"
Its Cause and Cure"

You can be quickly cured if you stammer. Send 10 cents, coin or stamps, for 288-page cloth bound book on Stammering and Stuttering. It tells how I cured myself after Stammering and Stuttering for 20 years.
BENJAMIN N. BOGUE
7545 Bogue Bldg., 1147 N. Ill. St. Indianapolis

ONE DAY AUTO-ELEC. TRICIAN PAYS BIG



Charge batteries in 1-3 the time required by others. Latest method recommended by the leading battery companies and approved by the U.S. Bureau of Standards. BIG YEAR ROUND PROFITS. Best paying business in automotive field. Requires no special experience, uses small spare. 30 days free trial at our risk under absolute money back guarantee. Write today for full particulars. HOBART BROS. CO., Box P97, TROY, OHIO.

ONLY $16.50 MONTHLY—

A 2c STAMP —will start you on the road to success. See Money Making Opportunities on pages 124 to 151.

Whirling Wheels

(*Continued from page 34*)

a machine shop with which he had been corresponding, run by two brothers named Dodge.

"Well, moving in, are you?" was their greeting. "Good enough. Manufacturing too—prices on ten sets? Sure, ready in a couple of days. They may call you fellows crazy, but the more the merrier. Keeps us busy. Gosh, we may get into the business ourselves, some day; who knows?"

They gave him a tip as to where a deserted carriage factory could be found. On another one of the ribs—the vertical one—was a foundry run by Leland and Falconer. Leland was an expert mechanic, almost old enough to be Gil's father. More drawings and business talk.

"YES, sir," said Leland, "automobiles seem to be catching on. Met R. E. Olds yet? Look him up; he's doing things. We're a little interested ourselves."

"Oh, in that case maybe I'd better take my drawings—"

"Don't let that worry you, Mr. Herrick. We're honest." Gil looked at him again, and knew that he was. "Plenty of room for all of us, I guess. Come here a minute; here's a little plant we're interested in." He led Gil to a small brick building next door. "Call it the Detroit Automobile Company. Want you to meet our designer, Mr. Ford. Henry, this is Mr. Herrick—"

On another rib, one extending northeast, was an old building that had housed a carriage shop, a frame structure perhaps seventy feet in length that backed up to a railroad. Long and narrow, its dusty floor resounded hollowly beneath Gil's solitary footsteps. Its walls were marked with long-dried streaks of vermilions, blues, greens, and blacks where painters had swiped enamels from their brushes. Not much of a factory, this place; probably more modest than the one Jim Wenden's company was operating, but compared to the barn with its box stall and space for one carriage, it was huge. There was one room at the rear that had once been the paint room. Its floor was an inch deep with dried paint, and it smelled musty and cobwebby. A good place, Gil thought, in which to work out a new idea for two cylinders that had come to him; to begin the more involved construction of a four-cylinder motor that he already had drafted in the rough. There was a lean-to shed at one side of the building; he could use that for his home, until he had a real one. And, because the place was far beyond the car line, in a section that for two blocks was undeveloped, the price was ridiculously low. He bought it, and wrote most happily to Gail. She answered—

"ARE you sure you want to come to Boston? Are you quite certain you want to come—after the show? That sounds as though you loved your work the most, Gil. It's been four years and more, and you haven't come to see me once. Even your letters have been few and far between. Jim has been here several times. He has changed, Gil. He is not nearly as crude as he used to be. He is friendly and nice, and says nice things about you."

Four years. They can accomplish other things than creation; they can undermine insidiously. Does absence really make the heart grow fonder? Mrs. Caswell didn't think so. Not with her methods of subtlety, learned on the day when she broke down in such an unladylike manner and cried before an outsider.

"He has a new transmission, has he?" she would comment when Gail would quote a bit from one of Gil's letters. "That's splendid . . . How much do you suppose that cost? As much as carfare to Boston? Well, it's time for tea." Or—

"Mr. Wenden and he drove to Elmont and back without a stop? (*Continued on page 148*)

Now You can learn
MAGIC
Quick-Easy-In Spare Time-at Home. . . .

Now—at last—the innermost secrets of Professional Magic are thrown open for you to learn. Never again need you hang back while others do the entertaining. Learn Magic and you become the magnetic center of every crowd. You will know the thrill of being popular, sought after, the man who everyone wants to know.

Earn $250 to $1000 a Month

No matter what your business—or what your earnings, Magic will bring you vastly greater success. You can also earn big money, as a side line, giving entertainments at clubs, church affairs and other gatherings right in your own community. If the Stage attracts you, here is a profession you positively CAN learn in surprisingly short time. Get in on the tremendous salaries paid to expert Magicians.



Astonish Your Friends!

You will be able to perform soon after getting your first lesson. Sleight-of-hand becomes easy when Dr. Tarbell shows you his simplified system with hundreds of pictures and clear explanation.

You get the most mystifying card tricks—Chinese and Hindu effects—even big stage illusions. Not only the tricks but the fundamental principles of Magic are now opened up to you by Tarbell—the teacher of Magicians.

Mail Coupon for Special Offer!

Act at once and we will make a Special Low Price on this entire course. Only a few more pupils will be accepted—*then the rate goes up!*



Protect yourself. Mail the coupon at once. A wonderful surprise and a splendid future awaits you!

Tarbell System, Inc., Dept. 13-66
1922 Sunnyside Avenue, Chicago, Illinois

Tarbell System, Inc., Dept. 13-66
1922 Sunnyside Ave., Chicago, Illinois

Tell me all about Dr. Tarbell's new and simple system by which I can learn the innermost secrets of Magic at a Special Low Rate now open to me.

Name .....

Address .....

..... *Age* .....

Amazing New Way to Shave
Astonishes Experts

KEEN, velvety shaves forever and no more blades to buy! That's what the amazing invention of a St. Louis man offers you today.

KRISS-KROSS—the super-stropper prolongs the life of any-make blade for months and even years! Strops on diagonal. Employs barbers' secret principle. Gives keenest edge that steel can take in only 11 seconds. Automatic timer signals when blade is done. You'll say that magic device is almost human!

Right now the inventor is offering a new kind of mystery razor FREE—to introduce KRISS-KROSS stropper. Really 3 razors in one. Instantly adjustable. Absolutely unique and astonishing!

Write for FREE Offer

Amazing KRISS-KROSS inventions are never sold in stores. Write for details and FREE mystery razor offer.

AGENTS wanted. Generous commissions and big profits. H. King made $66 a day. J. C. Kellogg made $200 in 7 days. Even spare time workers make $6–$12 a day extra. Nine out of 10 men want to buy on sight. Really astonishing. Get details at once. Mail coupon today.

RHODES MFG. COMPANY

Dept. L-242 1418 Pendleton Avenue St. Louis, Mo.

RHODES MFG. CO., Dept. L-242
1418 Pendleton Avenue, St. Louis, Missouri
Without obligation, please send me details of your amazing KRISS-KROSS stropper and FREE 3-way razor. Also proposition showing generous agent commissions.

Name.....

Address.....

City.....State.....

☐ Check here if interested in becoming representative.

BE A RAILWAY TRAFFIC INSPECTOR

Earn Up To $250 Per Month

NO SALARY

plus expenses

HUNTING FOR A POSITION AFTER COMPLETING YOUR TRAINING

Read what Dan'l M. Mack says:

"I received my certificate on April 15, was on my way to take a position on the evening of April 16, and started to work on April 17. If this is not quick work, I don't know what it is. I found the school very thorough."

Our students never worry about a position as one will be offered them within a few days after completing the Traffic Inspection course. You start at $120 or more per month plus expenses. Our contract shows why you take no risk.

As a Railway Traffic Inspector, you are practically your own boss, see new faces and places each minute, report only to high officials, are rapidly advanced. It's healthful outdoor work with regular hours.

Hundreds of Satisfied Graduates

Send coupon for details and contract agreeing to refund your money if position is not offered after graduation.

Standard Business Training Inst., Buffalo, N. Y.

Send me, entirely free, Booklet Div. 3, giving full particulars about course in Traffic Inspection.

Name.....

Address.....

Whirling Wheels

(Continued from page 145)

Remarkable! That's forty miles, isn't it? How many miles was it that Jim took us the other day?" Knowing full well that Jim had bragged "sixty" and not knowing that he had stretched it nearly double.

There were many such ways, and Gail ignored them all until, as time went on, it became necessary to resist their implications and strive to recall the memory of warm eyes. She knew Gil was working for her and toward her; he had told her so many times, on the front porch during those far-off days, in the speeding, popping wagon that he had built with his own slender hands, in the letters he wrote—with quite often an apology for being delayed because of a certain mechanical problem that had absorbed him. Was he really in love with her, or was it that wagon? That thought finally came and found expression.

YES, Jim had called, several times. "In Boston on business," he would say. "Selling stock to some parties here. How'd you like to take a spin, you two? Got an electric outside."

He looked and acted the man of affairs. Just a little crudely, perhaps, but her mother said that one could not outgrow one's farm environment in a day.

"Yes, they're the coming thing, electrics. Gas is too noisy and unreliable," as they purred silently along the thoroughfares of Boston. "Takes an engineer to run a gas engine; always will. With this all you have to do is push a lever and steer." It was indeed very pleasant, and Jim was a generous host. "How's Gil? Still trying to make his wagon go? That's fine! Well, you never can tell. Maybe he'll do it—some day."

"Are you sure you want to come to Boston?" Gail wrote. Followed by—"Why don't you take up electrics? They seem to be much more reliable." And Gil with a little factory just beginning to go!

What else was he laboring for but a trip to Boston and all that it meant to him? How could he labor night and day but for the knowledge that she, at least, was sure of him? After the show? Of course! For then he would have a prize to lay at her feet; now, nothing. She, and the job, and the future—all were twisted together like a rope, and Jim was trying to cut it. Why else was Jim calling and saying nice things about him, and disparaging things about his work? Didn't she understand that there was another way of making love besides the one of forcible embrace before a crowd? Gil wrote that, fiercely. As though it were a Jim Wenden to be mastered, as indeed it was.

GIL drove through to New York that November of 1900, in a race that was run alone. It was the hottest, most nerve-wracking contest that he had ever driven. What if there were no actual competitor vying with him? There was a much more threatening, invisible one, always just ahead—Jim Wenden. What if there were no definite prize hung up? There was a vastly greater possible one—recognition by the public, making a market for his first ten runabouts, then twenty, then—. That meant more money, with which he could develop his two, then his four, in a factory so large that it might turn out as many as one a day eventually. On and on those dreams led him. This runabout a thing accomplished, as good as he could make, the next advance was living in his mind. All to one end—Gail.

She had replied to his letter: "All right, Gil, but you needn't act so mad about it. Come to Boston—after the show. I'm sorry you can't come before, but you know best. Jim will be here, too, then. He is going to advise us about a trip abroad that mother is thinking of."

Which made him remember the triumphant look in her mother's eye when Gail had consented to return to Boston with her. How could he visit her before the show? This trip through was carefully planned to a schedule. He was taking a letter from the Mayor of Detroit to the Mayor of New York, and planned to arrive on the eve of the show's opening. He was taking a newspaper man along with him: a keen-eyed, alert young man who would write up every incident of the trip.

HIS runabout was as near perfection as he could get it; he was leaving behind another almost finished, and five men and a foreman to assemble the others as rapidly as possible. The original body, so obviously a buggy affair, had been altered to suit this new type of locomotion. Its seat was deeper, its back higher; both were softly upholstered in leather backed by coil springs. The old dashboard was gone. Instead, a slanting prow cut the wind and supplied a storage compartment in which he kept his dry cells and tools. A sloping rear deck concealed two tanks, one for gasoline and one for water, which was circulated through the engine and some coils beneath the floor by a pump driven through a friction pulley on the flywheel. The engine was under the seat, the only visible part of it being the lower portion of the flywheel. Instead of the transverse front spring of the old-fashioned buggy, he had suspended the body on two longitudinal ones, shackling them firmly to the yoke-ended round front axle. The rear springs were practically unchanged. The steering handle he retained, though he had attached a warning bell close to the hand grip where his thumb could find it readily. In the center of the front he had hung the latest model acetylene bicycle headlight. It was a good-looking runabout, save for the box of spare parts lashed upon the rear deck in this instance, and it was in good racing trim.

Cleveland the first day, with a reception committee to greet him when he wanted only to turn up the grease cups on the crank shaft bearings, pour some oil in the crankcase, and go to bed. Buffalo next, with a parade of cars waiting on the outskirts to escort him into town. There must have been fifteen of them; the automobile was beginning to catch on—and there were no electrics! Then the hills and valleys of New York State, and trouble. Cold when they started, it grew colder. The wind whistled against their faces, through their buttoned greatcoats. Dust, then mud, then ice, coated them so that they had to stop and remove their goggles and wipe them off with stiffened fingers. Roads—"thank-you-ma'ams" that demanded almost constant use of the brake which closed on a drum between the two planetary transmission boxes; streams with bridges that either humped high or sagged low; some with no bridges at all. The tires came unglued from their rims and had to be roped on. The ropes cut through and Gil used wire, and telegraphed New York for a new set to be waiting.

EVEN going downhill he had to go slowly, for there was the inevitable humped or sagging bridge. Going uphill was worse, for the periodic watershed had to be bounced over. Sometimes at these ridges the engine stalled, and Gil's passenger had to jump out quickly and set a stone behind the wheels; the brake was not strong enough. Twice he broke a spring, and lost valuable time getting it repaired. His front wheels jolted out of line and the axle had to be straightened. But five days later—better time than Winton had made—he drove into New York triumphantly, to be arrested by a bicycle cop for obstructing traffic.

New York had advanced to the point where one could drive

(Continued on page 147)

Gets $500.00 for Set of Drawings

Learn to Draw at Home Earn While You Learn

W. E. KENT

"I sold $500.00 worth of drawings to local boxing promoters," writes graduate W. E. Kent, New Jersey. "Have sold a drawing which took less than a day to do for $100.00."

P. C. Roberts, Fla., writes: "Earning $100.00 a week." Harold A. Allen, R. I., writes: "Have made $40.00 in a day."

EARN WHILE YOU LEARN. Miss H. H. Hartleigh, Mass., writes: "I made $235.00. Yet I've only sent in 12 lessons." David Gould, Maine, wrote, while learning: "I made $225.00 on a single job." E. V. Fritsch, Texas, wrote: "Making $10.00 to $15.00 a day."

GET FREE BOOK. Shows why you can learn to draw at home by THIS method even if you have never shown talent. Shows what graduates earn; how you earn while learning; why artists get $50, $75, $100 and $200 a week; shows big money opportunities in your own neighborhood. Send for it today. No obligation. No salesman will call.

Washington School of Art, Inc., Room 249-E, Washington, D. C.

Room 249-F, 1115-15th Street, N. W. Washington, D. C.

WASHINGTON SCHOOL OF ART, Inc., Washington, D. C.
1115-15th St., N. W.

Send your free book on how to become an artist. (Put name and address on margin or separate sheet.) Write plainly. State age and if Mr., Mrs. or Miss.

24th Year

CHICAGO TECHNICAL COLLEGE

LEARN DRAFTING IN 4 MONTHS

Trained Draftsmen earn $80 to $100 a week. 4 months' interesting study at Chicago Tech. fits you to earn big money in drafting's fertile field. Common schooling all you need. Expert instructors. Opportunities for self-support while studying. Free Employment Service. Day or Evening Classes. Athletics. Enter any time. Also intensive courses in Engineering, Electricity and Building. Write for free 84-page "Blue Book" and facts about how to qualify for a high-pay drafting job in 4 months.

Dept. H-410
118 East 26th St. **Chicago Technical College**
Chicago

If you can't come to Chicago, study at home. Write for Free Trial Lesson in Drafting.

Skin Troubles

Cleared Up—often in 24 hours. To prove you can be rid of pimples, blackheads, acne, eruptions on the face or body, barbers' itch, eczema, enlarged pores, oily or shiny skin, simply send me your name and address today—no cost—no obligation. CLEAR-TONE tried and tested in over 100,000 cases—used like toilet water—is simply magical in prompt results. You can repay the favor by telling your friends; if not, the loss is mine. WRITE TODAY.

E. S. GIVENS, 458 Chemical Bldg., Kansas City, Mo.

LAW STUDY AT HOME

Become a lawyer. Legally trained men win high positions and big success in business and public life. Be independent. Greater opportunities now than ever before. Big corporations are headed by men with legal training. Earn

$5,000 to $10,000 Annually

We guide you step by step. You can train at home during spare time. Degree of LL.B. conferred. LaSalle students found among practicing attorneys of every state. We furnish all text material, including fourteen-volume Law Library. Low cost, easy terms. Get our valuable 108-page "Law Guide" and "Evidence" books free. Send for them NOW.

LaSalle Extension University, Dept. 983-L Chicago
The World's Largest Business Training Institution

Learn Photography at HOME

Make money taking pictures. Prepare quickly during spare time. Also earn while you learn. No experience necessary. New easy method. Nothing else like it. Send at once for free book, *Opportunities in Modern Photography*, and full particulars.

AMERICAN SCHOOL OF PHOTOGRAPHY
Dept. 1366, 3601 Michigan Ave. Chicago, U. S. A.

Whirling Wheels

(Continued from page 146)

through Central Park without being arrested, but it seemed that one couldn't leave a mud-stained vehicle at the curb long enough to change a set of tires without first obtaining a parade permit. Here was where the newspaper man proved to be a friend in need. While the Goodrich men were mounting a new set of tires, he got busy on the telephone and arranged for Gil's release. And during that time Gil was told of a brand-new tire.

THE Goodrich people had acquired the American rights for the manufacture of a new type Michelin tire several months before. It was a double tube affair that embodied an advanced clincher arrangement. A rim, shaped in cross section like a double hook, was riveted to the wooden wheels. Into this rim an outer cover for a pneumatic tube was slipped, its projecting edges sliding under the rim hooks and being held there by six Y-shaped wedges, the legs of which extended down through the felloe of the wheel and carried wing nuts, accessible between the spokes. After the nuts were firmly screwed tight, thereby wedging the outer tube's projecting edges into the hooks of the rim, the inner tube was blown up with a hand pump, and there was a tire that was practically a part of the wheel. Gil ordered a set complete with wheels, the tires to be three-and-one-half-inch; asked that they be installed during the show, and drove away on his freshly glued single tubes to deliver his letter to the Mayor of New York. Another trouble surmounted—tires.

Then, with his bones shrieking for rest, he drove his travel-stained runabout, mud and all, directly into his booth at the Madison Square Garden—and forgot his aches to sit up half the night with a New York business man. The man's hair may have been almost white, his corpulence clothed in a dignity that was almost overawing, but there was red blood in his veins, and all the strain of the five-day trip had not been in vain. He wanted, for delivery the next year—twenty runabouts!

That explained the mood of Gil Herrick when, after four years, he met big Jim Wenden the next day. In an aisleway between exhibits—thirty-one of them!—Jim stopped directly in front of him as he had done once before, directing a quizzically humorous glance down at him.

"Who let you in?" he asked, in a voice that was reminiscent of Zach's, and stuck out a big hand. "Thought you'd be pluggin' away in that barn for the next ten years."

GIL was surprised. He had not been thinking of Jim at the moment; now—was there a pain in his left shoulder, or did he just imagine it? Jim looked prosperous in an obvious sort of way. The suit that covered his big frame was of well-cut material but a trifle too light and bechecked; his light brown derby was cocked a little; his shoes were brightly polished. Gil, who had been spending his money on other things, was far less impressive. He looked down at the extended hand.

"Guess I won't risk it again," he said with a smile on his lean face, and the hand dropped. "No, I left the barn last spring. I'm exhibiting."

"You don't say so! Well, that's fine! What company you working for?"

"Myself." Gil pointed down the bunting-draped aisle to a booth at the end where a sign "Herrick Runabout" was conspicuous above the heads of a crowd. Then he said, quite deliberately: "Who are you doing now?"

Jim stiffened and sobered. "I'm retaining my stock interest in the Consolidated Electric Vehicle Corporation," he said with dignity. "And forming a new company, to manufacture a four-cylinder car."

"Well, well, that's fine!" said Gil. "Talking like Wall Street—and *(Continued on page 148)*

Go to School at Home!



HIGH SCHOOL COURSE IN TWO YEARS

YOU ARE BADLY HANDICAPPED if you lack High School training. You cannot attain business or social prominence. You are barred from a successful business career, from the leading professions, from well-paid civil service jobs, from teaching and college entrance. In fact, employers of practically all worth-while positions demand High School training. You can't hope to succeed in the face of this handicap. But you can remove it. Let the American School help you.

FIT YOURSELF FOR A BIG FUTURE This course, which has been prepared by some of America's leading professors, will broaden your mind, and make you keen, alert and capable. It is complete, simplified and up-to-date. It covers all subjects given in a resident school and *meets all requirements* of a High School training. From the first lesson to the last you are carefully examined and coached.

USE SPARE TIME ONLY

Most people *idle* away *fifty* hours a week. Probably you do. Use only one-fifth of your wasted hours for study and you can remove your present handicap within *two years*. You will enjoy the lessons and the knowledge you will gain will well repay the time spent in study.

Check and mail the coupon NOW for full particulars and Free Bulletin.

American School
Dept. H-675,
Drexel Ave. and 58th St., Chicago

American School
Dept. H-675, Drexel Ave. & 58th St., Chicago

Send me full information on the subject checked and how you will help me win success.

.....Architect	.....Business Law
.....Building Contractor	.....Lawyer
.....Automobile Engineer	.....Machine Shop Practice
.....Automobile Repairman	.....Mechanical Engineer
.....Civil Engineer	.....Shop Superintendent
.....Structural Engineer	.....Employment Manager
.....Business Manager	.....Steam Engineer
.....Cert. Public Accountant	.....Foremanship
.....Accountant and Auditor	.....Sanitary Engineer
.....Bookkeeper	.....Surveyor (& Mapping)
.....Draftsman and Designer	.....Telephone Engineer
.....Electrical Engineer	.....Telegraph Engineer
.....Electric Light & Power	.....High School Graduate
.....General Education	.....Wireless Radio
.....Vocational Guidance	.....Undecided

Name .....

Address .....

The Sun Rises

offering a great new

Opportunity

THE big new field of Aviation is open to every ambitious young man. There are 53 different trades in the industry, many ground jobs. The business is humming. Manufacturing of machines and parts is growing by leaps and bounds. There are now 4,000 air ports operating in America—6,000 privately owned planes. Men in Aviation earn up to $100.00 weekly and more.

Wide awake men are needed as mail pilots, commercial flyers, instructors, inspectors, riggers, mechanics at flying fields, besides the thousands of positions in factories.

Training gets men ahead in Aviation

At home, in your spare time, you can learn the fundamentals of Aviation. Lieut. Walter Hinton, first Trans-Atlantic flyer, and his staff of experts will guide your instruction from beginning to end.

The Aviation Institute Course teaches you everything you need to know, right up to the point of actual flight instruction in the air. All the principal ground work, so absolutely necessary to qualify, is secured in a comparatively short time at home. When you have graduated from the Institute and received your credentials, you are ready to take your place in Aviation.

If you wish to become a pilot, final flying instructions are given in all parts of the United States in cooperation with the Institute, at reasonable rates. Five to ten hours with an instructor and you can fly alone.

Get all the facts about the Institute course and the way it leads to Opportunity. Do it now.

FREE *This Book Tells All*

Aviation Institute of U. S. A.

Walter Hinton, Pres.

Aviation Institute of U. S. A., Suite 29
71 West 45th St., New York, N. Y.

You may send me without obligation a Free copy of "Aviation and You."

Name.....

Age (Not under 15).....

Street.....

City.....State.....

Whirling Wheels

(*Continued from page 147*)

changing horses in the middle of the stream! The Amalgamated Automobile Company of the World, capital seventeen million dollars, I suppose. With another European engine, may I ask, or are you going to make this one out of paper and a pencil?"

"Look here, Gil—"

"Well, luck on the stock-jobbing. There'll always be suckers," Gil continued, then stepped aside as though to pass on.

But Jim stopped him with a hand laid on his shoulder. "Wait a minute, young feller; I don't like the way you talk."

Gil shrugged the hand off. "Going to pull some of your muscle-bound tricks?" he asked. "Thought you'd grown up. No, you may not like the way I talk, but you started it, asking foolish questions. You know what I've been doing without asking. And I know what you're doing, too. Don't forget it. You were going to beat me out with electrics, weren't you? Now you're going to gas. Engines, I suppose, not talk. Well—" he left it unfinished.

JIM laughed shortly. "Maybe we'll get you with Consolidated Electric yet," he retorted.

"Yeah, the Selden Patent; I heard about it. You will control the world, won't you, Jim? Reminds me of some talk I heard once about racing sprockets. Remember it?" and he walked away. To be overtaken by one last taunt:

"Hey, Gil! What's the latest from—"

Gil whirled and interrupted him. "That's something else you know. Answer it yourself."

They met several times during the following week, but only once for an exchange of cordialities. Gil was much too busy in the meantime, joining the newly formed National Association of Automobile Manufacturers, which included parts makers as associates; making a strong talk, backed by his personal experience, upon the necessity of forming an organization to improve the roads; interviewing parts makers, inspecting the innovations of all the exhibits—to say nothing of the press of affairs that a man on the verge of success encounters. Until—

Saturday. The pompous, white-haired gentleman who proposed to sell twenty runabouts had had a conference with his—"associates," he called them. They had come to the conclusion that runabouts could not be sold. The crowd that gathered about Gil's mud-stained vehicle were only curious; they were not buyers. Did the people who looked at a giraffe want to buy one? No doubt the runabout could cover the roads, but look at it—and remember what you looked like on the day you arrived in town. Sorry.

FROM Gail: "We're sailing from here on Wednesday! Isn't that great? Two more excited people you never saw, and mother is so gay! We're storing our furniture, because we don't know how long we'll be gone and we're so excited. Be sure to come and see us off, won't you? That was a wonderful thing you did, driving across the country like that. I read about it in the papers."

And from Jim: "That's a nice four you're working on, Gil," with a twinkle in his black eyes. "But it ain't one, two, three with mine."

Could Gil summon one more smile? To have all these things come at once—with Jim announcing treachery in Gil's little plant? This was worse than any hammer lock. But he swallowed—and raised a grin.

"Oh, that? I scrapped that engine. Like to have the drawings? I'll send 'em to you as soon as I get back," and he turned on his heel and walked away.

To find himself standing beside the inclined wooden runway on the roof of Madison Square Garden. How he got there he could not have told, but there he was, (*Continued on page 149*)

5 DE LUXE VOLUMES
Gold-stamped, flexible bindings. 2320 pages. Over 2000 illustrations, charts, wiring diagrams.
New edition just off the press!

CLIMB to a Better Job!

It might be safe for you to stand still and take it easy—if you could get every one around you to do the same. But they won't. Ambitious men, go-getters are studying their jobs, thinking out new ways to improve "upkeep" and repair service. You haven't a chance against better educated men, or those who are improving themselves by READING UP on Auto Maintenance. It will pay you—BIG—to turn even a part of your spare time into mastering all branches of Auto Engineering.

"Auto Engineering" Library

Loaned FREE!

to ambitious men!

Built especially for men with limited education, by eleven of America's greatest Automotive Engineers. The most COMPLETE, and authoritative work on auto "up-keep" ever compiled. Written so you can understand it, and benefit by it. Also used by THOUSANDS of Auto Owners, Service Station Superintendents, Garage Foremen and skilled mechanics to look up difficult problems in the day's work.

BE AN AUTO EXPERT!

There's a too much competition in the skilled and tinkerer class. Employers and the public are looking for someone with enough gumption enough to learn to KNOW every branch of automotive engineering. A glimpse or reading of this great "Auto Engineering" Library will help you push your way to the front QUICK!

Auto Owners FIX IT YOURSELF *and save money!*

Be prepared to make emergency adjustments and repairs, to locate trouble and FIX IT, on the road. Know your car. Borrow a set free and find out why 100,000 Auto Owners, men who want to learn as well as men who know autos, depend on this Library constantly.

AMERICAN TECHNICAL SOCIETY
Dept. A620 Drexel Av. & 58th St. Chicago

American Technical Society
Dept. A-620 Chicago, Illinois

I want to borrow FREE for 15 days' use, a brand new set of "Auto Engineering," the latest 6 volume edition. I will pay only the few cents delivery charges when books are received, but not one penny for the use of the library itself. In return for this, I agree to look them over very carefully, and determine for myself if I wish to keep them. If I do, I will pay you $2.00 after 15 days, then $3.00 a month until $24.80 is paid, your special advertising price. If not I will return charges collect, and owe you nothing.

3 Free Features
1. Home-Study Guidance FREE.
2. Membership in American Technical Society and a year's consultation FREE.
3. FREE Employment Service.

Name.....

Address.....

(Attach letter stating references' and employers' names and addresses, or write same plainly in margin.)

Learn to Mount Specimens like These

BE A TAXIDERMIST

Learn at home by mail to mount and stuff **birds, animals, game-heads, fish**—**tan furs and skins** and make fine rugs and robes. Wonderfully interesting and fascinating. Easily, quickly learned in spare time. Save your trophies. Decorate your room and home with finest of art. Make taxidermy your hobby.

Old reliable school—100,000 graduates. Success guaranteed. Big profits. Sell your mounted specimens and mount for others. Big demand for the work. Have a business of your own. Earn money in spare time for athletic goods, guns, traps, radio, books and supplies. A great opportunity. Grasp it. Write today.

FREE Beautiful illustrated book "How to Mount Game." Explains the secrets of taxidermy. Dozens of photos of mounted specimens. Tells how you can learn and earn. Every one who fishes, hunts, or likes outdoor life should have this great book. Just send your name and address. Write today. No obligation.

Northwestern School of Taxidermy
3396 Elwood Building Omaha, Nebraska

Science Discovers The Secret of Caruso's Marvelous Voice!

Why is it that the humble peasant boy of Italy became the greatest singer of all time? This diagram of his throat will show you. Caruso's marvelous voice was due to a superb development of his Hyo-Glossus muscle.

YOU Too, Can Develop a Beautiful Voice

Whether your voice is strong or weak, pleasant or unpleasant, melodious or harsh, you can have a beautiful singing or speaking voice if your Hyo-Glossus muscle is developed by correct training. The wonderful silent exercises devised by Eugene Feuchtinger, A.M., world famous discoverer of the Hyo-Glossus muscle, can be practiced in the privacy of your own home, no matter where you live.

100% Improvement Guaranteed

The Perfect Voice Institute guarantees that Prof. Feuchtinger's method will improve your voice 100%. You are to be your own judge—take this training—if your voice is not improved 100% in your own opinion, we will refund your money.

FREE BOOK Write today for a Free copy of "Physical Voice Culture". It may be the first step in your career. Don't delay. Send today!

PERFECT VOICE INSTITUTE
212 Sunnyside Ave., Studio 13-66 Chicago, Ill.

Part-Time Men Get This Suit FREE

Big Season NOW

Make $45 a Week and up

Cash profits paid in advance

No question about it, any man can easily earn $45 a week and up, just showing our wonderful outfit and taking orders for our high-grade tailoring. Never before such low prices and beautiful styles.

Your Own Clothes FREE

To introduce our unbeatable values, classy styles and perfect tailoring, we make this remarkable free suit offer—something different, better, bigger, more liberal than any offer ever made.

Handsome Carrying Case Outfit

of large real cloth samples — everything furnished FREE. *Write today for free suit and big money-making offer.*

Spencer Mead Co., Wholesale Tailors, Dept. J-821, Chicago

RADIO AT WHOLESALE

Write for my Big 1928 Radio Catalog—just off the press. Thousands of marvelous bargains in nationally advertised goods. All the LATEST IN RADIOS and equipment. Lowest wholesale prices. Agents Wanted.

It's a regular encyclopedia on Radio. All trouble finding FREE Log and Call Book and Catalog. Get your copy today. Send postcard now!

FREE

DEALERS NEW 1928 CATALOG

American Auto & Radio Mfg. Co.
BARRY SCHWARTZBERG, PRES.
Dept. 313 American Radio Bldg., Kansas City, Mo. 3

PAINT SIGNS and SHOW CARDS

We quickly teach you by mail, or at school, in spare time. Enormous demand. Big future. Interesting work. Oldest and foremost school.

Learn To Earn $50 To $200 Weekly

John Vasco, N. Y., gets $25 for single show card. Crawford, B. C., writes: "Earned $200 while taking course." Don't delay. Send today for complete information, samples and guarantee.

DETROIT SCHOOL OF LETTERING
Est. 1899
Lo Stinson Ave. DETROIT, MICH.

GOV'T. POSITIONS

Forest rangers, start $125 month; cabin and vacation; patrol forests; protect game. Railway mail clerks, postoffice clerks-carriers, rural carriers, prohibition agents and internal revenue agents. For list of positions and how to qualify write Mokane Dept. 306, Denver, Colo.

Whirling Wheels

(*Continued from page 148*)

watching a runabout puffing up and down the imitation hill. A demonstration of hill-climbing ability! It would halt part way up, then start on again; stop on the way down, then up some more. Marvelous—on a road built by hand of nice planks! Suppose that well-dressed demonstrator had to drive for five days on the roads Gil had come over! Well, at that, the man was probably selling his runabout. It wasn't covered with mud. It wasn't a giraffe.

"Say, are you Mr. Herrick?"

Gil turned slowly, and saw two alert-eyed young men with excitement in their faces. One was taller than he, dark and dapper. "My name's Morton, Chas. T." The other was Gil's size, with freckles on his beak of a nose, and red hair. "This is Fred Andrews. Got a minute to talk?"

THAT was about all Gil did have—time. "Yes, I guess so. What is it?" More questions, of course; that's all these people had to ask. Giraffes. Well, what else was he good for but to answer questions?

"Let's go down where it's private," said the tall one. "We're not interested in this cotton-padded stuff," with a gesture toward the "hill-climbing" exhibit. Gil pricked up his ears.

"Got an agency for your runabout in New York?" was what the freckled one asked when they had closed a door behind them. Gil hesitated. To them it may have seemed a moment of consideration; to him it was the time required to swallow his heart—and recall a certain previous offer—before he could speak.

"I'm considering a proposition," said he. Was his voice steady?

"Well, we've been figuring . . ."

". . . read about your stunt and . . ."

". . . overheard what you said about your four . . ."

". . . looked 'em all over . . ."

They stopped and looked at one another as though to say, "Who's doing this talking, anyway?" Then they laughed. Gil joined them.

"Maybe you'd better take a vote to see who's going to talk," he suggested. The two strangers looked at one another and came to a silent agreement at once. The tall dark one spoke up.

"WE'VE got a little money between us," said he, "and we've been knocking around town looking for some good business to get into. Don't know an awful lot about this automobile stuff, but it looks pretty good to us. With the way these foreign cars are coming in, it looks like we ought to be able to sell a few runabouts next year if we go at it right—and your proposition's good. Say—oh, twenty."

"Twenty!" The way Gil said it would have put the finest actor to shame; it intimated that such a proposition was not worth considering. "Why, you ought to be able to sell fifty."

The tall one looked at the red-headed one, who smiled and nodded in a way that meant but one thing: "See? I told you!" They seemed to understand one another pretty well, those two, though what reason there was for such a nod was a mystery. The dark one nodded assentingly then, whereupon the redhead seemed to bristle with a surge of energy. "Sure," said he with a glisten in his red-brown eyes, "why not?"

A pair of unclenched hands came out of trousers pockets, took a chair and swung it over to where three heads could get close together. "What did you say your names were?" said Gil.

Gil drove another, totally unanticipated race, on Monday. To Boston. He had not intended to drive through; he had planned to go by rail. But out of the conference with the two men of his own age another item of news had developed. Andrews and Morton, as his agents came to be

(*Continued on page 150*)

He Climbed from $1,800 to $10,000 a Year!

Can You Match This Record?

Eight years ago E. J. Dryden of Laredo, Texas, was an assistant bookkeeper at $150 a month. Today he is a department manager with an income of more than $10,000 annually. Mr. Dryden's progress illustrates the tremendous importance of ***planning one's future and persistently following it thru to success.***

Bookkeeping was his work; so he first trained in LaSalle Higher Accountancy; then in Commercial Spanish, because Laredo is just across the border from Mexico. Then came Business Management, to give him an all-around training; law was next, because he knew this training is necessary for a successful executive.

Steadily he moved upward, even while he was studying. First, cashier, then credit manager and now department manager. Each step increased his income. Is it surprising that eleven other employees of his firm have trained with LaSalle?

Send for Free Outline of LaSalle Salary-Increasing Plan

How much is it worth to you to gain, in a comparatively few months, substantial promotion—a new confidence and self-respect?

The way to all these things is outlined in a fascinating book, "Ten Years' Promotion in One"—a book which has set thousands and thousands of men on the path to real achievement. The coupon will bring it to you FREE.

In addition we will send you a 64-page book describing the unusual opportunities in any of the business fields listed below. If you want to look back a year from today and see a record of real progress, then—TODAY is the day to start—and the moment NOW!

—— —— —*Find Yourself Thru LaSalle!*— —— ——

LASALLE EXTENSION UNIVERSITY
The World's Largest Business Training Institution

Dept. 983-R Chicago

I should be glad to learn about your *salary-increasing plan* as applied to my advancement in the business field checked below. Send also copy of "Ten Years' Promotion in One," all without obligation.



- ☐ Business Management
- ☐ Modern Salesmanship
- ☐ Higher Accountancy
- ☐ Traffic Management
- ☐ Railway Station Management
- ☐ Law—Degree of LL.B.
- ☐ Commercial Law
- ☐ Industrial Management
- ☐ Modern Foremanship
- ☐ Personnel Management
- ☐ Modern Business Correspondence and Practice
- ☐ Banking and Finance
- ☐ Expert Bookkeeping
- ☐ C. P. A. Coaching
- ☐ Business English
- ☐ Commercial Spanish
- ☐ Effective Speaking
- ☐ Stenotypy

Name .....

Present Position .....

Address .....

Don't Envy The Plumber BE ONE!

$11.00-$16.00 PER DAY and work EVERY day, is the Plumber's wage.

Every skilled workman will tell you that Plumbers have the best of it. WINTER and SUMMER the Plumber is busy at top wages. No skilled Plumber is ever out of a job—compare his opportunities with any trade, plus the opportunities of having your own shop.

We teach you Plumbing with TOOLS (not books) under Licensed Master PLUMBERS in one of the finest equipped schools in America. We make you a Plumber, every branch is taught thoroughly—Lead Work—Blue Print for plan reading—all other tricks.

LEARN IN 8 to 12 WEEKS without previous experience.

If you are making less than $60.00 a week you owe it to yourself to investigate. Get FREE catalog that tells in pictures and words how we teach this trade. Special rates now.

UNIVERSAL PLUMBING SCHOOL
2031 Troost Ave. KANSAS CITY, MO.

ANY MAN who can read and write and use a pair of pliers can become an electrical expert and free himself forever from the long hours and drudgery of a small pay job.

And you can learn the BIG PAY profession of electricity right in New York City—the heart of the electrical world—the city of 100,000 jobs. At the same time you are learning the BIG PAY profession you can be enjoying the sights and wonders of New York, the modern Bagdad.

Be an Electrical Expert

Graduates of the **NEW YORK ELECTRICAL SCHOOL** are in demand by all the big electrical companies. Or, if you prefer the independence of a business of your own, there are thousands of opportunities for efficient, **dependable** men to become electrical contractors. When you are your own boss the money you can make is limited only by your own energy and ability.

Personal Instruction

The **NEW YORK ELECTRICAL SCHOOL is not** a correspondence school. You learn by doing—by personal instruction on full size standard electrical equipment under the personal supervision of trained instructors.

At N. Y. E. S. you train your hands and mind at the same time. You learn the theories of electricity—and then you are shown how to put the theories into actual practice by solving the problems with **your own hands.**

The man who has learned electricity by actually doing electrical work under intelligent personal instructors can go to any part of the world and be sure of a good living. There are N. Y. E. S. Graduates in all the countries of the world.

Write today for the 48-page booklet giving full information about the N. Y. E. S. Course and showing pictures of the equipment available for your personal use in our two seven-story buildings.

The NEW YORK ELECTRICAL SCHOOL
40 W. 17th Street, New York

MAIL TODAY

THE NEW YORK ELECTRICAL SCHOOL
40 W. 17th Street, New York.

Please send me **FREE** your 48-page booklet. It is understood that this request puts me under no obligation.

Name.....

Address.....

.....

Whirling Wheels

(*Continued from page 149*)

known, had tipped him off to a man named Tinsley who was thinking about opening an agency in Boston.

"A young man?" asked Gil.

"Yes, why?"

"This is a young man's business," was all the explanation he would offer. "And say, you made a remark when you were both talking at once—something about hearing me talk about fours."

MORTON looked at Andrews and they both laughed. "Yeah," said the redhead. "We were after you then. You were talking to a big chap and we were waiting to get hold of you. Looked to me like you had him outbluffed, and I told Mort, here, that if you were that kind, we'd better tie up to you. Mort didn't know, but—gosh, we had a time finding you! Guess you saw me nod to Mort then, didn't you?"

"Yes," said Gil thoughtfully, "I did." That defiant gesture of a defeated man; it had been observed—and now look! "I'll tell you about that some day . . . What about this man Tinsley?"

It seemed that Tinsley was a friend of Morton's, a square-shooting chap, hard to convince but ready to listen to reason. He had been unable to get down to the show on account of an illness in his family, and had asked Morton to look around for him. That was what had started him and Andrews. They ought to be able to do the same in New York, they thought—"and Tinsley ought to sell twenty-five runabouts in Boston if we sell fifty here."

"Thing to do is drive up," said Andrews, seized with an idea. "Big demonstration. Sweep him off his feet. It'll help us, too." His eyes grew brighter as the idea took form. "I've got a friend on a newspaper there. He'll write it up. Headlines—'Twentieth Century Methods. Man Versus Miles for Millions. New Era Business Man'—all that. See?"

"Great!" said Gil.

THEY had talked nearly all that Saturday night. Prices—"a dollar a pound, and my machine weighs seven-fifty,"—discounts, deliveries, all the details involved in the deal. Then he had gone to bed and dreamed, with open eyes staring at the ceiling, seeing a great factory with a procession of runabouts popping out of an open door; long buildings, sidings, a power plant; shafting, pulleys, belts, machines—blue eyes, crowned with coils of auburn hair with glints of gold in it, smiling.

"Starting for Boston tomorrow morning," he wired her when he got up from a few hours' sleep, "to give you a real ride and some great news. Better unpack your bags."

Andrews and Morton were wonders. They staged a send-off that would have done honor to a celebrity, and Gil broke the speed laws as he flew up Broadway. Fifteen, twenty miles an hour, with a bicycle cop hanging on either side of his runabout to make it legal, and a line of machines behind. Wine? No blood ever tingled with artificial stimulants as Gil's did that brisk November morning. The world was his oyster; he would open it and present it, in person, to Gail. The work involved in getting such a production going? The night and day labor to meet a demand for five times the number he had planned for? Nothing—with Gail. No Lochinvar ever rode into the East more gladly; no Hercules ever looked at a monumental task with less fear.

Will Gil's fine dreams come true? The rewards of his long struggle now seem within his grasp. Can he clinch them? And what of Gail? After years of separation, will she still feel the same toward him? Next month's installment tingles with romance and dramatic incident.

HELP

IN A HANDY FORM
$1 A MONTH
Expert Help and

Inside Information for Builders! Up-to-date, complete Trade Guides and Trade References—handy pocket size; fully illustrated; easy to learn. Don't fall behind! Be a boss! Study in spare time. Send for Guides covering your trade, on free trial. Pay $1 a month if satisfied. Mail Trial Coupon Today!

CARPENTERS FOUR GUIDES $6

Audels Carpenters Guides. (4 vols. $6.) Explains how to handle every kind of carpentry job—inside or outside work. Pictures, plans, calculations and diagrams make any job easy. New short-cuts, modern methods explained. Builders and contractors' questions answered. Steel Square and other problems solved. A practical Guide and helping hand for every carpenter; easy, quick methods of work that help you to be a leader.

PLUMBERS FOUR GUIDES $6

Audels Plumbers Guides. (4 vols. $6.) A standard Guide explaining the theory and practice of all plumbing, heating, steamfitting, gasfitting and sheet metal work. Answers your questions on any job. Clearly explains the new short-cuts and modern methods so you can understand. A complete reference of the Trade and home study course. Fully illustrated, authentic, up-to-date, with complete Plumbers' Code.

MASONS FOUR GUIDES $6

Audels Masons Guides. (4 vols. $6.) Every Bricklayer, Cement Worker, Plasterer, Tile Setter and Stone Mason will find the answer to his questions and problems in this series. Inside Trade information on all the latest and best practice. A Study Course and complete reference library covering the Mason's Trade; including practical outline of steel construction. A helping hand for workmen and contractors.

ELECTRICITY HANDY GUIDE $4

Audels Handy Book of Electricity. (1 vol. $4.) A reliable authority and handy helper for every Electrical Worker, covering Wiring, Radio, Calculations, Armatures, Maintenance, Motors, Batteries. A complete Study Course and Ready Reference in one handy Guide for Electrician, Engineer and Student.

THEO. AUDEL & CO. 65 W. 23 ST. New York City

TRIAL COUPON

Please mail me for *free examination* the books marked (x) below. If I find books satisfactory, I will mail $1 in 7 days on each set ordered and will mail $1 a month on each set ordered until I have paid purchase price.

☐ CARPENTERS FOUR GUIDES $6
☐ MASONS FOUR GUIDES $6
☐ PLUMBERS FOUR GUIDES $6
☐ ELECTRICIANS HANDY GUIDE $4

Name _____
Address _____
Occupation _____
Employed by _____ 9T34

Young outdoor men wanted

Interesting, vigorous outdoor work in a growing organization where merit wins advancement. Good starting wages. Permanent positions and a real future for men who make good. Our present field force of Davey Tree Experts cannot meet the increasing demand. So we are selecting now, to enter our employ, a few sturdy, clean young men, thorough Americans, single, between 20 and 30 years old, free to travel, industrious, with good practical education, and able to give good references. Write for qualification blank to serve in place of personal interview. The Davey Tree Expert Co., Inc.
868 Federal Bldg., Kent, Ohio

ELECTRICITY

Learn at home

NEARLY $200,000 has been spent in preparing the Electrical Courses of the International Correspondence Schools.

They have helped thousands of men to get good positions in this fascinating profession for two reasons. (1) They have been specially designed to meet the needs of the student who studies at home. (2) They have been written by such well-known men as: EDGAR KNOWLTON—Electrical Engineer, Alternating Current Engineering Department, General Electric Co.; J. LESTER WOODBRIDGE, E.D. and M.E.—Chief Engineer of the Electric Storage Battery Co.; O. J. BUSHNELL —Superintendent of the Meter Department, Commonwealth Edison Co.; S. A. FLETCHER—Electrical Engineer, Superintendent of Service, Alabama Power Co., and H. H. MORTENSON—Designer of Alternating Current Motors and Generators, Allis-Chalmers Manufacturing Co.

Mail Coupon for Free Booklet

INTERNATIONAL SCHOOL OF ELECTRICITY
Associated with the
International Correspondence Schools
Box 7642-E, Scranton, Penna.

Without cost or obligation, please send me full details of your home-study course in
ELECTRICITY

Name.....

Address.....

CHICAGO TECHNICAL COLLEGE

24th Year

Engineering
Architecture
Electricity
Drafting

Intensely practical training. 2 year Diploma; 3 year B.S. Degree; special 3 and 4 months' short courses. Courses adapted to your needs. No time wasted. Expert instructors. Graduates in constant demand. Opportunities for self-support while studying. Day and evening classes. Athletics. Enter any time. Low tuition—easy terms. Write today for your copy of 84-page illustrated "Blue Book," mailed free. Dept. H-80
118 East 26th St. Chicago Technical College

LEARN FLYING!

All the fundamentals can be learned without a plane. Be ready for the Flying Age, now starting. Full instructions by expert pilot at cost—25c. Send today and keep up with the times.

AVIATION PRESS, Yalesville, Conn.

Learn Cartooning

At Home—In Your Spare Time

from the school that has trained scores of today's successful cartoonists who earn from $50 to $200 and more a week. The Landon Picture Chart Method of teaching makes original drawing easy to learn. Send 6c in stamps for full information and chart to test your ability. *Also state age.*

THE LANDON SCHOOL
1451 National Bldg., Cleveland, O.

You Can Easily Earn
Four Men's Wages

Practically no investment. No payroll to meet. Start in your garage or any small space. HB Quick Paint Spray Method of Refinishing Autos with duco, paint or lacquer enables you to easily do the work of four men the old way. Pays for itself on easy monthly payments with big profits for you at the same time. Write today for bulletin P8. Hobart Bros., Box P971, Troy, O

A 2c STAMP —will start you on the road to success. See Money Making Opportunities on pages 124 to 151.

Here Are Correct Answers to Questions on Page 46

1. The answer to this question is to some extent a matter of opinion. It is probable, however, that the distinction is best deserved by the famous Bay of San Francisco. This bay has anchorage sufficient for all the navies of the world. And once a ship has entered through the narrow Golden Gate, it is protected completely from the waves and winds of the open sea.

2. A number of species of these blind fish have been found in cave waters in various parts of the world. The best known probably are those from the caves in the south central part of Kentucky. One of these caves is the famous Mammoth Cave.

3. This is a growing industry on a number of islands off the southern coast of Alaska. The blue fox, which produces the best skins, will not live in captivity. But on these islands the fox finds itself at home, food is provided, any animal enemies are exterminated and the foxes are allowed to live in the wild state. The sea prevents their escape.

4. These are the famous flat cakes made of corn meal by the Indian women of Mexico. They take the place of bread in the native diet.

5. The island of Porto Rico, formerly a Spanish possession, now a territory of the United States. The translation of the Spanish name, "Porto Rico," is "rich port." This name was given to the island because of the fertility of the soil and the plentiful supplies of food. In ancient Spanish, however, the word for "gate" and the word for "port" were the same; accordingly, the translation "Gate of Treasure" is legitimate.

6. The Amazon, which, flowing through northern Brazil, is more than 3000 miles long and nearly 50 miles wide at its mouth.

7. In ancient times this was supposed to be a great whirlpool located north of the British Isles, off the west coast of Norway. It was supposed that whole ships were sucked down into it. Of course, actually, no such whirlpool exists. However, the sea in this part of the world possesses some strong currents and tidal movements. So there grew up the legend of the Maelstrom.

8. The crocodile lives in the River Nile and its branches. Each crocodile is commonly accompanied by a little bird, called the "zic-zac." The bird picks bits of food, parasites and the like off the crocodile's teeth.

9. This name comes from the town of Mosul on the Tigris River in Northern Irak. When the thin cloth known as muslin first was introduced into Europe, it came from Mosul.

10. This is the native name of a priest of Tibet. The head of the Tibetan religion and of all the many orders of Tibetan monks is called the Grand Lama.

11. In the islands of the New Hebrides, in the South Seas, north of New Zealand, the natives frequently build hutlike houses in the trees.

12. This custom probably originated in China. Nowadays, small metal images of Buddha or of other gods are made in China and Japan and shipped to the pearling fields of the South Seas. Here divers put the idols into the shells of the living pearl oysters. Gradually the idols are covered with pearl. Years later the oysters are fished up and the pearl-covered idols are taken out and sold.

Get in *on the* Ground Floor *of* ELECTRIC REFRIGERATION

YOU have seen the fortunes that have been made by the men who got in on the ground floor of the automobile . . . movies . . . radio. Electric Refrigeration is going to be another tremendous money maker **for the men who get in on it early in the game.**

NOW is the Time!



Electric Refrigeration Offers You a Brilliant Future

3 *LEARNED IN* MONTHS In 3 months only—just 90 days you can be one of the new group of trained experts who will guide and develop the most lucrative and newest of America's gigantic industries.

Experts Needed Electrical refrigeration needs men, men and more men—with positions—big, responsible, well-paid positions open—waiting for them.

Special Training Essential Trained mechanics cannot service these new machines—they need refrigeration experts of which there are but a pitiful few.

A Complete, Practical, Electrical Education

Learn by the thorough, approved scientific methods which our twenty-three years of specializing enable us to give you. In addition to Electrical Refrigeration, the following complete courses are given: **A. C. and D. C. Armature Winding, Wiring and Testing, Junior Electrical Engineering, Electrotechnics, Commercial Electrical Engineering, Electrical Engineering (B. S. Degree in 3 years), Automotive Electricity, Radio Broadcasting Transmitters, Receivers and Code.**

FREE BOOKLETS

Don't miss this fortune-making opportunity. Let us prove what we say. Let us send you our literature on the course you are most interested in. It's free—no obligation—the coupon will bring it to you—no fuss—no trouble. Be sure to mention course interested in, age and education.

New Class Organizing September 1st. - Act at Once

SCHOOL of ENGINEERING of Milwaukee
Founded 1905

163 East Wells Street Milwaukee, Wis.

School of Engineering of Milwaukee,
PS-927, 163 East Wells St., Milwaukee, Wisconsin.

Send me FREE, with no obligations, more details on your course in .....

Name.....Age.....

Address.....

City.....State.....

Education.....

THE ELECTRIC RADIO

THE RADIO YOU'VE BEEN WAITING FOR

The Thrill of a Life-time! . . . .

Always Ready ~ Always Right

NO EXCUSES — NO BATTERIES — NO ACIDS
NO MAKESHIFTS — NO WATER — NO TROUBLE

$175.00
COMPLETE
READY TO
OPERATE

The *New AC Tubes* and scientifically developed circuit allow you to merely

plug in your light socket and listen

The cabinet, panelled entirely of genuine mahogany, contains a large cone speaker mounted on a Baffle Board, which is placed in a remarkably resonant tone chamber, rendering exceptionally fine tone quality and "true-to-life" reproduction.

A Freshman development—licensed under patents; RCA—General Electric Co.,—Westinghouse Electric & Mfg. Co. and American Tel. & Tel. Co.

Sold on Convenient Terms
by Authorized Freshman Dealers

Six tubes ~ One Control
FRESHMAN MASTERPIECE

CHAS. FRESHMAN CO. *Inc.*, Freshman Building, New York
Los Angeles Chicago

R. R. DONNELLEY & SONS CO., CHICAGO